

# Resale Private Line Order Submittal

## Table of Contents

<b>23. RESALE PRIVATE LINE .....</b>	<b>2</b>
23.1 BUSINESS DESCRIPTION.....	2
23.2 BUSINESS MODEL.....	4
23.3 DEVELOPER WORKSHEETS.....	5
23.4 TRADING PARTNER ACCESS INFORMATION.....	6
23.4.1 OVERVIEW: Qwest Specific Functional Group Envelope - Routing Information.....	6
23.4.2 ISA TABLE INFORMATION.....	7
23.4.3 GS TABLE INFORMATION .....	8
23.4.4 MAPPING EXAMPLE AND DATA DICTIONARY ITEMS .....	10
23.5 MAPPING EXAMPLES.....	12
23.5.1 850 Private Line (850PL) – Version 4020.....	12
23.5.2 860 Private Line Supplemental Service Request (860PL) – Version 4020.....	16
23.6 DATA DICTIONARY .....	17
23.6.1 850 Resale Private Line (850PL).....	17
23.6.2 860 Resale Private Line Supplemental Service Request (850PL).....	103

## 23. Resale Private Line

### 23.1 Business Description

Resale Private Line products provide the capability of joining two locations (Point to Point Resale Private Line) or multiple locations (Multi-point Resale Private Line) with analog or digital facilities for the transmission of voice and/or data.

A Point to Point Resale Private Line is composed of two circuit locations, referred to as Point A (Primary Location) and Point Z (Secondary Location).

A Multi-Point Private Line is composed of multiple circuit locations; one Primary Location and multiple Secondary Locations. For Multi-Point Private Lines, a maximum of ten locations can be accommodated.

Resale Private Line products are circuit type services and are assigned Qwest Circuit Numbers rather than telephone numbers. Directory Listings are **not** applicable to circuit type services.

The following forms will be used between Qwest and the CLEC for Resale Private Line ordering purposes:

- LSR – Local Service Request
- RPL – Resale Private Line

The following Order Activity Matrices define the available Order and Line Activities for Resale Private Line:

#### Business Rules for Combining Order and Line Activity for **Resale Private Line (RPL)**

##### Order Activity Definition

REQ TYP	ACT	Definition	Application	LNA	Forms required
KB	N	New Installation	New installation of Resale Private Line service.	N	LSR, RPL
	D	Disconnect	Disconnect all services at the account level.	Not Applicable	LSR, RPL
	W	Conversion As Is	Change from one CLEC to another with no change to product or service.	Not Applicable	LSR, RPL
	V	Conversion As Specified	Conversion As Specified valid on conversion from existing Retail or Resale Private Line from one CLEC to another with changes in the service.	V	LSR, RPL

Z	Conversion As Specified, No Directory Listing	Not Allowed	Not Allowed	
C	Change	Change to an existing Resale Private Line service such as, add/remove features, and change billing information.	N*, C, D*	LSR, RPL
T	Outside Move	Outside move of an existing Resale Private Line end user location.	N	LSR, RPL
L	Seasonal Suspend	Not Allowed	Not Allowed	
Y	Deny	Not Allowed	Not Allowed	
B	Restore	Not Allowed	Not Allowed	
R	Record	Not Allowed	Not Allowed	
M	Inside Move	Inside Move of an existing Resale Private Line end user location when the account is already owned by the CLEC submitting the request.	C	LSR, RPL

\*Applies to Secondary Location(s) only – not applicable to Primary Location  
n/a indicates that the form with the line activity is not permitted.

Line Activity

LNA	Definition	Application
N	New Line	New line installation.
D	Disconnect	Disconnect all services at the account level.
V	Conversion As Specified	A conversion of a line to the LSP where all attributes of the service are specified.
C	Line Change	A change to a line with only the changed fields populated. A change could additionally be supported by NC/NCI entries on the LSR form.
All other LNA	Not Allowed	

## **23.2 Business Model**

See Appendix H

## **23.3 Developer Worksheets**

See Appendices B and C – Developer Worksheets - Order

## 23.4 Trading Partner Access Information

ORDERING FUNCTION	PRODUCT ID
UNE P PRI ISDN Trunk	850PL
UNE P PRI ISDN Trunk Supplemental	860PL
Status Update – Auto Push	855SU
Firm Order Confirmation	855FOC
Firm Order Confirmation on Supplemental	865FOC
Non Fatal Error Response	855NF
Non Fatal Error Response on Supplemental	865NF
Fatal Error Response	855FATAL
Fatal Error Response on Supplemental	865FATAL
Jeopardy	865JEOP
Completion	865COMP

### Order Submittal

The process begins with an EDI Trading Partner Access Information between Qwest and the Co-Provider.

The order request is transmitted by the Co-Provider via the EDI 850/860 format. Qwest will translate and forward the data to the internal application system. The request may activate the following responses:

- Firm Order Confirmation (FOC) - an indicator to the Co-Provider that the order has been accepted and successfully entered into the Qwest Service Order Processor systems.
- Order Completion - notification returned to the Co-Provider when a service request is completed.
- Error/Jeopardy Notification - notification to the Co-Provider of Fatal and/or Non-Fatal errors, detected either manually or by the system. Fatal errors prevent the order from processing. Non-Fatal errors occur after the order has successfully processed through the IMA system. Jeopardy Notification will be issued if Qwest has a problem meeting the commitment on the local service request.

### 23.4.1 OVERVIEW: Qwest Specific Functional Group Envelope - Routing Information

Separate maps have been created per ordering function. EDI envelopes are used for the initiation of translation processing and to invoke the correct map. In order to optimize interactive performance, the Co-Provider and Qwest agree to include only one transaction set per Functional Group, and one Functional Group per Interchange.

The Interchange envelope provides the Interchange Sender ID and Receiver ID information for EDI transport to deliver the transmission for external routing. The Functional Group Envelope routes the enclosed transaction set's output after translation to a specific application or application interface.

The Application Sender's Code (GS02) and Receiver's Code (GS03) are the linkage from the Functional Group Envelope to the translator's trading partner profile/relationship database in which the proper mapping and routing information are stored. In addition, the Functional Identifier Code (GS01) is the code identifying a group application related transaction sets.

## 23.4.2 ISA TABLE INFORMATION

### ANSI X12 ISA and IEA definitions:

- The ISA segment is the Interchange Control Header.  
Purpose: To start and identify an interchange of zero or more functional groups and interchange related control segments.
- The IEA segment is the Interchange Control Trailer.  
Purpose: To define the end of an interchange of zero or more functional groups and interchange related control segments.

### The Co-Provider and Qwest agree to the following routing information:

	SENT TO Qwest	RECEIVED FROM Qwest
ISA01	'00' (No Authorization information present)	'00' (No Authorization information present)
ISA02	<b>Spaces</b> (Authorization information)	<b>Spaces</b> (Authorization information)
ISA03	'00' (No Security information is present)	'00' (No Security information is present)
ISA04	<b>Spaces</b> (Security Information)	<b>Spaces</b> (Security information)
ISA05	Co-Provider TP qualifier	'ZZ' (Mutually Defined)
ISA06	Co-Provider TP ID	'QWESTO' (Note: This Trading partner ID is used only for QWEST order and post-order transactions. The "O" is the unique identifier.)
ISA07	'ZZ' (Mutually Defined)	Co-Provider TP qualifier
ISA08	'QWESTO' (Note: This Trading partner ID is used only for QWEST order and post-order transactions. The "O" is the unique identifier.)	Co-Provider TP ID
ISA09	Date of the interchange. YYMMDD	Date of the interchange. YYMMDD
ISA10	Time of the interchange. HHMM (24 Hour Clock)	Time of the interchange. HHMM (24 Hour Clock)
ISA11	'U' (U.S. EDI Community of ASC X-12, TDCC, and UCS)	'U' (U.S. EDI Community of ASC X-12, TDCC, and UCS)
ISA12	'00402' (Interchange Version ID)	'00402' (Interchange Version ID)
ISA13	Sender's translator assigned sequential control number	Sender's translator assigned sequential control number
ISA14	'0' (No acknowledgment requested)	'0' (No acknowledgment requested)
ISA15	'P' (Production data)	'P' (Production data)
ISA16	'0x1f' (Sub-element Separator)	'0x1f' (Sub-element Separator)

### 23.4.3 GS TABLE INFORMATION

#### ANSI X12 GS and GE segment definitions:

- The GS segment is the Functional Group Header.  
Purpose: To indicate the beginning of a functional group and provide control information.
- The GE segment is the Functional Group Trailer.  
Purpose: To indicate the end of a functional group and provide control information.

The Co-Provider and Qwest agree to the following routing information:

	SENT TO Qwest	RECEIVED FROM Qwest
GS01	<b>SEE GS TABLE BELOW</b>	<b>SEE GS TABLE BELOW</b>
GS02	<i>Co-Provider TP ID</i>	<b>SEE GS TABLE BELOW</b>
GS03	<b>SEE GS TABLE BELOW</b>	<i>Co-Provider TP ID</i>
GS04	<i>Date of the functional group. CCYYMMDD</i>	<i>Date of the functional group. CCYYMMDD</i>
GS05	<i>Time of the functional group. HHMM (24 hour clock)</i>	<i>Time of the functional group. HHMM (24 hour clock)</i>
GS06	<i>Sender's translator assigned sequential control number</i>	<i>Sender's translator assigned sequential control number</i>
GS07	<b>'X'</b> (Accredited Standards Committee X-12)	<b>'X'</b> (Accredited Standards Committee X-12)
GS08	<b>'004020'</b> (Version)	<b>'004020'</b> (Version)

#### GS Table

The Co-Provider and Qwest agree to the following routing information:

ORDERING FUNCTION	Qwest SEND/ RECEIVE	DOCUMENT	GS01 VALUE	GS02 VALUE	GS03 VALUE
Service Request	Receive	850PL	PO	<i>Co-Provider TP ID</i>	<b>PL90</b>
Status Update – Auto Push	Send	855SU	PR	<b>SU90</b>	<i>Co-Provider TP ID</i>
Firm Order Confirmation	Send	855FOC	PR	<b>FOC90</b>	<i>Co-Provider TP ID</i>
Non Fatal Error Response	Send	855NF	PR	<b>NF90</b>	<i>Co-Provider TP ID</i>
Fatal Error Response	Send	855FATAL	PR	<b>FATAL90</b>	<i>Co-Provider TP ID</i>
Jeopardy	Send	865JEOP	CA	<b>JEOP90</b>	<i>Co-Provider TP ID</i>
Completion	Send	865COMP	CA	<b>COMP90</b>	<i>Co-Provider TP ID</i>

#### Supplemental Order

Once an order has been initiated and received by Qwest the Co-Provider may submit an 860 Purchase Order Change Request to cancel, correct, or change the original order. In response to receiving the 860 request from the Co-Provider, Qwest will transmit Functional Acknowledgments (997) and Purchase Order Change Acknowledgments (865).



## GS Table (Supplemental)

The Co-Provider and Qwest agree to the following routing information:

<b>ORDERING FUNCTION</b>	<b>Qwest SEND/ RECEIVE</b>	<b>DOCUMENT</b>	<b>GS01 VALUE</b>	<b>GS02 VALUE</b>	<b>GS03 VALUE</b>
Supplemental	Receive	860PL	PC	<i>Co-Provider TP ID</i>	<b>PL90</b>
Status Update – Auto Push	Send	855SU	PR	<b>SU90</b>	<i>Co-Provider TP ID</i>
Firm Order Confirmation	Send	865FOC	CA	<b>FOC90</b>	<i>Co-Provider TP ID</i>
Non Fatal Error Response	Send	865NF	CA	<b>NF90</b>	<i>Co-Provider TP ID</i>
Fatal Error Response	Send	865FATAL	CA	<b>FATAL90</b>	<i>Co-Provider TP ID</i>
Jeopardy	Send	865JEOP	CA	<b>JEOP90</b>	<i>Co-Provider TP ID</i>
Completion	Send	865COMP	CA	<b>COMP90</b>	<i>Co-Provider TP ID</i>

## 23.4.4 MAPPING EXAMPLE AND DATA DICTIONARY ITEMS

### **Purchase Order (PO) Date**

The Purchase Order (PO) Date is an ANSI ASC X12 mandatory field. The sender is expected to populate this field, Qwest however, will not map this date into the application file. For outbound transactions Qwest will populate this field with a date. This date is only used to satisfy ANSI ASC X12 standards and should not be used by the Co-Provider.

### **Time Code**

The Developer Worksheet time code fields of every transaction (i.e., D/T SENT) is assumed as follows:

- Transaction set(s) originating from the Co-Provider - time code should be consistent with your time zone.
- Transaction set(s) originating at Qwest - time code is Mountain Time.

### **4020 Exceptions**

Transaction sets 850, 855, 860 and 865 are used with the following exception:

- SLN loop maximum use has been changed to >1

### **Delimiters**

The following delimiters will be used:

- Element Separator:       HEX 7C = | (vertical bar or pipe)
- Sub-Element Separator:   HEX 1F = (non-printable characters of "0x1f")
- Segment Separator:       HEX 0A = linefeed

### **Qwest Specific Fields**

Order fields that are specific to the Qwest implementation were added to selected OBF forms and are indicated by an alpha following the field number, i.e., EU-19a (AHN). These fields are not defined in the OBF form for the corresponding LSOG issue.

**Industry Standards Table:**

<b>OBF FORM</b>	<b>OBF ISSUE</b>	<b>EDI SOSC ISSUE</b>	<b>X12 STANDARD</b>
Local Service Request	LSOG 5	ELMS 5	004020
Resale Private Line	LSOG 5 and LSOG 3 (When Applicable)	ELMS 5	004020
Status Updates			004020
Firm Order Confirmation			004020
Non Fatal Error Response			004020
Fatal Error Response			004020
Jeopardy			004020
Completion			004020

## 23.5 Mapping Examples

### 23.5.1 850 Private Line (850PL) – Version 4020

Legend of Symbols in this transaction example

Symbol/Definition	Example
{ } = Valid Format	{CCYYMMDD}
<b>Bold/Italics</b> = Developer's Worksheet Element	<b>PON</b>
Superscript = Developer's Worksheet Ref # DWS used in this mapping example:  LSR = Local Service Request RPL = Resale Private Line	<sup>LSR-1</sup>
<i>Italics</i> = Literal	<i>GOOD</i>
<u>Underline</u> = Apply code conversion, used with <b>Bold/Italics</b> . Code conversion tables can be found in the data dictionary of this disclosure.	<u><b>ACT</b></u>
[ ] = Segment notes for this line	[SI Segment repeats ...]
( ) = Element notes for this line	(This element states ...)
N	Counter 1...n
* = Element separator in this example and related data dictionary.	= Actual element separator in an EDI transaction.
> = Sub-element separator in this example and related data dictionary.	non-printable characters of "0x1f" = Actual sub-element separator in an EDI transaction.

ST\*850\*TRAN SET CONTROL #  
 BEG\*00\*SS\***PON**<sup>LSR-2</sup>\*\*PO Date(See Trading Partner Access Information)  
 REF\*11\***AN**<sup>LSR-7</sup>\***AN**<sup>LSR-20</sup>  
 REF\*JB\***PROJECT**<sup>LSR-28</sup>  
 REF\*SU\***RTR**<sup>LSR-28</sup>\***RTR**<sup>LSR-51</sup>  
 REF\*CO\***RPON**<sup>LSR-61</sup>\***RPON**<sup>LSR-52</sup>  
 REF\*12\***BAN1**<sup>LSR-52</sup>\***BAN1**<sup>LSR-10</sup>  
 REF\*1V\***RORD**<sup>LSR-10</sup>\***RORD**<sup>LSR-10</sup>  
 PAM\*48\***PG\_**<sup>LSR-10</sup>**of**<sup>LSR-10</sup>(1<sup>st</sup> 2 Bytes)\*EA  
 PAM\*47\***PG\_**<sup>LSR-10</sup>**of**<sup>LSR-10</sup>(2<sup>nd</sup> 2 Bytes)\*EA  
 PAM\*QO\***RSQTY**<sup>RPL-5</sup>\*EA  
 PAM\*KC\***DQTY**<sup>RPL-6</sup>\*EA  
 PAM\*1Q\***SECLOCQTY**<sup>RPL-41a</sup>\*EA  
 PAM\*1R\***SECLOCSEVDETQTY**<sup>RPL-108a</sup>\*EA  
 SAC\*N\*\*TI\*EXP [If this segment appears then **EXP**<sup>LSR-26</sup> = "Y"]  
 SAC\*N\*\*TI\*VT\*\*\*\*\***VTA**<sup>LSR-80</sup>  
 SAC\*N\*\*TI\*EEH [If this segment appears then **AENG**<sup>LSR-32</sup> = "Y"]  
 SAC\*N\*\*TI\*OAC [If this segment appears then **ALBR**<sup>LSR-33</sup> = "Y"]  
 DTM\*097\***D/SENT**{CCYYMMDD}<sup>LSR-12</sup>\***D/SENT**{HHMM}<sup>LSR-12</sup>  
 DTM\*150\***DDD**{CCYYMMDD}<sup>LSR-14</sup>  
 DTM\*270\***DATED**{CCYYMMDD}<sup>LSR-36</sup>  
 SI\*TI\*RE\***REQTYP**<sup>LSR-23</sup>  
 SI\*TI\*AA\***ACT**<sup>LSR-24</sup>  
 SI\*TI\*TY\***TOS**<sup>LSR-44</sup>  
 SI\*TI\*NC\***NC**<sup>LSR-46</sup>

SI\*TI\*NI\* **NCI**<sup>LSR-48</sup>  
 SI\*TI\*NJ\* **SEC NCI**<sup>LSR-50</sup>  
 PID\*S\*\*TI\*AO\*\*\*SO-RSQ\* **AGAUTH**<sup>LSR-35</sup>  
 PID\*S\*\*TI\*BI\*\*\*SO-RSQ\* **FBI**<sup>RPL-76</sup>  
 PID\*S\*\*TI\*PENDING\*\*\*SO-RSQ\* **PENDING ORDER**<sup>LSR-108b</sup>  
 PWK\*DW\*NS\*1\*DG\*91\* **DRC**<sup>LSR-98</sup>  
 N9\*H7\*ORI\* **LSR\*\*\*\*2W>MANUAL IND**<sup>LSR-108a</sup>  
 MTX\*\***REMARKS**<sup>LSR-108</sup>  
 N1\*78\* **CCNA**<sup>LSR-1</sup>  
 PER\*AG\* **INIT**<sup>LSR-81</sup>\*TE\* **TEL NO**<sup>LSR-82</sup>\*FX\* **FAX NO**<sup>LSR-84</sup>\*EM\* **EMAIL**<sup>LSR-83</sup>  
 PER\*CN\* **IMPCON**<sup>LSR-91</sup>\*TE\* **TEL NO**<sup>LSR-92</sup>\*BN\* **PAGER**<sup>LSR-93</sup>  
 PER\*AL\* **ALT IMPCON**<sup>LSR-94</sup>\*TE\* **TEL NO**<sup>LSR-95</sup>\*BN\* **PAGER**<sup>LSR-96</sup>  
 N1\*AN\* **AUTHNM**<sup>LSR-37</sup>  
 N1\*DG\* **DSGCON**<sup>LSR-97</sup>  
 PER\*DE\*\*TE\* **TEL NO**<sup>LSR-99</sup>\*FX\* **FAX NO**<sup>LSR-100</sup>  
 N1\*X1\* **BILLNM**<sup>RPL-77</sup>  
 N2\* **SBILLNM**<sup>RPL-78</sup>  
 N4\*\* **STATE**<sup>RPL-83</sup>\* **ZIP**<sup>RPL-84</sup>  
 NX2\*01\* **SANO**<sup>RPL-79b</sup>  
 NX2\*02\* **SASN**<sup>RPL-79e</sup>  
 NX2\*03\* **SASD**<sup>RPL-79d</sup>  
 NX2\*07\* **CITY**<sup>RPL-82</sup>  
 NX2\*32\* **FLOOR**<sup>RPL-80</sup>  
 NX2\*35\* **ROOM/MAIL STOP**<sup>RPL-81</sup>  
 NX2\*40\* **SASS**<sup>RPL-79g</sup>  
 NX2\*59\* **SAPR**<sup>RPL-79a</sup>  
 NX2\*61\* **SASF**<sup>RPL-79c</sup>  
 NX2\*62\* **SATH**<sup>RPL-79f</sup>  
 PER\*BI\* **BILLCON**<sup>RPL-85</sup>\*TE\* **TEL NO**<sup>RPL-86</sup>  
 SI\*TI\*AF\* **AFT**<sup>RPL-78a</sup>

### Primary Location Section

PO1\*n\*1\*EA\*\*\*ZZ\* **RPL\_PLS**  
 SI\*TI\*LT\*02 (designates "primary")  
 SI\*TI\*LS\* **RLSO**<sup>RPL-26</sup>  
 SI\*TI\*IW\* **IWO**<sup>RPL-35</sup>  
 PID\*S\*\*TI\*ANV\*\*\*SO-RSQ\* **ANV**<sup>RPL-10b</sup>  
 REF\*IX\* **LOCNUM**<sup>RPL-9\*</sup> **LOCNUM**  
 N9\*H7\*LOC\*AA/  
 MTX\*\* **AAI**<sup>RPL-25</sup>  
 N9\*L1\*ALOC\* **RPLPRI**  
 MTX\*\* **ALOC**<sup>RPL-30</sup>  
 N9\*L1\*ACC\* **RPLPRI**  
 MTX\*\* **ACC**<sup>RPL-39</sup>  
 N1\*IT\* **PRIOLOC**<sup>RPL-10</sup>\*93\* **LIT**<sup>RPL-8</sup>  
 N2\* **NAME**<sup>RPL-10a</sup>  
 N4\*\* **STATE**<sup>RPL-28\*</sup> **ZIP**<sup>RPL-29\*\*</sup> **RJ\* CALA**<sup>RPL-29a</sup>  
 NX2\*01\* **SANO**<sup>RPL-13</sup>  
 NX2\*02\* **SASN**<sup>RPL-16</sup>  
 NX2\*03\* **SASD**<sup>RPL-15</sup>  
 NX2\*05\* **BOX**<sup>RPL-26c</sup>  
 NX2\*06\* **ROUTE**<sup>RPL-26b</sup>  
 NX2\*07\* **CITY**<sup>RPL-27</sup>  
 NX2\*39\* **AHN**<sup>RPL-26a</sup>  
 NX2\*40\* **SASS**<sup>RPL-18</sup>  
 NX2\*59\* **SAPR**<sup>RPL-12</sup>

NX2\*61\***SASF**<sup>RPL-14</sup>  
 NX2\*62\***SATH**<sup>RPL-17</sup>  
 NX2\***LD1**<sup>RPL-19</sup>\***LV1**<sup>RPL-20</sup>  
 NX2\***LD2**<sup>RPL-21</sup>\***LV2**<sup>RPL-22</sup>  
 NX2\***LD3**<sup>RPL-23</sup>\***LV3**<sup>RPL-24</sup>  
 PER\*CA\***LCON**<sup>RPL-31</sup>\*TE\***ACTEL NO**<sup>RPL-32</sup>  
 PER\*AL\***ALCON**<sup>RPL-33</sup>\*TE\***AACTEL**<sup>RPL-34</sup>  
 SI\*TI\*AF\***AFT**<sup>RPL-11</sup>

## Secondary Location Section

PO1\*n\*1\*EA\*\*\*ZZ\***RPL\_SLS** [PO1 Loop repeats **SECLOCQTY**<sup>RPL41a</sup> times]  
 SI\*TI\*LT\*04 (designates "secondary")  
 SI\*TI\*LS\***RLSO**<sup>RPL-60</sup>  
 SI\*TI\*IW\***IWO**<sup>RPL-69</sup>  
 PID\*S\*TI\*ANV\*\*\*SO-RSQ\***ANV**<sup>RPL-44b</sup>  
 REF\*IX\***LOCNUM**<sup>RPL-43</sup>\***LOCNUM**  
 N9\*H7\*LOC\*AA/  
 MTX\*\***AAI**<sup>RPL-59</sup>  
 N9\*L1\*ALOC\***RPLSEC**  
 MTX\*\***ALOC**<sup>RPL-64</sup>  
 N9\*L1\*ACC\***RPLSEC**  
 MTX\*\***ACC**<sup>RPL-73</sup>  
 N1\*IT\***SECLOC**<sup>RPL-44</sup>\*93\***LIT**<sup>RPL-42</sup>  
 N2\***NAME**<sup>RPL-44a</sup>  
 N4\*\***STATE**<sup>RPL-62</sup>\***ZIP**<sup>RPL-63</sup>\*\*RJ\***CALA**<sup>RPL-63a</sup>  
 NX2\*01\***SANO**<sup>RPL-47</sup>  
 NX2\*02\***SASN**<sup>RPL-50</sup>  
 NX2\*03\***SASD**<sup>RPL-49</sup>  
 NX2\*05\***BOX**<sup>RPL-60c</sup>  
 NX2\*06\***ROUTE**<sup>RPL-60b</sup>  
 NX2\*07\***CITY**<sup>RPL-61</sup>  
 NX2\*39\***AHN**<sup>RPL-60a</sup>  
 NX2\*40\***SASS**<sup>RPL-52</sup>  
 NX2\*59\***SAPR**<sup>RPL-46</sup>  
 NX2\*61\***SASF**<sup>RPL-48</sup>  
 NX2\*62\***SATH**<sup>RPL-51</sup>  
 NX2\***LD1**<sup>RPL-53</sup>\***LV1**<sup>RPL-54</sup>  
 NX2\***LD2**<sup>RPL-55</sup>\***LV2**<sup>RPL-56</sup>  
 NX2\***LD3**<sup>RPL-57</sup>\***LV3**<sup>RPL-58</sup>  
 PER\*CA\***LCON**<sup>RPL-65</sup>\*TE\***ACTEL NO**<sup>RPL-66</sup>  
 PER\*AL\***ALCON**<sup>RPL-67</sup>\*TE\***AACTEL**<sup>RPL-68</sup>  
 SI\*TI\*AF\***AFT**<sup>RPL-45</sup>

## Disconnect Information

PO1\*n\*1\*EA\*\*\*ZZ\***RPL\_DISC**  
 SI\*TI\*ED\***DISC ECCKT**<sup>RPL-90</sup>

## Remarks Information

PO1\*n\*1\*EA\*\*\*ZZ\***RPL\_REM**  
 N9\*H7\*ORI\***RPL**\*\*\*\*2W>**MANUAL IND**<sup>RPL-91a</sup>  
 MTX\*\***REMARKS**<sup>RPL-91</sup>

## Primary Location Service Details

PO1\*n\*1\*EA\*\*\*ZZ\***RPL\_PLSD**

SI\*TI\*LT\*02 (designates "primary")  
SI\*TI\*SA\*LNA<sup>RPL-94</sup>  
SI\*TI\*CN\*ECCKT<sup>RPL-104</sup>  
PID\*X\*\*TI\*CFA\*CFA<sup>RPL-105</sup>  
REF\*AE\*SAN<sup>RPL-94a</sup>  
SLN\*/W\*n\*A\*IWJQ<sup>RPL-101</sup>\*EA\*\*\*\*EQ\*IWJK<sup>RPL-102</sup> [SLN Loop may repeat per Inside Wiring Pair]

### Secondary Location Service Details

PO1\*n\*1\*EA\*\*\*ZZ\*RPL\_SLSD [PO1 Loop repeats **SECLOCSEVDEQTY**<sup>RPL-108a</sup> times]  
SI\*TI\*LT\*04 (designates "secondary")  
SI\*TI\*SA\*LNA<sup>RPL-111</sup>  
SI\*TI\*CN\*ECCKT<sup>RPL-119</sup>  
PID\*X\*\*TI\*CFA\*CFA<sup>RPL-120</sup>  
REF\*IX\*LOCNUM<sup>RPL-109</sup>\*LOCNUM  
SLN\*/W\*n\*A\*IWJQ<sup>RPL-116</sup>\*EA\*\*\*\*EQ\*IWJK<sup>RPL-117</sup> [SLN Loop may repeat per Inside Wiring Pair]

**IMPORTANT NOTE:** If none of the above PO1 loops is applicable, a "Dummy" PO1 loop is used in this format:

PO1\*DUMMY\*1\*EA\*\*\*ZZ\*DD

CTT\*Number of PO1 Segments

SE\*No of Segments\*TRAN SET CONTROL#

### 23.5.2 860 Private Line Supplemental Service Request (860PL) – Version 4020

The 860PL is identical to the 850PL except the following exceptions:

ST\*860\*TRAN SET CONTROL #

BCH\*<sup>LSR-25</sup>**SUP**\*SS\*<sup>LSR-2</sup>**PON**\*\*<sup>LSR-3</sup>**VER**\*PO Date(See Trading Partner Access Information )

POC\*n\*RZ\*\*\*\*\*ZZ\*?? Where ?? = "RPL\_PLS" or "RPL\_SLS" or "RPL\_DISC" or "RPL\_REM" or "RPL\_PLSD" or "RPL\_SLSD"

**IMPORTANT NOTE:** Dummy POC loops are not required on 860 Transactions.

CTT\*Number of POC Segments

SE\*Number of Segments\*TRAN SET CONTROL #



## 23.6 DATA DICTIONARY

### 23.6.1 850 Resale Private Line (850PL)

Functional Group ID=**PO**

#### Introduction:

The Resale Private Line (850PL) is used by the Co-Provider to initiate the resale of primary and secondary service with details.

This implementation guideline is based on the following:

1. LSOG 5, when applicable, and Qwest assigned fields
2. ANSI ASC X12 Version 4020
3. TCIF/SOSC Guidelines, ELMS5

#### Notes:

This 850 Transaction includes the mappings for Local Service Request and Resale Private Line.

#### Heading:

	<u>Pos. No.</u>	<u>Seg. ID</u>	<u>Name</u>	<u>Req. Des.</u>	<u>Max.Use</u>	<u>Loop Repeat</u>	<u>Notes and Comments</u>
M	0100	ST	Transaction Set Header	M	1		
M	0200	BEG	Beginning Segment for Purchase Order	M	1		
	0500	REF	Reference Identification	O	>1		
	0950	PAM	Period Amount	O	10		
						25	
	1200	SAC	Service, Promotion, Allowance, or Charge Information	O	1		
	1500	DTM	Date/Time Reference	O	10		
	1850	SI	Service Characteristic Identification	O	>1		
	1900	PID	Product/Item Description	O	200		
	2100	PWK	Paperwork	O	25		
						1000	
	2950	N9	Reference Identification	O	1		
	3000	MTX	Text	O	>1		
						200	
	3100	N1	Name	O	1		
	3600	PER	Administrative Communications Contact	O	>1		
						200	
	3100	N1	Name	O	1		
						200	

3100	N1	Name	O	1
3600	PER	Administrative Communications Contact	O	>1
LOOP ID - N1				200
3100	N1	Name	O	1
3200	N2	Additional Name Information	O	2
3400	N4	Geographic Location	O	>1
3450	NX2	Location ID Component	O	>1
3600	PER	Administrative Communications Contact	O	>1
3650	SI	Service Characteristic Identification	O	>1

**Detail:**

	<u>Pos. No.</u>	<u>Seg. ID</u>	<u>Name</u>	<u>Req. Des.</u>	<u>Max.Use</u>	<u>Loop Repeat</u>	<u>Notes and Comments</u>
	LOOP ID - PO1					100000	
M	0100	PO1	Baseline Item Data - Primary Location Section	M	1		n1
	0180	SI	Service Characteristic Identification	O	>1		
	LOOP ID - PID					1000	
	0500	PID	Product/Item Description	O	1		
	1000	REF	Reference Identification	O	>1		
	LOOP ID - N9					1000	
	3300	N9	Reference Identification	O	1		
	3400	MTX	Text	O	>1		
	LOOP ID - N9					1000	
	3300	N9	Reference Identification	O	1		
	3400	MTX	Text	O	>1		
	LOOP ID - N9					1000	
	3300	N9	Reference Identification	O	1		
	3400	MTX	Text	O	>1		
	LOOP ID - N1					200	
	3500	N1	Name	O	1		
	3600	N2	Additional Name Information	O	2		
	3800	N4	Geographic Location	O	1		
	3850	NX2	Location ID Component	O	>1		
	4000	PER	Administrative Communications Contact	O	3		
	4050	SI	Service Characteristic Identification	O	>1		
	LOOP ID - PO1					100000	
M	0100	PO1	Baseline Item Data - Secondary Location Section	M	1		n2
	0180	SI	Service Characteristic Identification	O	>1		
	LOOP ID - PID					1000	
	0500	PID	Product/Item Description	O	1		
	1000	REF	Reference Identification	O	>1		
	LOOP ID - N9					1000	
	3300	N9	Reference Identification	O	1		

	3400	MTX	Text	O	>1	
	LOOP ID - N9					1000
	3300	N9	Reference Identification	O	1	
	3400	MTX	Text	O	>1	
	LOOP ID - N9					1000
	3300	N9	Reference Identification	O	1	
	3400	MTX	Text	O	>1	
	LOOP ID - N1					200
	3500	N1	Name	O	1	
	3600	N2	Additional Name Information	O	2	
	3800	N4	Geographic Location	O	1	
	3850	NX2	Location ID Component	O	>1	
	4000	PER	Administrative Communications Contact	O	3	
	4050	SI	Service Characteristic Identification	O	>1	
	LOOP ID - PO1					100000
M	0100	PO1	Baseline Item Data - Disconnect Information	M	1	n3
	0180	SI	Service Characteristic Identification	O	>1	
	LOOP ID - PO1					100000
M	0100	PO1	Baseline Item Data - Remarks Information	M	1	n4
	LOOP ID - N9					1000
	3300	N9	Reference Identification	O	1	
	3400	MTX	Text	O	>1	
	LOOP ID - PO1					100000
M	0100	PO1	Baseline Item Data - Primary Location Service Details	M	1	n5
	0180	SI	Service Characteristic Identification	O	>1	
	LOOP ID - PID					1000
	0500	PID	Product/Item Description	O	1	
	1000	REF	Reference Identification	O	>1	
	LOOP ID - SLN					>1
	4700	SLN	Subline Item Detail	O	1	
	LOOP ID - PO1					100000
M	0100	PO1	Baseline Item Data - Secondary Location Service Details	M	1	n6
	0180	SI	Service Characteristic Identification	O	>1	
	LOOP ID - PID					1000
	0500	PID	Product/Item Description	O	1	
	1000	REF	Reference Identification	O	>1	
	LOOP ID - SLN					>1
	4700	SLN	Subline Item Detail	O	1	
	LOOP ID - PO1					100000
M	0100	PO1	Baseline Item Data - Dummy (DA)	M	1	n7

## Summary:

<u>Pos. No.</u>	<u>Seg. ID</u>	<u>Name</u>	<u>Req. Des.</u>	<u>Max.Use</u>	<u>Loop Repeat</u>	<u>Notes and Comments</u>
		LOOP ID - CTT			1	
0100	CTT	Transaction Totals	O	1		n8
M	0300	SE	Transaction Set Trailer	M	1	

### Transaction Set Notes

1. PO102 is required.
2. PO102 is required.
3. PO102 is required.
4. PO102 is required.
5. PO102 is required.
6. PO102 is required.
7. PO102 is required.
8. The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

**Segment:** **ST** Transaction Set Header

**Position:** 0100

**Loop:**

**Level:** Heading

**Usage:** Mandatory

**Max Use:** 1

**Purpose:** To indicate the start of a transaction set and to assign a control number

**Syntax Notes:**

**Semantic Notes:**

- 1 The transaction set identifier (ST01) is used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).
- 2 The implementation convention reference (ST03) is used by the translation routines of the interchange partners to select the appropriate implementation convention to match the transaction set definition.

**Comments:**

**Notes:** ST\*850\*TRAN SET CONTROL#

#### Data Element Summary

	<u>Ref.</u> <u>Des.</u>	<u>Data</u> <u>Element</u>	<u>Name</u>		
M	ST01	143	<b>Transaction Set Identifier Code</b> Code uniquely identifying a Transaction Set 850 Purchase Order	M	ID 3/3
M	ST02	329	<b>Transaction Set Control Number</b> Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set	M	AN 4/9

**Segment:** **BEG** Beginning Segment for Purchase Order  
**Position:** 0200  
**Loop:**  
**Level:** Heading  
**Usage:** Mandatory  
**Max Use:** 1  
**Purpose:** To indicate the beginning of the Purchase Order Transaction Set and transmit identifying numbers and dates

**Syntax Notes:**  
**Semantic Notes:** 1 BEG05 is the date assigned by the purchaser to purchase order.

**Comments:**  
**Notes:** BEG\*00\*SS\*PON (LSR-2)\*\*PO Date(See Trading Partner Access Information)

**Data Element Summary**

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>		
	<u>Des.</u>	<u>Element</u>			
M	BEG01	353	<b>Transaction Set Purpose Code</b> Code identifying purpose of transaction set 00 Original	M	ID 2/2
M	BEG02	92	<b>Purchase Order Type Code</b> Code specifying the type of Purchase Order SS Supply or Service Order	M	ID 2/2
M	BEG03	324	<b>Purchase Order Number</b> Identifying number for Purchase Order assigned by the orderer/purchaser PON (LSR-2) = Purchase Order Number	M	AN 1/22
M	BEG05	373	<b>Date</b> Date expressed as CCYYMMDD PO Date = Purchase Order Date(See Trading Partner Access Information)	M	DT 8/8

**Segment:** **REF** Reference Identification  
**Position:** 0500  
**Loop:**  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To specify identifying information  
**Syntax Notes:**

- 1 At least one of REF02 or REF03 is required.
- 2 If either C04003 or C04004 is present, then the other is required.
- 3 If either C04005 or C04006 is present, then the other is required.

**Semantic Notes:**

- 1 REF04 contains data relating to the value cited in REF02.

**Comments:**  
**Notes:**

REF\*11\*AN (LSR-7)\*AN  
 REF\*JB\*PROJECT (LSR-20)  
 REF\*SU\*RTR (LSR-28)\*RTR  
 REF\*CO\*RPON (LSR-51)\*RPON  
 REF\*12\*BAN1 (LSR-61)\*BAN1  
 REF\*1V\*RORD (LSR-52)\*RORD

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	REF01	128	<b>Reference Identification Qualifier</b>	M	ID 2/3
			Code qualifying the Reference Identification		
			11 Account Number		
			Number identifies a telecommunications industry account		
			12 Billing Account		
			Account number under which billing is rendered		
			1V Related Vendor Order Number		
			A vendor's order number that is in addition to a primary order number		
			CO Customer Order Number		
			JB Job (Project) Number		
			SU Special Processing Code		
			Unique code identifying the special handling requirements for the claim		
	REF02	127	<b>Reference Identification</b>	X	AN 1/30
			Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier		
			AN (LSR-7) = Account Number		
			PROJECT (LSR-20) = Project Identification		
			RTR (LSR-28) = Response Type Requested		
			RPON (LSR-51) = Related Purchase Order Number		
			BAN1 (LSR-61) = Billing Account Number 1		
			RORD (LSR-52) = Related Order Number		
	REF03	352	<b>Description</b>	X	AN 1/80
			A free-form description to clarify the related data elements and their content		
			"AN"		
			"RTR"		
			"RPON"		

"BAN1"  
"RORD"



**Segment:** **PAM** Period Amount  
**Position:** 0950  
**Loop:**  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** 10  
**Purpose:** To indicate a quantity, and/or amount for an identified period  
**Syntax Notes:**

- 1 If any of PAM01 PAM02 or PAM03 is present, then all are required.
- 2 At least one of PAM02 PAM05 or PAM14 is required.
- 3 If either PAM04 or PAM05 is present, then the other is required.
- 4 If either PAM06 or PAM07 is present, then the other is required.
- 5 If PAM07 is present, then at least one of PAM08 or PAM09 is required.
- 6 If PAM07 is present, then PAM06 is required.
- 7 If PAM08 is present, then PAM07 is required.
- 8 If PAM09 is present, then PAM07 is required.
- 9 If PAM10 is present, then at least one of PAM11 or PAM12 is required.
- 10 If PAM11 is present, then PAM10 is required.
- 11 If either PAM13 or PAM14 is present, then the other is required.

**Semantic Notes:**

- 1 PAM10, PAM11, or PAM12 are used when two dates are required.
- 2 PAM15 indicates whether the monetary amount identified in PAM05 is a net or gross value. A "Y" indicates amount is a gross value; an "N" indicates amount is a net value.

**Comments:**

**Notes:**  
PAM\*48\*PG\_of\_(LSR-10)(1st 2 Bytes)\*EA  
PAM\*47\*PG\_of\_(LSR-10)(2nd 2 Bytes)\*EA  
PAM\*QO\*RSQTY (RPL-5)\*EA  
PAM\*KC\*DQTY (RPL-6)\*EA  
PAM\*1Q\*SECLOCQTY (RPL-41a)\*EA  
PAM\*1R\*SECLOCSEVDETQTY (RPL-108a)\*EA

**Data Element Summary**

<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
<b>PAM01</b>	<b>673</b>	<b>Quantity Qualifier</b>	<b>X</b>	<b>ID 2/2</b>
		Code specifying the type of quantity		
		1Q Total Resource (Quantity)		
		Total amount of the resources available for the total duration of the task or activity		
		1R Level Resource (Quantity)		
		The amount of resources available for each time unit for the duration of the task or activity		
		47 Primary Net Quantity		
		48 Secondary Net Quantity		
		KC Net Quantity Decrease		
		The resultant quantity represents a net decrease to a previously transmitted quantity, after adjustments have been made		
		QO Operating Quantity		
<b>PAM02</b>	<b>380</b>	<b>Quantity</b>	<b>X</b>	<b>R 1/15</b>
		Numeric value of quantity		

First 2 bytes of PG\_of\_ (LSR-10)  
 Second 2 bytes of PG\_of\_ (LSR-10)  
 RSQTY (RPL-5) = Resale Quantity  
 DQTY (RPL-6) = Disconnect Quantity  
 SECLOCQTY (RPL-41a) = Secondary Location Quantity  
 SECLOCSEVDETQTY (RPL-108a) = Secondary Location Service  
 Details Quantity

	<b>PAM03</b>	<b>C001</b>	<b>Composite Unit of Measure</b>	<b>X</b>	
			To identify a composite unit of measure (See Figures Appendix for examples of use)		
<b>M</b>	<b>C00101</b>	<b>355</b>	<b>Unit or Basis for Measurement Code</b>	<b>M</b>	<b>ID 2/2</b>
			Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken		
			EA                      Each		

**Segment:** **SAC** Service, Promotion, Allowance, or Charge Information  
**Position:** 1200  
**Loop:** SAC Optional  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** 1  
**Purpose:** To request or identify a service, promotion, allowance, or charge; to specify the amount or percentage for the service, promotion, allowance, or charge

- Syntax Notes:**
- 1 At least one of SAC02 or SAC03 is required.
  - 2 If either SAC03 or SAC04 is present, then the other is required.
  - 3 If either SAC06 or SAC07 is present, then the other is required.
  - 4 If either SAC09 or SAC10 is present, then the other is required.
  - 5 If SAC11 is present, then SAC10 is required.
  - 6 If SAC13 is present, then at least one of SAC02 or SAC04 is required.
  - 7 If SAC14 is present, then SAC13 is required.
  - 8 If SAC16 is present, then SAC15 is required.

- Semantic Notes:**
- 1 If SAC01 is "A" or "C", then at least one of SAC05, SAC07, or SAC08 is required.
  - 2 SAC05 is the total amount for the service, promotion, allowance, or charge.  
If SAC05 is present with SAC07 or SAC08, then SAC05 takes precedence.
  - 3 SAC08 is the allowance or charge rate per unit.
  - 4 SAC10 and SAC11 is the quantity basis when the allowance or charge quantity is different from the purchase order or invoice quantity.  
SAC10 and SAC11 used together indicate a quantity range, which could be a dollar amount, that is applicable to service, promotion, allowance, or charge.
  - 5 SAC13 is used in conjunction with SAC02 or SAC04 to provide a specific reference number as identified by the code used.
  - 6 SAC14 is used in conjunction with SAC13 to identify an option when there is more than one option of the promotion.
  - 7 SAC16 is used to identify the language being used in SAC15.

- Comments:**
- 1 SAC04 may be used to uniquely identify the service, promotion, allowance, or charge. In addition, it may be used in conjunction with SAC03 to further define SAC02.
  - 2 In some business applications, it is necessary to advise the trading partner of the actual dollar amount that a particular allowance, charge, or promotion was based on to reduce ambiguity. This amount is commonly referred to as "Dollar Basis Amount". It is represented in the SAC segment in SAC10 using the qualifier "DO" - Dollars in SAC09.

**Notes:**

SAC\*N\*\*TI\*EXP [If this segment appears then EXP (LSR-26)="Y"]  
SAC\*N\*\*TI\*VT\*\*\*\*\*VTA (LSR-80)  
SAC\*N\*\*TI\*EEH [If this segment appears then AENG (LSR-32)="Y"]  
SAC\*N\*\*TI\*OAC [If this segment appears then ALBR (LSR-33)="Y"]

#### Data Element Summary

Ref.	Data		
<u>Des.</u>	<u>Element</u>	<u>Name</u>	
<u>Attributes</u>			
M	SAC01	248 Allowance or Charge Indicator	M ID 1/1

		Code which indicates an allowance or charge for the service specified		
		N	No Allowance or Charge	
<b>SAC03</b>	<b>559</b>	<b>Agency Qualifier Code</b>		<b>X ID 2/2</b>
		Code identifying the agency assigning the code values		
		TI	Telecommunications Industry	
<b>SAC04</b>	<b>1301</b>	<b>Agency Service, Promotion, Allowance, or Charge Code</b>		<b>X AN 1/10</b>
		Agency maintained code identifying the service, promotion, allowance, or charge		
		EEH	Engineering Charge	
		EXP	Expedited Service Charge	
		OAC	Overtime Loading	
		VT	Variable Term Contract Pricing Plan	
<b>SAC15</b>	<b>352</b>	<b>Description</b>		<b>X AN 1/80</b>
		A free-form description to clarify the related data elements and their content		
		VTA (LSR-80) = Variable Term Agreement		

**Segment:** **DTM** Date/Time Reference  
**Position:** 1500  
**Loop:**  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** 10  
**Purpose:** To specify pertinent dates and times  
**Syntax Notes:**

- 1 At least one of DTM02 DTM03 or DTM05 is required.
- 2 If DTM04 is present, then DTM03 is required.
- 3 If either DTM05 or DTM06 is present, then the other is required.

**Semantic Notes:**

**Comments:**

**Notes:**

DTM\*097\*D/TSENT{CCYYMMDD} (LSR-12)\*D/TSENT{HHMM} (LSR-12)  
 DTM\*150\*DDD{CCYYMMDD} (LSR-14)  
 DTM\*270\*DATED{CCYYMMDD} (LSR-36)

**Data Element Summary**

	<u>Ref.</u>	<u>Data</u>	<u>Element</u>	<u>Name</u>		
M	DTM01	374	Date/Time Qualifier		M	ID 3/3
				Code specifying type of date or time, or both date and time		
				097 Transaction Creation 150 Service Period Start 270 Date Filed		
	DTM02	373	Date		X	DT 8/8
			Date expressed as CCYYMMDD			
			D/TSENT (LSR-12) = Date Sent			
			DDD (LSR-14) = Desired Due Date			
			DATED (LSR-36) = Date of Agency Authorization			
	DTM03	337	Time		X	TM 4/8
			Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)			
			D/TSENT{HHMM} (LSR-12) = Time Sent			

**Segment:** **SI** Service Characteristic Identification

**Position:** 1850

**Loop:**

**Level:** Heading

**Usage:** Optional

**Max Use:** >1

**Purpose:** To specify service characteristic data

**Syntax Notes:**

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

**Semantic Notes:**

**Comments:**

- 1 SI01 defines the source for each of the service characteristics qualifiers.

**Notes:**

SI\*TI\*RE\*REQTYP (LSR-23)  
 SI\*TI\*AA\*ACT (LSR-24)  
 SI\*TI\*TY\*TOS (LSR-44)  
 SI\*TI\*NC\*NC (LSR-46)  
 SI\*TI\*NI\*NCI (LSR-48)  
 SI\*TI\*NJ\*SEC NCI (LSR-50)

#### Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
	<b>Attributes</b>				
M	SI01	559	<b>Agency Qualifier Code</b>	M	ID 2/2
			Code identifying the agency assigning the code values		
			TI Telecommunications Industry		
M	SI02	1000	<b>Service Characteristics Qualifier</b>	M	AN 2/2
			Code from an industry code list qualifying the type of service characteristics		
			AA Account Activity		
			NC Network Channel		
			NI Network Channel Interface		
			NJ Secondary Network Channel Interface		
			RE Requisition Type		
			TY Type of Service		
M	SI03	234	<b>Product/Service ID</b>	M	AN 1/48
			Identifying number for a product or service		
			ACT (LSR-24) = Activity		
			A = (DWS: N-New Installation)		
			D = (DWS: D-Disconnect of Entire Account)		
			M = (DWS: M-Inside Move (CO, IA, MN only))		
			C = (DWS: C-Change)		
			V = (DWS: V-Conversion As Specified)		
			W = (DWS: W-Conversion As Is)		
			T = (DWS: T-Outside Move (T/F))		

REQTYP (LSR-23) = Requisition Type and Status  
TOS (LSR-44) = Type of Service  
NC (LSR-46) = Network Channel Code  
NCI (LSR-48) = Network Channel Interface Code  
SEC NCI (LSR-50) = Secondary Network Channel Interface Code

**Segment:** **PID** Product/Item Description

**Position:** 1900

**Loop:**

**Level:** Heading

**Usage:** Optional

**Max Use:** 200

**Purpose:** To describe a product or process in coded or free-form format

**Syntax Notes:**

- 1 If PID04 is present, then PID03 is required.
- 2 At least one of PID04 or PID05 is required.
- 3 If PID07 is present, then PID03 is required.
- 4 If PID08 is present, then PID04 is required.
- 5 If PID09 is present, then PID05 is required.

**Semantic Notes:**

- 1 Use PID03 to indicate the organization that publishes the code list being referred to.
- 2 PID04 should be used for industry-specific product description codes.
- 3 PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
- 4 PID09 is used to identify the language being used in PID05.

**Comments:**

- 1 If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
- 2 Use PID06 when necessary to refer to the product surface or layer being described in the segment.
- 3 PID07 specifies the individual code list of the agency specified in PID03.

**Notes:**

PID\*S\*\*TI\*AO\*\*\*SO-RSQ\*AGAUTH (LSR-35)  
 PID\*S\*\*TI\*BI\*\*\*SO-RSQ\*FBI (RPL-76)  
 PID\*S\*\*TI\*PENDING\*\*\*SO-RSQ\*PENDING ORDER (LSR-108b)

#### Data Element Summary

Ref. Des.	Data Element	Name		
<b>M</b>	<b>PID01</b>	<b>349</b>	<b>Item Description Type</b>	<b>M ID 1/1</b>
			Code indicating the format of a description	
			S Structured (From Industry Code List)	
	<b>PID03</b>	<b>559</b>	<b>Agency Qualifier Code</b>	<b>X ID 2/2</b>
			Code identifying the agency assigning the code values	
			TI Telecommunications Industry	
	<b>PID04</b>	<b>751</b>	<b>Product Description Code</b>	<b>X AN 1/12</b>
			A code from an industry code list which provides specific data about a product characteristic	
			AO Agency Authorization Status	
			BI Final Bill Information Indicator	
			PENDING Pending Order Indicator	
	<b>PID07</b>	<b>822</b>	<b>Source Subqualifier</b>	<b>O AN 1/15</b>
			A reference that indicates the table or text maintained by the Source Qualifier	
			SO-RSQ Service Order - Reseller Questions list	



**PID08 1073 Yes/No Condition or Response Code O ID 1/1**

Code indicating a Yes or No condition or response

FBI (RPL-76) = Final Bill Information Indicator

N = (DWS: E-Existing)

Y = (DWS: D-Different)

AGAUTH (LSR-35) = Agency Authorization Status

PENDING ORDER (LSR-108b) = Pending Order

Segment: **PWK** Paperwork

Position: 2100

Loop:

Level: Heading

Usage: Optional

Max Use: 25

Purpose: To identify the type or transmission or both of paperwork or supporting information

Syntax Notes: 1 If either PWK05 or PWK06 is present, then the other is required.

Semantic Notes:

Comments:

- 1 PWK05 and PWK06 may be used to identify the addressee by a code number.
- 2 PWK07 may be used to indicate special information to be shown on the specified report.
- 3 PWK08 may be used to indicate action pertaining to a report.

Notes: PWK\*DW\*NS\*1\*DG\*91\*DRC (LSR-98)

#### Data Element Summary

Ref.	Data			
	<u>Des.</u>	<u>Element</u>	<u>Name</u>	
M	<u>Attributes</u> PWK01	755	<b>Report Type Code</b> Code indicating the title or contents of a document, report or supporting item DW Drawing(s)	M ID 2/2
	PWK02	756	<b>Report Transmission Code</b> Code defining timing, transmission method or format by which reports are to be sent NS Not Specified Indicates that a report will be transmitted via a nonspecified medium	O ID 1/2
	PWK03	757	<b>Report Copies Needed</b> The number of copies of a report that should be sent to the addressee 1 Always One	O NO 1/2
	PWK04	98	<b>Entity Identifier Code</b> Code identifying an organizational entity, a physical location, property or an individual DG Design Engineering Identifies the design engineer or office of the design engineer who will receive design specifications	O ID 2/3
	PWK05	66	<b>Identification Code Qualifier</b> Code designating the system/method of code structure used for Identification Code (67) 91 Assigned by Seller or Seller's Agent	X ID 1/2
	PWK06	67	<b>Identification Code</b> Code identifying a party or other code DRC (LSR-98) = Design Routing Code	X AN 2/80

**Segment:** **N9 Reference Identification**

**Position:** 2950

**Loop:** N9 Optional

**Level:** Heading

**Usage:** Optional

**Max Use:** 1

**Purpose:** To transmit identifying information as specified by the Reference Identification Qualifier

- Syntax Notes:**
- 1 At least one of N902 or N903 is required.
  - 2 If N906 is present, then N905 is required.
  - 3 If either C04003 or C04004 is present, then the other is required.
  - 4 If either C04005 or C04006 is present, then the other is required.

- Semantic Notes:**
- 1 N906 reflects the time zone which the time reflects.
  - 2 N907 contains data relating to the value cited in N902.

**Comments:**

**Notes:** N9\*H7\*ORI\*LSR\*\*\*\*2W>MANUAL IND (LSR-108a)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	N901	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification H7 Standard Clause	M	ID 2/3
	N902	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier ORI Order Instructions	X	AN 1/30
	N903	369	<b>Free-form Description</b> Free-form descriptive text "LSR"	X	AN 1/45
	N907	C040	<b>Reference Identifier</b> To identify one or more reference numbers or identification numbers as specified by the Reference Qualifier	O	
M	C04001	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification 2W Change Order Authority	M	ID 2/3
M	C04002	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier MANUAL IND (LSR-108a) = Manual Indicator	M	AN 1/30

**Segment:** **MTX** Text  
**Position:** 3000  
**Loop:** N9 Optional  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To specify textual data  
**Syntax Notes:**

- 1 If MTX01 is present, then MTX02 is required.
- 2 If MTX03 is present, then MTX02 is required.
- 3 If MTX05 is present, then MTX04 is required.

**Semantic Notes:**

- 1 MTX05 is the number of lines to advance before printing.

**Comments:**

- 1 If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

**Notes:** MTX\*\*REMARKS (LSR-108)

**Data Element Summary**

<u>Ref.</u> <u>Des.</u>	<u>Data</u> <u>Element</u>	<u>Name</u>		
<b>Attributes</b> MTX02	1551	<b>Message Text</b>		<b>X AN 1/4096</b>
		To transmit large volumes of message text		
		REMARKS (LSR-108) = Remarks		

**Segment:** **N1** Name  
**Position:** 3100  
**Loop:** N1 Optional  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** 1  
**Purpose:** To identify a party by type of organization, name, and code  
**Syntax Notes:**

- 1 At least one of N102 or N103 is required.
- 2 If either N103 or N104 is present, then the other is required.

**Semantic Notes:**  
**Comments:**

- 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
- 2 N105 and N106 further define the type of entity in N101.

**Notes:** N1\*78\*CCNA (LSR-1)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	N101	98	<b>Entity Identifier Code</b> Code identifying an organizational entity, a physical location, property or an individual	M	ID 2/3
		78	Service Requester		
	N102	93	<b>Name</b> Free-form name	X	AN 1/60
			CCNA (LSR-1) = Customer Carrier Name Abbreviation		

**Segment:** **PER Administrative Communications Contact**

**Position:** 3600

**Loop:** N1 Optional

**Level:** Heading

**Usage:** Optional

**Max Use:** >1

**Purpose:** To identify a person or office to whom administrative communications should be directed

- Syntax Notes:**
- 1 If either PER03 or PER04 is present, then the other is required.
  - 2 If either PER05 or PER06 is present, then the other is required.
  - 3 If either PER07 or PER08 is present, then the other is required.

**Semantic Notes:**

**Comments:**

**Notes:** PER\*AG\*INIT (LSR-81)\*TE\*TEL NO (LSR-82)\*FX\*FAX NO (LSR-84)\*EM\*EMAIL (LSR-83)

PER\*CN\*IMPCON (LSR-91)\*TE\*TEL NO (LSR-92)\*BN\*PAGER (LSR-93)  
 PER\*AL\*ALT IMPCON (LSR-94)\*TE\*TEL NO (LSR-95)\*BN\*PAGER (LSR-96)

**Data Element Summary**

Ref.	Data		
<u>Des.</u>	<u>Element</u>	<u>Name</u>	
M	PER01	366	<b>Contact Function Code</b> M ID 2/2
			Code identifying the major duty or responsibility of the person or group named
		AG	Agent
		AL	Alternate Contact
			Person to be contacted when the main contact is not available
		CN	General Contact
	PER02	93	<b>Name</b> O AN 1/60
			Free-form name
			INIT (LSR-81) = Initiator Identification
			IMPCON (LSR-91) = Implementation Contact
			ALT IMPCON (LSR-94) = Alternate Implementation Contact
	PER03	365	<b>Communication Number Qualifier</b> X ID 2/2
			Code identifying the type of communication number
		TE	Telephone
	PER04	364	<b>Communication Number</b> X AN 1/256
			Complete communications number including country or area code when applicable
			TEL NO (LSR-82) = Telephone Number
			TEL NO (LSR-92) = Telephone Number
			TEL NO (LSR-95) = Telephone Number
	PER05	365	<b>Communication Number Qualifier</b> X ID 2/2
			Code identifying the type of communication number
		BN	Beeper Number
		FX	Facsimile
	PER06	364	<b>Communication Number</b> X AN 1/256
			Complete communications number including country or area code when applicable

		FAX NO (LSR-84) = Facsimile Number		
		PAGER (LSR-93) = Pager Number		
		PAGER (LSR-96) = Pager Number		
<b>PER07</b>	<b>365</b>	<b>Communication Number Qualifier</b>	<b>X</b>	<b>ID 2/2</b>
		Code identifying the type of communication number		
		EM                      Electronic Mail		
<b>PER08</b>	<b>364</b>	<b>Communication Number</b>	<b>X</b>	<b>AN 1/256</b>
		Complete communications number including country or area code when applicable		
		EMAIL (LSR-83) = Electronic Mail Address		

**Segment:** **N1** Name  
**Position:** 3100  
**Loop:** N1 Optional  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** 1  
**Purpose:** To identify a party by type of organization, name, and code  
**Syntax Notes:**

- 1 At least one of N102 or N103 is required.
- 2 If either N103 or N104 is present, then the other is required.

**Semantic Notes:**  
**Comments:**

- 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
- 2 N105 and N106 further define the type of entity in N101.

**Notes:** N1\*AN\*AUTHNM (LSR-37)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	N101	98	<b>Entity Identifier Code</b> Code identifying an organizational entity, a physical location, property or an individual AN Authorized From A geographic location designated as an authorized pick-up or origin point for a shipment	M	ID 2/3
	N102	93	<b>Name</b> Free-form name AUTHNM (LSR-37) = Authorization Name	X	AN 1/60



**Segment:** **N1** Name  
**Position:** 3100  
**Loop:** N1 Optional  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** 1  
**Purpose:** To identify a party by type of organization, name, and code  
**Syntax Notes:**

- 1 At least one of N102 or N103 is required.
- 2 If either N103 or N104 is present, then the other is required.

**Semantic Notes:**  
**Comments:**

- 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
- 2 N105 and N106 further define the type of entity in N101.

**Notes:** N1\*DG\*DSGCON (LSR-97)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	
M	N101	98	Entity Identifier Code Code identifying an organizational entity, a physical location, property or an individual DG Design Engineering Identifies the design engineer or office of the design engineer who will receive design specifications	M ID 2/3
	N102	93	Name Free-form name DSGCON (LSR-97) = Design / Engineering Contact	X AN 1/60

**Segment:** **PER** Administrative Communications Contact  
**Position:** 3600  
**Loop:** N1 Optional  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To identify a person or office to whom administrative communications should be directed

**Syntax Notes:**  
**1** If either PER03 or PER04 is present, then the other is required.  
**2** If either PER05 or PER06 is present, then the other is required.  
**3** If either PER07 or PER08 is present, then the other is required.

**Semantic Notes:**

**Comments:**

**Notes:** PER\*DE\*\*TE\*TEL NO (LSR-99)\*FX\*FAX NO (LSR-100)

### Data Element Summary

Ref. Des.	Data Element	Name		
M	<b>PER01</b>	<b>366</b>	<b>Contact Function Code</b>	<b>M ID 2/2</b>
			Code identifying the major duty or responsibility of the person or group named DE Design Engineer	
	<b>PER03</b>	<b>365</b>	<b>Communication Number Qualifier</b>	<b>X ID 2/2</b>
			Code identifying the type of communication number TE Telephone	
	<b>PER04</b>	<b>364</b>	<b>Communication Number</b>	<b>X AN 1/256</b>
			Complete communications number including country or area code when applicable TEL NO (LSR-99) = Telephone Number	
	<b>PER05</b>	<b>365</b>	<b>Communication Number Qualifier</b>	<b>X ID 2/2</b>
			Code identifying the type of communication number FX Facsimile	
	<b>PER06</b>	<b>364</b>	<b>Communication Number</b>	<b>X AN 1/256</b>
			Complete communications number including country or area code when applicable FAX NO (LSR-100) = Facsimile Number	

**Segment:** **N1** Name  
**Position:** 3100  
**Loop:** N1 Optional  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** 1  
**Purpose:** To identify a party by type of organization, name, and code  
**Syntax Notes:**

- 1 At least one of N102 or N103 is required.
- 2 If either N103 or N104 is present, then the other is required.

**Semantic Notes:**  
**Comments:**

- 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
- 2 N105 and N106 further define the type of entity in N101.

**Notes:** N1\*X1\*BILLNM (RPL-77)

**Data Element Summary**

<b>Ref.</b>	<b>Data</b>	<b>Element</b>	<b>Name</b>	<b>Attributes</b>
<b>M</b>	<b>N101</b>	<b>98</b>	<b>Entity Identifier Code</b> Code identifying an organizational entity, a physical location, property or an individual X1 Mail to An address to which a specified item is to be mailed	<b>M ID 2/3</b>
	<b>N102</b>	<b>93</b>	<b>Name</b> Free-form name BILLNM (RPL-77) = Bill Name	<b>X AN 1/60</b>

**Segment:** **N2** Additional Name Information  
**Position:** 3200  
**Loop:** N1 Optional  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** 2  
**Purpose:** To specify additional names  
**Syntax Notes:**  
**Semantic Notes:**  
**Comments:**  
**Notes:** N2\*SBILLNM (RPL-78)

**Data Element Summary**

	<u>Ref.</u> <u>Des.</u> <u>Attributes</u>	<u>Data</u> <u>Element</u>	<u>Name</u>	
M	N201	93	Name Free-form name SBILLNM (RPL-78) = Secondary Billing Name	M AN 1/60

**Segment:** **N4 Geographic Location**

**Position:** 3400

**Loop:** N1 Optional

**Level:** Heading

**Usage:** Optional

**Max Use:** >1

**Purpose:** To specify the geographic place of the named party

- Syntax Notes:**
- 1 Only one of N402 or N407 may be present.
  - 2 If N406 is present, then N405 is required.
  - 3 If N407 is present, then N404 is required.

**Semantic Notes:**

- Comments:**
- 1 A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
  - 2 N402 is required only if city name (N401) is in the U.S. or Canada.

**Notes:** N4\*\*STATE (RPL-83)\*ZIP (RPL-84)

**Data Element Summary**

<u>Ref.</u>	<u>Data</u>	<u>Element</u>	<u>Name</u>		
<b>N402</b>	<b>156</b>	<b>State or Province Code</b>		<b>X</b>	<b>ID 2/2</b>
			Code (Standard State/Province) as defined by appropriate government agency		
			STATE (RPL-83) = State/Province		
<b>N403</b>	<b>116</b>	<b>Postal Code</b>		<b>O</b>	<b>ID 3/15</b>
			Code defining international postal zone code excluding punctuation and blanks (zip code for United States)		
			ZIP (RPL-84) = ZIP/Postal Code		

**Segment:** **NX2** Location ID Component

**Position:** 3450

**Loop:** N1 Optional

**Level:** Heading

**Usage:** Optional

**Max Use:** >1

**Purpose:** To define types and values of a geographic location

**Syntax Notes:**

**Semantic Notes:**

**Comments:**

**Notes:**

NX2\*01\*SANO (RPL-79b)  
 NX2\*02\*SASN (RPL-79e)  
 NX2\*03\*SASD (RPL-79d)  
 NX2\*07\*CITY (RPL-82)  
 NX2\*32\*FLOOR (RPL-80)  
 NX2\*35\*ROOM/MAIL STOP (RPL-81)  
 NX2\*40\*SASS (RPL-79g)  
 NX2\*59\*SAPR (RPL-79a)  
 NX2\*61\*SASF (RPL-79c)  
 NX2\*62\*SATH (RPL79f)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	
M	<b>NX201</b>	<b>1106</b>	<b>Address Component Qualifier</b> Code qualifying the type of address component	M ID 2/2
			01 Street Number	
			02 Street Name	
			03 Prefix Direction	
			07 City Name	
			32 Floor	
			A particular floor or level of a building	
			35 Room	
			A walled room or partitioned area of a building	
			40 Street Suffix	
			59 Street Number Low	
			61 Street Number Fraction	
			62 Street Name Suffix	
M	<b>NX202</b>	<b>166</b>	<b>Address Information</b> Address information	M AN 1/55
			SANO (RPL-79b) = Service Address Number	
			SASN (RPL-79e) = Service Address Street Name	
			SASD (RPL-79d) = Service Address Street Directional Prefix	
			CITY (RPL-82) = City	
			FLOOR (RPL-80) = Floor	
			ROOM/MAIL STOP (RPL-81) = Room/Mail Stop	
			SASS (RPL-79g) = Service Address Street Directional Suffix	
			SAPR (RPL-79a) = Service Address Number Prefix	
			SASF (RPL-79c) = Service Address Number Suffix	
			SATH (RPL-79f) = Service Address Street Type	

**Segment:** **PER** Administrative Communications Contact  
**Position:** 3600  
**Loop:** N1 Optional  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To identify a person or office to whom administrative communications should be directed

- Syntax Notes:**
- 1 If either PER03 or PER04 is present, then the other is required.
  - 2 If either PER05 or PER06 is present, then the other is required.
  - 3 If either PER07 or PER08 is present, then the other is required.

**Semantic Notes:**

**Comments:**

**Notes:** PER\*BI\*BILLCON (RPL85)\*TE\*TEL NO (RPL-86)

**Data Element Summary**

Ref. Des.	Data Element	Name		
M	PER01	366	<b>Contact Function Code</b> Code identifying the major duty or responsibility of the person or group named BI Bill Inquiry Contact Service Provider contact for making inquires about information on the invoice	M ID 2/2
	PER02	93	<b>Name</b> Free-form name BILLCON (RPL-85) = Billing Contact	O AN 1/60
	PER03	365	<b>Communication Number Qualifier</b> Code identifying the type of communication number TE Telephone	X ID 2/2
	PER04	364	<b>Communication Number</b> Complete communications number including country or area code when applicable TEL NO (RPL-86) = Telephone Number	X AN 1/256

**Segment:** **SI** Service Characteristic Identification

**Position:** 3650

**Loop:** N1 Optional

**Level:** Heading

**Usage:** Optional

**Max Use:** >1

**Purpose:** To specify service characteristic data

- Syntax Notes:**
- 1 If either SI04 or SI05 is present, then the other is required.
  - 2 If either SI06 or SI07 is present, then the other is required.
  - 3 If either SI08 or SI09 is present, then the other is required.
  - 4 If either SI10 or SI11 is present, then the other is required.
  - 5 If either SI12 or SI13 is present, then the other is required.
  - 6 If either SI14 or SI15 is present, then the other is required.
  - 7 If either SI16 or SI17 is present, then the other is required.
  - 8 If either SI18 or SI19 is present, then the other is required.
  - 9 If either SI20 or SI21 is present, then the other is required.

**Semantic Notes:**

**Comments:** 1 SI01 defines the source for each of the service characteristics qualifiers.

**Notes:** SI\*TI\*AF\*AFT (RPL-78a)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
	<u>Attributes</u>				
M	SI01	559	<b>Agency Qualifier Code</b>	M	ID 2/2
			Code identifying the agency assigning the code values		
			TI Telecommunications Industry		
M	SI02	1000	<b>Service Characteristics Qualifier</b>	M	AN 2/2
			Code from an industry code list qualifying the type of service characteristics		
			AF Address Format Type		
M	SI03	234	<b>Product/Service ID</b>	M	AN 1/48
			Identifying number for a product or service		
			AFT (RPL-78a) = Address Format Type		



**Segment:** **PO1** **Baseline Item Data - Primary Location Section**

**Position:** 0100  
**Loop:** PO1 Mandatory  
**Level:** Detail  
**Usage:** Mandatory  
**Max Use:** 1

**Purpose:** To specify basic and most frequently used line item data  
**Syntax Notes:**

- 1 If PO103 is present, then PO102 is required.
- 2 If PO105 is present, then PO104 is required.
- 3 If either PO106 or PO107 is present, then the other is required.
- 4 If either PO108 or PO109 is present, then the other is required.
- 5 If either PO110 or PO111 is present, then the other is required.
- 6 If either PO112 or PO113 is present, then the other is required.
- 7 If either PO114 or PO115 is present, then the other is required.
- 8 If either PO116 or PO117 is present, then the other is required.
- 9 If either PO118 or PO119 is present, then the other is required.
- 10 If either PO120 or PO121 is present, then the other is required.
- 11 If either PO122 or PO123 is present, then the other is required.
- 12 If either PO124 or PO125 is present, then the other is required.

**Semantic Notes:**  
**Comments:**

- 1 See the Data Element Dictionary for a complete list of IDs.
- 2 PO101 is the line item identification.
- 3 PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

**Notes:** PO1\*n\*1\*EA\*\*\*ZZ\*RPL\_PLS

**Data Element Summary**

<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
<b>Attributes</b>				
<b>PO101</b>	<b>350</b>	<b>Assigned Identification</b>	<b>O</b>	<b>AN 1/20</b>
		Alphanumeric characters assigned for differentiation within a transaction set		
		"n" = nth assigned ID within PO1 loop		
<b>PO102</b>	<b>330</b>	<b>Quantity Ordered</b>	<b>X</b>	<b>R 1/15</b>
		Quantity ordered		
		1 Always One		
<b>PO103</b>	<b>355</b>	<b>Unit or Basis for Measurement Code</b>	<b>O</b>	<b>ID 2/2</b>
		Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken		
		EA Each		
<b>PO106</b>	<b>235</b>	<b>Product/Service ID Qualifier</b>	<b>X</b>	<b>ID 2/2</b>
		Code identifying the type/source of the descriptive number used in Product/Service ID (234)		
		ZZ Mutually Defined		
<b>PO107</b>	<b>234</b>	<b>Product/Service ID</b>	<b>X</b>	<b>AN 1/48</b>
		Identifying number for a product or service		
		"RPL_PLS"		

**Segment:** **SI** Service Characteristic Identification

**Position:** 0180  
**Loop:** PO1 Mandatory  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1

**Purpose:** To specify service characteristic data  
**Syntax Notes:**

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

**Semantic Notes:**

**Comments:** 1 SI01 defines the source for each of the service characteristics qualifiers.

**Notes:** SI\*TI\*LT\*02 (designates "primary")  
 SI\*TI\*LS\*RLSO (RPL-26)  
 SI\*TI\*IW\*IWO (RPL-35)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
	<b>Attributes</b>				
M	SI01	559	<b>Agency Qualifier Code</b>	M	ID 2/2
			Code identifying the agency assigning the code values		
			TI Telecommunications Industry		
M	SI02	1000	<b>Service Characteristics Qualifier</b>	M	AN 2/2
			Code from an industry code list qualifying the type of service characteristics		
			IW Inside Wire Options		
			LS Local Serving Office		
			LT Location Type		
M	SI03	234	<b>Product/Service ID</b>	M	AN 1/48
			Identifying number for a product or service		
			02 = (designates "primary")		
			RLSO (RPL-26) = Resale Local Serving Office		
			IWO (RPL-35) = Inside Wiring Option		

**Segment:** **PID** Product/Item Description

**Position:** 0500

**Loop:** PID Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To describe a product or process in coded or free-form format

**Syntax Notes:**

- 1 If PID04 is present, then PID03 is required.
- 2 At least one of PID04 or PID05 is required.
- 3 If PID07 is present, then PID03 is required.
- 4 If PID08 is present, then PID04 is required.
- 5 If PID09 is present, then PID05 is required.

**Semantic Notes:**

- 1 Use PID03 to indicate the organization that publishes the code list being referred to.
- 2 PID04 should be used for industry-specific product description codes.
- 3 PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
- 4 PID09 is used to identify the language being used in PID05.

**Comments:**

- 1 If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
- 2 Use PID06 when necessary to refer to the product surface or layer being described in the segment.
- 3 PID07 specifies the individual code list of the agency specified in PID03.

**Notes:** PID\*S\*\*TI\*ANV\*\*\*SO-RSQ\*ANV (RPL-10b)

#### Data Element Summary

Ref. Des.	Data Element	Name		
<b>Attributes</b>				
M	PID01	349	<b>Item Description Type</b> Code indicating the format of a description S Structured (From Industry Code List)	M ID 1/1
	PID03	559	<b>Agency Qualifier Code</b> Code identifying the agency assigning the code values TI Telecommunications Industry	X ID 2/2
	PID04	751	<b>Product Description Code</b> A code from an industry code list which provides specific data about a product characteristic ANV Address Not Validated Indicator	X AN 1/12
	PID07	822	<b>Source Subqualifier</b> A reference that indicates the table or text maintained by the Source Qualifier SO-RSQ Service Order - Reseller Questions list	O AN 1/15
	PID08	1073	<b>Yes/No Condition or Response Code</b> Code indicating a Yes or No condition or response ANV (RPL-10b) = Address Not Validated Indicator	O ID 1/1

**Segment:** **REF** Reference Identification

**Position:** 1000

**Loop:** PO1 Mandatory

**Level:** Detail

**Usage:** Optional

**Max Use:** >1

**Purpose:** To specify identifying information

- Syntax Notes:**
- 1 At least one of REF02 or REF03 is required.
  - 2 If either C04003 or C04004 is present, then the other is required.
  - 3 If either C04005 or C04006 is present, then the other is required.
- Semantic Notes:**
- 1 REF04 contains data relating to the value cited in REF02.

**Comments:**

**Notes:** REF\*IX\*LOCNUM (RPL-9)\*LOCNUM

#### Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	REF01	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification IX Item Number	M	ID 2/3
	REF02	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier LOCNUM (RPL-9) = Location Number	X	AN 1/30
	REF03	352	<b>Description</b> A free-form description to clarify the related data elements and their content "LOCNUM"	X	AN 1/80

**Segment:** **N9 Reference Identification**

**Position:** 3300

**Loop:** N9 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To transmit identifying information as specified by the Reference Identification Qualifier

- Syntax Notes:**
- 1 At least one of N902 or N903 is required.
  - 2 If N906 is present, then N905 is required.
  - 3 If either C04003 or C04004 is present, then the other is required.
  - 4 If either C04005 or C04006 is present, then the other is required.

- Semantic Notes:**
- 1 N906 reflects the time zone which the time reflects.
  - 2 N907 contains data relating to the value cited in N902.

**Comments:**

**Notes:** N9\*H7\*LOC\*AAI

#### Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	N901	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification H7 Standard Clause	M	ID 2/3
	N902	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier LOC Location Instructions	X	AN 1/30
	N903	369	<b>Free-form Description</b> Free-form descriptive text "AAI"	X	AN 1/45

**Segment:** **MTX** Text  
**Position:** 3400  
**Loop:** N9 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To specify textual data  
**Syntax Notes:**

- 1 If MTX01 is present, then MTX02 is required.
- 2 If MTX03 is present, then MTX02 is required.
- 3 If MTX05 is present, then MTX04 is required.

**Semantic Notes:**

- 1 MTX05 is the number of lines to advance before printing.

**Comments:**

- 1 If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

**Notes:** MTX\*\*AAI (RPL-25)

**Data Element Summary**

<u>Ref.</u> <u>Des.</u>	<u>Data</u> <u>Element</u>	<u>Name</u>		
<b>Attributes</b> MTX02	1551	<b>Message Text</b>	<b>X</b>	<b>AN 1/4096</b>
		To transmit large volumes of message text		
		AAI (RPL-25) = Additional Address Information		

**Segment:** **N9 Reference Identification**

**Position:** 3300

**Loop:** N9 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To transmit identifying information as specified by the Reference Identification Qualifier

- Syntax Notes:**
- 1 At least one of N902 or N903 is required.
  - 2 If N906 is present, then N905 is required.
  - 3 If either C04003 or C04004 is present, then the other is required.
  - 4 If either C04005 or C04006 is present, then the other is required.

- Semantic Notes:**
- 1 N906 reflects the time zone which the time reflects.
  - 2 N907 contains data relating to the value cited in N902.

**Comments:**

**Notes:** N9\*L1\*ALOC\*RPLPRI

#### Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	N901	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification L1 Letters or Notes	M	ID 2/3
	N902	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier ALOC Additional Location Detail	X	AN 1/30
	N903	369	<b>Free-form Description</b> Free-form descriptive text "RPLPRI"	X	AN 1/45

**Segment:** **MTX** Text  
**Position:** 3400  
**Loop:** N9 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To specify textual data  
**Syntax Notes:**

- 1 If MTX01 is present, then MTX02 is required.
- 2 If MTX03 is present, then MTX02 is required.
- 3 If MTX05 is present, then MTX04 is required.

**Semantic Notes:**

- 1 MTX05 is the number of lines to advance before printing.

**Comments:**

- 1 If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

**Notes:** MTX\*\*ALOC (RPL-30)

**Data Element Summary**

Ref. Des.	Data Element	Name		
<b>Attributes</b> MTX02	1551	<b>Message Text</b>	X	AN 1/4096
		To transmit large volumes of message text		
		ALOC (RPL-30) = Additional Location Details		



**Segment:** **N9 Reference Identification**

**Position:** 3300

**Loop:** N9 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To transmit identifying information as specified by the Reference Identification Qualifier

- Syntax Notes:**
- 1 At least one of N902 or N903 is required.
  - 2 If N906 is present, then N905 is required.
  - 3 If either C04003 or C04004 is present, then the other is required.
  - 4 If either C04005 or C04006 is present, then the other is required.

- Semantic Notes:**
- 1 N906 reflects the time zone which the time reflects.
  - 2 N907 contains data relating to the value cited in N902.

**Comments:**

**Notes:** N9\*L1\*ACC\*RPLPRI

#### Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	N901	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification L1 Letters or Notes	M	ID 2/3
	N902	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier ACC Access Instructions	X	AN 1/30
	N903	369	<b>Free-form Description</b> Free-form descriptive text "RPLPRI"	X	AN 1/45

**Segment:** **MTX** Text  
**Position:** 3400  
**Loop:** N9 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To specify textual data  
**Syntax Notes:**

- 1 If MTX01 is present, then MTX02 is required.
- 2 If MTX03 is present, then MTX02 is required.
- 3 If MTX05 is present, then MTX04 is required.

**Semantic Notes:**

- 1 MTX05 is the number of lines to advance before printing.

**Comments:**

- 1 If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

**Notes:** MTX\*\*ACC (RPL-39)

**Data Element Summary**

<u>Ref.</u> <u>Des.</u>	<u>Data</u> <u>Element</u>	<u>Name</u>		
<b>Attributes</b> MTX02	1551	<b>Message Text</b>	<b>X</b>	<b>AN 1/4096</b>
		To transmit large volumes of message text		
		ACC (RPL-39) = Access Information		

**Segment:** **N1** Name  
**Position:** 3500  
**Loop:** N1 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** 1  
**Purpose:** To identify a party by type of organization, name, and code  
**Syntax Notes:**

- 1 At least one of N102 or N103 is required.
- 2 If either N103 or N104 is present, then the other is required.

**Semantic Notes:**  
**Comments:**

- 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
- 2 N105 and N106 further define the type of entity in N101.

**Notes:** N1\*IT\*PRILOC (RPL-10)\*93\*LIT (RPL-8)

**Data Element Summary**

Ref. Des. Attributes	Data Element	Name		
M	N101	98	<b>Entity Identifier Code</b> Code identifying an organizational entity, a physical location, property or an individual IT Installation on Site	M ID 2/3
	N102	93	<b>Name</b> Free-form name PRILOC (RPL-10) = Primary Location	X AN 1/60
	N103	66	<b>Identification Code Qualifier</b> Code designating the system/method of code structure used for Identification Code (67) 93 Code assigned by the organization originating the transaction set	X ID 1/2
	N104	67	<b>Identification Code</b> Code identifying a party or other code LIT (RPL-8) = Location Identification Type EU = (DWS: E-End User Name) CL = (DWS: C-CLLI Code)	X AN 2/80

**Segment:** **N2** Additional Name Information  
**Position:** 3600  
**Loop:** N1 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** 2  
**Purpose:** To specify additional names  
**Syntax Notes:**  
**Semantic Notes:**  
**Comments:**  
**Notes:** N2\*NAME (RPL-10a)

**Data Element Summary**

	<u>Ref.</u> <u>Des.</u> <u>Attributes</u>	<u>Data</u> <u>Element</u>	<u>Name</u>		
M	N201	93	Name Free-form name NAME (RPL-10a) = End User Name	M	AN 1/60

**Segment:** **N4 Geographic Location**

**Position:** 3800

**Loop:** N1 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To specify the geographic place of the named party

- Syntax Notes:**
- 1 Only one of N402 or N407 may be present.
  - 2 If N406 is present, then N405 is required.
  - 3 If N407 is present, then N404 is required.

**Semantic Notes:**

- Comments:**
- 1 A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
  - 2 N402 is required only if city name (N401) is in the U.S. or Canada.

**Notes:** N4\*\*STATE (RPL-28)\*ZIP (RPL-29)\*\*RJ\*CALA (RPL-29a)

**Data Element Summary**

<u>Ref.</u>	<u>Data</u>	<u>Name</u>		
<u>Des.</u>	<u>Element</u>			
<b>N402</b>	<b>156</b>	<b>State or Province Code</b>	<b>X</b>	<b>ID 2/2</b>
		Code (Standard State/Province) as defined by appropriate government agency		
		STATE (RPL-28) = State/Province		
<b>N403</b>	<b>116</b>	<b>Postal Code</b>	<b>O</b>	<b>ID 3/15</b>
		Code defining international postal zone code excluding punctuation and blanks (zip code for United States)		
		ZIP (RPL-29) = ZIP/Postal Code		
<b>N405</b>	<b>309</b>	<b>Location Qualifier</b>	<b>X</b>	<b>ID 1/2</b>
		Code identifying type of location		
		RJ Region		
<b>N406</b>	<b>310</b>	<b>Location Identifier</b>	<b>O</b>	<b>AN 1/30</b>
		Code which identifies a specific location		
		CALA (RPL-29a) = Customer Address Location Area		

**Segment:** **NX2** Location ID Component

**Position:** 3850

**Loop:** N1 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** >1

**Purpose:** To define types and values of a geographic location

**Syntax Notes:**

**Semantic Notes:**

**Comments:**

**Notes:**

NX2\*01\*SANO (RPL-13)  
 NX2\*02\*SASN (RPL-16)  
 NX2\*03\*SASD (RPL-15)  
 NX2\*05\*BOX (RPL-26c)  
 NX2\*06\*ROUTE (RPL-26b)  
 NX2\*07\*CITY (RPL-27)  
 NX2\*39\*AHN (RPL-26a)  
 NX2\*40\*SASS (RPL-18)  
 NX2\*59\*SAPR (RPL-12)  
 NX2\*61\*SASF (RPL-14)  
 NX2\*62\*SATH (RPL-17)  
 NX2\*LD1 (RPL-19)\*LV1 (RPL-20)  
 NX2\*LD2 (RPL-21)\*LV2 (RPL-22)  
 NX2\*LD3 (RPL-23)\*LV3 (RPL-24)

**Data Element Summary**

	<u>Ref.</u>	<u>Data</u>	<u>Element</u>	<u>Name</u>	
M	<u>Des.</u> Attributes NX201		1106	<b>Address Component Qualifier</b> Code qualifying the type of address component	M ID 2/2
				LD1 (RPL-19) = Location Designator 1 13 = (DWS: APT) 34 = (DWS: LOT) 35 = (DWS: RM) 36 = (DWS: SLIP) 37 = (DWS: UNIT) 14 = (DWS: SUIT)	
				LD2 (RPL-21) = Location Designator 2 32 = (DWS: FLR)	
				LD3 (RPL-23) = Location Designator 3 12 = (DWS: BLDG) 63 = (DWS: WNG) 30 = (DWS : PIER)	
				01 Street Number	
				02 Street Name	
				03 Prefix Direction	
				05 P.O. Box Number	
				06 Rural Route Number	
				07 City Name	
				12 Building Name	

13	Apartment Number
14	Suite Number
30	Pier The pier at which a ship or boat is docked
32	Floor A particular floor or level of a building
34	Lot A particular lot or piece of land
35	Room A walled room or partitioned area of a building
36	Slip The slip or location on a pier at which a ship or boat is docked
37	Unit A unit or separate structure
39	Unstructured Property
40	Street Suffix
59	Street Number Low
61	Street Number Fraction
62	Street Name Suffix
63	Secondary Unit Identifier

**M NX202 166 Address Information M AN 1/55**

Address information

SANO (RPL-13) = Service Address Number  
 SASN (RPL-16) = Service Address Street Name  
 SASD (RPL-15) = Service Address Street Directional Prefix  
 BOX (RPL-26c) = Box  
 ROUTE (RPL-26b) = Route  
 CITY (RPL-27) = City  
 AHN (RPL-26a) = Assigned House Number  
 SASS (RPL-18) = Service Address Street Directional Suffix  
 SAPR (RPL-12) = Service Address Number Prefix  
 SASF (RPL-14) = Service Address Number Suffix  
 SATH (RPL-17) = Service Address Street Type  
 LV1 (RPL-20) = Location Value 1  
 LV2 (RPL-22) = Location Value 2  
 LV3 (RPL-24) = Location Value 3

**Segment:** **PER** Administrative Communications Contact

**Position:** 4000

**Loop:** N1 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 3

**Purpose:** To identify a person or office to whom administrative communications should be directed

- Syntax Notes:**
- 1 If either PER03 or PER04 is present, then the other is required.
  - 2 If either PER05 or PER06 is present, then the other is required.
  - 3 If either PER07 or PER08 is present, then the other is required.

**Semantic Notes:**

**Comments:**

**Notes:** PER\*CA\*LCON (RPL-31)\*TE\*ACTEL NO (RPL-32)  
PER\*AL\*ALCON (RPL-33)\*TE\*AACTEL (RPL-34)

#### Data Element Summary

Ref.	Data		
<u>Des.</u>	<u>Element</u>	<u>Name</u>	
M	<u>Attributes</u> PER01	366 <b>Contact Function Code</b>	M ID 2/2
		Code identifying the major duty or responsibility of the person or group named	
		AL Alternate Contact	
		CA Person to be contacted when the main contact is not available	
		Customer Contact Granting Appointment	
	PER02	93 <b>Name</b>	O AN 1/60
		Free-form name	
		LCON (RPL-31) = Local Contact	
		ALCON (RPL-33) = Alternate Local Contact	
	PER03	365 <b>Communication Number Qualifier</b>	X ID 2/2
		Code identifying the type of communication number	
		TE Telephone	
	PER04	364 <b>Communication Number</b>	X AN 1/256
		Complete communications number including country or area code when applicable	
		ACTEL NO (RPL-32) = Access Telephone Number	
		AACTEL (RPL-34) = Alternate Access Telephone Number	



**Segment:** **SI** Service Characteristic Identification

**Position:** 4050

**Loop:** N1 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** >1

**Purpose:** To specify service characteristic data

- Syntax Notes:**
- 1 If either SI04 or SI05 is present, then the other is required.
  - 2 If either SI06 or SI07 is present, then the other is required.
  - 3 If either SI08 or SI09 is present, then the other is required.
  - 4 If either SI10 or SI11 is present, then the other is required.
  - 5 If either SI12 or SI13 is present, then the other is required.
  - 6 If either SI14 or SI15 is present, then the other is required.
  - 7 If either SI16 or SI17 is present, then the other is required.
  - 8 If either SI18 or SI19 is present, then the other is required.
  - 9 If either SI20 or SI21 is present, then the other is required.

**Semantic Notes:**

- Comments:**
- 1 SI01 defines the source for each of the service characteristics qualifiers.

**Notes:** SI\*TI\*AF\*AFT (RPL-11)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
	<u>Attributes</u>				
M	SI01	559	<b>Agency Qualifier Code</b>	M	ID 2/2
			Code identifying the agency assigning the code values		
			TI Telecommunications Industry		
M	SI02	1000	<b>Service Characteristics Qualifier</b>	M	AN 2/2
			Code from an industry code list qualifying the type of service characteristics		
			AF Address Format Type		
M	SI03	234	<b>Product/Service ID</b>	M	AN 1/48
			Identifying number for a product or service		
			AFT (RPL-11) = Address Format Type		

**Segment:** **PO1** **Baseline Item Data - Secondary Location Section**

**Position:** 0100  
**Loop:** PO1 Mandatory  
**Level:** Detail  
**Usage:** Mandatory  
**Max Use:** 1

**Purpose:** To specify basic and most frequently used line item data  
**Syntax Notes:**

- 1 If PO103 is present, then PO102 is required.
- 2 If PO105 is present, then PO104 is required.
- 3 If either PO106 or PO107 is present, then the other is required.
- 4 If either PO108 or PO109 is present, then the other is required.
- 5 If either PO110 or PO111 is present, then the other is required.
- 6 If either PO112 or PO113 is present, then the other is required.
- 7 If either PO114 or PO115 is present, then the other is required.
- 8 If either PO116 or PO117 is present, then the other is required.
- 9 If either PO118 or PO119 is present, then the other is required.
- 10 If either PO120 or PO121 is present, then the other is required.
- 11 If either PO122 or PO123 is present, then the other is required.
- 12 If either PO124 or PO125 is present, then the other is required.

**Semantic Notes:**  
**Comments:**

- 1 See the Data Element Dictionary for a complete list of IDs.
- 2 PO101 is the line item identification.
- 3 PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

**Notes:** PO1\*n\*1\*EA\*\*\*ZZ\*RPL\_SLS [PO1 Loop repeats SECLOCQTY(RPL-41a) times]

**Data Element Summary**

<u>Ref.</u> <u>Des.</u> <u>Attributes</u>	<u>Data</u> <u>Element</u>	<u>Name</u>		
PO101	350	<b>Assigned Identification</b> Alphanumeric characters assigned for differentiation within a transaction set "n" = nth assigned ID within PO1 loop	O	AN 1/20
PO102	330	<b>Quantity Ordered</b> Quantity ordered 1 Always One	X	R 1/15
PO103	355	<b>Unit or Basis for Measurement Code</b> Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken EA Each	O	ID 2/2
PO106	235	<b>Product/Service ID Qualifier</b> Code identifying the type/source of the descriptive number used in Product/Service ID (234) ZZ Mutually Defined	X	ID 2/2
PO107	234	<b>Product/Service ID</b> Identifying number for a product or service "RPL_SLS"	X	AN 1/48

**Segment:** **SI** Service Characteristic Identification

**Position:** 0180

**Loop:** PO1 Mandatory

**Level:** Detail

**Usage:** Optional

**Max Use:** >1

**Purpose:** To specify service characteristic data

- Syntax Notes:**
- 1 If either SI04 or SI05 is present, then the other is required.
  - 2 If either SI06 or SI07 is present, then the other is required.
  - 3 If either SI08 or SI09 is present, then the other is required.
  - 4 If either SI10 or SI11 is present, then the other is required.
  - 5 If either SI12 or SI13 is present, then the other is required.
  - 6 If either SI14 or SI15 is present, then the other is required.
  - 7 If either SI16 or SI17 is present, then the other is required.
  - 8 If either SI18 or SI19 is present, then the other is required.
  - 9 If either SI20 or SI21 is present, then the other is required.

**Semantic Notes:**

**Comments:** 1 SI01 defines the source for each of the service characteristics qualifiers.

**Notes:** SI\*TI\*LT\*04 (designates "secondary")  
 SI\*TI\*LS\*RLSO (RPL-60)  
 SI\*TI\*IW\*IWO (RPL-69)

**Data Element Summary**

Ref.	Data			
<u>Des.</u>	<u>Element</u>	<u>Name</u>		
<b>M</b>	<b>SI01</b>	<b>559</b>	<b>Agency Qualifier Code</b>	<b>M ID 2/2</b>
			Code identifying the agency assigning the code values	
			TI Telecommunications Industry	
<b>M</b>	<b>SI02</b>	<b>1000</b>	<b>Service Characteristics Qualifier</b>	<b>M AN 2/2</b>
			Code from an industry code list qualifying the type of service characteristics	
			IW Inside Wire Options	
			LS Local Serving Office	
			LT Location Type	
<b>M</b>	<b>SI03</b>	<b>234</b>	<b>Product/Service ID</b>	<b>M AN 1/48</b>
			Identifying number for a product or service	

04 = Secondary  
 RLSO (RPL-60) = Resale Local Serving Office (SECLOC)  
 IWO (RPL-69) = Inside Wiring Options (SECLOC)

**Segment:** **PID** Product/Item Description

**Position:** 0500

**Loop:** PID Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To describe a product or process in coded or free-form format

**Syntax Notes:**

- 1 If PID04 is present, then PID03 is required.
- 2 At least one of PID04 or PID05 is required.
- 3 If PID07 is present, then PID03 is required.
- 4 If PID08 is present, then PID04 is required.
- 5 If PID09 is present, then PID05 is required.

**Semantic Notes:**

- 1 Use PID03 to indicate the organization that publishes the code list being referred to.
- 2 PID04 should be used for industry-specific product description codes.
- 3 PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
- 4 PID09 is used to identify the language being used in PID05.

**Comments:**

- 1 If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
- 2 Use PID06 when necessary to refer to the product surface or layer being described in the segment.
- 3 PID07 specifies the individual code list of the agency specified in PID03.

**Notes:** PID\*S\*\*TI\*ANV\*\*\*SO-RSQ\*ANV (RPL-44b)

**Data Element Summary**

Ref.	Data			
<u>Des.</u>	<u>Element</u>	<u>Name</u>		
<b>Attributes</b>				
M	PID01	349	<b>Item Description Type</b>	M ID 1/1
			Code indicating the format of a description	
			S Structured (From Industry Code List)	
	PID03	559	<b>Agency Qualifier Code</b>	X ID 2/2
			Code identifying the agency assigning the code values	
			TI Telecommunications Industry	
	PID04	751	<b>Product Description Code</b>	X AN 1/12
			A code from an industry code list which provides specific data about a product characteristic	
			ANV Address Not Validated Indicator	
	PID07	822	<b>Source Subqualifier</b>	O AN 1/15
			A reference that indicates the table or text maintained by the Source Qualifier	
			SO-RSQ Service Order - Reseller Questions list	
	PID08	1073	<b>Yes/No Condition or Response Code</b>	O ID 1/1
			Code indicating a Yes or No condition or response	
			ANV (RPL-44b) = Address Not Validated Indicator	

**Segment:** **REF** Reference Identification

**Position:** 1000

**Loop:** PO1 Mandatory

**Level:** Detail

**Usage:** Optional

**Max Use:** >1

**Purpose:** To specify identifying information

- Syntax Notes:**
- 1 At least one of REF02 or REF03 is required.
  - 2 If either C04003 or C04004 is present, then the other is required.
  - 3 If either C04005 or C04006 is present, then the other is required.
- Semantic Notes:**
- 1 REF04 contains data relating to the value cited in REF02.

**Comments:**

**Notes:** REF\*IX\*LOCNUM (RPL-43)\*LOCNUM

#### Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	REF01	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification IX Item Number	M	ID 2/3
	REF02	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier LOCNUM (RPL-43) = Location Number	X	AN 1/30
	REF03	352	<b>Description</b> A free-form description to clarify the related data elements and their content "LOCNUM"	X	AN 1/80

**Segment:** **N9** Reference Identification

**Position:** 3300

**Loop:** N9 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To transmit identifying information as specified by the Reference Identification Qualifier

- Syntax Notes:**
- 1 At least one of N902 or N903 is required.
  - 2 If N906 is present, then N905 is required.
  - 3 If either C04003 or C04004 is present, then the other is required.
  - 4 If either C04005 or C04006 is present, then the other is required.

- Semantic Notes:**
- 1 N906 reflects the time zone which the time reflects.
  - 2 N907 contains data relating to the value cited in N902.

**Comments:**

**Notes:** N9\*H7\*LOC\*AAI

#### Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	N901	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification H7 Standard Clause	M	ID 2/3
	N902	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier LOC Location Instructions	X	AN 1/30
	N903	369	<b>Free-form Description</b> Free-form descriptive text "AAI"	X	AN 1/45

**Segment:** **MTX** Text  
**Position:** 3400  
**Loop:** N9 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To specify textual data  
**Syntax Notes:**

- 1 If MTX01 is present, then MTX02 is required.
- 2 If MTX03 is present, then MTX02 is required.
- 3 If MTX05 is present, then MTX04 is required.

**Semantic Notes:**

- 1 MTX05 is the number of lines to advance before printing.

**Comments:**

- 1 If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

**Notes:** MTX\*\*AAI (RPL-59)

**Data Element Summary**

<u>Ref.</u> <u>Des.</u>	<u>Data</u> <u>Element</u>	<u>Name</u>		
<b>Attributes</b> MTX02	1551	<b>Message Text</b>	<b>X</b>	<b>AN 1/4096</b>
		To transmit large volumes of message text		
		AAI (RPL-59) = Additional Address Information		

**Segment:** **N9** Reference Identification

**Position:** 3300

**Loop:** N9 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To transmit identifying information as specified by the Reference Identification Qualifier

- Syntax Notes:**
- 1 At least one of N902 or N903 is required.
  - 2 If N906 is present, then N905 is required.
  - 3 If either C04003 or C04004 is present, then the other is required.
  - 4 If either C04005 or C04006 is present, then the other is required.

- Semantic Notes:**
- 1 N906 reflects the time zone which the time reflects.
  - 2 N907 contains data relating to the value cited in N902.

**Comments:**

**Notes:** N9\*L1\*ALOC\*RPLSEC

#### Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	N901	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification L1 Letters or Notes	M	ID 2/3
	N902	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier ALOC Additional Location Detail	X	AN 1/30
	N903	369	<b>Free-form Description</b> Free-form descriptive text "RPLSEC"	X	AN 1/45



**Segment:** **MTX** Text  
**Position:** 3400  
**Loop:** N9 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To specify textual data  
**Syntax Notes:**

- 1 If MTX01 is present, then MTX02 is required.
- 2 If MTX03 is present, then MTX02 is required.
- 3 If MTX05 is present, then MTX04 is required.

**Semantic Notes:**

- 1 MTX05 is the number of lines to advance before printing.

**Comments:**

- 1 If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

**Notes:** MTX\*\*ALOC (RPL-64)

#### Data Element Summary

<u>Ref.</u>	<u>Data</u>	<u>Element</u>	<u>Name</u>		
<b>Attributes</b>					
<b>MTX02</b>	<b>1551</b>	<b>Message Text</b>		<b>X</b>	<b>AN 1/4096</b>
		To transmit large volumes of message text			
		ALOC (RPL-64) = Additional Location Details			

**Segment:** **N9 Reference Identification**

**Position:** 3300

**Loop:** N9 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To transmit identifying information as specified by the Reference Identification Qualifier

- Syntax Notes:**
- 1 At least one of N902 or N903 is required.
  - 2 If N906 is present, then N905 is required.
  - 3 If either C04003 or C04004 is present, then the other is required.
  - 4 If either C04005 or C04006 is present, then the other is required.

- Semantic Notes:**
- 1 N906 reflects the time zone which the time reflects.
  - 2 N907 contains data relating to the value cited in N902.

**Comments:**

**Notes:** N9\*L1\*ACC\*RPLSEC

#### Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	N901	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification L1 Letters or Notes	M	ID 2/3
	N902	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier ACC Access Instructions	X	AN 1/30
	N903	369	<b>Free-form Description</b> Free-form descriptive text "RPLSEC"	X	AN 1/45

**Segment:** **MTX** Text  
**Position:** 3400  
**Loop:** N9 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To specify textual data  
**Syntax Notes:**

- 1 If MTX01 is present, then MTX02 is required.
- 2 If MTX03 is present, then MTX02 is required.
- 3 If MTX05 is present, then MTX04 is required.

**Semantic Notes:**

- 1 MTX05 is the number of lines to advance before printing.

**Comments:**

- 1 If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

**Notes:** MTX\*\*ACC (RPL-73)

**Data Element Summary**

<u>Ref.</u> <u>Des.</u>	<u>Data</u> <u>Element</u>	<u>Name</u>		
<b>Attributes</b> MTX02	1551	<b>Message Text</b>	<b>X</b>	<b>AN 1/4096</b>
		To transmit large volumes of message text		
		ACC (RPL-73) = Access Information		

**Segment:** **N1** Name  
**Position:** 3500  
**Loop:** N1 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** 1  
**Purpose:** To identify a party by type of organization, name, and code  
**Syntax Notes:**

- 1 At least one of N102 or N103 is required.
- 2 If either N103 or N104 is present, then the other is required.

**Semantic Notes:**  
**Comments:**

- 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
- 2 N105 and N106 further define the type of entity in N101.

**Notes:** N1\*IT\*SECLOC (RPL-44)\*93\*LIT (RPL-42)

**Data Element Summary**

Ref.	Data	Element	Name		
<u>Des.</u>					
<u>Attributes</u>					
M	N101	98	<b>Entity Identifier Code</b> Code identifying an organizational entity, a physical location, property or an individual IT Installation on Site	M	ID 2/3
	N102	93	<b>Name</b> Free-form name SECLOC (RPL-44) = Secondary Location	X	AN 1/60
	N103	66	<b>Identification Code Qualifier</b> Code designating the system/method of code structure used for Identification Code (67) 93 Code assigned by the organization originating the transaction set	X	ID 1/2
	N104	67	<b>Identification Code</b> Code identifying a party or other code LIT (RPL-42) = Location Identification Type EU = (DWS: E-End User Name) CL = (DWS: C-CLLI Code)	X	AN 2/80

**Segment:** **N2** Additional Name Information  
**Position:** 3600  
**Loop:** N1 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** 2  
**Purpose:** To specify additional names  
**Syntax Notes:**  
**Semantic Notes:**  
**Comments:**  
**Notes:** N2\*NAME (RPL-44a)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	<u>Attributes</u> N201	93	Name Free-form name NAME (RPL-44a) = End User Name	M	AN 1/60

**Segment:** **N4 Geographic Location**

**Position:** 3800

**Loop:** N1 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To specify the geographic place of the named party

- Syntax Notes:**
- 1 Only one of N402 or N407 may be present.
  - 2 If N406 is present, then N405 is required.
  - 3 If N407 is present, then N404 is required.

**Semantic Notes:**

- Comments:**
- 1 A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
  - 2 N402 is required only if city name (N401) is in the U.S. or Canada.

**Notes:** N4\*\*STATE (RPL-62)\*ZIP (RPL-63)\*\*RJ\*CALA (RPL-63a)

**Data Element Summary**

<u>Ref.</u>	<u>Data</u>	<u>Name</u>		
<u>Des.</u>	<u>Element</u>			
<b>N402</b>	<b>156</b>	<b>State or Province Code</b>	<b>X</b>	<b>ID 2/2</b>
		Code (Standard State/Province) as defined by appropriate government agency		
		STATE (RPL-62) = State/Province		
<b>N403</b>	<b>116</b>	<b>Postal Code</b>	<b>O</b>	<b>ID 3/15</b>
		Code defining international postal zone code excluding punctuation and blanks (zip code for United States)		
		ZIP (RPL-63) = ZIP/Postal Code		
<b>N405</b>	<b>309</b>	<b>Location Qualifier</b>	<b>X</b>	<b>ID 1/2</b>
		Code identifying type of location		
		RJ Region		
<b>N406</b>	<b>310</b>	<b>Location Identifier</b>	<b>O</b>	<b>AN 1/30</b>
		Code which identifies a specific location		
		CALA (RPL-63a) = Customer Address Location Area		

**Segment:** **NX2** Location ID Component  
**Position:** 3850  
**Loop:** N1 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To define types and values of a geographic location  
**Syntax Notes:**  
**Semantic Notes:**  
**Comments:**  
**Notes:**

NX2\*01\*SANO (RPL-47)  
 NX2\*02\*SASN (RPL-50)  
 NX2\*03\*SASD (RPL-49)  
 NX2\*05\*BOX (RPL-60c)  
 NX2\*06\*ROUTE (RPL-60b)  
 NX2\*07\*CITY (RPL-61)  
 NX2\*39\*AHN (RPL-60a)  
 NX2\*40\*SASS (RPL-52)  
 NX2\*59\*SAPR (RPL-46)  
 NX2\*61\*SASF (RPL-48)  
 NX2\*62\*SATH (RPL-51)  
 NX2\*LD1 (RPL-53)\*LV1 (RPL-54)  
 NX2\*LD2 (RPL-55)\*LV2 (RPL-56)  
 NX2\*LD3 (RPL-57)\*LV3 (RPL-58)

**Data Element Summary**

Ref.	Data			
<u>Des.</u>	<u>Element</u>	<u>Name</u>		
M	<b>Attributes</b> NX201	1106	<b>Address Component Qualifier</b> Code qualifying the type of address component LD1 (RPL-53) = Location Designator 1 13 = (DWS: APT) 34 = (DWS: LOT) 35 = (DWS: RM) 36 = (DWS: SLIP) 37 = (DWS: UNIT) 14 = (DWS: SUIT) LD2 (RPL-55) = Location Designator 2 32 = (DWS: FLR) LD3 (RPL-57) = Location Designator 3 12 = (DWS: BLDG) 63 = (DWS: WNG) 30 = (DWS: PIER) 01 Street Number 02 Street Name 03 Prefix Direction 05 P.O. Box Number 06 Rural Route Number 07 City Name 12 Building Name	M ID 2/2

13	Apartment Number
14	Suite Number
30	Pier The pier at which a ship or boat is docked
32	Floor A particular floor or level of a building
34	Lot A particular lot or piece of land
35	Room A walled room or partitioned area of a building
36	Slip The slip or location on a pier at which a ship or boat is docked
37	Unit A unit or separate structure
39	Unstructured Property
40	Street Suffix
59	Street Number Low
61	Street Number Fraction
62	Street Name Suffix
63	Secondary Unit Identifier

**M**      **NX202**      **166**      **Address Information**      **M**      **AN 1/55**

Address information

SANO (RPL-47) = Service Address Number  
 SASN (RPL-50) = Service Address Street Name  
 SASD (RPL-49) = Service Address Street Directional Prefix  
 BOX (RPL-60c) = Box  
 ROUTE (RPL-60b) = Route  
 CITY (RPL-61) = City  
 AHN (RPL-60a) = Assigned House Number  
 SASS (RPL-52) = Service Address Street Directional Suffix  
 SAPR (RPL-46) = Service Address Number Prefix  
 SASF (RPL-48) = Service Address Number Suffix  
 SATH (RPL-51) = Service Address Street Type  
 LV1 (RPL-54) = Location Value 1  
 LV2 (RPL-56) = Location Value 2  
 LV3 (RPL-58) = Location Value 3



**Segment:** **PER** Administrative Communications Contact

**Position:** 4000

**Loop:** N1 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 3

**Purpose:** To identify a person or office to whom administrative communications should be directed

- Syntax Notes:**
- 1 If either PER03 or PER04 is present, then the other is required.
  - 2 If either PER05 or PER06 is present, then the other is required.
  - 3 If either PER07 or PER08 is present, then the other is required.

**Semantic Notes:**

**Comments:**

**Notes:** PER\*CA\*LCON (RPL-65)\*TE\*ACTEL NO (RPL-66)  
 PER\*AL\*ALCON (RPL-67)\*TE\*AACTEL (RPL-68)

**Data Element Summary**

Ref.	Data		
<u>Des.</u>	<u>Element</u>	<u>Name</u>	
M	<b>PER01</b>	<b>366</b>	<b>Contact Function Code</b> <span style="float: right;"><b>M ID 2/2</b></span>
		Code identifying the major duty or responsibility of the person or group named	
		AL Alternate Contact	
		CA Person to be contacted when the main contact is not available	
		Customer Contact Granting Appointment	
	<b>PER02</b>	<b>93</b>	<b>Name</b> <span style="float: right;"><b>O AN 1/60</b></span>
		Free-form name	
		LCON (RPL-65) = Local Contact	
		ALCON (RPL-67) = Alternate Local Contact	
	<b>PER03</b>	<b>365</b>	<b>Communication Number Qualifier</b> <span style="float: right;"><b>X ID 2/2</b></span>
		Code identifying the type of communication number	
		TE Telephone	
	<b>PER04</b>	<b>364</b>	<b>Communication Number</b> <span style="float: right;"><b>X AN 1/256</b></span>
		Complete communications number including country or area code when applicable	
		ACTEL NO (RPL-66) = Access Telephone Number	
		AACTEL (RPL-68) = Alternate Access Telephone Number	

**Segment:** **SI** Service Characteristic Identification

**Position:** 4050

**Loop:** N1 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** >1

**Purpose:** To specify service characteristic data

- Syntax Notes:**
- 1 If either SI04 or SI05 is present, then the other is required.
  - 2 If either SI06 or SI07 is present, then the other is required.
  - 3 If either SI08 or SI09 is present, then the other is required.
  - 4 If either SI10 or SI11 is present, then the other is required.
  - 5 If either SI12 or SI13 is present, then the other is required.
  - 6 If either SI14 or SI15 is present, then the other is required.
  - 7 If either SI16 or SI17 is present, then the other is required.
  - 8 If either SI18 or SI19 is present, then the other is required.
  - 9 If either SI20 or SI21 is present, then the other is required.

**Semantic Notes:**

- Comments:**
- 1 SI01 defines the source for each of the service characteristics qualifiers.

**Notes:** SI\*TI\*AF\*AFT (RPL-45)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
	<u>Attributes</u>				
M	SI01	559	<b>Agency Qualifier Code</b>	M	ID 2/2
			Code identifying the agency assigning the code values		
			TI Telecommunications Industry		
M	SI02	1000	<b>Service Characteristics Qualifier</b>	M	AN 2/2
			Code from an industry code list qualifying the type of service characteristics		
			AF Address Format Type		
M	SI03	234	<b>Product/Service ID</b>	M	AN 1/48
			Identifying number for a product or service		
			AFT (RPL-45) = Address Format Type		

**Segment:** **PO1** **Baseline Item Data - Disconnect Information**

**Position:** 0100  
**Loop:** PO1 Mandatory  
**Level:** Detail  
**Usage:** Mandatory  
**Max Use:** 1

**Purpose:** To specify basic and most frequently used line item data  
**Syntax Notes:**

- 1 If PO103 is present, then PO102 is required.
- 2 If PO105 is present, then PO104 is required.
- 3 If either PO106 or PO107 is present, then the other is required.
- 4 If either PO108 or PO109 is present, then the other is required.
- 5 If either PO110 or PO111 is present, then the other is required.
- 6 If either PO112 or PO113 is present, then the other is required.
- 7 If either PO114 or PO115 is present, then the other is required.
- 8 If either PO116 or PO117 is present, then the other is required.
- 9 If either PO118 or PO119 is present, then the other is required.
- 10 If either PO120 or PO121 is present, then the other is required.
- 11 If either PO122 or PO123 is present, then the other is required.
- 12 If either PO124 or PO125 is present, then the other is required.

**Semantic Notes:**  
**Comments:**

- 1 See the Data Element Dictionary for a complete list of IDs.
- 2 PO101 is the line item identification.
- 3 PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

**Notes:** PO1\*n\*1\*EA\*\*\*ZZ\*RPL\_DISC

**Data Element Summary**

<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
<b>Attributes</b>				
<b>PO101</b>	<b>350</b>	<b>Assigned Identification</b>	<b>O</b>	<b>AN 1/20</b>
		Alphanumeric characters assigned for differentiation within a transaction set		
		"n" = nth assigned ID within PO1 loop		
<b>PO102</b>	<b>330</b>	<b>Quantity Ordered</b>	<b>X</b>	<b>R 1/15</b>
		Quantity ordered		
		1 Always One		
<b>PO103</b>	<b>355</b>	<b>Unit or Basis for Measurement Code</b>	<b>O</b>	<b>ID 2/2</b>
		Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken		
		EA Each		
<b>PO106</b>	<b>235</b>	<b>Product/Service ID Qualifier</b>	<b>X</b>	<b>ID 2/2</b>
		Code identifying the type/source of the descriptive number used in Product/Service ID (234)		
		ZZ Mutually Defined		
<b>PO107</b>	<b>234</b>	<b>Product/Service ID</b>	<b>X</b>	<b>AN 1/48</b>
		Identifying number for a product or service		
		"RPL_DISC"		

**Segment:** **SI** Service Characteristic Identification

**Position:** 0180

**Loop:** PO1 Mandatory

**Level:** Detail

**Usage:** Optional

**Max Use:** >1

**Purpose:** To specify service characteristic data

- Syntax Notes:**
- 1 If either SI04 or SI05 is present, then the other is required.
  - 2 If either SI06 or SI07 is present, then the other is required.
  - 3 If either SI08 or SI09 is present, then the other is required.
  - 4 If either SI10 or SI11 is present, then the other is required.
  - 5 If either SI12 or SI13 is present, then the other is required.
  - 6 If either SI14 or SI15 is present, then the other is required.
  - 7 If either SI16 or SI17 is present, then the other is required.
  - 8 If either SI18 or SI19 is present, then the other is required.
  - 9 If either SI20 or SI21 is present, then the other is required.

**Semantic Notes:**

- Comments:**
- 1 SI01 defines the source for each of the service characteristics qualifiers.

**Notes:** SI\*TI\*ED\*DISC ECCKT (RPL-90)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
	<u>Attributes</u>				
M	SI01	559	<b>Agency Qualifier Code</b>	M	ID 2/2
			Code identifying the agency assigning the code values		
			TI Telecommunications Industry		
M	SI02	1000	<b>Service Characteristics Qualifier</b>	M	AN 2/2
			Code from an industry code list qualifying the type of service characteristics		
			ED Disconnect ECCKT		
M	SI03	234	<b>Product/Service ID</b>	M	AN 1/48
			Identifying number for a product or service		
			DISC ECCKT (RPL-90) = Disconnect ECCKT		

**Segment:** **PO1** **Baseline Item Data - Remarks Information**

**Position:** 0100  
**Loop:** PO1 Mandatory  
**Level:** Detail  
**Usage:** Mandatory  
**Max Use:** 1

**Purpose:** To specify basic and most frequently used line item data  
**Syntax Notes:**

- 1 If PO103 is present, then PO102 is required.
- 2 If PO105 is present, then PO104 is required.
- 3 If either PO106 or PO107 is present, then the other is required.
- 4 If either PO108 or PO109 is present, then the other is required.
- 5 If either PO110 or PO111 is present, then the other is required.
- 6 If either PO112 or PO113 is present, then the other is required.
- 7 If either PO114 or PO115 is present, then the other is required.
- 8 If either PO116 or PO117 is present, then the other is required.
- 9 If either PO118 or PO119 is present, then the other is required.
- 10 If either PO120 or PO121 is present, then the other is required.
- 11 If either PO122 or PO123 is present, then the other is required.
- 12 If either PO124 or PO125 is present, then the other is required.

**Semantic Notes:**  
**Comments:**

- 1 See the Data Element Dictionary for a complete list of IDs.
- 2 PO101 is the line item identification.
- 3 PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

**Notes:** PO1\*n\*1\*EA\*\*\*ZZ\*RPL\_REM

**Data Element Summary**

<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
<b>Attributes</b>				
<b>PO101</b>	<b>350</b>	<b>Assigned Identification</b>	<b>O</b>	<b>AN 1/20</b>
		Alphanumeric characters assigned for differentiation within a transaction set		
		"n" = nth assigned ID within PO1 loop		
<b>PO102</b>	<b>330</b>	<b>Quantity Ordered</b>	<b>X</b>	<b>R 1/15</b>
		Quantity ordered		
		1 Always One		
<b>PO103</b>	<b>355</b>	<b>Unit or Basis for Measurement Code</b>	<b>O</b>	<b>ID 2/2</b>
		Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken		
		EA Each		
<b>PO106</b>	<b>235</b>	<b>Product/Service ID Qualifier</b>	<b>X</b>	<b>ID 2/2</b>
		Code identifying the type/source of the descriptive number used in Product/Service ID (234)		
		ZZ Mutually Defined		
<b>PO107</b>	<b>234</b>	<b>Product/Service ID</b>	<b>X</b>	<b>AN 1/48</b>
		Identifying number for a product or service		
		"RPL_REM"		

**Segment:** **N9 Reference Identification**

**Position:** 3300

**Loop:** N9 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To transmit identifying information as specified by the Reference Identification Qualifier

- Syntax Notes:**
- 1 At least one of N902 or N903 is required.
  - 2 If N906 is present, then N905 is required.
  - 3 If either C04003 or C04004 is present, then the other is required.
  - 4 If either C04005 or C04006 is present, then the other is required.

- Semantic Notes:**
- 1 N906 reflects the time zone which the time reflects.
  - 2 N907 contains data relating to the value cited in N902.

**Comments:**

**Notes:** N9\*H7\*ORI\*RPL\*\*\*\*2W>MANUAL IND (RPL-91a)

**Data Element Summary**

	<u>Ref. Des. Attributes</u>	<u>Data Element</u>	<u>Name</u>		
M	N901	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification H7 Standard Clause	M	ID 2/3
	N902	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier ORI Order Instructions	X	AN 1/30
	N903	369	<b>Free-form Description</b> Free-form descriptive text "RPL"	X	AN 1/45
	N907	C040	<b>Reference Identifier</b> To identify one or more reference numbers or identification numbers as specified by the Reference Qualifier	O	
M	C04001	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification 2W Change Order Authority	M	ID 2/3
M	C04002	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier MANUAL IND (RPL-91a) = Manual Indicator	M	AN 1/30

**Segment:** **MTX** Text  
**Position:** 3400  
**Loop:** N9 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To specify textual data  
**Syntax Notes:**

- 1 If MTX01 is present, then MTX02 is required.
- 2 If MTX03 is present, then MTX02 is required.
- 3 If MTX05 is present, then MTX04 is required.

**Semantic Notes:**

- 1 MTX05 is the number of lines to advance before printing.

**Comments:**

- 1 If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

**Notes:** MTX\*\*REMARKS (RPL-91)

**Data Element Summary**

<u>Ref.</u> <u>Des.</u>	<u>Data</u> <u>Element</u>	<u>Name</u>		
<b>Attributes</b> MTX02	1551	<b>Message Text</b>		<b>X AN 1/4096</b>
		To transmit large volumes of message text		
		REMARKS (RPL-91) = Remarks		

**Segment:** **PO1** **Baseline Item Data - Primary Location Service Details**

**Position:** 0100

**Loop:** PO1 Mandatory

**Level:** Detail

**Usage:** Mandatory

**Max Use:** 1

**Purpose:** To specify basic and most frequently used line item data

- Syntax Notes:**
- 1 If PO103 is present, then PO102 is required.
  - 2 If PO105 is present, then PO104 is required.
  - 3 If either PO106 or PO107 is present, then the other is required.
  - 4 If either PO108 or PO109 is present, then the other is required.
  - 5 If either PO110 or PO111 is present, then the other is required.
  - 6 If either PO112 or PO113 is present, then the other is required.
  - 7 If either PO114 or PO115 is present, then the other is required.
  - 8 If either PO116 or PO117 is present, then the other is required.
  - 9 If either PO118 or PO119 is present, then the other is required.
  - 10 If either PO120 or PO121 is present, then the other is required.
  - 11 If either PO122 or PO123 is present, then the other is required.
  - 12 If either PO124 or PO125 is present, then the other is required.

**Semantic Notes:**

- Comments:**
- 1 See the Data Element Dictionary for a complete list of IDs.
  - 2 PO101 is the line item identification.
  - 3 PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

**Notes:** PO1\*n\*1\*EA\*\*\*ZZ\*RPL\_PLSD

**Data Element Summary**

<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
<b>Attributes</b>				
<b>PO101</b>	<b>350</b>	<b>Assigned Identification</b>	<b>O</b>	<b>AN 1/20</b>
		Alphanumeric characters assigned for differentiation within a transaction set		
		"n" = nth assigned ID within PO1 loop		
<b>PO102</b>	<b>330</b>	<b>Quantity Ordered</b>	<b>X</b>	<b>R 1/15</b>
		Quantity ordered		
		1 Always One		
<b>PO103</b>	<b>355</b>	<b>Unit or Basis for Measurement Code</b>	<b>O</b>	<b>ID 2/2</b>
		Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken		
		EA Each		
<b>PO106</b>	<b>235</b>	<b>Product/Service ID Qualifier</b>	<b>X</b>	<b>ID 2/2</b>
		Code identifying the type/source of the descriptive number used in Product/Service ID (234)		
		ZZ Mutually Defined		
<b>PO107</b>	<b>234</b>	<b>Product/Service ID</b>	<b>X</b>	<b>AN 1/48</b>
		Identifying number for a product or service		
		"RPL_PLSD"		



**Segment:** **SI** Service Characteristic Identification

**Position:** 0180  
**Loop:** PO1 Mandatory  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1

**Purpose:** To specify service characteristic data  
**Syntax Notes:**

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

**Semantic Notes:**

**Comments:** 1 SI01 defines the source for each of the service characteristics qualifiers.

**Notes:** SI\*TI\*LT\*02 (designates "primary")  
 SI\*TI\*SA\*LNA (RPL-94)  
 SI\*TI\*CN\*ECCKT (RPL-104)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
	<b>Attributes</b>				
M	SI01	559	<b>Agency Qualifier Code</b>	M	ID 2/2
			Code identifying the agency assigning the code values		
			TI Telecommunications Industry		
M	SI02	1000	<b>Service Characteristics Qualifier</b>	M	AN 2/2
			Code from an industry code list qualifying the type of service characteristics		
			CN Circuit Number Identification		
			LT Location Type		
			SA Service Activity		
M	SI03	234	<b>Product/Service ID</b>	M	AN 1/48
			Identifying number for a product or service		
			LNA (RPL-94) = Line Activity		
			C = (DWS: C-Change or Modification to an Existing Wholesale Service)		
			A = (DWS: N-New Installation)		
			V = (DWS: V-Conversion As Specified)		
			02 = Primary		
			ECCKT (RPL-104) = Exchange Company Circuit ID		

**Segment:** **PID** **Product/Item Description**

**Position:** 0500

**Loop:** PID Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To describe a product or process in coded or free-form format

**Syntax Notes:**

- 1 If PID04 is present, then PID03 is required.
- 2 At least one of PID04 or PID05 is required.
- 3 If PID07 is present, then PID03 is required.
- 4 If PID08 is present, then PID04 is required.
- 5 If PID09 is present, then PID05 is required.

**Semantic Notes:**

- 1 Use PID03 to indicate the organization that publishes the code list being referred to.
- 2 PID04 should be used for industry-specific product description codes.
- 3 PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
- 4 PID09 is used to identify the language being used in PID05.

**Comments:**

- 1 If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
- 2 Use PID06 when necessary to refer to the product surface or layer being described in the segment.
- 3 PID07 specifies the individual code list of the agency specified in PID03.

**Notes:** PID\*X\*\*TI\*CFA\*CFA (RPL-105)

#### Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	<b>PID01</b>	<b>349</b>	<b>Item Description Type</b>	<b>M</b>	<b>ID 1/1</b>
			Code indicating the format of a description		
			X Semi-structured (Code and Text)		
	<b>PID03</b>	<b>559</b>	<b>Agency Qualifier Code</b>	<b>X</b>	<b>ID 2/2</b>
			Code identifying the agency assigning the code values		
		TI Telecommunications Industry			
	<b>PID04</b>	<b>751</b>	<b>Product Description Code</b>	<b>X</b>	<b>AN 1/12</b>
			A code from an industry code list which provides specific data about a product characteristic		
			CFA Connecting Facility Assignment		
	<b>PID05</b>	<b>352</b>	<b>Description</b>	<b>X</b>	<b>AN 1/80</b>
			A free-form description to clarify the related data elements and their content		
			CFA (RPL-105) = Connecting Facility Assignment		

**Segment:** **REF** Reference Identification  
**Position:** 1000  
**Loop:** PO1 Mandatory  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To specify identifying information  
**Syntax Notes:**

- 1 At least one of REF02 or REF03 is required.
- 2 If either C04003 or C04004 is present, then the other is required.
- 3 If either C04005 or C04006 is present, then the other is required.

**Semantic Notes:**

- 1 REF04 contains data relating to the value cited in REF02.

**Comments:**  
**Notes:** REF\*AE\*SAN (RPL-94a)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	REF01	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification AE Authorization for Expense (AFE) Number	M	ID 2/3
	REF02	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier SAN (RPL-94a) = Subscriber Authorization Number	X	AN 1/30

**Segment:** **SLN** Subline Item Detail

**Position:** 4700

**Loop:** SLN Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To specify product subline detail item data

**Syntax Notes:**

- 1 If either SLN04 or SLN05 is present, then the other is required.
- 2 If SLN07 is present, then SLN06 is required.
- 3 If SLN08 is present, then SLN06 is required.
- 4 If either SLN09 or SLN10 is present, then the other is required.
- 5 If either SLN11 or SLN12 is present, then the other is required.
- 6 If either SLN13 or SLN14 is present, then the other is required.
- 7 If either SLN15 or SLN16 is present, then the other is required.
- 8 If either SLN17 or SLN18 is present, then the other is required.
- 9 If either SLN19 or SLN20 is present, then the other is required.
- 10 If either SLN21 or SLN22 is present, then the other is required.
- 11 If either SLN23 or SLN24 is present, then the other is required.
- 12 If either SLN25 or SLN26 is present, then the other is required.
- 13 If either SLN27 or SLN28 is present, then the other is required.

**Semantic Notes:**

- 1 SLN01 is the identifying number for the subline item.
- 2 SLN02 is the identifying number for the subline level. The subline level is analogous to the level code used in a bill of materials.
- 3 SLN03 is the configuration code indicating the relationship of the subline item to the baseline item.
- 4 SLN08 is a code indicating the relationship of the price or amount to the associated segment.

**Comments:**

- 1 See the Data Element Dictionary for a complete list of IDs.
- 2 SLN01 is related to (but not necessarily equivalent to) the baseline item number. Example: 1.1 or 1A might be used as a subline number to relate to baseline number 1.
- 3 SLN09 through SLN28 provide for ten different product/service IDs for each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

**Notes:** SLN\*IW\*n\*A\*IWJQ (RPL-101)\*EA\*\*\*\*EQ\*IWJK (RPL-102) [SLN Loop may repeat per Inside Wiring Pair]

#### Data Element Summary

	Ref. Des.	Data Element	Name		
M	SLN01	350	Assigned Identification	M	AN 1/20
			Alphanumeric characters assigned for differentiation within a transaction set		
			"IW"		
	SLN02	350	Assigned Identification	O	AN 1/20
			Alphanumeric characters assigned for differentiation within a transaction set		
			"n" = nth assigned ID within SLN loop		
M	SLN03	662	Relationship Code	M	ID 1/1
			Code indicating the relationship between entities		
			A Add		
	SLN04	380	Quantity	X	R 1/15

			Numeric value of quantity		
			IWJQ (RPL-101) = Inside Wire Jack Quantity		
	<b>SLN05</b>	<b>C001</b>	<b>Composite Unit of Measure</b>	<b>X</b>	
			To identify a composite unit of measure (See Figures Appendix for examples of use)		
<b>M</b>	<b>C00101</b>	<b>355</b>	<b>Unit or Basis for Measurement Code</b>	<b>M</b>	<b>ID 2/2</b>
			Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken		
			EA                      Each		
	<b>SLN09</b>	<b>235</b>	<b>Product/Service ID Qualifier</b>	<b>X</b>	<b>ID 2/2</b>
			Code identifying the type/source of the descriptive number used in Product/Service ID (234)		
			EQ                      Equipment Type		
	<b>SLN10</b>	<b>234</b>	<b>Product/Service ID</b>	<b>X</b>	<b>AN 1/48</b>
			Identifying number for a product or service		
			IWJK (RPL-102) = Inside Wire Jack Code		

**Segment:** **PO1** **Baseline Item Data - Secondary Location Service Details**

**Position:** 0100  
**Loop:** PO1 Mandatory  
**Level:** Detail  
**Usage:** Mandatory  
**Max Use:** 1

**Purpose:** To specify basic and most frequently used line item data  
**Syntax Notes:**

- 1 If PO103 is present, then PO102 is required.
- 2 If PO105 is present, then PO104 is required.
- 3 If either PO106 or PO107 is present, then the other is required.
- 4 If either PO108 or PO109 is present, then the other is required.
- 5 If either PO110 or PO111 is present, then the other is required.
- 6 If either PO112 or PO113 is present, then the other is required.
- 7 If either PO114 or PO115 is present, then the other is required.
- 8 If either PO116 or PO117 is present, then the other is required.
- 9 If either PO118 or PO119 is present, then the other is required.
- 10 If either PO120 or PO121 is present, then the other is required.
- 11 If either PO122 or PO123 is present, then the other is required.
- 12 If either PO124 or PO125 is present, then the other is required.

**Semantic Notes:**  
**Comments:**

- 1 See the Data Element Dictionary for a complete list of IDs.
- 2 PO101 is the line item identification.
- 3 PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

**Notes:** PO1\*n\*1\*EA\*\*\*ZZ\*RPL\_SLSD [PO1 Loop repeats SECLOCSEVDETQTY(RPL-108a) times]

**Data Element Summary**

<u>Ref.</u>	<u>Data</u>	<u>Element</u>	<u>Name</u>		
<b>PO101</b>	<b>350</b>	<b>Assigned Identification</b>		<b>O</b>	<b>AN 1/20</b>
			Alphanumeric characters assigned for differentiation within a transaction set "n" = nth assigned ID within PO1 loop		
<b>PO102</b>	<b>330</b>	<b>Quantity Ordered</b>		<b>X</b>	<b>R 1/15</b>
			Quantity ordered 1 Always One		
<b>PO103</b>	<b>355</b>	<b>Unit or Basis for Measurement Code</b>		<b>O</b>	<b>ID 2/2</b>
			Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken EA Each		
<b>PO106</b>	<b>235</b>	<b>Product/Service ID Qualifier</b>		<b>X</b>	<b>ID 2/2</b>
			Code identifying the type/source of the descriptive number used in Product/Service ID (234) ZZ Mutually Defined		
<b>PO107</b>	<b>234</b>	<b>Product/Service ID</b>		<b>X</b>	<b>AN 1/48</b>
			Identifying number for a product or service "RPL_SLSD"		

**Segment:** **SI** Service Characteristic Identification

**Position:** 0180  
**Loop:** PO1 Mandatory  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1

**Purpose:** To specify service characteristic data  
**Syntax Notes:**

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

**Semantic Notes:**

**Comments:** 1 SI01 defines the source for each of the service characteristics qualifiers.

**Notes:** SI\*TI\*LT\*04 (designates "secondary")  
 SI\*TI\*SA\*LNA (RPL-111)  
 SI\*TI\*CN\*ECCKT (RPL-119)

**Data Element Summary**

Ref.	Data			
<u>Des.</u>	<u>Element</u>	<u>Name</u>		
<b>M</b>	<b>SI01</b>	<b>559</b>	<b>Agency Qualifier Code</b>	<b>M ID 2/2</b>
			Code identifying the agency assigning the code values	
			TI Telecommunications Industry	
<b>M</b>	<b>SI02</b>	<b>1000</b>	<b>Service Characteristics Qualifier</b>	<b>M AN 2/2</b>
			Code from an industry code list qualifying the type of service characteristics	
			CN Circuit Number Identification	
			LT Location Type	
			SA Service Activity	
<b>M</b>	<b>SI03</b>	<b>234</b>	<b>Product/Service ID</b>	<b>M AN 1/48</b>
			Identifying number for a product or service	
			LNA (RPL-111) = Line Activity	
			C = (DWS: C-Change or Modification to Existing Wholesale Service)	
			A = (DWS: N-New installation)	
			V = (DWS: V-Conversion as specified)	
			D = (DWS: D-Remove a secondary location)	
			04 = Secondary	
			ECCKT (RPL-119) = Exchange Company Circuit ID	

**Segment:** **PID** Product/Item Description

**Position:** 0500

**Loop:** PID Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To describe a product or process in coded or free-form format

**Syntax Notes:**

- 1 If PID04 is present, then PID03 is required.
- 2 At least one of PID04 or PID05 is required.
- 3 If PID07 is present, then PID03 is required.
- 4 If PID08 is present, then PID04 is required.
- 5 If PID09 is present, then PID05 is required.

**Semantic Notes:**

- 1 Use PID03 to indicate the organization that publishes the code list being referred to.
- 2 PID04 should be used for industry-specific product description codes.
- 3 PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
- 4 PID09 is used to identify the language being used in PID05.

**Comments:**

- 1 If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
- 2 Use PID06 when necessary to refer to the product surface or layer being described in the segment.
- 3 PID07 specifies the individual code list of the agency specified in PID03.

**Notes:** PID\*X\*\*TI\*CFA\*CFA (RPL-120)

#### Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	<b>PID01</b>	<b>349</b>	<b>Item Description Type</b>	<b>M</b>	<b>ID 1/1</b>
			Code indicating the format of a description		
			X Semi-structured (Code and Text)		
	<b>PID03</b>	<b>559</b>	<b>Agency Qualifier Code</b>	<b>X</b>	<b>ID 2/2</b>
			Code identifying the agency assigning the code values		
		TI Telecommunications Industry			
	<b>PID04</b>	<b>751</b>	<b>Product Description Code</b>	<b>X</b>	<b>AN 1/12</b>
			A code from an industry code list which provides specific data about a product characteristic		
			CFA Connecting Facility Assignment		
	<b>PID05</b>	<b>352</b>	<b>Description</b>	<b>X</b>	<b>AN 1/80</b>
			A free-form description to clarify the related data elements and their content		
			CFA (RPL-120) = Connecting Facility Assignment		



**Segment:** **REF** Reference Identification  
**Position:** 1000  
**Loop:** PO1 Mandatory  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To specify identifying information  
**Syntax Notes:**

- 1 At least one of REF02 or REF03 is required.
- 2 If either C04003 or C04004 is present, then the other is required.
- 3 If either C04005 or C04006 is present, then the other is required.

**Semantic Notes:**

- 1 REF04 contains data relating to the value cited in REF02.

**Comments:**  
**Notes:** REF\*IX\*LOCNUM (RPL-109)\*LOCNUM

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	REF01	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification IX Item Number	M	ID 2/3
	REF02	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier LOCNUM (RPL-109) = Location Number	X	AN 1/30
	REF03	352	<b>Description</b> A free-form description to clarify the related data elements and their content "LOCNUM"	X	AN 1/80

**Segment:** **SLN** Subline Item Detail

**Position:** 4700

**Loop:** SLN Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To specify product subline detail item data

**Syntax Notes:**

- 1 If either SLN04 or SLN05 is present, then the other is required.
- 2 If SLN07 is present, then SLN06 is required.
- 3 If SLN08 is present, then SLN06 is required.
- 4 If either SLN09 or SLN10 is present, then the other is required.
- 5 If either SLN11 or SLN12 is present, then the other is required.
- 6 If either SLN13 or SLN14 is present, then the other is required.
- 7 If either SLN15 or SLN16 is present, then the other is required.
- 8 If either SLN17 or SLN18 is present, then the other is required.
- 9 If either SLN19 or SLN20 is present, then the other is required.
- 10 If either SLN21 or SLN22 is present, then the other is required.
- 11 If either SLN23 or SLN24 is present, then the other is required.
- 12 If either SLN25 or SLN26 is present, then the other is required.
- 13 If either SLN27 or SLN28 is present, then the other is required.

**Semantic Notes:**

- 1 SLN01 is the identifying number for the subline item.
- 2 SLN02 is the identifying number for the subline level. The subline level is analogous to the level code used in a bill of materials.
- 3 SLN03 is the configuration code indicating the relationship of the subline item to the baseline item.
- 4 SLN08 is a code indicating the relationship of the price or amount to the associated segment.

**Comments:**

- 1 See the Data Element Dictionary for a complete list of IDs.
- 2 SLN01 is related to (but not necessarily equivalent to) the baseline item number. Example: 1.1 or 1A might be used as a subline number to relate to baseline number 1.
- 3 SLN09 through SLN28 provide for ten different product/service IDs for each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

**Notes:** SLN\*IW\*n\*A\*IWJQ (RPL-116)\*EA\*\*\*\*EQ\*IWJK (RPL-117) [SLN Loop may repeat per Inside Wiring Pair]

#### Data Element Summary

	Ref. Des.	Data Element	Name		
M	SLN01	350	Assigned Identification	M	AN 1/20
			Alphanumeric characters assigned for differentiation within a transaction set		
			"IW"		
	SLN02	350	Assigned Identification	O	AN 1/20
			Alphanumeric characters assigned for differentiation within a transaction set		
			"n" = nth assigned ID within SLN loop		
M	SLN03	662	Relationship Code	M	ID 1/1
			Code indicating the relationship between entities		
			A Add		
	SLN04	380	Quantity	X	R 1/15

			Numeric value of quantity		
			IWJQ (RPL-116) = Inside Wire Jack Quantity		
	<b>SLN05</b>	<b>C001</b>	<b>Composite Unit of Measure</b>	<b>X</b>	
			To identify a composite unit of measure (See Figures Appendix for examples of use)		
<b>M</b>	<b>C00101</b>	<b>355</b>	<b>Unit or Basis for Measurement Code</b>	<b>M</b>	<b>ID 2/2</b>
			Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken		
			EA                      Each		
	<b>SLN09</b>	<b>235</b>	<b>Product/Service ID Qualifier</b>	<b>X</b>	<b>ID 2/2</b>
			Code identifying the type/source of the descriptive number used in Product/Service ID (234)		
			EQ                      Equipment Type		
	<b>SLN10</b>	<b>234</b>	<b>Product/Service ID</b>	<b>X</b>	<b>AN 1/48</b>
			Identifying number for a product or service		
			IWJK (RPL-117) = Inside Wire Jack Code		

**Segment:** **PO1** **Baseline Item Data - Dummy (DA)**

**Position:** 0100

**Loop:** PO1 Mandatory

**Level:** Detail

**Usage:** Mandatory

**Max Use:** 1

**Purpose:** To specify basic and most frequently used line item data

**Syntax Notes:**

- 1 If PO103 is present, then PO102 is required.
- 2 If PO105 is present, then PO104 is required.
- 3 If either PO106 or PO107 is present, then the other is required.
- 4 If either PO108 or PO109 is present, then the other is required.
- 5 If either PO110 or PO111 is present, then the other is required.
- 6 If either PO112 or PO113 is present, then the other is required.
- 7 If either PO114 or PO115 is present, then the other is required.
- 8 If either PO116 or PO117 is present, then the other is required.
- 9 If either PO118 or PO119 is present, then the other is required.
- 10 If either PO120 or PO121 is present, then the other is required.
- 11 If either PO122 or PO123 is present, then the other is required.
- 12 If either PO124 or PO125 is present, then the other is required.

**Semantic Notes:**

**Comments:**

- 1 See the Data Element Dictionary for a complete list of IDs.
- 2 PO101 is the line item identification.
- 3 PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

**Notes:** PO1\*DUMMY\*1\*EA\*\*\*ZZ\*DD

**Data Element Summary**

<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
<b>Attributes</b>				
<b>PO101</b>	<b>350</b>	<b>Assigned Identification</b>	<b>O</b>	<b>AN 1/20</b>
		Alphanumeric characters assigned for differentiation within a transaction set		
		"DUMMY"		
<b>PO102</b>	<b>330</b>	<b>Quantity Ordered</b>	<b>X</b>	<b>R 1/15</b>
		Quantity ordered		
		1 Always One		
<b>PO103</b>	<b>355</b>	<b>Unit or Basis for Measurement Code</b>	<b>O</b>	<b>ID 2/2</b>
		Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken		
		EA Each		
<b>PO106</b>	<b>235</b>	<b>Product/Service ID Qualifier</b>	<b>X</b>	<b>ID 2/2</b>
		Code identifying the type/source of the descriptive number used in Product/Service ID (234)		
		ZZ Mutually Defined		
<b>PO107</b>	<b>234</b>	<b>Product/Service ID</b>	<b>X</b>	<b>AN 1/48</b>
		Identifying number for a product or service		
		"DD"		

**Segment:** **CTT** Transaction Totals

**Position:** 0100

**Loop:** CTT Optional

**Level:** Summary

**Usage:** Optional

**Max Use:** 1

**Purpose:** To transmit a hash total for a specific element in the transaction set

**Syntax Notes:** 1 If either CTT03 or CTT04 is present, then the other is required.

2 If either CTT05 or CTT06 is present, then the other is required.

**Semantic Notes:**

**Comments:** 1 This segment is intended to provide hash totals to validate transaction completeness and correctness.

**Notes:** CTT\*Number of PO1 Segments

#### Data Element Summary

	<u>Ref.</u> <u>Des.</u> <u>Attributes</u>	<u>Data</u> <u>Element</u>	<u>Name</u>	
M	CTT01	354	Number of Line Items Total number of line items in the transaction set	M NO 1/6

**Segment:** **SE** Transaction Set Trailer  
**Position:** 0300  
**Loop:**  
**Level:** Summary  
**Usage:** Mandatory  
**Max Use:** 1  
**Purpose:** To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

**Syntax Notes:**

**Semantic Notes:**

**Comments:** 1 SE is the last segment of each transaction set.

**Notes:** SE\*No of Segments\*TRANS SET CONTROL#

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
<b>M</b>	<b>SE01</b>	<b>96</b>	<b>Number of Included Segments</b>	<b>M</b>	<b>NO 1/10</b>
			Total number of segments included in a transaction set including ST and SE segments		
<b>M</b>	<b>SE02</b>	<b>329</b>	<b>Transaction Set Control Number</b>	<b>M</b>	<b>AN 4/9</b>
			Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set		

## 23.6.2 860 Resale Private Line Supplemental Service Request (850PL)

Functional Group ID=**PC**

### Introduction:

The supplemental (860PL) for Resale Private Line is used by the Co-Provider to initiate the resale of primary and secondary service with details.

This implementation guideline is based on the following:

1. LSOG 5, when applicable, and Qwest assigned fields
2. ANSI ASC X12 Version 4020
3. TCIF/SOSC Guidelines, ELMS5

### Notes:

This 860 Transaction includes the mappings for Local Service Request and Resale Private Line.

### Heading:

	<u>Pos. No.</u>	<u>Seg. ID</u>	<u>Name</u>	<u>Req. Des.</u>	<u>Max.Use</u>	<u>Loop Repeat</u>	<u>Notes and Comments</u>
M	0100	ST	Transaction Set Header	M	1		
M	0200	BCH	Beginning Segment for Purchase Order Change	M	1		
	0500	REF	Reference Identification	O	>1		
	0950	PAM	Period Amount	O	10		
						<b>LOOP ID - SAC</b>	<b>25</b>
	1200	SAC	Service, Promotion, Allowance, or Charge Information	O	1		
	1500	DTM	Date/Time Reference	O	10		
	1850	SI	Service Characteristic Identification	O	>1		
	1900	PID	Product/Item Description	O	200		
	2100	PWK	Paperwork	O	25		
						<b>LOOP ID - N9</b>	<b>1000</b>
	2850	N9	Reference Identification	O	1		
	2900	MTX	Text	O	>1		
						<b>LOOP ID - N1</b>	<b>200</b>
	3000	N1	Name	O	1		
	3500	PER	Administrative Communications Contact	O	>1		
						<b>LOOP ID - N1</b>	<b>200</b>
	3000	N1	Name	O	1		
						<b>LOOP ID - N1</b>	<b>200</b>
	3000	N1	Name	O	1		
	3500	PER	Administrative Communications Contact	O	>1		

Pos. No.	Seg. ID	Name	Req. Des.	Max.Use	Loop Repeat	Notes and Comments
LOOP ID - N1					200	
3000	N1	Name	O	1		
3100	N2	Additional Name Information	O	2		
3300	N4	Geographic Location	O	>1		
3350	NX2	Location ID Component	O	>1		
3500	PER	Administrative Communications Contact	O	>1		
3550	SI	Service Characteristic Identification	O	>1		

**Detail:**

Pos. No.	Seg. ID	Name	Req. Des.	Max.Use	Loop Repeat	Notes and Comments
LOOP ID - POC					>1	
0100	POC	Line Item Change - RPL, Primary Location Section	O	1		
0180	SI	Service Characteristic Identification	O	>1		
LOOP ID - PID					1000	
0500	PID	Product/Item Description	O	1		
1000	REF	Reference Identification	O	>1		
LOOP ID - N9					1000	
3200	N9	Reference Identification	O	1		
3260	MTX	Text	O	>1		
LOOP ID - N9					1000	
3200	N9	Reference Identification	O	1		
3260	MTX	Text	O	>1		
LOOP ID - N9					1000	
3200	N9	Reference Identification	O	1		
3260	MTX	Text	O	>1		
LOOP ID - N1					200	
3400	N1	Name	O	1		
3500	N2	Additional Name Information	O	2		
3700	N4	Geographic Location	O	1		
3750	NX2	Location ID Component	O	>1		
3900	PER	Administrative Communications Contact	O	3		
3950	SI	Service Characteristic Identification	O	>1		
LOOP ID - POC					>1	
0100	POC	Line Item Change - RPL, Secondary Location Section	O	1		
0180	SI	Service Characteristic Identification	O	>1		
LOOP ID - PID					1000	
0500	PID	Product/Item Description	O	1		
1000	REF	Reference Identification	O	>1		
LOOP ID - N9					1000	
3200	N9	Reference Identification	O	1		
3260	MTX	Text	O	>1		
LOOP ID - N9					1000	



3200	N9	Reference Identification	O	1	
3260	MTX	Text	O	>1	
LOOP ID - N9					1000
3200	N9	Reference Identification	O	1	
3260	MTX	Text	O	>1	
LOOP ID - N1					200
3400	N1	Name	O	1	
3500	N2	Additional Name Information	O	2	
3700	N4	Geographic Location	O	1	
3750	NX2	Location ID Component	O	>1	
3900	PER	Administrative Communications Contact	O	3	
3950	SI	Service Characteristic Identification	O	>1	
LOOP ID - POC					>1
0100	POC	Line Item Change - RPL, Disconnect Information	O	1	
0180	SI	Service Characteristic Identification	O	>1	
LOOP ID - POC					>1
0100	POC	Line Item Change - RPL, Remarks Information	O	1	
LOOP ID - N9					1000
3200	N9	Reference Identification	O	1	
3260	MTX	Text	O	>1	
LOOP ID - POC					>1
0100	POC	Line Item Change - RPL, Primary Location - Services Details	O	1	
0180	SI	Service Characteristic Identification	O	>1	
LOOP ID - PID					1000
0500	PID	Product/Item Description	O	1	
1000	REF	Reference Identification	O	>1	
LOOP ID - SLN					>1
4600	SLN	Subline Item Detail	O	1	
LOOP ID - POC					>1
0100	POC	Line Item Change - RPL, Secondary Location - Service Details	O	1	
0180	SI	Service Characteristic Identification	O	>1	
LOOP ID - PID					1000
0500	PID	Product/Item Description	O	1	
1000	REF	Reference Identification	O	>1	
LOOP ID - SLN					>1
4600	SLN	Subline Item Detail	O	1	

### Summary:

<u>Pos. No.</u>	<u>Seg. ID</u>	<u>Name</u>	<u>Req. Des.</u>	<u>Max.Use</u>	<u>Loop Repeat</u>	<u>Notes and Comments</u>
LOOP ID - CTT					1	
0100	CTT	Transaction Totals	O	1		n1

### **Transaction Set Notes**

1. Number of line items (CTT01) is the accumulation of the number of POC segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (POC03) for each POC segment.

**Segment:** **ST** Transaction Set Header

**Position:** 0100

**Loop:**

**Level:** Heading

**Usage:** Mandatory

**Max Use:** 1

**Purpose:** To indicate the start of a transaction set and to assign a control number

**Syntax Notes:**

**Semantic Notes:**

- 1 The transaction set identifier (ST01) is used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).
- 2 The implementation convention reference (ST03) is used by the translation routines of the interchange partners to select the appropriate implementation convention to match the transaction set definition.

**Comments:**

**Notes:** ST\*860\*TRAN SET CONTROL#

#### Data Element Summary

	<u>Ref.</u> <u>Des.</u>	<u>Data</u> <u>Element</u>	<u>Name</u>		
<b>M</b>	<b>ST01</b>	<b>143</b>	<b>Transaction Set Identifier Code</b>	<b>M</b>	<b>ID 3/3</b>
			Code uniquely identifying a Transaction Set 860 Purchase Order Change Request - Buyer Initiated		
<b>M</b>	<b>ST02</b>	<b>329</b>	<b>Transaction Set Control Number</b>	<b>M</b>	<b>AN 4/9</b>
			Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set		

**Segment:** **BCH** Beginning Segment for Purchase Order Change

**Position:** 0200

**Loop:**

**Level:** Heading

**Usage:** Mandatory

**Max Use:** 1

**Purpose:** To indicate the beginning of the Purchase Order Change Transaction Set and transmit identifying numbers and dates

**Syntax Notes:**

**Semantic Notes:**

- 1 BCH06 is the date assigned by the purchaser to purchase order.
- 2 BCH09 is the seller's order number.
- 3 BCH10 is the date assigned by the sender to the acknowledgment.
- 4 BCH11 is the date of the purchase order change request.

**Comments:**

**Notes:** BCH\*SUP (LSR-25)\*SS\*PON (LSR-2)\*\*VER (LSR-3)\*PO Date (See Trading Partner Access Information)

#### Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	<u>Attributes</u> BCH01	353	<b>Transaction Set Purpose Code</b> Code identifying purpose of transaction set SUP (LSR-25) = Supplement Type 01 = Cancel 04 = DDD - Change 05 = Other 01 Cancellation 04 Change 05 Replace	M	ID 2/2
M	BCH02	92	<b>Purchase Order Type Code</b> Code specifying the type of Purchase Order SS Supply or Service Order	M	ID 2/2
M	BCH03	324	<b>Purchase Order Number</b> Identifying number for Purchase Order assigned by the orderer/purchaser PON (LSR-2) = Purchase Order Number	M	AN 1/22
	BCH05	327	<b>Change Order Sequence Number</b> Number assigned by the orderer identifying a specific change or revision to a previously transmitted transaction set VER (LSR-3) = Version Identification	O	AN 1/8
M	BCH06	373	<b>Date</b> Date expressed as CCYYMMDD PO Date = Purchase Order Date (See Trading Partner Access Information)	M	DT 8/8

**Segment:** **REF** Reference Identification  
**Position:** 0500  
**Loop:**  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To specify identifying information  
**Syntax Notes:**

- 1 At least one of REF02 or REF03 is required.
- 2 If either C04003 or C04004 is present, then the other is required.
- 3 If either C04005 or C04006 is present, then the other is required.

**Semantic Notes:**

- 1 REF04 contains data relating to the value cited in REF02.

**Comments:**  
**Notes:**

```

REF*11*AN (LSR-7)*AN
REF*JB*PROJECT (LSR-20)
REF*SU*RTR (LSR-28)*RTR
REF*CO*RPON (LSR-51)*RPON
REF*12*BAN1 (LSR-61)*BAN1
REF*1V*RORD (LSR-52)*RORD

```

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	REF01	128	<b>Reference Identification Qualifier</b>	M	ID 2/3
			Code qualifying the Reference Identification		
			11 Account Number		
			Number identifies a telecommunications industry account		
			12 Billing Account		
			Account number under which billing is rendered		
			1V Related Vendor Order Number		
			A vendor's order number that is in addition to a primary order number		
			CO Customer Order Number		
			JB Job (Project) Number		
			SU Special Processing Code		
			Unique code identifying the special handling requirements for the claim		
	REF02	127	<b>Reference Identification</b>	X	AN 1/30
			Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier		
			AN (LSR-7) = Account Number		
			PROJECT (LSR-20) = Project Identification		
			RTR (LSR-28) = Response Type Requested		
			RPON (LSR-51) = Related Purchase Order Number		
			BAN1 (LSR-61) = Billing Account Number 1		
			RORD (LSR-52) = Related Order Number		
	REF03	352	<b>Description</b>	X	AN 1/80
			A free-form description to clarify the related data elements and their content		
			"AN"		
			"RTR"		
			"RPON"		

"BAN1"  
"RORD"

**Segment:** **PAM** Period Amount  
**Position:** 0950  
**Loop:**  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** 10  
**Purpose:** To indicate a quantity, and/or amount for an identified period  
**Syntax Notes:**

- 1 If any of PAM01 PAM02 or PAM03 is present, then all are required.
- 2 At least one of PAM02 PAM05 or PAM14 is required.
- 3 If either PAM04 or PAM05 is present, then the other is required.
- 4 If either PAM06 or PAM07 is present, then the other is required.
- 5 If PAM07 is present, then at least one of PAM08 or PAM09 is required.
- 6 If PAM07 is present, then PAM06 is required.
- 7 If PAM08 is present, then PAM07 is required.
- 8 If PAM09 is present, then PAM07 is required.
- 9 If PAM10 is present, then at least one of PAM11 or PAM12 is required.
- 10 If PAM11 is present, then PAM10 is required.
- 11 If either PAM13 or PAM14 is present, then the other is required.

**Semantic Notes:**

- 1 PAM10, PAM11, or PAM12 are used when two dates are required.
- 2 PAM15 indicates whether the monetary amount identified in PAM05 is a net or gross value. A "Y" indicates amount is a gross value; an "N" indicates amount is a net value.

**Comments:**

**Notes:**  
PAM\*48\*PG\_of\_(LSR-10)(1st 2 Bytes)\*EA  
PAM\*47\*PG\_of\_(LSR-10)(2nd 2 Bytes)\*EA  
PAM\*QO\*RSQTY (RPL-5)\*EA  
PAM\*KC\*DQTY (RPL-6)\*EA  
PAM\*1Q\*SECLOCQTY (RPL-41a)\*EA  
PAM\*1R\*SECLOCSEVDETQTY (RPL-108a)\*EA

**Data Element Summary**

<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
<b>PAM01</b>	<b>673</b>	<b>Quantity Qualifier</b>	<b>X</b>	<b>ID 2/2</b>
		Code specifying the type of quantity		
		1Q Total Resource (Quantity)		
		Total amount of the resources available for the total duration of the task or activity		
		1R Level Resource (Quantity)		
		The amount of resources available for each time unit for the duration of the task or activity		
		47 Primary Net Quantity		
		48 Secondary Net Quantity		
		KC Net Quantity Decrease		
		The resultant quantity represents a net decrease to a previously transmitted quantity, after adjustments have been made		
		QO Operating Quantity		
<b>PAM02</b>	<b>380</b>	<b>Quantity</b>	<b>X</b>	<b>R 1/15</b>
		Numeric value of quantity		

First 2 bytes of PG\_of\_ (LSR-10)  
 Second 2 bytes of PG\_of\_ (LSR-10)  
 RSQTY (RPL-5) = Resale Quantity  
 DQTY (RPL-6) = Disconnect Quantity  
 SECLOCQTY (RPL-41a) = Secondary Location Quantity  
 SECLOCSEVDETQTY (RPL-108a) = Secondary Location Service  
 Details Quantity

	<b>PAM03</b>	<b>C001</b>	<b>Composite Unit of Measure</b>	<b>X</b>
			To identify a composite unit of measure (See Figures Appendix for examples of use)	
<b>M</b>	<b>C00101</b>	<b>355</b>	<b>Unit or Basis for Measurement Code</b>	<b>M ID 2/2</b>
			Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken	
			EA                      Each	



**Segment:** **SAC** Service, Promotion, Allowance, or Charge Information  
**Position:** 1200  
**Loop:** SAC Optional  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** 1  
**Purpose:** To request or identify a service, promotion, allowance, or charge; to specify the amount or percentage for the service, promotion, allowance, or charge

- Syntax Notes:**
- 1 At least one of SAC02 or SAC03 is required.
  - 2 If either SAC03 or SAC04 is present, then the other is required.
  - 3 If either SAC06 or SAC07 is present, then the other is required.
  - 4 If either SAC09 or SAC10 is present, then the other is required.
  - 5 If SAC11 is present, then SAC10 is required.
  - 6 If SAC13 is present, then at least one of SAC02 or SAC04 is required.
  - 7 If SAC14 is present, then SAC13 is required.
  - 8 If SAC16 is present, then SAC15 is required.

- Semantic Notes:**
- 1 If SAC01 is "A" or "C", then at least one of SAC05, SAC07, or SAC08 is required.
  - 2 SAC05 is the total amount for the service, promotion, allowance, or charge.  
If SAC05 is present with SAC07 or SAC08, then SAC05 takes precedence.
  - 3 SAC08 is the allowance or charge rate per unit.
  - 4 SAC10 and SAC11 is the quantity basis when the allowance or charge quantity is different from the purchase order or invoice quantity.  
SAC10 and SAC11 used together indicate a quantity range, which could be a dollar amount, that is applicable to service, promotion, allowance, or charge.
  - 5 SAC13 is used in conjunction with SAC02 or SAC04 to provide a specific reference number as identified by the code used.
  - 6 SAC14 is used in conjunction with SAC13 to identify an option when there is more than one option of the promotion.
  - 7 SAC16 is used to identify the language being used in SAC15.

- Comments:**
- 1 SAC04 may be used to uniquely identify the service, promotion, allowance, or charge. In addition, it may be used in conjunction with SAC03 to further define SAC02.
  - 2 In some business applications, it is necessary to advise the trading partner of the actual dollar amount that a particular allowance, charge, or promotion was based on to reduce ambiguity. This amount is commonly referred to as "Dollar Basis Amount". It is represented in the SAC segment in SAC10 using the qualifier "DO" - Dollars in SAC09.

**Notes:**

SAC\*N\*\*TI\*EXP [If this segment appears then EXP (LSR-26)="Y"]  
SAC\*N\*\*TI\*VT\*\*\*\*\*VTA (LSR-80)  
SAC\*N\*\*TI\*EEH [If this segment appears then AENG (LSR-32)="Y"]  
SAC\*N\*\*TI\*OAC [If this segment appears then ALBR (LSR-33)="Y"]

#### Data Element Summary

Ref.	Data		
<u>Des.</u>	<u>Element</u>	<u>Name</u>	
<u>Attributes</u>			
M	SAC01	248 Allowance or Charge Indicator	M ID 1/1

		Code which indicates an allowance or charge for the service specified		
		N	No Allowance or Charge	
<b>SAC03</b>	<b>559</b>	<b>Agency Qualifier Code</b>		<b>X ID 2/2</b>
		Code identifying the agency assigning the code values		
		TI	Telecommunications Industry	
<b>SAC04</b>	<b>1301</b>	<b>Agency Service, Promotion, Allowance, or Charge Code</b>		<b>X AN 1/10</b>
		Agency maintained code identifying the service, promotion, allowance, or charge		
		EEH	Engineering Charge	
		EXP	Expedited Service Charge	
		OAC	Overtime Loading	
		VT	Variable Term Contract Pricing Plan	
<b>SAC15</b>	<b>352</b>	<b>Description</b>		<b>X AN 1/80</b>
		A free-form description to clarify the related data elements and their content		
		VTA (LSR-80) = Variable Term Agreement		

**Segment:** **DTM** Date/Time Reference  
**Position:** 1500  
**Loop:**  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** 10  
**Purpose:** To specify pertinent dates and times  
**Syntax Notes:**

- 1 At least one of DTM02 DTM03 or DTM05 is required.
- 2 If DTM04 is present, then DTM03 is required.
- 3 If either DTM05 or DTM06 is present, then the other is required.

**Semantic Notes:**

**Comments:**

**Notes:**

DTM\*097\*D/TSENT{CCYYMMDD} (LSR-12)\*D/TSENT{HHMM} (LSR-12)  
 DTM\*150\*DDD{CCYYMMDD} (LSR-14)  
 DTM\*270\*DATED{CCYYMMDD} (LSR-36)

**Data Element Summary**

	<u>Ref.</u>	<u>Data</u>	<u>Element</u>	<u>Name</u>			
M	DTM01	374	Date/Time Qualifier		M	ID 3/3	
				Code specifying type of date or time, or both date and time			
				097			Transaction Creation
				150		Service Period Start	
				270		Date Filed	
	DTM02	373	Date		X	DT 8/8	
		Date expressed as CCYYMMDD					
		D/TSENT (LSR-12) = Date Sent					
		DDD (LSR-14) = Desired Due Date					
		DATED (LSR-36) = Date of Agency Authorization					
	DTM03	337	Time		X	TM 4/8	
		Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)					
		D/TSENT{HHMM} (LSR-12) = Time Sent					

**Segment:** **SI** Service Characteristic Identification

**Position:** 1850

**Loop:**

**Level:** Heading

**Usage:** Optional

**Max Use:** >1

**Purpose:** To specify service characteristic data

**Syntax Notes:**

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

**Semantic Notes:**

**Comments:**

- 1 SI01 defines the source for each of the service characteristics qualifiers.

**Notes:**

SI\*TI\*RE\*REQTYP (LSR-23)  
 SI\*TI\*AA\*ACT (LSR-24)  
 SI\*TI\*TY\*TOS (LSR-44)  
 SI\*TI\*NC\*NC (LSR-46)  
 SI\*TI\*NI\*NCI (LSR-48)  
 SI\*TI\*NJ\*SEC NCI (LSR-50)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
	<b>Attributes</b>				
M	SI01	559	<b>Agency Qualifier Code</b>	M	ID 2/2
			Code identifying the agency assigning the code values		
			TI Telecommunications Industry		
M	SI02	1000	<b>Service Characteristics Qualifier</b>	M	AN 2/2
			Code from an industry code list qualifying the type of service characteristics		
			AA Account Activity		
			NC Network Channel		
			NI Network Channel Interface		
			NJ Secondary Network Channel Interface		
			RE Requisition Type		
			TY Type of Service		
M	SI03	234	<b>Product/Service ID</b>	M	AN 1/48
			Identifying number for a product or service		
			ACT (LSR-24) = Activity		
			A = (DWS: N-New Installation)		
			D = (DWS: D-Disconnect of Entire Account)		
			M = (DWS: M-Inside Move (CO, IA, MN only))		
			C = (DWS: C-Change)		
			V = (DWS: V-Conversion As Specified)		
			W = (DWS: W-Conversion As Is)		
			T = (DWS: T-Outside Move (T/F))		

REQTYP (LSR-23) = Requisition Type and Status  
TOS (LSR-44) = Type of Service  
NC (LSR-46) = Network Channel Code  
NCI (LSR-48) = Network Channel Interface Code  
SEC NCI (LSR-50) = Secondary Network Channel Interface Code

<b>Segment:</b>	<b>PID</b> Product/Item Description
<b>Position:</b>	1900
<b>Loop:</b>	
<b>Level:</b>	Heading
<b>Usage:</b>	Optional
<b>Max Use:</b>	200
<b>Purpose:</b>	To describe a product or process in coded or free-form format
<b>Syntax Notes:</b>	<ol style="list-style-type: none"> <li>1 If PID04 is present, then PID03 is required.</li> <li>2 At least one of PID04 or PID05 is required.</li> <li>3 If PID07 is present, then PID03 is required.</li> <li>4 If PID08 is present, then PID04 is required.</li> <li>5 If PID09 is present, then PID05 is required.</li> </ol>
<b>Semantic Notes:</b>	<ol style="list-style-type: none"> <li>1 Use PID03 to indicate the organization that publishes the code list being referred to.</li> <li>2 PID04 should be used for industry-specific product description codes.</li> <li>3 PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.</li> <li>4 PID09 is used to identify the language being used in PID05.</li> </ol>
<b>Comments:</b>	<ol style="list-style-type: none"> <li>1 If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.</li> <li>2 Use PID06 when necessary to refer to the product surface or layer being described in the segment.</li> <li>3 PID07 specifies the individual code list of the agency specified in PID03.</li> </ol>
<b>Notes:</b>	<div style="background-color: #e0e0e0; padding: 5px;">           PID*S**TI*AO***SO-RSQ*AGAUTH (LSR-35)            PID*S**TI*BI***SO-RSQ*FBI (RPL-76)            PID*S**TI*PENDING***SO-RSQ*PENDING ORDER (LSR-108b)         </div>

#### Data Element Summary

Ref.	Data	Name		
<u>Des.</u>	<u>Element</u>	<u>Name</u>		
<b>M</b>	<b>PID01</b>	<b>349</b>	<b>Item Description Type</b>	<b>M ID 1/1</b>
			Code indicating the format of a description	
			S                      Structured (From Industry Code List)	
	<b>PID03</b>	<b>559</b>	<b>Agency Qualifier Code</b>	<b>X ID 2/2</b>
			Code identifying the agency assigning the code values	
			TI                      Telecommunications Industry	
	<b>PID04</b>	<b>751</b>	<b>Product Description Code</b>	<b>X AN 1/12</b>
			A code from an industry code list which provides specific data about a product characteristic	
			AO                      Agency Authorization Status	
			BI                      Final Bill Information Indicator	
			PENDING              Pending Order Indicator	
	<b>PID07</b>	<b>822</b>	<b>Source Subqualifier</b>	<b>O AN 1/15</b>
			A reference that indicates the table or text maintained by the Source Qualifier	
			SO-RSQ              Service Order - Reseller Questions list	

**PID08**      **1073**      **Yes/No Condition or Response Code**      **O**      **ID 1/1**

Code indicating a Yes or No condition or response

FBI (RPL-76) = Final Bill Information Indicator

N = (DWS: E-Existing)

Y = (DWS: D-Different)

AGAUTH (LSR-35) = Agency Authorization Status

PENDING ORDER (LSR-108b) = Pending Order

Segment: **PWK** Paperwork

Position: 2100

Loop:

Level: Heading

Usage: Optional

Max Use: 25

Purpose: To identify the type or transmission or both of paperwork or supporting information

Syntax Notes: 1 If either PWK05 or PWK06 is present, then the other is required.

Semantic Notes:

Comments:

- 1 PWK05 and PWK06 may be used to identify the addressee by a code number.
- 2 PWK07 may be used to indicate special information to be shown on the specified report.
- 3 PWK08 may be used to indicate action pertaining to a report.

Notes: PWK\*DW\*NS\*1\*DG\*91\*DRC (LSR-98)

#### Data Element Summary

Ref.	Data			
	<u>Des.</u>	<u>Element</u>	<u>Name</u>	
M	PWK01	755	<b>Report Type Code</b>	M ID 2/2
			Code indicating the title or contents of a document, report or supporting item	
			DW Drawing(s)	
	PWK02	756	<b>Report Transmission Code</b>	O ID 1/2
			Code defining timing, transmission method or format by which reports are to be sent	
			NS Not Specified	
			Indicates that a report will be transmitted via a nonspecified medium	
	PWK03	757	<b>Report Copies Needed</b>	O NO 1/2
			The number of copies of a report that should be sent to the addressee	
			1 Always One	
	PWK04	98	<b>Entity Identifier Code</b>	O ID 2/3
			Code identifying an organizational entity, a physical location, property or an individual	
			DG Design Engineering	
			Identifies the design engineer or office of the design engineer who will receive design specifications	
	PWK05	66	<b>Identification Code Qualifier</b>	X ID 1/2
			Code designating the system/method of code structure used for Identification Code (67)	
			91 Assigned by Seller or Seller's Agent	
	PWK06	67	<b>Identification Code</b>	X AN 2/80
			Code identifying a party or other code	
			DRC (LSR-98) = Design Routing Code	



**Segment:** **N9 Reference Identification**

**Position:** 2850

**Loop:** N9 Optional

**Level:** Heading

**Usage:** Optional

**Max Use:** 1

**Purpose:** To transmit identifying information as specified by the Reference Identification Qualifier

- Syntax Notes:**
- 1 At least one of N902 or N903 is required.
  - 2 If N906 is present, then N905 is required.
  - 3 If either C04003 or C04004 is present, then the other is required.
  - 4 If either C04005 or C04006 is present, then the other is required.

- Semantic Notes:**
- 1 N906 reflects the time zone which the time reflects.
  - 2 N907 contains data relating to the value cited in N902.

**Comments:**

**Notes:** N9\*H7\*ORI\*LSR\*\*\*\*2W>MANUAL IND (LSR-108a)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	N901	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification H7 Standard Clause	M	ID 2/3
	N902	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier ORI Order Instructions	X	AN 1/30
	N903	369	<b>Free-form Description</b> Free-form descriptive text "LSR"	X	AN 1/45
	N907	C040	<b>Reference Identifier</b> To identify one or more reference numbers or identification numbers as specified by the Reference Qualifier	O	
M	C04001	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification 2W Change Order Authority	M	ID 2/3
M	C04002	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier MANUAL IND (LSR-108a) = Manual Indicator	M	AN 1/30

**Segment:** **MTX** Text  
**Position:** 2900  
**Loop:** N9 Optional  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To specify textual data  
**Syntax Notes:**

- 1 If MTX01 is present, then MTX02 is required.
- 2 If MTX03 is present, then MTX02 is required.
- 3 If MTX05 is present, then MTX04 is required.

**Semantic Notes:**

- 1 MTX05 is the number of lines to advance before printing.

**Comments:**

- 1 If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

**Notes:** MTX\*\*REMARKS (LSR-108)

#### Data Element Summary

<u>Ref.</u>	<u>Data</u>	<u>Element</u>	<u>Name</u>		
<b>MTX02</b>	<b>1551</b>	<b>Message Text</b>		<b>X</b>	<b>AN 1/4096</b>
			To transmit large volumes of message text		
			REMARKS (LSR-108) = Remarks		

**Segment:** **N1** Name  
**Position:** 3000  
**Loop:** N1 Optional  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** 1  
**Purpose:** To identify a party by type of organization, name, and code  
**Syntax Notes:**

- 1 At least one of N102 or N103 is required.
- 2 If either N103 or N104 is present, then the other is required.

**Semantic Notes:**  
**Comments:**

- 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
- 2 N105 and N106 further define the type of entity in N101.

**Notes:** N1\*78\*CCNA (LSR-1)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	N101	98	<b>Entity Identifier Code</b> Code identifying an organizational entity, a physical location, property or an individual	M	ID 2/3
		78	Service Requester		
	N102	93	<b>Name</b> Free-form name	X	AN 1/60
			CCNA (LSR-1) = Customer Carrier Name Abbreviation		

**Segment:** **PER Administrative Communications Contact**

**Position:** 3500

**Loop:** N1 Optional

**Level:** Heading

**Usage:** Optional

**Max Use:** >1

**Purpose:** To identify a person or office to whom administrative communications should be directed

- Syntax Notes:**
- 1 If either PER03 or PER04 is present, then the other is required.
  - 2 If either PER05 or PER06 is present, then the other is required.
  - 3 If either PER07 or PER08 is present, then the other is required.

**Semantic Notes:**

**Comments:**

**Notes:** PER\*AG\*INIT (LSR-81)\*TE\*TEL NO (LSR-82)\*FX\*FAX NO (LSR-84)\*EM\*EMAIL (LSR-83)

PER\*CN\*IMPCON (LSR-91)\*TE\*TEL NO (LSR-92)\*BN\*PAGER (LSR-93)  
 PER\*AL\*ALT IMPCON (LSR-94)\*TE\*TEL NO (LSR-95)\*BN\*PAGER (LSR-96)

**Data Element Summary**

Ref.	Data		
<u>Des.</u>	<u>Element</u>	<u>Name</u>	
M	PER01	366	<b>Contact Function Code</b> M ID 2/2
			Code identifying the major duty or responsibility of the person or group named
		AG	Agent
		AL	Alternate Contact
			Person to be contacted when the main contact is not available
		CN	General Contact
	PER02	93	<b>Name</b> O AN 1/60
			Free-form name
			INIT (LSR-81) = Initiator Identification
			IMPCON (LSR-91) = Implementation Contact
			ALT IMPCON (LSR-94) = Alternate Implementation Contact
	PER03	365	<b>Communication Number Qualifier</b> X ID 2/2
			Code identifying the type of communication number
		TE	Telephone
	PER04	364	<b>Communication Number</b> X AN 1/256
			Complete communications number including country or area code when applicable
			TEL NO (LSR-82) = Telephone Number
			TEL NO (LSR-92) = Telephone Number
			TEL NO (LSR-95) = Telephone Number
	PER05	365	<b>Communication Number Qualifier</b> X ID 2/2
			Code identifying the type of communication number
		BN	Beeper Number
		FX	Facsimile
	PER06	364	<b>Communication Number</b> X AN 1/256
			Complete communications number including country or area code when applicable

		FAX NO (LSR-84) = Facsimile Number		
		PAGER (LSR-93) = Pager Number		
		PAGER (LSR-96) = Pager Number		
<b>PER07</b>	<b>365</b>	<b>Communication Number Qualifier</b>	<b>X</b>	<b>ID 2/2</b>
		Code identifying the type of communication number		
		EM                      Electronic Mail		
<b>PER08</b>	<b>364</b>	<b>Communication Number</b>	<b>X</b>	<b>AN 1/256</b>
		Complete communications number including country or area code when applicable		
		EMAIL (LSR-83) = Electronic Mail Address		

**Segment:** **N1** Name  
**Position:** 3000  
**Loop:** N1 Optional  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** 1  
**Purpose:** To identify a party by type of organization, name, and code  
**Syntax Notes:**

- 1 At least one of N102 or N103 is required.
- 2 If either N103 or N104 is present, then the other is required.

**Semantic Notes:**  
**Comments:**

- 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
- 2 N105 and N106 further define the type of entity in N101.

**Notes:** N1\*AN\*AUTHNM (LSR-37)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	N101	98	<b>Entity Identifier Code</b> Code identifying an organizational entity, a physical location, property or an individual AN Authorized From A geographic location designated as an authorized pick-up or origin point for a shipment	M	ID 2/3
	N102	93	<b>Name</b> Free-form name AUTHNM (LSR-37) = Authorization Name	X	AN 1/60

**Segment:** **N1** Name  
**Position:** 3000  
**Loop:** N1 Optional  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** 1  
**Purpose:** To identify a party by type of organization, name, and code  
**Syntax Notes:**

- 1 At least one of N102 or N103 is required.
- 2 If either N103 or N104 is present, then the other is required.

**Semantic Notes:**  
**Comments:**

- 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
- 2 N105 and N106 further define the type of entity in N101.

**Notes:** N1\*DG\*DSGCON (LSR-97)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	
M	N101	98	<b>Entity Identifier Code</b> Code identifying an organizational entity, a physical location, property or an individual DG Design Engineering Identifies the design engineer or office of the design engineer who will receive design specifications	M ID 2/3
	N102	93	<b>Name</b> Free-form name DSGCON (LSR-97) = Design / Engineering Contact	X AN 1/60

**Segment:** **PER** Administrative Communications Contact  
**Position:** 3500  
**Loop:** N1 Optional  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To identify a person or office to whom administrative communications should be directed

**Syntax Notes:**  
**1** If either PER03 or PER04 is present, then the other is required.  
**2** If either PER05 or PER06 is present, then the other is required.  
**3** If either PER07 or PER08 is present, then the other is required.

**Semantic Notes:**

**Comments:**

**Notes:** PER\*DE\*\*TE\*TEL NO (LSR-99)\*FX\*FAX NO (LSR-100)

#### Data Element Summary

	Ref. Des.	Data Element	Name		
M	<u>Attributes</u> PER01	366	<b>Contact Function Code</b> Code identifying the major duty or responsibility of the person or group named DE Design Engineer	M	ID 2/2
	PER03	365	<b>Communication Number Qualifier</b> Code identifying the type of communication number TE Telephone	X	ID 2/2
	PER04	364	<b>Communication Number</b> Complete communications number including country or area code when applicable TEL NO (LSR-99) = Telephone Number	X	AN 1/256
	PER05	365	<b>Communication Number Qualifier</b> Code identifying the type of communication number FX Facsimile	X	ID 2/2
	PER06	364	<b>Communication Number</b> Complete communications number including country or area code when applicable FAX NO (LSR-100) = Facsimile Number	X	AN 1/256



**Segment:** **N1** Name  
**Position:** 3000  
**Loop:** N1 Optional  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** 1  
**Purpose:** To identify a party by type of organization, name, and code  
**Syntax Notes:**

- 1 At least one of N102 or N103 is required.
- 2 If either N103 or N104 is present, then the other is required.

**Semantic Notes:**  
**Comments:**

- 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
- 2 N105 and N106 further define the type of entity in N101.

**Notes:** N1\*X1\*BILLNM (RPL-77)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	
M	N101	98	<b>Entity Identifier Code</b> Code identifying an organizational entity, a physical location, property or an individual X1 Mail to An address to which a specified item is to be mailed	M ID 2/3
	N102	93	<b>Name</b> Free-form name BILLNM (RPL-77) = Bill Name	X AN 1/60

**Segment:** **N2** Additional Name Information  
**Position:** 3100  
**Loop:** N1 Optional  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** 2  
**Purpose:** To specify additional names  
**Syntax Notes:**  
**Semantic Notes:**  
**Comments:**  
**Notes:** N2\*SBILLNM (RPL-78)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	<u>Attributes</u> N201	93	Name Free-form name SBILLNM (RPL-78) = Secondary Billing Name	M	AN 1/60

**Segment:** **N4 Geographic Location**

**Position:** 3300

**Loop:** N1 Optional

**Level:** Heading

**Usage:** Optional

**Max Use:** >1

**Purpose:** To specify the geographic place of the named party

- Syntax Notes:**
- 1 Only one of N402 or N407 may be present.
  - 2 If N406 is present, then N405 is required.
  - 3 If N407 is present, then N404 is required.

**Semantic Notes:**

- Comments:**
- 1 A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
  - 2 N402 is required only if city name (N401) is in the U.S. or Canada.

**Notes:** N4\*\*STATE (RPL-83)\*ZIP (RPL-84)

**Data Element Summary**

<u>Ref.</u>	<u>Data</u>	<u>Element</u>	<u>Name</u>		
<b>N402</b>	<b>156</b>	<b>State or Province Code</b>		<b>X</b>	<b>ID 2/2</b>
			Code (Standard State/Province) as defined by appropriate government agency		
			STATE (RPL-83) = State/Province		
<b>N403</b>	<b>116</b>	<b>Postal Code</b>		<b>O</b>	<b>ID 3/15</b>
			Code defining international postal zone code excluding punctuation and blanks (zip code for United States)		
			ZIP (RPL-84) = ZIP/Postal Code		

**Segment:** **NX2** Location ID Component

**Position:** 3350

**Loop:** N1 Optional

**Level:** Heading

**Usage:** Optional

**Max Use:** >1

**Purpose:** To define types and values of a geographic location

**Syntax Notes:**

**Semantic Notes:**

**Comments:**

**Notes:**

NX2\*01\*SANO (RPL-79b)  
 NX2\*02\*SASN (RPL-79e)  
 NX2\*03\*SASD (RPL-79d)  
 NX2\*07\*CITY (RPL-82)  
 NX2\*32\*FLOOR (RPL-80)  
 NX2\*35\*ROOM/MAIL STOP (RPL-81)  
 NX2\*40\*SASS (RPL-79g)  
 NX2\*59\*SAPR (RPL-79a)  
 NX2\*61\*SASF (RPL-79c)  
 NX2\*62\*SATH (RPL79f)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	
M	<b>NX201</b>	<b>1106</b>	<b>Address Component Qualifier</b> Code qualifying the type of address component	M ID 2/2
			01 Street Number	
			02 Street Name	
			03 Prefix Direction	
			07 City Name	
			32 Floor	
			A particular floor or level of a building	
			35 Room	
			A walled room or partitioned area of a building	
			40 Street Suffix	
			59 Street Number Low	
			61 Street Number Fraction	
			62 Street Name Suffix	
M	<b>NX202</b>	<b>166</b>	<b>Address Information</b> Address information	M AN 1/55
			SANO (RPL-79b) = Service Address Number	
			SASN (RPL-79e) = Service Address Street Name	
			SASD (RPL-79d) = Service Address Street Directional Prefix	
			CITY (RPL-82) = City	
			FLOOR (RPL-80) = Floor	
			ROOM/MAIL STOP (RPL-81) = Room/Mail Stop	
			SASS (RPL-79g) = Service Address Street Directional Suffix	
			SAPR (RPL-79a) = Service Address Number Prefix	
			SASF (RPL-79c) = Service Address Number Suffix	
			SATH (RPL-79f) = Service Address Street Type	

**Segment:** **PER** Administrative Communications Contact  
**Position:** 3500  
**Loop:** N1 Optional  
**Level:** Heading  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To identify a person or office to whom administrative communications should be directed

- Syntax Notes:**
- 1 If either PER03 or PER04 is present, then the other is required.
  - 2 If either PER05 or PER06 is present, then the other is required.
  - 3 If either PER07 or PER08 is present, then the other is required.

**Semantic Notes:**

**Comments:**

**Notes:** PER\*BI\*BILLCON (RPL85)\*TE\*TEL NO (RPL-86)

#### Data Element Summary

Ref. Des.	Data Element	Name	
M	PER01	366 Contact Function Code	M ID 2/2
		Code identifying the major duty or responsibility of the person or group named	
		BI Bill Inquiry Contact	
		Service Provider contact for making inquires about information on the invoice	
	PER02	93 Name	O AN 1/60
		Free-form name	
		BILLCON (RPL-85) = Billing Contact	
	PER03	365 Communication Number Qualifier	X ID 2/2
		Code identifying the type of communication number	
		TE Telephone	
	PER04	364 Communication Number	X AN 1/256
		Complete communications number including country or area code when applicable	
		TEL NO (RPL-86) = Telephone Number	

**Segment:** **SI** Service Characteristic Identification

**Position:** 3550

**Loop:** N1 Optional

**Level:** Heading

**Usage:** Optional

**Max Use:** >1

**Purpose:** To specify service characteristic data

- Syntax Notes:**
- 1 If either SI04 or SI05 is present, then the other is required.
  - 2 If either SI06 or SI07 is present, then the other is required.
  - 3 If either SI08 or SI09 is present, then the other is required.
  - 4 If either SI10 or SI11 is present, then the other is required.
  - 5 If either SI12 or SI13 is present, then the other is required.
  - 6 If either SI14 or SI15 is present, then the other is required.
  - 7 If either SI16 or SI17 is present, then the other is required.
  - 8 If either SI18 or SI19 is present, then the other is required.
  - 9 If either SI20 or SI21 is present, then the other is required.

**Semantic Notes:**

**Comments:** 1 SI01 defines the source for each of the service characteristics qualifiers.

**Notes:** SI\*TI\*AF\*AFT (RPL-78a)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
	<u>Attributes</u>				
M	SI01	559	<b>Agency Qualifier Code</b>	M	ID 2/2
			Code identifying the agency assigning the code values		
			TI Telecommunications Industry		
M	SI02	1000	<b>Service Characteristics Qualifier</b>	M	AN 2/2
			Code from an industry code list qualifying the type of service characteristics		
			AF Address Format Type		
M	SI03	234	<b>Product/Service ID</b>	M	AN 1/48
			Identifying number for a product or service		
			AFT (RPL-78a) = Address Format Type		

**Segment:** **POC** Line Item Change - RPL, Primary Location Section

**Position:** 0100  
**Loop:** POC Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** 1

**Purpose:** To specify changes to a line item

- Syntax Notes:**
- 1 If POC03 is present, then both POC04 and POC05 are required.
  - 2 If POC07 is present, then POC06 is required.
  - 3 If either POC08 or POC09 is present, then the other is required.
  - 4 If either POC10 or POC11 is present, then the other is required.
  - 5 If either POC12 or POC13 is present, then the other is required.
  - 6 If either POC14 or POC15 is present, then the other is required.
  - 7 If either POC16 or POC17 is present, then the other is required.
  - 8 If either POC18 or POC19 is present, then the other is required.
  - 9 If either POC20 or POC21 is present, then the other is required.
  - 10 If either POC22 or POC23 is present, then the other is required.
  - 11 If either POC24 or POC25 is present, then the other is required.
  - 12 If either POC26 or POC27 is present, then the other is required.
- Semantic Notes:**
- 1 POC01 is the purchase order line item identification.

**Comments:**

**Notes:** POC\*n\*RZ\*\*\*\*\*ZZ\*RPL\_PLS

**Data Element Summary**

Ref.	Data		
<u>Des.</u>	<u>Element</u>	<u>Name</u>	
<b>Attributes</b>			
<b>POC01</b>	<b>350</b>	<b>Assigned Identification</b>	<b>O AN 1/20</b>
		Alphanumeric characters assigned for differentiation within a transaction set	
		"n" = nth assigned ID within POC loop	
<b>M</b>	<b>POC02</b>	<b>670</b>	<b>Change or Response Type Code</b> <b>M ID 2/2</b>
		Code specifying the type of change to the line item	
		RZ Replace All Values	
		Receiver should replace the corresponding values in the original purchase order with the values contained in the Purchase Order Change Transaction Set	
	<b>POC08</b>	<b>235</b>	<b>Product/Service ID Qualifier</b> <b>X ID 2/2</b>
		Code identifying the type/source of the descriptive number used in Product/Service ID (234)	
		ZZ Mutually Defined	
	<b>POC09</b>	<b>234</b>	<b>Product/Service ID</b> <b>X AN 1/48</b>
		Identifying number for a product or service	
		"RPL_PLS"	

**Segment:** **SI** Service Characteristic Identification

**Position:** 0180  
**Loop:** POC Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1

**Purpose:** To specify service characteristic data  
**Syntax Notes:**

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

**Semantic Notes:**

**Comments:** 1 SI01 defines the source for each of the service characteristics qualifiers.

**Notes:** SI\*TI\*LT\*02 (designates "primary")  
 SI\*TI\*LS\*RLSO (RPL-26)  
 SI\*TI\*IW\*IWO (RPL-35)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
	<b>Attributes</b>				
M	SI01	559	<b>Agency Qualifier Code</b>	M	ID 2/2
			Code identifying the agency assigning the code values		
			TI Telecommunications Industry		
M	SI02	1000	<b>Service Characteristics Qualifier</b>	M	AN 2/2
			Code from an industry code list qualifying the type of service characteristics		
			IW Inside Wire Options		
			LS Local Serving Office		
			LT Location Type		
M	SI03	234	<b>Product/Service ID</b>	M	AN 1/48
			Identifying number for a product or service		
			02 = (designates "primary")		
			RLSO (RPL-26) = Resale Local Serving Office		
			IWO (RPL-35) = Inside Wiring Option		



**Segment:** **PID** Product/Item Description

**Position:** 0500

**Loop:** PID Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To describe a product or process in coded or free-form format

**Syntax Notes:**

- 1 If PID04 is present, then PID03 is required.
- 2 At least one of PID04 or PID05 is required.
- 3 If PID07 is present, then PID03 is required.
- 4 If PID08 is present, then PID04 is required.
- 5 If PID09 is present, then PID05 is required.

**Semantic Notes:**

- 1 Use PID03 to indicate the organization that publishes the code list being referred to.
- 2 PID04 should be used for industry-specific product description codes.
- 3 PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
- 4 PID09 is used to identify the language being used in PID05.

**Comments:**

- 1 If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
- 2 Use PID06 when necessary to refer to the product surface or layer being described in the segment.
- 3 PID07 specifies the individual code list of the agency specified in PID03.

**Notes:** PID\*S\*\*TI\*ANV\*\*\*SO-RSQ\*ANV (RPL-10b)

#### Data Element Summary

Ref.	Data			
<u>Des.</u>	<u>Element</u>	<u>Name</u>		
<b>Attributes</b>				
M	PID01	349	<b>Item Description Type</b> Code indicating the format of a description S Structured (From Industry Code List)	M ID 1/1
	PID03	559	<b>Agency Qualifier Code</b> Code identifying the agency assigning the code values TI Telecommunications Industry	X ID 2/2
	PID04	751	<b>Product Description Code</b> A code from an industry code list which provides specific data about a product characteristic ANV Address Not Validated Indicator	X AN 1/12
	PID07	822	<b>Source Subqualifier</b> A reference that indicates the table or text maintained by the Source Qualifier SO-RSQ Service Order - Reseller Questions list	O AN 1/15
	PID08	1073	<b>Yes/No Condition or Response Code</b> Code indicating a Yes or No condition or response ANV (RPL-10b) = Address Not Validated Indicator	O ID 1/1

**Segment:** **REF** Reference Identification  
**Position:** 1000  
**Loop:** POC Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To specify identifying information  
**Syntax Notes:**

- 1 At least one of REF02 or REF03 is required.
- 2 If either C04003 or C04004 is present, then the other is required.
- 3 If either C04005 or C04006 is present, then the other is required.

**Semantic Notes:**

- 1 REF04 contains data relating to the value cited in REF02.

**Comments:**  
**Notes:** REF\*IX\*LOCNUM (RPL-9)\*LOCNUM

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	REF01	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification IX Item Number	M	ID 2/3
	REF02	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier LOCNUM (RPL-9) = Location Number	X	AN 1/30
	REF03	352	<b>Description</b> A free-form description to clarify the related data elements and their content "LOCNUM"	X	AN 1/80

**Segment:** **N9 Reference Identification**

**Position:** 3200

**Loop:** N9 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To transmit identifying information as specified by the Reference Identification Qualifier

- Syntax Notes:**
- 1 At least one of N902 or N903 is required.
  - 2 If N906 is present, then N905 is required.
  - 3 If either C04003 or C04004 is present, then the other is required.
  - 4 If either C04005 or C04006 is present, then the other is required.

- Semantic Notes:**
- 1 N906 reflects the time zone which the time reflects.
  - 2 N907 contains data relating to the value cited in N902.

**Comments:**

**Notes:** N9\*H7\*LOC\*AAI

#### Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	N901	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification H7 Standard Clause	M	ID 2/3
	N902	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier LOC Location Instructions	X	AN 1/30
	N903	369	<b>Free-form Description</b> Free-form descriptive text "AAI"	X	AN 1/45

**Segment:** **MTX** Text  
**Position:** 3260  
**Loop:** N9 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To specify textual data  
**Syntax Notes:**

- 1 If MTX01 is present, then MTX02 is required.
- 2 If MTX03 is present, then MTX02 is required.
- 3 If MTX05 is present, then MTX04 is required.

**Semantic Notes:**

- 1 MTX05 is the number of lines to advance before printing.

**Comments:**

- 1 If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

**Notes:** MTX\*\*AAI (RPL-25)

**Data Element Summary**

<u>Ref.</u> <u>Des.</u>	<u>Data</u> <u>Element</u>	<u>Name</u>		
<b>Attributes</b> MTX02	1551	<b>Message Text</b>	<b>X</b>	<b>AN 1/4096</b>
		To transmit large volumes of message text		
		AAI (RPL-25) = Additional Address Information		

**Segment:** **N9 Reference Identification**

**Position:** 3200

**Loop:** N9 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To transmit identifying information as specified by the Reference Identification Qualifier

- Syntax Notes:**
- 1 At least one of N902 or N903 is required.
  - 2 If N906 is present, then N905 is required.
  - 3 If either C04003 or C04004 is present, then the other is required.
  - 4 If either C04005 or C04006 is present, then the other is required.

- Semantic Notes:**
- 1 N906 reflects the time zone which the time reflects.
  - 2 N907 contains data relating to the value cited in N902.

**Comments:**

**Notes:** N9\*L1\*ALOC\*RPLPRI

#### Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	N901	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification L1 Letters or Notes	M	ID 2/3
	N902	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier ALOC Additional Location Detail	X	AN 1/30
	N903	369	<b>Free-form Description</b> Free-form descriptive text "RPLPRI"	X	AN 1/45

**Segment:** **MTX** Text  
**Position:** 3260  
**Loop:** N9 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To specify textual data  
**Syntax Notes:**

- 1 If MTX01 is present, then MTX02 is required.
- 2 If MTX03 is present, then MTX02 is required.
- 3 If MTX05 is present, then MTX04 is required.

**Semantic Notes:**

- 1 MTX05 is the number of lines to advance before printing.

**Comments:**

- 1 If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

**Notes:** MTX\*\*ALOC (RPL-30)

#### Data Element Summary

<u>Ref.</u>	<u>Data</u>	<u>Element</u>	<u>Name</u>		
<b>Attributes</b>					
<b>MTX02</b>	<b>1551</b>	<b>Message Text</b>		<b>X</b>	<b>AN 1/4096</b>
		To transmit large volumes of message text			
		ALOC (RPL-30) = Additional Location Details			

**Segment:** **N9 Reference Identification**

**Position:** 3200

**Loop:** N9 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To transmit identifying information as specified by the Reference Identification Qualifier

- Syntax Notes:**
- 1 At least one of N902 or N903 is required.
  - 2 If N906 is present, then N905 is required.
  - 3 If either C04003 or C04004 is present, then the other is required.
  - 4 If either C04005 or C04006 is present, then the other is required.

- Semantic Notes:**
- 1 N906 reflects the time zone which the time reflects.
  - 2 N907 contains data relating to the value cited in N902.

**Comments:**

**Notes:** N9\*L1\*ACC\*RPLPRI

#### Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	N901	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification L1 Letters or Notes	M	ID 2/3
	N902	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier ACC Access Instructions	X	AN 1/30
	N903	369	<b>Free-form Description</b> Free-form descriptive text "RPLPRI"	X	AN 1/45

**Segment:** **MTX** Text  
**Position:** 3260  
**Loop:** N9 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To specify textual data  
**Syntax Notes:**

- 1 If MTX01 is present, then MTX02 is required.
- 2 If MTX03 is present, then MTX02 is required.
- 3 If MTX05 is present, then MTX04 is required.

**Semantic Notes:**

- 1 MTX05 is the number of lines to advance before printing.

**Comments:**

- 1 If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

**Notes:** MTX\*\*ACC (RPL-39)

**Data Element Summary**

<u>Ref.</u> <u>Des.</u> <u>Attributes</u>	<u>Data</u> <u>Element</u>	<u>Name</u>		
MTX02	1551	Message Text	X	AN 1/4096
		To transmit large volumes of message text		
		ACC (RPL-39) = Access Information		



**Segment:** **N1** Name  
**Position:** 3400  
**Loop:** N1 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** 1  
**Purpose:** To identify a party by type of organization, name, and code  
**Syntax Notes:**

- 1 At least one of N102 or N103 is required.
- 2 If either N103 or N104 is present, then the other is required.

**Semantic Notes:**  
**Comments:**

- 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
- 2 N105 and N106 further define the type of entity in N101.

**Notes:** N1\*IT\*PRILOC (RPL-10)\*93\*LIT (RPL-8)

**Data Element Summary**

Ref. Des. Attributes	Data Element	Name		
M	N101	98	<b>Entity Identifier Code</b> Code identifying an organizational entity, a physical location, property or an individual IT Installation on Site	M ID 2/3
	N102	93	<b>Name</b> Free-form name PRILOC (RPL-10) = Primary Location	X AN 1/60
	N103	66	<b>Identification Code Qualifier</b> Code designating the system/method of code structure used for Identification Code (67) 93 Code assigned by the organization originating the transaction set	X ID 1/2
	N104	67	<b>Identification Code</b> Code identifying a party or other code LIT (RPL-8) = Location Identification Type EU = (DWS: E-End User Name) CL = (DWS: C-CLLI Code)	X AN 2/80

**Segment:** **N2** Additional Name Information  
**Position:** 3500  
**Loop:** N1 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** 2  
**Purpose:** To specify additional names  
**Syntax Notes:**  
**Semantic Notes:**  
**Comments:**  
**Notes:** N2\*NAME (RPL-10a)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	<u>Attributes</u> N201	93	Name Free-form name NAME (RPL-10a) = End User Name	M	AN 1/60

**Segment:** **N4 Geographic Location**  
**Position:** 3700  
**Loop:** N1 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** 1  
**Purpose:** To specify the geographic place of the named party  
**Syntax Notes:**

- 1 Only one of N402 or N407 may be present.
- 2 If N406 is present, then N405 is required.
- 3 If N407 is present, then N404 is required.

**Semantic Notes:**

**Comments:**

- 1 A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
- 2 N402 is required only if city name (N401) is in the U.S. or Canada.

**Notes:** N4\*\*STATE (RPL-28)\*ZIP (RPL-29)\*\*RJ\*CALA (RPL-29a)

**Data Element Summary**

Ref.	Data		
<u>Des.</u>	<u>Element</u>	<u>Name</u>	
<b>N402</b>	<b>156</b>	<b>State or Province Code</b>	<b>X ID 2/2</b>
		Code (Standard State/Province) as defined by appropriate government agency	
		STATE (RPL-28) = State/Province	
<b>N403</b>	<b>116</b>	<b>Postal Code</b>	<b>O ID 3/15</b>
		Code defining international postal zone code excluding punctuation and blanks (zip code for United States)	
		ZIP (RPL-29) = ZIP/Postal Code	
<b>N405</b>	<b>309</b>	<b>Location Qualifier</b>	<b>X ID 1/2</b>
		Code identifying type of location	
		RJ Region	
<b>N406</b>	<b>310</b>	<b>Location Identifier</b>	<b>O AN 1/30</b>
		Code which identifies a specific location	
		CALA (RPL-29a) = Customer Address Location Area	

**Segment:** **NX2** Location ID Component

**Position:** 3750

**Loop:** N1 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** >1

**Purpose:** To define types and values of a geographic location

**Syntax Notes:**

**Semantic Notes:**

**Comments:**

**Notes:**

NX2\*01\*SANO (RPL-13)  
 NX2\*02\*SASN (RPL-16)  
 NX2\*03\*SASD (RPL-15)  
 NX2\*05\*BOX (RPL-26c)  
 NX2\*06\*ROUTE (RPL-26b)  
 NX2\*07\*CITY (RPL-27)  
 NX2\*39\*AHN (RPL-26a)  
 NX2\*40\*SASS (RPL-18)  
 NX2\*59\*SAPR (RPL-12)  
 NX2\*61\*SASF (RPL-14)  
 NX2\*62\*SATH (RPL-17)  
 NX2\*LD1 (RPL-19)\*LV1 (RPL-20)  
 NX2\*LD2 (RPL-21)\*LV2 (RPL-22)  
 NX2\*LD3 (RPL-23)\*LV3 (RPL-24)

**Data Element Summary**

<u>Ref.</u>	<u>Data</u>	<u>Element</u>	<u>Name</u>	
M	<u>Attributes</u> NX201	1106	<b>Address Component Qualifier</b> Code qualifying the type of address component	M ID 2/2
			LD1 (RPL-19) = Location Designator 1 13 = (DWS: APT) 34 = (DWS: LOT) 35 = (DWS: RM) 36 = (DWS: SLIP) 37 = (DWS: UNIT) 14 = (DWS: SUIT)	
			LD2 (RPL-21) = Location Designator 2 32 = (DWS: FLR)	
			LD3 (RPL-23) = Location Designator 3 12 = (DWS: BLDG) 63 = (DWS: WNG) 30 = (DWS : PIER)	
			01 Street Number	
			02 Street Name	
			03 Prefix Direction	
			05 P.O. Box Number	
			06 Rural Route Number	
			07 City Name	
			12 Building Name	

13	Apartment Number
14	Suite Number
30	Pier The pier at which a ship or boat is docked
32	Floor A particular floor or level of a building
34	Lot A particular lot or piece of land
35	Room A walled room or partitioned area of a building
36	Slip The slip or location on a pier at which a ship or boat is docked
37	Unit A unit or separate structure
39	Unstructured Property
40	Street Suffix
59	Street Number Low
61	Street Number Fraction
62	Street Name Suffix
63	Secondary Unit Identifier

**M**      **NX202**      **166**      **Address Information**      **M**      **AN 1/55**

Address information

SANO (RPL-13) = Service Address Number  
 SASN (RPL-16) = Service Address Street Name  
 SASD (RPL-15) = Service Address Street Directional Prefix  
 BOX (RPL-26c) = Box  
 ROUTE (RPL-26b) = Route  
 CITY (RPL-27) = City  
 AHN (RPL-26a) = Assigned House Number  
 SASS (RPL-18) = Service Address Street Directional Suffix  
 SAPR (RPL-12) = Service Address Number Prefix  
 SASF (RPL-14) = Service Address Number Suffix  
 SATH (RPL-17) = Service Address Street Type  
 LV1 (RPL-20) = Location Value 1  
 LV2 (RPL-22) = Location Value 2  
 LV3 (RPL-24) = Location Value 3

**Segment:** **PER** Administrative Communications Contact

**Position:** 3900

**Loop:** N1 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 3

**Purpose:** To identify a person or office to whom administrative communications should be directed

- Syntax Notes:**
- 1 If either PER03 or PER04 is present, then the other is required.
  - 2 If either PER05 or PER06 is present, then the other is required.
  - 3 If either PER07 or PER08 is present, then the other is required.

**Semantic Notes:**

**Comments:**

**Notes:** PER\*CA\*LCON (RPL-31)\*TE\*ACTEL NO (RPL-32)  
 PER\*AL\*ALCON (RPL-33)\*TE\*AACTEL (RPL-34)

**Data Element Summary**

Ref.	Data		
<u>Des.</u>	<u>Element</u>	<u>Name</u>	
M	<b>PER01</b>	<b>366</b>	<b>Contact Function Code</b> <span style="float: right;"><b>M ID 2/2</b></span>
			Code identifying the major duty or responsibility of the person or group named
		AL	Alternate Contact
			Person to be contacted when the main contact is not available
		CA	Customer Contact Granting Appointment
	<b>PER02</b>	<b>93</b>	<b>Name</b> <span style="float: right;"><b>O AN 1/60</b></span>
			Free-form name
			LCON (RPL-31) = Local Contact
			ALCON (RPL-33) = Alternate Local Contact
	<b>PER03</b>	<b>365</b>	<b>Communication Number Qualifier</b> <span style="float: right;"><b>X ID 2/2</b></span>
			Code identifying the type of communication number
		TE	Telephone
	<b>PER04</b>	<b>364</b>	<b>Communication Number</b> <span style="float: right;"><b>X AN 1/256</b></span>
			Complete communications number including country or area code when applicable
			ACTEL NO (RPL-32) = Access Telephone Number
			AACTEL (RPL-34) = Alternate Access Telephone Number

**Segment:** **SI** Service Characteristic Identification

**Position:** 3950

**Loop:** N1 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** >1

**Purpose:** To specify service characteristic data

- Syntax Notes:**
- 1 If either SI04 or SI05 is present, then the other is required.
  - 2 If either SI06 or SI07 is present, then the other is required.
  - 3 If either SI08 or SI09 is present, then the other is required.
  - 4 If either SI10 or SI11 is present, then the other is required.
  - 5 If either SI12 or SI13 is present, then the other is required.
  - 6 If either SI14 or SI15 is present, then the other is required.
  - 7 If either SI16 or SI17 is present, then the other is required.
  - 8 If either SI18 or SI19 is present, then the other is required.
  - 9 If either SI20 or SI21 is present, then the other is required.

**Semantic Notes:**

**Comments:** 1 SI01 defines the source for each of the service characteristics qualifiers.

**Notes:** SI\*TI\*AF\*AFT (RPL-11)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
	<u>Attributes</u>				
M	SI01	559	<b>Agency Qualifier Code</b>	M	ID 2/2
			Code identifying the agency assigning the code values		
			TI Telecommunications Industry		
M	SI02	1000	<b>Service Characteristics Qualifier</b>	M	AN 2/2
			Code from an industry code list qualifying the type of service characteristics		
			AF Address Format Type		
M	SI03	234	<b>Product/Service ID</b>	M	AN 1/48
			Identifying number for a product or service		
			AFT (RPL-11) = Address Format Type		

**Segment:** **POC** Line Item Change - RPL, Secondary Location Section

**Position:** 0100

**Loop:** POC Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To specify changes to a line item

- Syntax Notes:**
- 1 If POC03 is present, then both POC04 and POC05 are required.
  - 2 If POC07 is present, then POC06 is required.
  - 3 If either POC08 or POC09 is present, then the other is required.
  - 4 If either POC10 or POC11 is present, then the other is required.
  - 5 If either POC12 or POC13 is present, then the other is required.
  - 6 If either POC14 or POC15 is present, then the other is required.
  - 7 If either POC16 or POC17 is present, then the other is required.
  - 8 If either POC18 or POC19 is present, then the other is required.
  - 9 If either POC20 or POC21 is present, then the other is required.
  - 10 If either POC22 or POC23 is present, then the other is required.
  - 11 If either POC24 or POC25 is present, then the other is required.
  - 12 If either POC26 or POC27 is present, then the other is required.
- Semantic Notes:**
- 1 POC01 is the purchase order line item identification.

**Comments:**

**Notes:** POC\*n\*RZ\*\*\*\*\*ZZ\*RPL\_SLS [POC Loop repeats SECLOCQTY (RPL-41a) times]

#### Data Element Summary

Ref.	Data		
<u>Des.</u>	<u>Element</u>	<u>Name</u>	
<b>Attributes</b>			
<b>POC01</b>	<b>350</b>	<b>Assigned Identification</b>	<b>O AN 1/20</b>
		Alphanumeric characters assigned for differentiation within a transaction set	
		"n" = nth assigned ID within PO1 loop	
<b>M</b>	<b>POC02</b>	<b>670</b>	<b>Change or Response Type Code</b>
			<b>M ID 2/2</b>
		Code specifying the type of change to the line item	
		RZ Replace All Values	
		Receiver should replace the corresponding values in the original purchase order with the values contained in the Purchase Order Change Transaction Set	
	<b>POC08</b>	<b>235</b>	<b>Product/Service ID Qualifier</b>
			<b>X ID 2/2</b>
		Code identifying the type/source of the descriptive number used in Product/Service ID (234)	
		ZZ Mutually Defined	
	<b>POC09</b>	<b>234</b>	<b>Product/Service ID</b>
			<b>X AN 1/48</b>
		Identifying number for a product or service	
		"RPL_SLS"	



**Segment:** **SI** Service Characteristic Identification

**Position:** 0180  
**Loop:** POC Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1

**Purpose:** To specify service characteristic data  
**Syntax Notes:**

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

**Semantic Notes:**

**Comments:** 1 SI01 defines the source for each of the service characteristics qualifiers.

**Notes:** SI\*TI\*LT\*04 (designates "secondary")  
 SI\*TI\*LS\*RLSO (RPL-60)  
 SI\*TI\*IW\*IWO (RPL-69)

**Data Element Summary**

Ref.	Data			
<u>Des.</u>	<u>Element</u>	<u>Name</u>		
<b>M</b>	<b>SI01</b>	<b>559</b>	<b>Agency Qualifier Code</b>	<b>M ID 2/2</b>
			Code identifying the agency assigning the code values	
			TI Telecommunications Industry	
<b>M</b>	<b>SI02</b>	<b>1000</b>	<b>Service Characteristics Qualifier</b>	<b>M AN 2/2</b>
			Code from an industry code list qualifying the type of service characteristics	
			IW Inside Wire Options	
			LS Local Serving Office	
			LT Location Type	
<b>M</b>	<b>SI03</b>	<b>234</b>	<b>Product/Service ID</b>	<b>M AN 1/48</b>
			Identifying number for a product or service	

04 = Secondary  
 RLSO (RPL-60) = Resale Local Serving Office (SECLOC)  
 IWO (RPL-69) = Inside Wiring Options (SECLOC)

**Segment:** **PID** Product/Item Description

**Position:** 0500

**Loop:** PID Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To describe a product or process in coded or free-form format

**Syntax Notes:**

- 1 If PID04 is present, then PID03 is required.
- 2 At least one of PID04 or PID05 is required.
- 3 If PID07 is present, then PID03 is required.
- 4 If PID08 is present, then PID04 is required.
- 5 If PID09 is present, then PID05 is required.

**Semantic Notes:**

- 1 Use PID03 to indicate the organization that publishes the code list being referred to.
- 2 PID04 should be used for industry-specific product description codes.
- 3 PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
- 4 PID09 is used to identify the language being used in PID05.

**Comments:**

- 1 If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
- 2 Use PID06 when necessary to refer to the product surface or layer being described in the segment.
- 3 PID07 specifies the individual code list of the agency specified in PID03.

**Notes:** PID\*S\*\*TI\*ANV\*\*\*SO-RSQ\*ANV (RPL-44b)

#### Data Element Summary

Ref.	Data			
<u>Des.</u>	<u>Element</u>	<u>Name</u>		
<b>Attributes</b>				
M	PID01	349	<b>Item Description Type</b> Code indicating the format of a description S Structured (From Industry Code List)	M ID 1/1
	PID03	559	<b>Agency Qualifier Code</b> Code identifying the agency assigning the code values TI Telecommunications Industry	X ID 2/2
	PID04	751	<b>Product Description Code</b> A code from an industry code list which provides specific data about a product characteristic ANV Address Not Validated Indicator	X AN 1/12
	PID07	822	<b>Source Subqualifier</b> A reference that indicates the table or text maintained by the Source Qualifier SO-RSQ Service Order - Reseller Questions list	O AN 1/15
	PID08	1073	<b>Yes/No Condition or Response Code</b> Code indicating a Yes or No condition or response ANV (RPL-44b) = Address Not Validated Indicator	O ID 1/1

**Segment:** **REF** Reference Identification  
**Position:** 1000  
**Loop:** POC Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To specify identifying information  
**Syntax Notes:**

- 1 At least one of REF02 or REF03 is required.
- 2 If either C04003 or C04004 is present, then the other is required.
- 3 If either C04005 or C04006 is present, then the other is required.

**Semantic Notes:**

- 1 REF04 contains data relating to the value cited in REF02.

**Comments:**  
**Notes:** REF\*IX\*LOCNUM (RPL-43)\*LOCNUM

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
<b>M</b>	<b>REF01</b>	<b>128</b>	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification IX Item Number	<b>M</b>	<b>ID 2/3</b>
	<b>REF02</b>	<b>127</b>	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier LOCNUM (RPL-43) = Location Number	<b>X</b>	<b>AN 1/30</b>
	<b>REF03</b>	<b>352</b>	<b>Description</b> A free-form description to clarify the related data elements and their content "LOCNUM"	<b>X</b>	<b>AN 1/80</b>

**Segment:** **N9 Reference Identification**

**Position:** 3200

**Loop:** N9 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To transmit identifying information as specified by the Reference Identification Qualifier

- Syntax Notes:**
- 1 At least one of N902 or N903 is required.
  - 2 If N906 is present, then N905 is required.
  - 3 If either C04003 or C04004 is present, then the other is required.
  - 4 If either C04005 or C04006 is present, then the other is required.

- Semantic Notes:**
- 1 N906 reflects the time zone which the time reflects.
  - 2 N907 contains data relating to the value cited in N902.

**Comments:**

**Notes:** N9\*H7\*LOC\*AAI

#### Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	N901	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification H7 Standard Clause	M	ID 2/3
	N902	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier LOC Location Instructions	X	AN 1/30
	N903	369	<b>Free-form Description</b> Free-form descriptive text "AAI"	X	AN 1/45

**Segment:** **MTX** Text  
**Position:** 3260  
**Loop:** N9 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To specify textual data  
**Syntax Notes:**

- 1 If MTX01 is present, then MTX02 is required.
- 2 If MTX03 is present, then MTX02 is required.
- 3 If MTX05 is present, then MTX04 is required.

**Semantic Notes:**

- 1 MTX05 is the number of lines to advance before printing.

**Comments:**

- 1 If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

**Notes:** MTX\*\*AAI (RPL-59)

**Data Element Summary**

<u>Ref.</u> <u>Des.</u>	<u>Data</u> <u>Element</u>	<u>Name</u>		
<b>Attributes</b> MTX02	1551	<b>Message Text</b>	<b>X</b>	<b>AN 1/4096</b>
		To transmit large volumes of message text		
		AAI (RPL-59) = Additional Address Information		

**Segment:** **N9 Reference Identification**

**Position:** 3200

**Loop:** N9 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To transmit identifying information as specified by the Reference Identification Qualifier

- Syntax Notes:**
- 1 At least one of N902 or N903 is required.
  - 2 If N906 is present, then N905 is required.
  - 3 If either C04003 or C04004 is present, then the other is required.
  - 4 If either C04005 or C04006 is present, then the other is required.

- Semantic Notes:**
- 1 N906 reflects the time zone which the time reflects.
  - 2 N907 contains data relating to the value cited in N902.

**Comments:**

**Notes:** N9\*L1\*ALOC\*RPLSEC

#### Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	N901	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification L1 Letters or Notes	M	ID 2/3
	N902	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier ALOC Additional Location Detail	X	AN 1/30
	N903	369	<b>Free-form Description</b> Free-form descriptive text "RPLSEC"	X	AN 1/45

**Segment:** **MTX** Text  
**Position:** 3260  
**Loop:** N9 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To specify textual data  
**Syntax Notes:**

- 1 If MTX01 is present, then MTX02 is required.
- 2 If MTX03 is present, then MTX02 is required.
- 3 If MTX05 is present, then MTX04 is required.

**Semantic Notes:**

- 1 MTX05 is the number of lines to advance before printing.

**Comments:**

- 1 If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

**Notes:** MTX\*\*ALOC (RPL-64)

#### Data Element Summary

<u>Ref.</u> <u>Des.</u>	<u>Data</u> <u>Element</u>	<u>Name</u>		
<b>Attributes</b> MTX02	1551	<b>Message Text</b>		
		To transmit large volumes of message text		
		ALOC (RPL-64) = Additional Location Details		
			X	AN 1/4096

**Segment:** **N9 Reference Identification**

**Position:** 3200

**Loop:** N9 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To transmit identifying information as specified by the Reference Identification Qualifier

- Syntax Notes:**
- 1 At least one of N902 or N903 is required.
  - 2 If N906 is present, then N905 is required.
  - 3 If either C04003 or C04004 is present, then the other is required.
  - 4 If either C04005 or C04006 is present, then the other is required.

- Semantic Notes:**
- 1 N906 reflects the time zone which the time reflects.
  - 2 N907 contains data relating to the value cited in N902.

**Comments:**

**Notes:** N9\*L1\*ACC\*RPLSEC

#### Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	N901	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification L1 Letters or Notes	M	ID 2/3
	N902	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier ACC Access Instructions	X	AN 1/30
	N903	369	<b>Free-form Description</b> Free-form descriptive text "RPLSEC"	X	AN 1/45



**Segment:** **MTX** Text  
**Position:** 3260  
**Loop:** N9 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To specify textual data  
**Syntax Notes:**

- 1 If MTX01 is present, then MTX02 is required.
- 2 If MTX03 is present, then MTX02 is required.
- 3 If MTX05 is present, then MTX04 is required.

**Semantic Notes:**

- 1 MTX05 is the number of lines to advance before printing.

**Comments:**

- 1 If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

**Notes:** MTX\*\*ACC (RPL-73)

**Data Element Summary**

<u>Ref.</u> <u>Des.</u>	<u>Data</u> <u>Element</u>	<u>Name</u>		
<b>Attributes</b> MTX02	1551	<b>Message Text</b>	<b>X</b>	<b>AN 1/4096</b>
		To transmit large volumes of message text		
		ACC (RPL-73) = Access Information		

**Segment:** **N1** Name  
**Position:** 3400  
**Loop:** N1 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** 1  
**Purpose:** To identify a party by type of organization, name, and code  
**Syntax Notes:**

- 1 At least one of N102 or N103 is required.
- 2 If either N103 or N104 is present, then the other is required.

**Semantic Notes:**  
**Comments:**

- 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
- 2 N105 and N106 further define the type of entity in N101.

**Notes:** N1\*IT\*SECLOC (RPL-44)\*93\*LIT (RPL-42)

**Data Element Summary**

Ref. Des.	Data Element	Name		
M	N101	98	<b>Entity Identifier Code</b> Code identifying an organizational entity, a physical location, property or an individual IT Installation on Site	M ID 2/3
	N102	93	<b>Name</b> Free-form name SECLOC (RPL-44) = Secondary Location	X AN 1/60
	N103	66	<b>Identification Code Qualifier</b> Code designating the system/method of code structure used for Identification Code (67) 93 Code assigned by the organization originating the transaction set	X ID 1/2
	N104	67	<b>Identification Code</b> Code identifying a party or other code LIT (RPL-42) = Location Identification Type EU = (DWS: E-End User Name) CL = (DWS: C-CLLI Code)	X AN 2/80

**Segment:** **N2** Additional Name Information

**Position:** 3500

**Loop:** N1 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 2

**Purpose:** To specify additional names

**Syntax Notes:**

**Semantic Notes:**

**Comments:**

**Notes:** N2\*NAME (RPL-44a)

#### Data Element Summary

	<u>Ref.</u> <u>Des.</u>	<u>Data</u> <u>Element</u>	<u>Name</u>		
M	<u>Attributes</u> N201	93	Name Free-form name NAME (RPL-44a) = End User Name	M	AN 1/60

**Segment:** **N4 Geographic Location**

**Position:** 3700

**Loop:** N1 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To specify the geographic place of the named party

- Syntax Notes:**
- 1 Only one of N402 or N407 may be present.
  - 2 If N406 is present, then N405 is required.
  - 3 If N407 is present, then N404 is required.

**Semantic Notes:**

- Comments:**
- 1 A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
  - 2 N402 is required only if city name (N401) is in the U.S. or Canada.

**Notes:** N4\*\*STATE (RPL-62)\*ZIP (RPL-63)\*\*RJ\*CALA (RPL-63a)

**Data Element Summary**

<u>Ref.</u>	<u>Data</u>	<u>Element</u>	<u>Name</u>		
<b>N402</b>	<b>156</b>	<b>State or Province Code</b>		<b>X</b>	<b>ID 2/2</b>
			Code (Standard State/Province) as defined by appropriate government agency		
			STATE (RPL-62) = State/Province		
<b>N403</b>	<b>116</b>	<b>Postal Code</b>		<b>O</b>	<b>ID 3/15</b>
			Code defining international postal zone code excluding punctuation and blanks (zip code for United States)		
			ZIP (RPL-63) = ZIP/Postal Code		
<b>N405</b>	<b>309</b>	<b>Location Qualifier</b>		<b>X</b>	<b>ID 1/2</b>
			Code identifying type of location		
			RJ Region		
<b>N406</b>	<b>310</b>	<b>Location Identifier</b>		<b>O</b>	<b>AN 1/30</b>
			Code which identifies a specific location		
			CALA (RPL-63a) = Customer Address Location Area		

**Segment:** **NX2** Location ID Component  
**Position:** 3750  
**Loop:** N1 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To define types and values of a geographic location  
**Syntax Notes:**  
**Semantic Notes:**  
**Comments:**  
**Notes:**

NX2\*01\*SANO (RPL-47)  
 NX2\*02\*SASN (RPL-50)  
 NX2\*03\*SASD (RPL-49)  
 NX2\*05\*BOX (RPL-60c)  
 NX2\*06\*ROUTE (RPL-60b)  
 NX2\*07\*CITY (RPL-61)  
 NX2\*39\*AHN (RPL-60a)  
 NX2\*40\*SASS (RPL-52)  
 NX2\*59\*SAPR (RPL-46)  
 NX2\*61\*SASF (RPL-48)  
 NX2\*62\*SATH (RPL-51)  
 NX2\*LD1 (RPL-53)\*LV1 (RPL-54)  
 NX2\*LD2 (RPL-55)\*LV2 (RPL-56)  
 NX2\*LD3 (RPL-57)\*LV3 (RPL-58)

**Data Element Summary**

Ref.	Data			
<u>Des.</u>	<u>Element</u>	<u>Name</u>		
M	<b>Attributes</b> NX201	1106	<b>Address Component Qualifier</b> Code qualifying the type of address component LD1 (RPL-53) = Location Designator 1 13 = (DWS: APT) 34 = (DWS: LOT) 35 = (DWS: RM) 36 = (DWS: SLIP) 37 = (DWS: UNIT) 14 = (DWS: SUIT) LD2 (RPL-55) = Location Designator 2 32 = (DWS: FLR) LD3 (RPL-57) = Location Designator 3 12 = (DWS: BLDG) 63 = (DWS: WNG) 30 = (DWS: PIER) 01 Street Number 02 Street Name 03 Prefix Direction 05 P.O. Box Number 06 Rural Route Number 07 City Name 12 Building Name	M ID 2/2

13	Apartment Number
14	Suite Number
30	Pier The pier at which a ship or boat is docked
32	Floor A particular floor or level of a building
34	Lot A particular lot or piece of land
35	Room A walled room or partitioned area of a building
36	Slip The slip or location on a pier at which a ship or boat is docked
37	Unit A unit or separate structure
39	Unstructured Property
40	Street Suffix
59	Street Number Low
61	Street Number Fraction
62	Street Name Suffix
63	Secondary Unit Identifier

**M**

**NX202**

**166**

**Address Information**

**M AN 1/55**

Address information

SANO (RPL-47) = Service Address Number  
 SASN (RPL-50) = Service Address Street Name  
 SASD (RPL-49) = Service Address Street Directional Prefix  
 BOX (RPL-60c) = Box  
 ROUTE (RPL-60b) = Route  
 CITY (RPL-61) = City  
 AHN (RPL-60a) = Assigned House Number  
 SASS (RPL-52) = Service Address Street Directional Suffix  
 SAPR (RPL-46) = Service Address Number Prefix  
 SASF (RPL-48) = Service Address Number Suffix  
 SATH (RPL-51) = Service Address Street Type  
 LV1 (RPL-54) = Location Value 1  
 LV2 (RPL-56) = Location Value 2  
 LV3 (RPL-58) = Location Value 3

**Segment:** **PER** Administrative Communications Contact

**Position:** 3900

**Loop:** N1 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 3

**Purpose:** To identify a person or office to whom administrative communications should be directed

- Syntax Notes:**
- 1 If either PER03 or PER04 is present, then the other is required.
  - 2 If either PER05 or PER06 is present, then the other is required.
  - 3 If either PER07 or PER08 is present, then the other is required.

**Semantic Notes:**

**Comments:**

**Notes:** PER\*CA\*LCON (RPL-65)\*TE\*ACTEL NO (RPL-66)  
PER\*AL\*ALCON (RPL-67)\*TE\*AACTEL (RPL-68)

#### Data Element Summary

Ref.	Data			
	<u>Des.</u>	<u>Element</u>	<u>Name</u>	
M	<u>Attributes</u> PER01	366	<b>Contact Function Code</b> Code identifying the major duty or responsibility of the person or group named AL Alternate Contact Person to be contacted when the main contact is not available CA Customer Contact Granting Appointment	M ID 2/2
	PER02	93	<b>Name</b> Free-form name LCON (RPL-65) = Local Contact ALCON (RPL-67) = Alternate Local Contact	O AN 1/60
	PER03	365	<b>Communication Number Qualifier</b> Code identifying the type of communication number TE Telephone	X ID 2/2
	PER04	364	<b>Communication Number</b> Complete communications number including country or area code when applicable ACTEL NO (RPL-66) = Access Telephone Number AACTEL (RPL-68) = Alternate Access Telephone Number	X AN 1/256

**Segment:** **SI** Service Characteristic Identification

**Position:** 3950

**Loop:** N1 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** >1

**Purpose:** To specify service characteristic data

- Syntax Notes:**
- 1 If either SI04 or SI05 is present, then the other is required.
  - 2 If either SI06 or SI07 is present, then the other is required.
  - 3 If either SI08 or SI09 is present, then the other is required.
  - 4 If either SI10 or SI11 is present, then the other is required.
  - 5 If either SI12 or SI13 is present, then the other is required.
  - 6 If either SI14 or SI15 is present, then the other is required.
  - 7 If either SI16 or SI17 is present, then the other is required.
  - 8 If either SI18 or SI19 is present, then the other is required.
  - 9 If either SI20 or SI21 is present, then the other is required.

**Semantic Notes:**

- Comments:**
- 1 SI01 defines the source for each of the service characteristics qualifiers.

**Notes:** SI\*TI\*AF\*AFT (RPL-45)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
	<u>Attributes</u>				
M	SI01	559	<b>Agency Qualifier Code</b>	M	ID 2/2
			Code identifying the agency assigning the code values		
			TI Telecommunications Industry		
M	SI02	1000	<b>Service Characteristics Qualifier</b>	M	AN 2/2
			Code from an industry code list qualifying the type of service characteristics		
			AF Address Format Type		
M	SI03	234	<b>Product/Service ID</b>	M	AN 1/48
			Identifying number for a product or service		
			AFT (RPL-45) = Address Format Type		



**Segment:** **POC** Line Item Change - RPL, Disconnect Information

**Position:** 0100  
**Loop:** POC Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** 1

**Purpose:** To specify changes to a line item

- Syntax Notes:**
- 1 If POC03 is present, then both POC04 and POC05 are required.
  - 2 If POC07 is present, then POC06 is required.
  - 3 If either POC08 or POC09 is present, then the other is required.
  - 4 If either POC10 or POC11 is present, then the other is required.
  - 5 If either POC12 or POC13 is present, then the other is required.
  - 6 If either POC14 or POC15 is present, then the other is required.
  - 7 If either POC16 or POC17 is present, then the other is required.
  - 8 If either POC18 or POC19 is present, then the other is required.
  - 9 If either POC20 or POC21 is present, then the other is required.
  - 10 If either POC22 or POC23 is present, then the other is required.
  - 11 If either POC24 or POC25 is present, then the other is required.
  - 12 If either POC26 or POC27 is present, then the other is required.
- Semantic Notes:**
- 1 POC01 is the purchase order line item identification.

**Comments:**

**Notes:** POC\*n\*RZ\*\*\*\*\*ZZ\*RPL\_DISC

**Data Element Summary**

Ref.	Data		
<u>Des.</u>	<u>Element</u>	<u>Name</u>	
<u>Attributes</u>			
	<b>POC01</b>	<b>350</b>	<b>Assigned Identification</b> <span style="float: right;"><b>O AN 1/20</b></span>
			Alphanumeric characters assigned for differentiation within a transaction set
			"n" = nth assigned ID within POC loop
<b>M</b>	<b>POC02</b>	<b>670</b>	<b>Change or Response Type Code</b> <span style="float: right;"><b>M ID 2/2</b></span>
			Code specifying the type of change to the line item
		RZ	Replace All Values
			Receiver should replace the corresponding values in the original purchase order with the values contained in the Purchase Order Change Transaction Set
	<b>POC08</b>	<b>235</b>	<b>Product/Service ID Qualifier</b> <span style="float: right;"><b>X ID 2/2</b></span>
			Code identifying the type/source of the descriptive number used in Product/Service ID (234)
		ZZ	Mutually Defined
	<b>POC09</b>	<b>234</b>	<b>Product/Service</b> <span style="float: right;"><b>X AN 1/48</b></span>
			Identifying number for a product or service
			"RPL_DISC"

**Segment:** **SI** Service Characteristic Identification

**Position:** 0180  
**Loop:** POC Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1

**Purpose:** To specify service characteristic data  
**Syntax Notes:**

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

**Semantic Notes:**

**Comments:** 1 SI01 defines the source for each of the service characteristics qualifiers.

**Notes:** SI\*TI\*ED\*DISC ECCKT (RPL-90)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
	<u>Attributes</u>				
M	SI01	559	<b>Agency Qualifier Code</b>	M	ID 2/2
			Code identifying the agency assigning the code values		
			TI Telecommunications Industry		
M	SI02	1000	<b>Service Characteristics Qualifier</b>	M	AN 2/2
			Code from an industry code list qualifying the type of service characteristics		
			ED Disconnect ECCKT		
M	SI03	234	<b>Product/Service ID</b>	M	AN 1/48
			Identifying number for a product or service		
			DISC ECCKT (RPL-90) = Disconnect ECCKT		

**Segment:** **POC** Line Item Change - RPL, Remarks Information

**Position:** 0100  
**Loop:** POC Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** 1

**Purpose:** To specify changes to a line item

- Syntax Notes:**
- 1 If POC03 is present, then both POC04 and POC05 are required.
  - 2 If POC07 is present, then POC06 is required.
  - 3 If either POC08 or POC09 is present, then the other is required.
  - 4 If either POC10 or POC11 is present, then the other is required.
  - 5 If either POC12 or POC13 is present, then the other is required.
  - 6 If either POC14 or POC15 is present, then the other is required.
  - 7 If either POC16 or POC17 is present, then the other is required.
  - 8 If either POC18 or POC19 is present, then the other is required.
  - 9 If either POC20 or POC21 is present, then the other is required.
  - 10 If either POC22 or POC23 is present, then the other is required.
  - 11 If either POC24 or POC25 is present, then the other is required.
  - 12 If either POC26 or POC27 is present, then the other is required.
- Semantic Notes:**
- 1 POC01 is the purchase order line item identification.

**Comments:**

**Notes:** POC\*n\*RZ\*\*\*\*\*ZZ\*RPL\_REM

**Data Element Summary**

Ref.	Data		
<u>Des.</u>	<u>Element</u>	<u>Name</u>	
<u>Attributes</u>			
	<b>POC01</b>	<b>350</b>	<b>Assigned Identification</b> <b>O AN 1/20</b>
			Alphanumeric characters assigned for differentiation within a transaction set
			"n" = nth assigned ID within POC loop
<b>M</b>	<b>POC02</b>	<b>670</b>	<b>Change or Response Type Code</b> <b>M ID 2/2</b>
			Code specifying the type of change to the line item
		RZ	Replace All Values
			Receiver should replace the corresponding values in the original purchase order with the values contained in the Purchase Order Change Transaction Set
	<b>POC08</b>	<b>235</b>	<b>Product/Service ID Qualifier</b> <b>X ID 2/2</b>
			Code identifying the type/source of the descriptive number used in Product/Service ID (234)
		ZZ	Mutually Defined
	<b>POC09</b>	<b>234</b>	<b>Product/Service ID</b> <b>X AN 1/48</b>
			Identifying number for a product or service
			"RPL_REM"

**Segment:** **N9 Reference Identification**

**Position:** 3200

**Loop:** N9 Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To transmit identifying information as specified by the Reference Identification Qualifier

- Syntax Notes:**
- 1 At least one of N902 or N903 is required.
  - 2 If N906 is present, then N905 is required.
  - 3 If either C04003 or C04004 is present, then the other is required.
  - 4 If either C04005 or C04006 is present, then the other is required.

- Semantic Notes:**
- 1 N906 reflects the time zone which the time reflects.
  - 2 N907 contains data relating to the value cited in N902.

**Comments:**

**Notes:** N9\*H7\*ORI\*RPL\*\*\*\*2W>MANUAL IND (RPL-91a)

**Data Element Summary**

	<u>Ref. Des. Attributes</u>	<u>Data Element</u>	<u>Name</u>		
M	N901	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification H7 Standard Clause	M	ID 2/3
	N902	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier ORI Order Instructions	X	AN 1/30
	N903	369	<b>Free-form Description</b> Free-form descriptive text "RPL"	X	AN 1/45
	N907	C040	<b>Reference Identifier</b> To identify one or more reference numbers or identification numbers as specified by the Reference Qualifier	O	
M	C04001	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification 2W Change Order Authority	M	ID 2/3
M	C04002	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier MANUAL IND (RPL-91a) = Manual Indicator	M	AN 1/30

**Segment:** **MTX** Text  
**Position:** 3260  
**Loop:** N9 Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To specify textual data  
**Syntax Notes:**

- 1 If MTX01 is present, then MTX02 is required.
- 2 If MTX03 is present, then MTX02 is required.
- 3 If MTX05 is present, then MTX04 is required.

**Semantic Notes:**

- 1 MTX05 is the number of lines to advance before printing.

**Comments:**

- 1 If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

**Notes:** MTX\*\*REMARKS (RPL-91)

**Data Element Summary**

<u>Ref.</u> <u>Des.</u>	<u>Data</u> <u>Element</u>	<u>Name</u>		
<b>Attributes</b> MTX02	1551	<b>Message Text</b> To transmit large volumes of message text REMARKS (RPL-91) = Remarks	X	AN 1/4096

Segment: **POC** Line Item Change - RPL, Primary Location - Services

**Details**

Position: 0100  
 Loop: POC Optional  
 Level: Detail  
 Usage: Optional  
 Max Use: 1

Purpose: To specify changes to a line item  
 Syntax Notes:  
 1 If POC03 is present, then both POC04 and POC05 are required.  
 2 If POC07 is present, then POC06 is required.  
 3 If either POC08 or POC09 is present, then the other is required.  
 4 If either POC10 or POC11 is present, then the other is required.  
 5 If either POC12 or POC13 is present, then the other is required.  
 6 If either POC14 or POC15 is present, then the other is required.  
 7 If either POC16 or POC17 is present, then the other is required.  
 8 If either POC18 or POC19 is present, then the other is required.  
 9 If either POC20 or POC21 is present, then the other is required.  
 10 If either POC22 or POC23 is present, then the other is required.  
 11 If either POC24 or POC25 is present, then the other is required.  
 12 If either POC26 or POC27 is present, then the other is required.  
 Semantic Notes:  
 1 POC01 is the purchase order line item identification.

**Comments:**

Notes: POC\*n\*RZ\*\*\*\*\*ZZ\*RPL\_PLSD

**Data Element Summary**

Ref.	Data		
<u>Des.</u>	<u>Element</u>	<u>Name</u>	
<b>Attributes</b>			
POC01	350	<b>Assigned Identification</b>	<b>O AN 1/20</b>
		Alphanumeric characters assigned for differentiation within a transaction set	
		"n" = nth assigned ID within POC loop	
<b>M</b>	POC02	<b>Change or Response Type Code</b>	<b>M ID 2/2</b>
		Code specifying the type of change to the line item	
		RZ Replace All Values	
		Receiver should replace the corresponding values in the original purchase order with the values contained in the Purchase Order Change Transaction Set	
	POC08	<b>Product/Service ID Qualifier</b>	<b>X ID 2/2</b>
		Code identifying the type/source of the descriptive number used in Product/Service ID (234)	
		ZZ Mutually Defined	
	POC09	<b>Product/Service ID</b>	<b>X AN 1/48</b>
		Identifying number for a product or service	
		"RPL_PLSD"	

**Segment:** **SI** Service Characteristic Identification

**Position:** 0180  
**Loop:** POC Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1

**Purpose:** To specify service characteristic data  
**Syntax Notes:**

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

**Semantic Notes:**

**Comments:** 1 SI01 defines the source for each of the service characteristics qualifiers.

**Notes:** SI\*TI\*LT\*02 (designates "primary")  
 SI\*TI\*SA\*LNA (RPL-94)  
 SI\*TI\*CN\*ECCKT (RPL-104)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
	<b>Attributes</b>				
M	SI01	559	<b>Agency Qualifier Code</b>	M	ID 2/2
			Code identifying the agency assigning the code values		
			TI Telecommunications Industry		
M	SI02	1000	<b>Service Characteristics Qualifier</b>	M	AN 2/2
			Code from an industry code list qualifying the type of service characteristics		
			CN Circuit Number Identification		
			LT Location Type		
			SA Service Activity		
M	SI03	234	<b>Product/Service ID</b>	M	AN 1/48
			Identifying number for a product or service		
			LNA (RPL-94) = Line Activity		
			C = (DWS: C-Change or Modification to an Existing Wholesale Service)		
			A = (DWS: N-New Installation)		
			V = (DWS: V-Conversion As Specified)		
			02 = Primary		
			ECCKT (RPL-104) = Exchange Company Circuit ID		

**Segment:** **PID** Product/Item Description

**Position:** 0500

**Loop:** PID Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To describe a product or process in coded or free-form format

**Syntax Notes:**

- 1 If PID04 is present, then PID03 is required.
- 2 At least one of PID04 or PID05 is required.
- 3 If PID07 is present, then PID03 is required.
- 4 If PID08 is present, then PID04 is required.
- 5 If PID09 is present, then PID05 is required.

**Semantic Notes:**

- 1 Use PID03 to indicate the organization that publishes the code list being referred to.
- 2 PID04 should be used for industry-specific product description codes.
- 3 PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
- 4 PID09 is used to identify the language being used in PID05.

**Comments:**

- 1 If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
- 2 Use PID06 when necessary to refer to the product surface or layer being described in the segment.
- 3 PID07 specifies the individual code list of the agency specified in PID03.

**Notes:** PID\*X\*\*TI\*CFA\*CFA (RPL-105)

#### Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	<b>PID01</b>	<b>349</b>	<b>Item Description Type</b>	<b>M</b>	<b>ID 1/1</b>
			Code indicating the format of a description		
			X Semi-structured (Code and Text)		
	<b>PID03</b>	<b>559</b>	<b>Agency Qualifier Code</b>	<b>X</b>	<b>ID 2/2</b>
			Code identifying the agency assigning the code values		
		TI Telecommunications Industry			
	<b>PID04</b>	<b>751</b>	<b>Product Description Code</b>	<b>X</b>	<b>AN 1/12</b>
			A code from an industry code list which provides specific data about a product characteristic		
			CFA Connecting Facility Assignment		
	<b>PID05</b>	<b>352</b>	<b>Description</b>	<b>X</b>	<b>AN 1/80</b>
			A free-form description to clarify the related data elements and their content		
			CFA (RPL-105) = Connecting Facility Assignment		



**Segment:** **REF** Reference Identification  
**Position:** 1000  
**Loop:** POC Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1  
**Purpose:** To specify identifying information  
**Syntax Notes:**

- 1 At least one of REF02 or REF03 is required.
- 2 If either C04003 or C04004 is present, then the other is required.
- 3 If either C04005 or C04006 is present, then the other is required.

**Semantic Notes:**

- 1 REF04 contains data relating to the value cited in REF02.

**Comments:**  
**Notes:** REF\*AE\*SAN (RPL-94a)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	REF01	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification AE Authorization for Expense (AFE) Number	M	ID 2/3
	REF02	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier SAN (RPL-94a) = Subscriber Authorization Number	X	AN 1/30

**Segment:** **SLN** Subline Item Detail

**Position:** 4600

**Loop:** SLN Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To specify product subline detail item data

**Syntax Notes:**

- 1 If either SLN04 or SLN05 is present, then the other is required.
- 2 If SLN07 is present, then SLN06 is required.
- 3 If SLN08 is present, then SLN06 is required.
- 4 If either SLN09 or SLN10 is present, then the other is required.
- 5 If either SLN11 or SLN12 is present, then the other is required.
- 6 If either SLN13 or SLN14 is present, then the other is required.
- 7 If either SLN15 or SLN16 is present, then the other is required.
- 8 If either SLN17 or SLN18 is present, then the other is required.
- 9 If either SLN19 or SLN20 is present, then the other is required.
- 10 If either SLN21 or SLN22 is present, then the other is required.
- 11 If either SLN23 or SLN24 is present, then the other is required.
- 12 If either SLN25 or SLN26 is present, then the other is required.
- 13 If either SLN27 or SLN28 is present, then the other is required.

**Semantic Notes:**

- 1 SLN01 is the identifying number for the subline item.
- 2 SLN02 is the identifying number for the subline level. The subline level is analogous to the level code used in a bill of materials.
- 3 SLN03 is the configuration code indicating the relationship of the subline item to the baseline item.
- 4 SLN08 is a code indicating the relationship of the price or amount to the associated segment.

**Comments:**

- 1 See the Data Element Dictionary for a complete list of IDs.
- 2 SLN01 is related to (but not necessarily equivalent to) the baseline item number. Example: 1.1 or 1A might be used as a subline number to relate to baseline number 1.
- 3 SLN09 through SLN28 provide for ten different product/service IDs for each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

**Notes:** SLN\*IW\*n\*A\*IWJQ (RPL-101)\*EA\*\*\*\*EQ\*IWJK (RPL-102) [SLN Loop may repeat per Inside Wiring Pair]

#### Data Element Summary

	Ref. Des.	Data Element	Name		
M	SLN01	350	Assigned Identification	M	AN 1/20
			Alphanumeric characters assigned for differentiation within a transaction set		
			"IW"		
	SLN02	350	Assigned Identification	O	AN 1/20
			Alphanumeric characters assigned for differentiation within a transaction set		
			"n" = nth assigned ID within SLN loop		
M	SLN03	662	Relationship Code	M	ID 1/1
			Code indicating the relationship between entities		
			A Add		
	SLN04	380	Quantity	X	R 1/15

			Numeric value of quantity		
			IWJQ (RPL-101) = Inside Wire Jack Quantity		
	<b>SLN05</b>	<b>C001</b>	<b>Composite Unit of Measure</b>	<b>X</b>	
			To identify a composite unit of measure (See Figures Appendix for examples of use)		
<b>M</b>	<b>C00101</b>	<b>355</b>	<b>Unit or Basis for Measurement Code</b>	<b>M</b>	<b>ID 2/2</b>
			Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken		
			EA                      Each		
	<b>SLN09</b>	<b>235</b>	<b>Product/Service ID Qualifier</b>	<b>X</b>	<b>ID 2/2</b>
			Code identifying the type/source of the descriptive number used in Product/Service ID (234)		
			EQ                      Equipment Type		
	<b>SLN10</b>	<b>234</b>	<b>Product/Service ID</b>	<b>X</b>	<b>AN 1/48</b>
			Identifying number for a product or service		
			IWJK (RPL-102) = Inside Wire Jack Code		

Segment: **POC** Line Item Change - RPL, Secondary Location - Service

**Details**

Position: 0100  
 Loop: POC Optional  
 Level: Detail  
 Usage: Optional  
 Max Use: 1

**Purpose:** To specify changes to a line item  
**Syntax Notes:**  
 1 If POC03 is present, then both POC04 and POC05 are required.  
 2 If POC07 is present, then POC06 is required.  
 3 If either POC08 or POC09 is present, then the other is required.  
 4 If either POC10 or POC11 is present, then the other is required.  
 5 If either POC12 or POC13 is present, then the other is required.  
 6 If either POC14 or POC15 is present, then the other is required.  
 7 If either POC16 or POC17 is present, then the other is required.  
 8 If either POC18 or POC19 is present, then the other is required.  
 9 If either POC20 or POC21 is present, then the other is required.  
 10 If either POC22 or POC23 is present, then the other is required.  
 11 If either POC24 or POC25 is present, then the other is required.  
 12 If either POC26 or POC27 is present, then the other is required.  
**Semantic Notes:**  
 1 POC01 is the purchase order line item identification.

**Comments:**

**Notes:** POC\*n\*RZ\*\*\*\*\*ZZ\*RPL\_SLSD [POC Loop repeats SECLOCSEVDETQTY (RPL-108a) times]

**Data Element Summary**

Ref.	Data		
<u>Des.</u>	<u>Element</u>	<u>Name</u>	
<b>Attributes</b>			
<b>POC01</b>	<b>350</b>	<b>Assigned Identification</b>	<b>O AN 1/20</b>
		Alphanumeric characters assigned for differentiation within a transaction set	
		"n" = nth assigned ID within POC loop	
<b>M</b>	<b>POC02</b>	<b>670</b>	<b>Change or Response Type Code</b>
			<b>M ID 2/2</b>
		Code specifying the type of change to the line item	
		RZ Replace All Values	
		Receiver should replace the corresponding values in the original purchase order with the values contained in the Purchase Order Change Transaction Set	
	<b>POC08</b>	<b>235</b>	<b>Product/Service ID Qualifier</b>
			<b>X ID 2/2</b>
		Code identifying the type/source of the descriptive number used in Product/Service ID (234)	
		ZZ Mutually Defined	
	<b>POC09</b>	<b>234</b>	<b>Product/Service ID</b>
			<b>X AN 1/48</b>
		Identifying number for a product or service	
		"RPL_SLSD"	

**Segment:** **SI** Service Characteristic Identification

**Position:** 0180  
**Loop:** POC Optional  
**Level:** Detail  
**Usage:** Optional  
**Max Use:** >1

**Purpose:** To specify service characteristic data  
**Syntax Notes:**

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

**Semantic Notes:**

**Comments:** 1 SI01 defines the source for each of the service characteristics qualifiers.

**Notes:** SI\*TI\*LT\*04 (designates "secondary")  
 SI\*TI\*SA\*LNA (RPL-111)  
 SI\*TI\*CN\*ECCKT (RPL-119)

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
	<b>Attributes</b>				
M	SI01	559	<b>Agency Qualifier Code</b>	M	ID 2/2
			Code identifying the agency assigning the code values		
			TI Telecommunications Industry		
M	SI02	1000	<b>Service Characteristics Qualifier</b>	M	AN 2/2
			Code from an industry code list qualifying the type of service characteristics		
			CN Circuit Number Identification		
			LT Location Type		
			SA Service Activity		
M	SI03	234	<b>Product/Service ID</b>	M	AN 1/48
			Identifying number for a product or service		
			LNA (RPL-111) = Line Activity		
			C = (DWS: C-Change or Modification to Existing Wholesale Service)		
			A = (DWS: N-New installation)		
			V = (DWS: V-Conversion as specified)		
			D = (DWS: D-Remove a secondary location)		
			04 = Secondary		
			ECCKT (RPL-119) = Exchange Company Circuit ID		

**Segment:** **PID** Product/Item Description

**Position:** 0500

**Loop:** PID Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To describe a product or process in coded or free-form format

**Syntax Notes:**

- 1 If PID04 is present, then PID03 is required.
- 2 At least one of PID04 or PID05 is required.
- 3 If PID07 is present, then PID03 is required.
- 4 If PID08 is present, then PID04 is required.
- 5 If PID09 is present, then PID05 is required.

**Semantic Notes:**

- 1 Use PID03 to indicate the organization that publishes the code list being referred to.
- 2 PID04 should be used for industry-specific product description codes.
- 3 PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
- 4 PID09 is used to identify the language being used in PID05.

**Comments:**

- 1 If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
- 2 Use PID06 when necessary to refer to the product surface or layer being described in the segment.
- 3 PID07 specifies the individual code list of the agency specified in PID03.

**Notes:** PID\*X\*\*TI\*CFA\*CFA (RPL-120)

#### Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	<b>PID01</b>	<b>349</b>	<b>Item Description Type</b>	<b>M</b>	<b>ID 1/1</b>
			Code indicating the format of a description		
			X Semi-structured (Code and Text)		
	<b>PID03</b>	<b>559</b>	<b>Agency Qualifier Code</b>	<b>X</b>	<b>ID 2/2</b>
			Code identifying the agency assigning the code values		
		TI Telecommunications Industry			
	<b>PID04</b>	<b>751</b>	<b>Product Description Code</b>	<b>X</b>	<b>AN 1/12</b>
			A code from an industry code list which provides specific data about a product characteristic		
			CFA Connecting Facility Assignment		
	<b>PID05</b>	<b>352</b>	<b>Description</b>	<b>X</b>	<b>AN 1/80</b>
			A free-form description to clarify the related data elements and their content		
			CFA (RPL-120) = Connecting Facility Assignment		

**Segment:** **REF** Reference Identification

**Position:** 1000

**Loop:** POC Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** >1

**Purpose:** To specify identifying information

- Syntax Notes:**
- 1 At least one of REF02 or REF03 is required.
  - 2 If either C04003 or C04004 is present, then the other is required.
  - 3 If either C04005 or C04006 is present, then the other is required.
- Semantic Notes:**
- 1 REF04 contains data relating to the value cited in REF02.

**Comments:**

**Notes:** REF\*IX\*LOCNUM (RPL-109)\*LOCNUM

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
M	REF01	128	<b>Reference Identification Qualifier</b> Code qualifying the Reference Identification IX Item Number	M	ID 2/3
	REF02	127	<b>Reference Identification</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier LOCNUM (RPL-109) = Location Number	X	AN 1/30
	REF03	352	<b>Description</b> A free-form description to clarify the related data elements and their content "LOCNUM"	X	AN 1/80

**Segment:** **SLN** Subline Item Detail

**Position:** 4600

**Loop:** SLN Optional

**Level:** Detail

**Usage:** Optional

**Max Use:** 1

**Purpose:** To specify product subline detail item data

**Syntax Notes:**

- 1 If either SLN04 or SLN05 is present, then the other is required.
- 2 If SLN07 is present, then SLN06 is required.
- 3 If SLN08 is present, then SLN06 is required.
- 4 If either SLN09 or SLN10 is present, then the other is required.
- 5 If either SLN11 or SLN12 is present, then the other is required.
- 6 If either SLN13 or SLN14 is present, then the other is required.
- 7 If either SLN15 or SLN16 is present, then the other is required.
- 8 If either SLN17 or SLN18 is present, then the other is required.
- 9 If either SLN19 or SLN20 is present, then the other is required.
- 10 If either SLN21 or SLN22 is present, then the other is required.
- 11 If either SLN23 or SLN24 is present, then the other is required.
- 12 If either SLN25 or SLN26 is present, then the other is required.
- 13 If either SLN27 or SLN28 is present, then the other is required.

**Semantic Notes:**

- 1 SLN01 is the identifying number for the subline item.
- 2 SLN02 is the identifying number for the subline level. The subline level is analogous to the level code used in a bill of materials.
- 3 SLN03 is the configuration code indicating the relationship of the subline item to the baseline item.
- 4 SLN08 is a code indicating the relationship of the price or amount to the associated segment.

**Comments:**

- 1 See the Data Element Dictionary for a complete list of IDs.
- 2 SLN01 is related to (but not necessarily equivalent to) the baseline item number. Example: 1.1 or 1A might be used as a subline number to relate to baseline number 1.
- 3 SLN09 through SLN28 provide for ten different product/service IDs for each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

**Notes:** SLN\*IW\*n\*A\*IWJQ (RPL-116)\*EA\*\*\*\*EQ\*IWJK (RPL-117) [SLN Loop may repeat per Inside Wiring Pair]

#### Data Element Summary

	Ref. Des.	Data Element	Name		
M	SLN01	350	Assigned Identification	M	AN 1/20
			Alphanumeric characters assigned for differentiation within a transaction set		
			"IW"		
	SLN02	350	Assigned Identification	O	AN 1/20
			Alphanumeric characters assigned for differentiation within a transaction set		
			"n" = nth assigned ID within SLN loop		
M	SLN03	662	Relationship Code	M	ID 1/1
			Code indicating the relationship between entities		
			A Add		
	SLN04	380	Quantity	X	R 1/15



			Numeric value of quantity		
			IWJQ (RPL-116) = Inside Wire Jack Quantity		
	<b>SLN05</b>	<b>C001</b>	<b>Composite Unit of Measure</b>	<b>X</b>	
			To identify a composite unit of measure (See Figures Appendix for examples of use)		
<b>M</b>	<b>C00101</b>	<b>355</b>	<b>Unit or Basis for Measurement Code</b>	<b>M</b>	<b>ID 2/2</b>
			Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken		
			EA                      Each		
	<b>SLN09</b>	<b>235</b>	<b>Product/Service ID Qualifier</b>	<b>X</b>	<b>ID 2/2</b>
			Code identifying the type/source of the descriptive number used in Product/Service ID (234)		
			EQ                      Equipment Type		
	<b>SLN10</b>	<b>234</b>	<b>Product/Service ID</b>	<b>X</b>	<b>AN 1/48</b>
			Identifying number for a product or service		
			IWJK (RPL-117) = Inside Wire Jack Code		

**Segment:** **CTT** Transaction Totals

**Position:** 0100

**Loop:** CTT Optional

**Level:** Summary

**Usage:** Optional

**Max Use:** 1

**Purpose:** To transmit a hash total for a specific element in the transaction set

**Syntax Notes:** 1 If either CTT03 or CTT04 is present, then the other is required.

2 If either CTT05 or CTT06 is present, then the other is required.

**Semantic Notes:**

**Comments:** 1 This segment is intended to provide hash totals to validate transaction completeness and correctness.

**Notes:** CTT\*Number of POC Segments

#### Data Element Summary

	<u>Ref.</u> <u>Des.</u> <u>Attributes</u>	<u>Data</u> <u>Element</u>	<u>Name</u>	
M	CTT01	354	Number of Line Items Total number of line items in the transaction set	M NO 1/6

**Segment:** **SE** Transaction Set Trailer  
**Position:** 0300  
**Loop:**  
**Level:** Summary  
**Usage:** Mandatory  
**Max Use:** 1  
**Purpose:** To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

**Syntax Notes:**

**Semantic Notes:**

**Comments:** 1 SE is the last segment of each transaction set.

**Notes:** SE\*Number of Segments\*TRANS SET CONTROL#

**Data Element Summary**

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>		
<b>M</b>	<b>SE01</b>	<b>96</b>	<b>Number of Included Segments</b>	<b>M</b>	<b>NO 1/10</b>
			Total number of segments included in a transaction set including ST and SE segments		
<b>M</b>	<b>SE02</b>	<b>329</b>	<b>Transaction Set Control Number</b>	<b>M</b>	<b>AN 4/9</b>
			Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set		