

Interim Number Portability (INP) Order Submittal

Table of Contents

18.	INTERIM NUMBER PORTABILITY (INP) ORDER SUBMITTAL.....	2
18.1	BUSINESS DESCRIPTION.....	2
18.2	BUSINESS MODEL.....	5
18.3	DEVELOPER WORKSHEETS.....	6
18.4	TRADING PARTNER ACCESS INFORMATION.....	7
18.4.1	OVERVIEW: Qwest Specific Functional Group Envelope - Routing Information.....	7
18.4.2	ISA TABLE INFORMATION.....	9
18.4.3	GS TABLE INFORMATION.....	10
18.4.4	MAPPING EXAMPLE AND DATA DICTIONARY ITEMS.....	12
18.5	MAPPING EXAMPLES.....	13
18.5.1	850 Interim Number Portability Service Request (850INP) – Version 4020.....	13
18.5.2	860 Interim Number Portability Supplemental Service Request (860INP)-Version 4020.....	16
18.6	DATA DICTIONARY.....	17
18.6.1	850 Interim Number Portability Service Request (850INP).....	17
18.6.2	860 Interim Number Portability Supplemental Service Request (860INP).....	88

18. Interim Number Portability (INP) Order Submittal

18.1 Business Description

Number Portability Service involves transferring a telephone number to a CLEC such that the end customer does not have to incur a telephone number change when moving to a CLEC's facilities. Qwest will disconnect the existing telephone service provided to the customer.

Number Portability can be achieved in two ways:

1. Interim Number Portability (INP) - allows an end-customer who elects to transfer his/her existing telephone service from Qwest to a CLEC while retaining the telephone number. The telephone number will remain physically resident on the Qwest switch and be ported to the CLEC's switch. INP can be achieved in one of three ways:
 - Remote Call Forwarding. This feature allows a call to a Qwest assigned telephone number to be forwarded to the CLEC's dialable local number.
 - Direct-Inward-Dialing (DID). This service allows a call to a Qwest assigned telephone number to be routed to the CLEC's switch via a DID trunk.
 - Directory Number Routing Index (DNRI). This service allows an incoming call to a Qwest assigned telephone number to be routed to the CLEC's switch via a trunk terminating on the Signaling System 7 (SS7) network.
2. Local Number Portability (LNP)

The following forms will be used between Qwest and the CLEC for Interim Number Portability ordering purposes:

- LSR - Local Service Request
- EU - End User Information
- NP – Number Portability

The following Order Activity Matrices define the available Order and Line Activities for Interim Number Portability:

Combining Order and Line Activity

Business Rules for Combining Order and Line Activity for Interim Number Portability

Order Activity Definition

REQ TYPE	ACT	Definition	Application	LNA	Forms required
CB	N	New Installation	Not Allowed	Not Allowed	
	D	Disconnect	Disconnect all INP services at the Account level.	Not Allowed	LSR, EU

W	Conversion As Is	Not Allowed	Not Allowed	
V	Conversion As Specified	An ACT entry of V will discontinue the Listing(s) associated with the Port Activity (all listings are removed)	V, D	LSR, EU, NP
Z	Conversion As Specified, No Directory Listing	An ACT entry of Z will retain the current Listing(s).	V, D	LSR, EU, NP
C	Change	Change to a customer's INP service where some or all of the customer's numbers have already been ordered to the CLECs.	C,D	LSR, EU, NP
T	Outside Move	Not Allowed	Not Allowed	
L	Seasonal Suspend	Not Allowed	Not Allowed	
Y	Deny	Not Allowed	Not Allowed	
B	Restore	Not Allowed	Not Allowed	
R	Record	Not Allowed	Not Allowed	
M	Inside Move	Not Allowed	Not Allowed	

Line Activities

LNA	Definition	Application
D	Line Disconnect.	Used to disconnect end users numbers as opposed to porting them.
C	Change	Used to make changes to the characteristics of an Interim Number Portability number.
V	Line Conversion As Specified	Porting of a telephone number to the CLEC where all attributes of the service are specified.
All other LNA		Not Allowed

18.2 Business Model

See Appendix H

18.3 Developer Worksheets

See Appendices B and C– Developer Worksheets - Order

18.4 Trading Partner Access Information

ORDERING FUNCTION	PRODUCT ID
Interim Number Portability Service Request	850INP
Interim Number Portability Supplemental	860INP
Status Update – Auto Push	855SU
Firm Order Confirmation	855FOC
Firm Order Confirmation on Supplemental	865FOC
Non Fatal Error Response	855NF
Non Fatal Error Response on Supplemental	865NF
Fatal Error Response	855FATAL
Fatal Error Response on Supplemental	865FATAL
Jeopardy	865JEOP
Completion	865COMP

Order Submittal

The process begins with an EDI Trading Partner Agreement between Qwest and the Co-Provider. The order request is transmitted by the Co-Provider via the EDI 850/860 format. Qwest will translate and forward the data to the internal application system. The request may activate the following responses:

- Firm Order Confirmation (FOC) - an indicator to the Co-Provider that the order has been accepted and successfully entered into the Qwest Service Order Processor systems.
- Order Completion - notification returned to the Co-Provider when a service request is completed.
- Error/Jeopardy Notification - notification to the Co-Provider of Fatal and/or Non-Fatal errors, detected either manually or by the system. Fatal errors prevent the order from processing. Non-Fatal errors occur after the order has successfully processed through the IMA system. Jeopardy Notification will be issued if Qwest has a problem meeting the commitment on the local service request.

18.4.1 OVERVIEW: Qwest Specific Functional Group Envelope - Routing Information

Separate maps have been created per ordering function. EDI envelopes are used to initiate translation processing and to invoke the correct map. In order to optimize interactive performance, the Co-Provider and Qwest agree to include only one transaction set per Functional Group, and one Functional Group per Interchange.

The Interchange envelope provides the Interchange Sender ID and Receiver ID information for EDI transport to deliver the transmission for external routing. The Functional Group Envelope routes the enclosed transaction set's output after translation to a specific application or application interface.

The Application Sender's Code (GS02) and Receiver's Code (GS03) are the linkage from the Functional Group Envelope to the translator's trading partner profile/relationship database in which the proper mapping and routing information are stored. In addition, the Functional Identifier Code (GS01) is the code identifying a group application related transaction sets.

18.4.2 ISA TABLE INFORMATION

ANSI X12 ISA and IEA definitions:

- The ISA segment is the Interchange Control Header.
Purpose: To start and identify an interchange of zero or more functional groups and interchange related control segments.
- The IEA segment is the Interchange Control Trailer.
Purpose: To define the end of an interchange of zero or more functional groups and interchange related control segments.

The Co-Provider and Qwest agree to the following routing information:

	SENT TO QWEST	RECEIVED FROM QWEST
ISA01	'00' (No Authorization information present)	'00' (No Authorization information present)
ISA02	Spaces (Authorization information)	Spaces (Authorization information)
ISA03	'00' (No Security information is present)	'00' (No Security information is present)
ISA04	Spaces (Security Information)	Spaces (Security information)
ISA05	Co-Provider TP qualifier	'ZZ' (Mutually Defined)
ISA06	Co-Provider TP ID	'QWESTO' (Note: This Trading partner ID is used only for Qwest order and post-order transactions. The "O" is the unique identifier.)
ISA07	'ZZ' (Mutually Defined)	Co-Provider TP qualifier
ISA08	'QWESTO' (Note: This Trading partner ID is used only for Qwest order and post-order transactions. The "O" is the unique identifier.)	Co-Provider TP ID
ISA09	Date of the interchange. YYMMDD	Date of the interchange. YYMMDD
ISA10	Time of the interchange. HHMM (24 Hour Clock)	Time of the interchange. HHMM (24 Hour Clock)
ISA11	'U' (U.S. EDI Community of ASC X-12, TDCC, and UCS)	'U' (U.S. EDI Community of ASC X-12, TDCC, and UCS)
ISA12	'00402' (Interchange Version ID)	'00402' (Interchange Version ID)
ISA13	Sender's translator assigned sequential control number	Sender's translator assigned sequential control number
ISA14	'0' (No acknowledgment requested)	'0' (No acknowledgment requested)
ISA15	'P' (Production data)	'P' (Production data)
ISA16	'0x1f' (Sub-element Separator)	'0x1f' (Sub-element Separator)

18.4.3 GS TABLE INFORMATION

GS and GE segment definitions:

- The GS segment is the Functional Group Header.
Purpose: To indicate the beginning of a functional group and provide control information.
- The GE segment is the Functional Group Trailer.
Purpose: To indicate the end of a functional group and provide control information.

The Co-Provider and Qwest agree to the following routing information:

	SENT TO QWEST	RECEIVED FROM QWEST
GS01	SEE GS TABLE BELOW	SEE GS TABLE BELOW
GS02	<i>Co-Provider TP ID</i>	SEE GS TABLE BELOW
GS03	SEE GS TABLE BELOW	<i>Co-Provider TP ID</i>
GS04	<i>Date of the functional group. CCYYMMDD</i>	<i>Date of the functional group. CCYYMMDD</i>
GS05	<i>Time of the functional group. HHMM (24 hour clock)</i>	<i>Time of the functional group. HHMM (24 hour clock)</i>
GS06	<i>Sender's translator assigned sequential control number</i>	<i>Sender's translator assigned sequential control number</i>
GS07	'X' (Accredited Standards Committee X-12)	'X' (Accredited Standards Committee X-12)
GS08	'004020' (Version)	'004020' (Version)

GS Table

The Co-Provider and Qwest agree to the following routing information:

ORDERING FUNCTION	QWEST SEND/ RECEIVE	DOCUMENT	GS01 VALUE	GS02 VALUE	GS03 VALUE
Service Request	Receive	850INP	PO	<i>Co-Provider TP ID</i>	INP90
Status Update – Auto Push	Send	855SU	PR	SU90	<i>Co-Provider TP ID</i>
Firm Order Confirmation	Send	855FOC	PR	FOC90	<i>Co-Provider TP ID</i>
Non Fatal Error Response	Send	855NF	PR	NF90	<i>Co-Provider TP ID</i>
Fatal Error Response	Send	855FATAL	PR	FATAL90	<i>Co-Provider TP ID</i>
Jeopardy	Send	865JEOP	CA	JEOP90	<i>Co-Provider TP ID</i>
Completion	Send	865COMP	CA	COMP90	<i>Co-Provider TP ID</i>

Supplemental Order

Once an order has been initiated and received by Qwest the Co-Provider may submit an 860 Purchase Order Change Request to cancel, correct, or change the original order. In response to receiving the 860 request from the Co-Provider, Qwest will transmit Functional Acknowledgments (997) and Purchase Order Change Acknowledgments (865).

GS Table (Supplemental)

The Co-Provider and Qwest agree to the following routing information:

ORDERING FUNCTION	QWEST SEND/ RECEIVE	DOCUMENT	GS01 VALUE	GS02 VALUE	GS03 VALUE
Supplemental	Receive	860INP	PC	<i>Co-Provider TP ID</i>	INP90
Status Update – Auto Push	Send	855SU	PR	SU90	<i>Co-Provider TP ID</i>
Firm Order Confirmation	Send	865FOC	CA	FOC90	<i>Co-Provider TP ID</i>
Non Fatal Error Response	Send	865NF	CA	NF90	<i>Co-Provider TP ID</i>
Fatal Error Response	Send	865FATAL	CA	FATAL90	<i>Co-Provider TP ID</i>
Jeopardy	Send	865JEOP	CA	JEOP90	<i>Co-Provider TP ID</i>
Completion	Send	865COMP	CA	COMP90	<i>Co-Provider TP ID</i>

18.4.4 MAPPING EXAMPLE AND DATA DICTIONARY ITEMS

Purchase Order (PO) Date

The Purchase Order (PO) Date is an ANSI ASC X12 mandatory field. The sender is expected to populate this field, Qwest however, will not map this date into the application file. For outbound transactions Qwest will populate this field with a date. This date is only used to satisfy ANSI ASC X12 standards and should not be used by the Co-Provider.

Time Code

The DWS time code fields of every transaction, (i.e., D/T SENT) is assumed as follows:

- Transaction set(s) originating from the Co-Provider - time code should be consistent with your time zone.
- Transaction set(s) originating at Qwest - time code is Mountain Time.

4020 Exceptions

Transaction sets 850, 855, 860 and 865 are used with the following exception:

- SLN loop maximum use has been changed to >1

Delimiters

The following delimiters will be used:

- Element Separator: HEX 7C = | (vertical bar or pipe)
- Sub-Element Separator: HEX 1F = (non-printable characters of "0x1f")
- Segment Separator: HEX 0A = linefeed

Qwest Specific Fields

Order fields that are specific to the Qwest implementation were added to selected OBF forms and are indicated by an alpha following the field number, i.e., EU-19a (AHN). These fields are not defined in the OBF form for the corresponding LSOG issue.

Industry Standards Table:

OBF FORM	OBF ISSUE	EDI SOSC ISSUE	X12 STANDARD
End User	LSOG 5	ELMS 5	004020
Local Service Request	LSOG 5	ELMS 5	004020
Number Portability	LSOG 5	ELMS 5	004020
Status Updates			004020
Firm Order Confirmation			004020
Non Fatal Error Response			004020
Fatal Error Response			004020
Jeopardy			004020
Completion			004020

18.5 Mapping Examples

18.5.1 850 Interim Number Portability Service Request (850INP) – Version 4020

Legend of Symbols in this transaction example

Symbol/Definition	Example
{ } = Valid Format	{CCYYMMDD}
Bold/Italics = Developer's Worksheet Element	PON
Superscript = Developer's Worksheet Ref # DWS used in this mapping example: LSR = Local Service Request EU = End User NP = Number Portability	LSR-2
<i>Italics</i> = Literal	<i>GOOD</i>
<u>Underline</u> = Apply code conversion, used with Bold/Italics . Code conversion tables can be found in the data dictionary of this disclosure.	<u>ACT</u>
[] = Segment notes for this line	[SI Segment repeats ...]
() = Element notes for this line	(This element states ...)
n	Counter 1...n
* = Element separator in this example and related data dictionary.	= Actual element separator in an EDI transaction.
> = Sub-element separator in this example and related data dictionary.	non-printable characters of "0x1f" = Actual sub-element separator in an EDI transaction.

```

ST*850*TRAN SET CONTROL #
BEG*00*SS*LSR-2PON*PO Date(See Trading Partner Access Information)
REF*11*LSR-7AN*LSR-7AN
REF*12*LSR-61BAN1*LSR-61BAN1
REF*JB*LSR-20PROJECT
REF*SU*LSR-28RTR*LSR-28RTR
REF*CO*LSR-51RPON*LSR-51RPON
REF*1V*LSR-52RORD*LSR-52RORD
PAM*48*LSR-10PG_of (1st 2 Bytes)*EA
PAM*47*LSR-10PG_of (2nd 2 Bytes)*EA
PAM*OC*NP-5NPQTY*EA
DTM*097*LSR-12D/TSENT{CCYYMMDD}LSR-12*LSR-12D/TSENT{HHMM}LSR-12
DTM*150*LSR-14DDD{CCYYMMDD}LSR-14
DTM*992*LSR-19TM*LSR-19DFDT{HHMM}LSR-19
DTM*270*LSR-36DATED{CCYYMMDD}LSR-36
SI*TI*RE*LSR-23REQTYPLSR-23
SI*TI*AA*LSR-24ACTLSR-24
SI*TI*TY*LSR-44TOSLSR-44
PID*S**TI*CONVIND***SO-RSQ*LSR-24aCONVINDLSR-24a
PID*S**TI*AO***SO-RSQ*LSR-35AGAUTHLSR-35
PID*S**TI*BI***SO-RSQ*EU-42FBIEU-42
PID*S**TI*PENDING***SO-RSQ*LSR-108bPENDING ORDERLSR-108b
N9*H7*ORI*NP-34aINP****2W>MANUAL INDNP-34a
MTX**NP-34REMARKSNP-34
N9*H7*ORI*LSR-108aLSR****2W>MANUAL INDLSR-108a
MTX**LSR-108REMARKSLSR-108
N9*H7*ORI*EU-63aEU****2W>MANUAL INDEU-63a

```

MTX**REMARKS^{EU-63}
 N1*78*CCNA^{LSR-1}
 PER*AG*INIT^{LSR-81}*TE*TEL NO^{LSR-82}*FX*FAX NO^{LSR-84}*EM*EMAIL^{LSR-83}
 PER*CN*IMPCON^{LSR-91}*TE*TEL NO^{LSR-92}
 N1*AN*AUTHNM^{LSR-37}
 N1*X1*BILLNM^{EU-43}
 N2*SBILLNM^{EU-44}
 N4**STATE^{EU-49}*ZIP^{EU-50}
 NX2*01*SANO^{EU-45b}
 NX2*02*SASN^{EU-45e}
 NX2*03*SASD^{EU-45d}
 NX2*07*CITY^{EU-48}
 NX2*32*FLOOR^{EU-46}
 NX2*35*ROOM/MAIL STOP^{EU-47}
 NX2*40*SASS^{EU-45g}
 NX2*59*SAPR^{EU-45a}
 NX2*61*SASF^{EU-45c}
 NX2*62*SATH^{EU-45f}
 PER*BI*BILLCON^{EU-51}*TE*TEL NO^{EU-52}
 SI*TI*AF*AFT^{EU-44a}

End User Form (Location and Access Section)

PO1*n*1*EA***ZZ*EU_SA [PO1 loop may repeat]
 N1*IT*NAME^{EU-8}
 N4**STATE^{EU-25}*ZIP^{EU-26}**RJ*CALA^{EU-26a}
 NX2*01*SANO^{EU-11}
 NX2*02*SASN^{EU-14}
 NX2*03*SASD^{EU-13}
 NX2*05*BOX^{EU-23c}
 NX2*06*ROUTE^{EU-23b}
 NX2*07*CITY^{EU-24}
 NX2*39*AHN^{EU-23a}
 NX2*40*SASS^{EU-16}
 NX2*59*SAPR^{EU-10}
 NX2*61*SASF^{EU-12}
 NX2*62*SATH^{EU-15}
 NX2*LD1^{EU-17}*LV1^{EU-18}
 NX2*LD2^{EU-19}*LV2^{EU-20}
 NX2*LD3^{EU-21}*LV3^{EU-22}
 SI*TI*AF*AFT^{EU-9}

End User Form (Disconnect Information Section)

PO1*n*1*EA***ZZ*EU_DISC [PO1 loop may repeat]
 SI*TI*ND*DISC NBR^{EU-55}
 SI*TI*T6*TC OPT^{EU-57}
 REF*IX*DNUM^{EU-54}*DNUM
 DTM*376*TC PER{CCYYMMDD}^{EU-62}
 SLN*TCPRI*n*A*1*EA
 SI*TI*TC*TC TO PRI^{EU-58}
 N1*TT*TC NAME^{EU-58b}
 REF*55*TCID^{EU-58a}*PRI
 SLN*TCSEC*n*A*1*EA [SLN loop may repeat]
 SI*TI*TC*TC TO SEC^{EU-59}

N1*TT*TC NAME^{EU-61}
REF*55*TCID^{EU-60}*SEC

NP Form (Service Details Section)

PO1*n*1*EA***ZZ*INP [PO1 repeats **NPQTY**^{NP-5} times]
SI*TI*SA*LNA^{NP-10}
SI*TI*IT*PORTED NBR^{NP-15}
SI*TI*C2*CFTN^{NP-17}
SI*TI*IP*NPT^{NP-18}
SI*TI*RI*RTI^{NP-19}
SI*TI*TH*NPTG^{NP-20}
SI*TI*FZ*FPI^{NP-24}
SI*TI*T6*TC OPT^{NP-26}
REF*IX*LNUM^{NP-8}*LNUM
DTM*376*TC PER {CCYYMMDD}^{NP-31}
QTY*43*TNP^{NP-16}*EA
N1*8V**41*LPIC^{NP-25}
SLN*TCPRI*n*A*1*EA
SI*TI*TC*TC TO PRI^{NP-27}
N1*TT*TC NAME^{NP-27b}
REF*55*TCID^{NP-27a}*PRI [SLN loop may repeat]
SLN*TCSEC*n*A*1*EA
SI*TI*TC*TC TO SEC^{NP-28}
N1*TT*TC NAME^{NP-30}
REF*55*TCID^{NP-29}*SEC
SLN*BL*n*A*1*EA
SI*TI*BB*BA^{NP-22}*TB*BLOCK^{NP-23}

Important Note: If none of the above PO1 loops are applicable a "Dummy" PO1 loop is used in this format:

PO1*DUMMY*1*EA***ZZ*DD

CTT*Number of PO1 Segments
SE*Number of Segments*TRAN SET CONTROL #

18.5.2 860 Interim Number Portability Supplemental Service Request (860INP)- Version 4020

The 860INP is identical to the 850INP with the following exceptions:

ST*860*TRAN SET CONTROL #
BCH***SUP**^{LSR-25}*SS***PON**^{LSR-2}****VER**^{LSR-3}*PO Date(See Trading Partner Access Information)
POC*n*RZ*****ZZ*?? (Where ?? = *EU_SA*, *EU_DISC*, *INP*) [POC Loop may Repeat]

IMPORTANT NOTE: Dummy POC loops are not required on 860 transactions.

CTT*Number of POC Segments
SE*Number of Segments*TRAN SET CONTROL #

18.6 DATA DICTIONARY

18.6.1 850 Interim Number Portability Service Request (850INP)

Functional Group ID=**PO**

Introduction:

The 850INP will be used by the Co-Provider to initiate Interim Number Portability Service Requests to Qwest.

This implementation guideline references the following:

1. ANSI ASC X12 Version 4020
2. LSOG5 and Qwest assigned fields
3. TCIF/SOSC Guidelines ELMS 5

Notes:

This 850 Transaction includes the mappings for Local Service Request, End User, and Number Portability.

Heading:

	<u>Pos. No.</u>	<u>Seg. ID</u>	<u>Name</u>	<u>Req. Des.</u>	<u>Max.Use</u>	<u>Loop Repeat</u>	<u>Notes and Comments</u>
M	0100	ST	Transaction Set Header	M	1		
M	0200	BEG	Beginning Segment for Purchase Order	M	1		
	0500	REF	Reference Identification	O	>1		
	0950	PAM	Period Amount	O	10		
	1500	DTM	Date/Time Reference	O	10		
	1850	SI	Service Characteristic Identification	O	>1		
	1900	PID	Product/Item Description	O	200		
						LOOP ID - N9	1000
	2950	N9	Reference Identification	O	1		
	3000	MTX	Text	O	>1		
						LOOP ID - N9	1000
	2950	N9	Reference Identification	O	1		
	3000	MTX	Text	O	>1		
						LOOP ID - N9	1000
	2950	N9	Reference Identification	O	1		
	3000	MTX	Text	O	>1		
						LOOP ID - N1	200
	3100	N1	Name	O	1		
	3600	PER	Administrative Communications Contact	O	>1		
						LOOP ID - N1	200
	3100	N1	Name	O	1		
						LOOP ID - N1	200

3100	N1	Name	O	1
3200	N2	Additional Name Information	O	2
3400	N4	Geographic Location	O	>1
3450	NX2	Location ID Component	O	>1
3600	PER	Administrative Communications Contact	O	>1
3650	SI	Service Characteristic Identification	O	>1

Detail:

Pos. No.	Seg. ID	Name	Req. Des.	Max.Use	Loop Repeat	Notes and Comments
LOOP ID - PO1						100000
M	0100	PO1	Baseline Item Data - End User Form (Location and Access Section)	M	1	n1
LOOP ID - N1						200
	3500	N1	Name	O	1	
	3800	N4	Geographic Location	O	1	
	3850	NX2	Location ID Component	O	>1	
	4050	SI	Service Characteristic Identification	O	>1	
LOOP ID - PO1						100000
M	0100	PO1	Baseline Item Data - End User Form (Disconnect Information Section)	M	1	n2
	0180	SI	Service Characteristic Identification	O	>1	
	1000	REF	Reference Identification	O	>1	
	2100	DTM	Date/Time Reference	O	10	
LOOP ID - SLN						>1
	4700	SLN	Subline Item Detail	O	1	
	4800	SI	Service Characteristic Identification	O	>1	
LOOP ID - N1						10
	5350	N1	Name	O	1	
	5800	REF	Reference Identification	O	12	
LOOP ID - SLN						>1
	4700	SLN	Subline Item Detail	O	1	
	4800	SI	Service Characteristic Identification	O	>1	
LOOP ID - N1						10
	5350	N1	Name	O	1	
	5800	REF	Reference Identification	O	12	
LOOP ID - PO1						100000
M	0100	PO1	Baseline Item Data - NP Form (Service Details Section)	M	1	n3
	0180	SI	Service Characteristic Identification	O	>1	
	1000	REF	Reference Identification	O	>1	
	2100	DTM	Date/Time Reference	O	10	
LOOP ID - QTY						>1
	2930	QTY	Quantity	O	1	
LOOP ID - N1						200
	3500	N1	Name	O	1	
LOOP ID - SLN						>1

	4700	SLN	Subline Item Detail	O	1	
	4800	SI	Service Characteristic Identification	O	>1	
					LOOP ID - N1	10
	5350	N1	Name	O	1	
	5800	REF	Reference Identification	O	12	
					LOOP ID - SLN	>1
	4700	SLN	Subline Item Detail	O	1	
	4800	SI	Service Characteristic Identification	O	>1	
					LOOP ID - N1	10
	5350	N1	Name	O	1	
	5800	REF	Reference Identification	O	12	
					LOOP ID - SLN	>1
	4700	SLN	Subline Item Detail	O	1	
	4800	SI	Service Characteristic Identification	O	>1	
					LOOP ID - PO1	100000
M	0100	PO1	Baseline Item Data - Dummy	M	1	n4

Summary:

	<u>Pos. No.</u>	<u>Seg. ID</u>	<u>Name</u>	<u>Req. Des.</u>	<u>Max.Use</u>	<u>Loop Repeat</u>	<u>Notes and Comments</u>
						LOOP ID - CTT	1
	0100	CTT	Transaction Totals	O	1		n5
M	0300	SE	Transaction Set Trailer	M	1		

Transaction Set Notes

1. PO102 is required.
2. PO102 is required.
3. PO102 is required.
4. PO102 is required.
5. The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

Segment: **ST** Transaction Set Header

Position: 0100

Loop:

Level: Heading

Usage: Mandatory

Max Use: 1

Purpose: To indicate the start of a transaction set and to assign a control number

Syntax Notes:

Semantic Notes:

- 1 The transaction set identifier (ST01) is used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).
- 2 The implementation convention reference (ST03) is used by the translation routines of the interchange partners to select the appropriate implementation convention to match the transaction set definition.

Comments:

Notes: ST*850*TRAN SET CONTROL #

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	ST01	143	Transaction Set Identifier Code Code uniquely identifying a Transaction Set 850 Purchase Order	M ID 3/3
M	ST02	329	Transaction Set Control Number Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set	M AN 4/9

Segment: **BEG** Beginning Segment for Purchase Order
Position: 0200
Loop:
Level: Heading
Usage: Mandatory
Max Use: 1
Purpose: To indicate the beginning of the Purchase Order Transaction Set and transmit identifying numbers and dates

Syntax Notes:
Semantic Notes: 1 BEG05 is the date assigned by the purchaser to purchase order.

Comments:
Notes: BEG*00*SS*PON (LSR-2)**PO Date (See Trading Partner Access Information)

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Element</u>	<u>Name</u>	<u>Attributes</u>
M	BEG01	353		Transaction Set Purpose Code Code identifying purpose of transaction set 00 Original	M ID 2/2
M	BEG02	92		Purchase Order Type Code Code specifying the type of Purchase Order SS Supply or Service Order	M ID 2/2
M	BEG03	324		Purchase Order Number Identifying number for Purchase Order assigned by the orderer/purchaser PON (LSR-2) = Purchase Order Number	M AN 1/22
M	BEG05	373		Date Date expressed as CCYYMMDD PO Date = Purchase Order Date (See Trading Partner Access Information)	M DT 8/8

Segment: **REF** Reference Identification

Position: 0500

Loop:

Level: Heading

Usage: Optional

Max Use: >1

Purpose: To specify identifying information

- Syntax Notes:**
- 1 At least one of REF02 or REF03 is required.
 - 2 If either C04003 or C04004 is present, then the other is required.
 - 3 If either C04005 or C04006 is present, then the other is required.
- Semantic Notes:**
- 1 REF04 contains data relating to the value cited in REF02.

Comments:

Notes:

```
REF*11*AN (LSR-7)*AN
REF*12*BAN1 (LSR-61)*BAN1
REF*JB*PROJECT (LSR-20)
REF*SU*RTR (LSR-28)*RTR
REF*CO*RPON (LSR-51)*RPON
REF*1V*RORD (LSR-52)*RORD
```

Data Element Summary

M	Ref. Des.	Data Element	Name	Attributes	
				M	ID 2/3
	REF01	128	Reference Identification Qualifier		
			Code qualifying the Reference Identification		
			11 Account Number		
			Number identifies a telecommunications industry account		
			12 Billing Account		
			Account number under which billing is rendered		
			1V Related Vendor Order Number		
			A vendor's order number that is in addition to a primary order number		
			CO Customer Order Number		
			JB Job (Project) Number		
			SU Special Processing Code		
			Unique code identifying the special handling requirements for the claim		
	REF02	127	Reference Identification	X	AN 1/30
			Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier		
			AN (LSR-7) = Account Number		
			BAN1 (LSR-61) = Billing Account Number 1		
			PROJECT (LSR-20) = Project Identification		
			RTR (LSR-28) = Response Type Requested		
			RPON (LSR-51) = Related Purchase Order Number		
			RORD (LSR-52) = Related Order Number		
	REF03	352	Description	X	AN 1/80
			A free-form description to clarify the related data elements and their content		
			"AN"		
			"BAN1"		
			"RTR"		
			"RPON"		

"RORD"

Segment: **PAM** Period Amount

Position: 0950

Loop:

Level: Heading

Usage: Optional

Max Use: 10

Purpose: To indicate a quantity, and/or amount for an identified period

Syntax Notes:

- 1 If any of PAM01 PAM02 or PAM03 is present, then all are required.
- 2 At least one of PAM02 PAM05 or PAM14 is required.
- 3 If either PAM04 or PAM05 is present, then the other is required.
- 4 If either PAM06 or PAM07 is present, then the other is required.
- 5 If PAM07 is present, then at least one of PAM08 or PAM09 is required.
- 6 If PAM07 is present, then PAM06 is required.
- 7 If PAM08 is present, then PAM07 is required.
- 8 If PAM09 is present, then PAM07 is required.
- 9 If PAM10 is present, then at least one of PAM11 or PAM12 is required.
- 10 If PAM11 is present, then PAM10 is required.
- 11 If either PAM13 or PAM14 is present, then the other is required.

Semantic Notes:

- 1 PAM10, PAM11, or PAM12 are used when two dates are required.
- 2 PAM15 indicates whether the monetary amount identified in PAM05 is a net or gross value. A "Y" indicates amount is a gross value; an "N" indicates amount is a net value.

Comments:

Notes:

```
PAM*48*PG_of_ (LSR-10) (1st 2 Bytes)*EA
PAM*47*PG_of_ (LSR-10) (2nd 2 Bytes)*EA
PAM*OC*NPQTY (NP-5)*EA
```

Data Element Summary

Ref.	Data	Name	Attributes
Des.	Element		
PAM01	673	Quantity Qualifier	X ID 2/2
		Code specifying the type of quantity	
		47 Primary Net Quantity	
		48 Secondary Net Quantity	
		OC Order Count	
PAM02	380	Quantity	X R 1/15
		Numeric value of quantity	
		First 2 bytes of PG_of_ (LSR-10)	
		Second 2 bytes of PG_of_ (LSR-10)	
		NPQTY (NP-5) = Number Portability Quantity	
PAM03	C001	Composite Unit of Measure	X
		To identify a composite unit of measure (See Figures Appendix for examples of use)	
M	C00101	355 Unit or Basis for Measurement Code	M ID 2/2
		Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken	
		EA Each	

Segment: **DTM** Date/Time Reference

Position: 1500

Loop:

Level: Heading

Usage: Optional

Max Use: 10

Purpose: To specify pertinent dates and times

Syntax Notes: 1 At least one of DTM02 DTM03 or DTM05 is required.

2 If DTM04 is present, then DTM03 is required.

3 If either DTM05 or DTM06 is present, then the other is required.

Semantic Notes:

Comments:

Notes:

DTM*097*D/TSENT{CCYYMMDD} (LSR-12)*D/TSENT{HHMM} (LSR-12)

DTM*150*DDD{CCYYMMDD} (LSR-14)

DTM*992****TM*DFDT(HHMM) (LSR-19)

DTM*270*DATED{CCYYMMDD} (LSR-36)

Data Element Summary

Ref.	Data	Name	Attributes
Des.	Element		
M	DTM01	374 Date/Time Qualifier	M ID 3/3
		Code specifying type of date or time, or both date and time	
		097 Transaction Creation	
		150 Service Period Start	
		270 Date Filed	
		992 Date Requested	
	DTM02	373 Date	X DT 8/8
		Date expressed as CCYYMMDD	
		D/TSENT (LSR-12) = Date Sent	
		DDD (LSR-14) = Desired Due Date	
		DATED (LSR-36) = Date of Agency Authorization	
	DTM03	337 Time	X TM 4/8
		Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)	
		D/TSENT{HHMM} (LSR-12) = Time Sent	
	DTM05	1250 Date Time Period Format Qualifier	X ID 2/3
		Code indicating the date format, time format, or date and time format	
		TM Time Expressed in Format HHMM	
		Time expressed in the format HHMM where HH is the numerical expression of hours in the day based on a twenty-four hour clock and MM is the numerical expression of minutes within an hour	
	DTM06	1251 Date Time Period	X AN 1/35
		Expression of a date, a time, or range of dates, times or dates and times	
		DFDT {HHMM} (LSR-19) = Desired Frame Due Time	

Segment: **SI** Service Characteristic Identification
Position: 1850
Loop:
Level: Heading
Usage: Optional
Max Use: >1
Purpose: To specify service characteristic data
Syntax Notes:

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

Semantic Notes:

Comments: 1 SI01 defines the source for each of the service characteristics qualifiers.

Notes: SI*TI*RE*REQTYP (LSR-23)
SI*TI*AA*ACT (LSR-24)
SI*TI*TY*TOS (LSR-44)

Data Element Summary

Ref.	Data			Attributes
<u>Des.</u>	<u>Element</u>	<u>Name</u>		
M	SI01	559	Agency Qualifier Code	M ID 2/2
			Code identifying the agency assigning the code values	
			TI Telecommunications Industry	
M	SI02	1000	Service Characteristics Qualifier	M AN 2/2
			Code from an industry code list qualifying the type of service characteristics	
			AA Account Activity	
			RE Requisition Type	
			TY Type of Service	
M	SI03	234	Product/Service ID	M AN 1/48
			Identifying number for a product or service	
			ACT (LSR-24) = Activity	
			D= (DWS: D = Disconnect)	
			C= (DWS: C = Change)	
			V= (DWS: V = Conversion as specified)	
			Z= (DWS: Z = Total Conversion as Spec/no listing)	
			TOS (LSR-44) = Type of Service	
			REQTYP (LSR-23) = Requisition Type and Status	

Segment: **PID** Product/Item Description

Position: 1900

Loop:

Level: Heading

Usage: Optional

Max Use: 200

Purpose: To describe a product or process in coded or free-form format

Syntax Notes:

- 1 If PID04 is present, then PID03 is required.
- 2 At least one of PID04 or PID05 is required.
- 3 If PID07 is present, then PID03 is required.
- 4 If PID08 is present, then PID04 is required.
- 5 If PID09 is present, then PID05 is required.

Semantic Notes:

- 1 Use PID03 to indicate the organization that publishes the code list being referred to.
- 2 PID04 should be used for industry-specific product description codes.
- 3 PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
- 4 PID09 is used to identify the language being used in PID05.

Comments:

- 1 If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
- 2 Use PID06 when necessary to refer to the product surface or layer being described in the segment.
- 3 PID07 specifies the individual code list of the agency specified in PID03.

Notes:

PID*S**TI*CONVIND***SO-RSQ*CONVIND (LSR-24a)
 PID*S**TI*AO***SO-RSQ*AGAUTH (LSR-35)
 PID*S**TI*BI***SO-RSQ*FBI (EU-42)
 PID*S**TI*PENDING***SO-RSQ*PENDING ORDER (LSR-108b)

Data Element Summary

Ref.	Data Element	Name	Attributes
M	PID01	Item Description Type	M ID 1/1
		Code indicating the format of a description	
		S Structured (From Industry Code List)	
	PID03	Agency Qualifier Code	X ID 2/2
		Code identifying the agency assigning the code values	
		TI Telecommunications Industry	
	PID04	Product Description Code	X AN 1/12
		A code from an industry code list which provides specific data about a product characteristic	
		AO Agency Authorization Status	
		BI Final Bill Information Indicator	
		CONVIND Conversion Indicator	
		PENDING Pending Order	
	PID07	Source Subqualifier	O AN 1/15
		A reference that indicates the table or text maintained by the Source Qualifier	
		SO-RSQ Service Order - Reseller Question list	
	PID08	Yes/No Condition or Response Code	O ID 1/1
		Code indicating a Yes or No condition or response	
		FBI (EU-42) = Final Bill Information Indicator	

Y= (DWS: D (Different))
N= (DWS: E (Existing (Default)))

CONVIND (LSR-24a) = Conversion Indicator

Y= (DWS: F - Full)
N= (DWS: P - Partial)

AGAUTH (LSR-35) = Agency Authorization Status

PENDING ORDER (LSR-108b) = Pending Order Indicator

Segment: **N9** Reference Identification
Position: 2950
Loop: N9 Optional
Level: Heading
Usage: Optional
Max Use: 1
Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Syntax Notes:
 1 At least one of N902 or N903 is required.
 2 If N906 is present, then N905 is required.
 3 If either C04003 or C04004 is present, then the other is required.
 4 If either C04005 or C04006 is present, then the other is required.

Semantic Notes:
 1 N906 reflects the time zone which the time reflects.
 2 N907 contains data relating to the value cited in N902.

Comments:

Notes: N9*H7*ORI*INP****2W>MANUAL IND (NP-34a)

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	N901	128	Reference Identification Qualifier Code qualifying the Reference Identification H7 Standard Clause	M ID 2/3
	N902	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier ORI Order Instructions	X AN 1/30
	N903	369	Free-form Description Free-form descriptive text	X AN 1/45
	N907	C040	Reference Identifier To identify one or more reference numbers or identification numbers as specified by the Reference Qualifier	O
M	C04001	128	Reference Identification Qualifier Code qualifying the Reference Identification 2W Change Order Authority	M ID 2/3
M	C04002	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier MANUAL IND (NP-34a) = Manual Indicator	M AN 1/30

Segment: **MTX** Text
Position: 3000
Loop: N9 Optional
Level: Heading
Usage: Optional
Max Use: >1
Purpose: To specify textual data
Syntax Notes:

- 1 If MTX01 is present, then MTX02 is required.
- 2 If MTX03 is present, then MTX02 is required.
- 3 If MTX05 is present, then MTX04 is required.

Semantic Notes:

- 1 MTX05 is the number of lines to advance before printing.

Comments:

- 1 If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

Notes: MTX**REMARKS (NP-34)

Data Element Summary

<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
<u>Des.</u>	<u>Element</u>		
MTX02	1551	Message Text	X AN 1/4096
		To transmit large volumes of message text	
		REMARKS (NP-34) = Remarks	

Segment: **N9 Reference Identification**
Position: 2950
Loop: N9 Optional
Level: Heading
Usage: Optional
Max Use: 1
Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Syntax Notes:
 1 At least one of N902 or N903 is required.
 2 If N906 is present, then N905 is required.
 3 If either C04003 or C04004 is present, then the other is required.
 4 If either C04005 or C04006 is present, then the other is required.

Semantic Notes:
 1 N906 reflects the time zone which the time reflects.
 2 N907 contains data relating to the value cited in N902.

Comments:

Notes: N9*H7*ORI*LSR****2W>MANUAL IND (LSR-108a)

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	N901	128	Reference Identification Qualifier Code qualifying the Reference Identification H7 Standard Clause	M ID 2/3
	N902	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier ORI Order Instructions	X AN 1/30
	N903	369	Free-form Description Free-form descriptive text	X AN 1/45
	N907	C040	Reference Identifier To identify one or more reference numbers or identification numbers as specified by the Reference Qualifier	O
M	C04001	128	Reference Identification Qualifier Code qualifying the Reference Identification 2W Change Order Authority	M ID 2/3
M	C04002	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier MANUAL IND (LSR-108a) = Manual Indicator	M AN 1/30

Segment: **MTX** Text
Position: 3000
Loop: N9 Optional
Level: Heading
Usage: Optional
Max Use: >1
Purpose: To specify textual data
Syntax Notes:

- 1 If MTX01 is present, then MTX02 is required.
- 2 If MTX03 is present, then MTX02 is required.
- 3 If MTX05 is present, then MTX04 is required.

Semantic Notes:

- 1 MTX05 is the number of lines to advance before printing.

Comments:

- 1 If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

Notes: MTX**REMARKS (LSR-108)

Data Element Summary

<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
<u>Des.</u>	<u>Element</u>		
MTX02	1551	Message Text	X AN 1/4096
		To transmit large volumes of message text	
		REMARKS (LSR-108) = Remarks	

Segment: **N9 Reference Identification**
Position: 2950
Loop: N9 Optional
Level: Heading
Usage: Optional
Max Use: 1
Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Syntax Notes:
 1 At least one of N902 or N903 is required.
 2 If N906 is present, then N905 is required.
 3 If either C04003 or C04004 is present, then the other is required.
 4 If either C04005 or C04006 is present, then the other is required.

Semantic Notes:
 1 N906 reflects the time zone which the time reflects.
 2 N907 contains data relating to the value cited in N902.

Comments:

Notes: N9*H7*ORI*EU****2W>MANUAL IND (EU-63a)

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	N901	128	Reference Identification Qualifier Code qualifying the Reference Identification H7 Standard Clause	M ID 2/3
	N902	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier ORI Order Instructions	X AN 1/30
	N903	369	Free-form Description Free-form descriptive text	X AN 1/45
	N907	C040	Reference Identifier To identify one or more reference numbers or identification numbers as specified by the Reference Qualifier	O
M	C04001	128	Reference Identification Qualifier Code qualifying the Reference Identification 2W Change Order Authority	M ID 2/3
M	C04002	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier MANUAL IND (EU-63a) = Manual Indicator	M AN 1/30

Segment: **MTX** Text
Position: 3000
Loop: N9 Optional
Level: Heading
Usage: Optional
Max Use: >1
Purpose: To specify textual data
Syntax Notes:

- 1 If MTX01 is present, then MTX02 is required.
- 2 If MTX03 is present, then MTX02 is required.
- 3 If MTX05 is present, then MTX04 is required.

Semantic Notes:

- 1 MTX05 is the number of lines to advance before printing.

Comments:

- 1 If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

Notes: MTX**REMARKS (EU-63)

Data Element Summary

<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
<u>Des.</u>	<u>Element</u>		
MTX02	1551	Message Text To transmit large volumes of message text REMARKS (EU-63) = Remarks	X AN 1/4096

Segment: **N1** Name
Position: 3100
Loop: N1 Optional
Level: Heading
Usage: Optional
Max Use: 1
Purpose: To identify a party by type of organization, name, and code
Syntax Notes:

- 1 At least one of N102 or N103 is required.
- 2 If either N103 or N104 is present, then the other is required.

Semantic Notes:
Comments:

- 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
- 2 N105 and N106 further define the type of entity in N101.

Notes: N1*78*CCNA (LSR-1)

Data Element Summary

Ref. Des.	Data Element	Name	Attributes
M	N101	98 Entity Identifier Code Code identifying an organizational entity, a physical location, property or an individual 78 Service Requester	M ID 2/3
	N102	93 Name Free-form name CCNA (LSR-1) = Customer Carrier Name Abbreviation	X AN 1/60

Segment: **PER** Administrative Communications Contact
Position: 3600
Loop: N1 Optional
Level: Heading
Usage: Optional
Max Use: >1
Purpose: To identify a person or office to whom administrative communications should be directed

Syntax Notes:
1 If either PER03 or PER04 is present, then the other is required.
2 If either PER05 or PER06 is present, then the other is required.
3 If either PER07 or PER08 is present, then the other is required.

Semantic Notes:

Comments:

Notes: PER*AG*INIT (LSR-81)*TE*TEL NO (LSR-82)*FX*FAX NO (LSR-84)*EM*EMAIL (LSR-83)

PER*CN*IMPCON (LSR-91)*TE*TEL NO (LSR-92)

Data Element Summary

Ref.	Data	Name	Attributes
Des.	Element		
M	PER01	366 Contact Function Code Code identifying the major duty or responsibility of the person or group named AG Agent CN General Contact	M ID 2/2
	PER02	93 Name Free-form name INIT (LSR-81) = Initiator Identification IMPCON (LSR-91) = Implementation Contact	O AN 1/60
	PER03	365 Communication Number Qualifier Code identifying the type of communication number TE Telephone	X ID 2/2
	PER04	364 Communication Number Complete communications number including country or area code when applicable TEL NO (LSR-82) = Telephone Number TEL NO (LSR-92) = Telephone Number	X AN 1/256
	PER05	365 Communication Number Qualifier Code identifying the type of communication number FX Facsimile	X ID 2/2
	PER06	364 Communication Number Complete communications number including country or area code when applicable FAX NO (LSR-84) = Facsimile Number	X AN 1/256
	PER07	365 Communication Number Qualifier Code identifying the type of communication number EM Electronic Mail	X ID 2/2
	PER08	364 Communication Number Complete communications number including country or area code when applicable	X AN 1/256

EMAIL (LSR-83) = Electronic Mail Address

Segment: **N1** Name
Position: 3100
Loop: N1 Optional
Level: Heading
Usage: Optional
Max Use: 1
Purpose: To identify a party by type of organization, name, and code
Syntax Notes:

- 1 At least one of N102 or N103 is required.
- 2 If either N103 or N104 is present, then the other is required.

Semantic Notes:
Comments:

- 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
- 2 N105 and N106 further define the type of entity in N101.

Notes: N1*AN*AUTHNM (LSR-37)

Data Element Summary

Ref.	Data	Name	Attributes
<u>Des.</u>	<u>Element</u>	<u>Name</u>	<u>Attributes</u>
M	N101	98 Entity Identifier Code Code identifying an organizational entity, a physical location, property or an individual AN Authorized From A geographic location designated as an authorized pick-up or origin point for a shipment	M ID 2/3
	N102	93 Name Free-form name AUTHNM (LSR-37) = Authorization Name	X AN 1/60

Segment: **N1** Name
Position: 3100
Loop: N1 Optional
Level: Heading
Usage: Optional
Max Use: 1
Purpose: To identify a party by type of organization, name, and code
Syntax Notes: 1 At least one of N102 or N103 is required.
 2 If either N103 or N104 is present, then the other is required.
Semantic Notes:
Comments: 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
 2 N105 and N106 further define the type of entity in N101.
Notes: N1*X1*BILLNM (EU-43)

Data Element Summary

Ref.	Data	Name	Attributes
Des.	Element		
M	N101	98 Entity Identifier Code	M ID 2/3
		Code identifying an organizational entity, a physical location, property or an individual	
		X1 Mail to	
		An address to which a specified item is to be mailed	
	N102	93 Name	X AN 1/60
		Free-form name	
		BILLNM (EU-43) = Bill Name	

Segment: **N2** Additional Name Information
Position: 3200
Loop: N1 Optional
Level: Heading
Usage: Optional
Max Use: 2
Purpose: To specify additional names
Syntax Notes:
Semantic Notes:
Comments:
Notes: N2*SBILLNM (EU-44)

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>	<u>Name</u>	
M	N201	93	Name Free-form name SBILLNM (EU-44) = Secondary Bill Name	M AN 1/60

Segment: **N4** Geographic Location

Position: 3400

Loop: N1 Optional

Level: Heading

Usage: Optional

Max Use: >1

Purpose: To specify the geographic place of the named party

- Syntax Notes:**
- 1 Only one of N402 or N407 may be present.
 - 2 If N406 is present, then N405 is required.
 - 3 If N407 is present, then N404 is required.

Semantic Notes:

- Comments:**
- 1 A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
 - 2 N402 is required only if city name (N401) is in the U.S. or Canada.

Notes: N4**STATE (EU-49)*ZIP (EU-50)

Data Element Summary

<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
N402	156	State or Province Code Code (Standard State/Province) as defined by appropriate government agency STATE (EU-49) = State/Province	X ID 2/2
N403	116	Postal Code Code defining international postal zone code excluding punctuation and blanks (zip code for United States) ZIP (EU-50) = ZIP/Postal Code	O ID 3/15

Segment: **NX2** Location ID Component
Position: 3450
Loop: N1 Optional
Level: Heading
Usage: Optional
Max Use: >1
Purpose: To define types and values of a geographic location
Syntax Notes:
Semantic Notes:
Comments:
Notes:

NX2*01*SANO (EU-45b)
 NX2*02*SASN (EU-45e)
 NX2*03*SASD (EU-45d)
 NX2*07*CITY (EU-48)
 NX2*32*FLOOR (EU-46)
 NX2*35*ROOM/MAIL STOP (EU-47)
 NX2*40*SASS (EU-45g)
 NX2*59*SAPR (EU-45a)
 NX2*61*SASF (EU-45c)
 NX2*62*SATH (EU-45f)

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	NX201	1106	Address Component Qualifier Code qualifying the type of address component 01 Street Number 02 Street Name 03 Prefix Direction 07 City Name 32 Floor A particular floor or level of a building 35 Room A walled room or partitioned area of a building 40 Street Suffix 59 Street Number Low 61 Street Number Fraction 62 Street Name Suffix	M ID 2/2
M	NX202	166	Address Information Address information SANO (EU-45b) = Service Address Number SASN (EU-45e) = Service Address Street Name SASD (EU-45d) = Service Address Street Directional Prefix CITY (EU-48) = City FLOOR (EU-46) = Floor ROOM/MAIL STOP (EU-47) = Room/Mail Stop SASS (EU-45g) = Service Address Street Directional Suffix SAPR (EU-45a) = Service Address Number Prefix SASF (EU-45c) = Street Address Number Suffix SATH (EU-45f) = Service Address Street Type	M AN 1/55

Segment: **PER** Administrative Communications Contact
Position: 3600
Loop: N1 Optional
Level: Heading
Usage: Optional
Max Use: >1
Purpose: To identify a person or office to whom administrative communications should be directed

- Syntax Notes:**
- 1 If either PER03 or PER04 is present, then the other is required.
 - 2 If either PER05 or PER06 is present, then the other is required.
 - 3 If either PER07 or PER08 is present, then the other is required.

Semantic Notes:

Comments:

Notes: PER*BI*BILLCON (EU-51)*TE*TEL NO (EU-52)

Data Element Summary

Ref. Des.	Data Element	Name	Attributes
M PER01	366	Contact Function Code Code identifying the major duty or responsibility of the person or group named BI Bill Inquiry Contact Service Provider contact for making inquires about information on the invoice	M ID 2/2
PER02	93	Name Free-form name BILLCON (EU-51) = Billing Contact	O AN 1/60
PER03	365	Communication Number Qualifier Code identifying the type of communication number TE Telephone	X ID 2/2
PER04	364	Communication Number Complete communications number including country or area code when applicable TEL NO (EU-52) = Telephone Number	X AN 1/256

Segment: **SI** Service Characteristic Identification

Position: 3650

Loop: N1 Optional

Level: Heading

Usage: Optional

Max Use: >1

Purpose: To specify service characteristic data

Syntax Notes:

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

Semantic Notes:

Comments: 1 SI01 defines the source for each of the service characteristics qualifiers.

Notes: SI*TI*AF*AFT (EU-44a)

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	SI01	559	Agency Qualifier Code Code identifying the agency assigning the code values TI Telecommunications Industry	M ID 2/2
M	SI02	1000	Service Characteristics Qualifier Code from an industry code list qualifying the type of service characteristics AF Address Format Type	M AN 2/2
M	SI03	234	Product/Service ID Identifying number for a product or service AFT (EU-44a) = Address Format Type	M AN 1/48

Segment: **PO1** **Baseline Item Data - End User Form (Location and Access Section)**

Position: 0100

Loop: PO1 Mandatory

Level: Detail

Usage: Mandatory

Max Use: 1

Purpose: To specify basic and most frequently used line item data

- Syntax Notes:**
- 1 If PO103 is present, then PO102 is required.
 - 2 If PO105 is present, then PO104 is required.
 - 3 If either PO106 or PO107 is present, then the other is required.
 - 4 If either PO108 or PO109 is present, then the other is required.
 - 5 If either PO110 or PO111 is present, then the other is required.
 - 6 If either PO112 or PO113 is present, then the other is required.
 - 7 If either PO114 or PO115 is present, then the other is required.
 - 8 If either PO116 or PO117 is present, then the other is required.
 - 9 If either PO118 or PO119 is present, then the other is required.
 - 10 If either PO120 or PO121 is present, then the other is required.
 - 11 If either PO122 or PO123 is present, then the other is required.
 - 12 If either PO124 or PO125 is present, then the other is required.

Semantic Notes:

- Comments:**
- 1 See the Data Element Dictionary for a complete list of IDs.
 - 2 PO101 is the line item identification.
 - 3 PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Notes: PO1*n*1*EA***ZZ*EU_SA [PO1 Loop may repeat]

Data Element Summary

Ref.	Data			
<u>Des.</u>	<u>Element</u>	<u>Name</u>	<u>Attributes</u>	
PO101	350	Assigned Identification	O	AN 1/20
		Alphanumeric characters assigned for differentiation within a transaction set		
		"n" = nth assigned ID within PO1 loop		
PO102	330	Quantity Ordered	X	R 1/15
		Quantity ordered		
		1 Always One		
PO103	355	Unit or Basis for Measurement Code	O	ID 2/2
		Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken		
		EA Each		
PO106	235	Product/Service ID Qualifier	X	ID 2/2
		Code identifying the type/source of the descriptive number used in Product/Service ID (234)		
		ZZ Mutually Defined		
PO107	234	Product/Service ID	X	AN 1/48
		Identifying number for a product or service		
		"EU_SA"		

Segment: **N1** Name

Position: 3500

Loop: N1 Optional

Level: Detail

Usage: Optional

Max Use: 1

Purpose: To identify a party by type of organization, name, and code

Syntax Notes: 1 At least one of N102 or N103 is required.

2 If either N103 or N104 is present, then the other is required.

Semantic Notes:

Comments:

1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.

2 N105 and N106 further define the type of entity in N101.

Notes: N1*IT*NAME (EU-8)

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>		
M	N101	98	Entity Identifier Code Code identifying an organizational entity, a physical location, property or an individual IT Installation on Site	M ID 2/3
	N102	93	Name Free-form name NAME (EU-8) = End User Name	X AN 1/60

Segment: **N4** Geographic Location

Position: 3800

Loop: N1 Optional

Level: Detail

Usage: Optional

Max Use: 1

Purpose: To specify the geographic place of the named party

Syntax Notes: 1 Only one of N402 or N407 may be present.

2 If N406 is present, then N405 is required.

3 If N407 is present, then N404 is required.

Semantic Notes:

Comments: 1 A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.

2 N402 is required only if city name (N401) is in the U.S. or Canada.

Notes: N4**STATE (EU-25)*ZIP (EU-26)**RJ*CALA (EU-26a)

Data Element Summary

<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
N402	156	State or Province Code Code (Standard State/Province) as defined by appropriate government agency STATE (EU-25) = State/Province	X ID 2/2
N403	116	Postal Code Code defining international postal zone code excluding punctuation and blanks (zip code for United States) ZIP (EU-26) = ZIP/Postal Code	O ID 3/15
N405	309	Location Qualifier Code identifying type of location RJ Region	X ID 1/2
N406	310	Location Identifier Code which identifies a specific location CALA (EU-26a) = Customer Address Location Area	O AN 1/30

Segment: **NX2** Location ID Component
Position: 3850
Loop: N1 Optional
Level: Detail
Usage: Optional
Max Use: >1
Purpose: To define types and values of a geographic location
Syntax Notes:
Semantic Notes:
Comments:
Notes:

NX2*01*SANO (EU-11)
 NX2*02*SASN (EU-14)
 NX2*03*SASD (EU-13)
 NX2*05*BOX (EU-23c)
 NX2*06*ROUTE (EU-23b)
 NX2*07*CITY (EU-24)
 NX2*39*AHN (EU-23a)
 NX2*40*SASS (EU-16)
 NX2*59*SAPR (EU-10)
 NX2*61*SASF (EU-12)
 NX2*62*SATH (EU-15)
 NX2*LD1 (EU-17)*LV1 (EU-18)
 NX2*LD2 (EU-19)*LV2 (EU-20)
 NX2*LD3 (EU-21)*LV3 (EU-22)

Data Element Summary

Ref.	Data			Attributes
<u>Des.</u>	<u>Element</u>	<u>Name</u>		
M	NX201	1106	Address Component Qualifier	M ID 2/2
			Code qualifying the type of address component	
			LD1 (EU-17) = Location Designator 1	
			13 = (DWS: APT)	
			34 = (DWS: LOT)	
			35 = (DWS: RM)	
			36 = (DWS: SLIP)	
			37 = (DWS: UNIT)	
			14 = (DWS: SUIT)	
			LD2 (EU-19) = Location Designator 2	
			32 = (DWS: FLR)	
			LD3 (EU-21) = Location Designator 3	
			12 = (DWS: BLDG)	
			63 = (DWS: WNG)	
			30 = (DWS: PIER)	
			01 Street Number	
			02 Street Name	
			03 Prefix Direction	
			05 P.O. Box Number	
			06 Rural Route Number	
			07 City Name	
			12 Building Name	
			13 Apartment Number	

14	Suite Number
30	Pier The pier at which a ship or boat is docked
32	Floor A particular floor or level of a building
34	Lot A particular lot or piece of land
35	Room A walled room or partitioned area of a building
36	Slip The slip or location on a pier at which a ship or boat is docked
37	Unit A unit or separate structure
39	Unstructured Property
40	Street Suffix
59	Street Number Low
61	Street Number Fraction
62	Street Name Suffix
63	Secondary Unit Identifier

M **NX202** **166** **Address Information** **M** **AN 1/55**

Address information

SANO (EU-11) = Service Address Number
SASN (EU-14) = Service Address Street Name
SASD (EU-13) = Service Address Street Directional Prefix
BOX (EU-23c) = Box
ROUTE (EU-23b) = Route
CITY (EU-24) = City
AHN (EU-23a) = Assigned House Number
SASS (EU-16) = Service Address Street Directional Suffix
SAPR (EU-10) = Service Address Number Prefix
SASF (EU-12) = Service Address Number Suffix
SATH (EU-15) = Service Address Street Type
LV1 (EU-18) = Location Value 1
LV2 (EU-20) = Location Value 2
LV3 (EU-22) = Location Value 3

Segment: **SI** Service Characteristic Identification

Position: 4050

Loop: N1 Optional

Level: Detail

Usage: Optional

Max Use: >1

Purpose: To specify service characteristic data

Syntax Notes:

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

Semantic Notes:

Comments: 1 SI01 defines the source for each of the service characteristics qualifiers.

Notes: SI*TI*AF*AFT (EU-9)

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	SI01	559	Agency Qualifier Code Code identifying the agency assigning the code values TI Telecommunications Industry	M ID 2/2
M	SI02	1000	Service Characteristics Qualifier Code from an industry code list qualifying the type of service characteristics AF Address Format Type	M AN 2/2
M	SI03	234	Product/Service ID Identifying number for a product or service AFT (EU-9) = Address Format Type	M AN 1/48

Segment: **PO1** **Baseline Item Data - End User Form (Disconnect Information Section)**

Position: 0100

Loop: PO1 Mandatory

Level: Detail

Usage: Mandatory

Max Use: 1

Purpose: To specify basic and most frequently used line item data

- Syntax Notes:**
- 1 If PO103 is present, then PO102 is required.
 - 2 If PO105 is present, then PO104 is required.
 - 3 If either PO106 or PO107 is present, then the other is required.
 - 4 If either PO108 or PO109 is present, then the other is required.
 - 5 If either PO110 or PO111 is present, then the other is required.
 - 6 If either PO112 or PO113 is present, then the other is required.
 - 7 If either PO114 or PO115 is present, then the other is required.
 - 8 If either PO116 or PO117 is present, then the other is required.
 - 9 If either PO118 or PO119 is present, then the other is required.
 - 10 If either PO120 or PO121 is present, then the other is required.
 - 11 If either PO122 or PO123 is present, then the other is required.
 - 12 If either PO124 or PO125 is present, then the other is required.

Semantic Notes:

- Comments:**
- 1 See the Data Element Dictionary for a complete list of IDs.
 - 2 PO101 is the line item identification.
 - 3 PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Notes: PO1*n*1*EA***ZZ*EU_DISC [PO1 Loop may repeat]

Data Element Summary

Ref.	Data			
<u>Des.</u>	<u>Element</u>	<u>Name</u>	<u>Attributes</u>	
PO101	350	Assigned Identification	O	AN 1/20
		Alphanumeric characters assigned for differentiation within a transaction set		
		"n" = nth assigned ID within PO1 loop		
PO102	330	Quantity Ordered	X	R 1/15
		Quantity ordered		
		1 Always One		
PO103	355	Unit or Basis for Measurement Code	O	ID 2/2
		Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken		
		EA Each		
PO106	235	Product/Service ID Qualifier	X	ID 2/2
		Code identifying the type/source of the descriptive number used in Product/Service ID (234)		
		ZZ Mutually Defined		
PO107	234	Product/Service ID	X	AN 1/48
		Identifying number for a product or service		
		"EU_DISC"		

Segment: **SI** Service Characteristic Identification

Position: 0180

Loop: PO1 Mandatory

Level: Detail

Usage: Optional

Max Use: >1

Purpose: To specify service characteristic data

Syntax Notes:

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

Semantic Notes:

Comments: 1 SI01 defines the source for each of the service characteristics qualifiers.

Notes: SI*TI*ND*DISC NBR (EU-55)
SI*TI*T6*TC OPT(EU-57)

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	SI01	559	Agency Qualifier Code Code identifying the agency assigning the code values TI Telecommunications Industry	M ID 2/2
M	SI02	1000	Service Characteristics Qualifier Code from an industry code list qualifying the type of service characteristics ND Disconnect Number T6 Transfer of Calls Options	M AN 2/2
M	SI03	234	Product/Service ID Identifying number for a product or service DISC NBR (EU-55) = Disconnect Telephone Number TC OPT (EU-57) = Transfer of Call Options	M AN 1/48

Segment: **REF** Reference Identification

Position: 1000

Loop: PO1 Mandatory

Level: Detail

Usage: Optional

Max Use: >1

Purpose: To specify identifying information

Syntax Notes: 1 At least one of REF02 or REF03 is required.

2 If either C04003 or C04004 is present, then the other is required.

3 If either C04005 or C04006 is present, then the other is required.

Semantic Notes: 1 REF04 contains data relating to the value cited in REF02.

Comments:

Notes: REF*IX*DNUM (EU-54)*DNUM

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>		
M	REF01	128	Reference Identification Qualifier Code qualifying the Reference Identification IX Item Number	M ID 2/3
	REF02	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier DNUM (EU-54) = Disconnect Line Number	X AN 1/30
	REF03	352	Description A free-form description to clarify the related data elements and their content "DNUM"	X AN 1/80

Segment: **DTM** Date/Time Reference

Position: 2100

Loop: PO1 Mandatory

Level: Detail

Usage: Optional

Max Use: 10

Purpose: To specify pertinent dates and times

Syntax Notes: 1 At least one of DTM02 DTM03 or DTM05 is required.

2 If DTM04 is present, then DTM03 is required.

3 If either DTM05 or DTM06 is present, then the other is required.

Semantic Notes:

Comments:

Notes: DTM*376*TC PER {CCYYMMDD} (EU-62)

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>		
M	DTM01	374	Date/Time Qualifier Code specifying type of date or time, or both date and time 376 Delivery End The date that deliveries will end	M ID 3/3
	DTM02	373	Date Date expressed as CCYYMMDD TC PER (EU-62) = Transfer of Calls Period	X DT 8/8

Segment: **SLN** Subline Item Detail

Position: 4700

Loop: SLN Optional

Level: Detail

Usage: Optional

Max Use: 1

Purpose: To specify product subline detail item data

Syntax Notes:

- 1 If either SLN04 or SLN05 is present, then the other is required.
- 2 If SLN07 is present, then SLN06 is required.
- 3 If SLN08 is present, then SLN06 is required.
- 4 If either SLN09 or SLN10 is present, then the other is required.
- 5 If either SLN11 or SLN12 is present, then the other is required.
- 6 If either SLN13 or SLN14 is present, then the other is required.
- 7 If either SLN15 or SLN16 is present, then the other is required.
- 8 If either SLN17 or SLN18 is present, then the other is required.
- 9 If either SLN19 or SLN20 is present, then the other is required.
- 10 If either SLN21 or SLN22 is present, then the other is required.
- 11 If either SLN23 or SLN24 is present, then the other is required.
- 12 If either SLN25 or SLN26 is present, then the other is required.
- 13 If either SLN27 or SLN28 is present, then the other is required.

Semantic Notes:

- 1 SLN01 is the identifying number for the subline item.
- 2 SLN02 is the identifying number for the subline level. The subline level is analogous to the level code used in a bill of materials.
- 3 SLN03 is the configuration code indicating the relationship of the subline item to the baseline item.
- 4 SLN08 is a code indicating the relationship of the price or amount to the associated segment.

Comments:

- 1 See the Data Element Dictionary for a complete list of IDs.
- 2 SLN01 is related to (but not necessarily equivalent to) the baseline item number. Example: 1.1 or 1A might be used as a subline number to relate to baseline number 1.
- 3 SLN09 through SLN28 provide for ten different product/service IDs for each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Notes: SLN*TCPRI*n*A*1*EA

Data Element Summary

Ref.	Data	Name	Attributes
Des.	Element		
M	SLN01	350 Assigned Identification	M AN 1/20
		Alphanumeric characters assigned for differentiation within a transaction set	
		"TCPRI"	
	SLN02	350 Assigned Identification	O AN 1/20
		Alphanumeric characters assigned for differentiation within a transaction set	
		"n" = nth assigned ID within SLN loop	
M	SLN03	662 Relationship Code	M ID 1/1
		Code indicating the relationship between entities	
		A Add	
	SLN04	380 Quantity	X R 1/15
		Numeric value of quantity	
		1 Always One	

	SLN05	C001	Composite Unit of Measure	X
			To identify a composite unit of measure (See Figures Appendix for examples of use)	
M	C00101	355	Unit or Basis for Measurement Code	M ID 2/2
			Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken	
			EA Each	

Segment: **SI** Service Characteristic Identification

Position: 4800

Loop: SLN Optional

Level: Detail

Usage: Optional

Max Use: >1

Purpose: To specify service characteristic data

Syntax Notes:

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

Semantic Notes:

Comments: 1 SI01 defines the source for each of the service characteristics qualifiers.

Notes: SI*TI*TC*TC TO PRI (EU-58)

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	SI01	559	Agency Qualifier Code Code identifying the agency assigning the code values TI Telecommunications Industry	M ID 2/2
M	SI02	1000	Service Characteristics Qualifier Code from an industry code list qualifying the type of service characteristics TC Transfer Announcement Number	M AN 2/2
M	SI03	234	Product/Service ID Identifying number for a product or service TC TO PRI (EU-58) = Transfer of Calls To Primary Number	M AN 1/48

Segment: **N1** Name
Position: 5350
Loop: N1 Optional
Level: Detail
Usage: Optional
Max Use: 1
Purpose: To identify a party by type of organization, name, and code
Syntax Notes:

- 1 At least one of N102 or N103 is required.
- 2 If either N103 or N104 is present, then the other is required.

Semantic Notes:
Comments:

- 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
- 2 N105 and N106 further define the type of entity in N101.

Notes: N1*TT*TC NAME (EU-58b)

Data Element Summary

Ref.	Data	Name	Attributes
<u>Des.</u>	<u>Element</u>	<u>Name</u>	<u>Attributes</u>
M	N101	98 Entity Identifier Code Code identifying an organizational entity, a physical location, property or an individual TT Transfer To	M ID 2/3
	N102	93 Name Free-form name TC NAME (EU-58b) = Transfer of Calls to Name	X AN 1/60

Segment: **REF** Reference Identification

Position: 5800

Loop: N1 Optional

Level: Detail

Usage: Optional

Max Use: 12

Purpose: To specify identifying information

Syntax Notes: 1 At least one of REF02 or REF03 is required.

2 If either C04003 or C04004 is present, then the other is required.

3 If either C04005 or C04006 is present, then the other is required.

Semantic Notes: 1 REF04 contains data relating to the value cited in REF02.

Comments:

Notes: REF*55*TCID (EU-58a)*PRI

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>		
M	REF01	128	Reference Identification Qualifier Code qualifying the Reference Identification 55 Sequence Number	M ID 2/3
	REF02	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier TCID (EU-58a) = Transfer of Calls to Identifier	X AN 1/30
	REF03	352	Description A free-form description to clarify the related data elements and their content "PRI"	X AN 1/80

Segment: **SLN** Subline Item Detail

Position: 4700

Loop: SLN Optional

Level: Detail

Usage: Optional

Max Use: 1

Purpose: To specify product subline detail item data

Syntax Notes:

- 1 If either SLN04 or SLN05 is present, then the other is required.
- 2 If SLN07 is present, then SLN06 is required.
- 3 If SLN08 is present, then SLN06 is required.
- 4 If either SLN09 or SLN10 is present, then the other is required.
- 5 If either SLN11 or SLN12 is present, then the other is required.
- 6 If either SLN13 or SLN14 is present, then the other is required.
- 7 If either SLN15 or SLN16 is present, then the other is required.
- 8 If either SLN17 or SLN18 is present, then the other is required.
- 9 If either SLN19 or SLN20 is present, then the other is required.
- 10 If either SLN21 or SLN22 is present, then the other is required.
- 11 If either SLN23 or SLN24 is present, then the other is required.
- 12 If either SLN25 or SLN26 is present, then the other is required.
- 13 If either SLN27 or SLN28 is present, then the other is required.

Semantic Notes:

- 1 SLN01 is the identifying number for the subline item.
- 2 SLN02 is the identifying number for the subline level. The subline level is analogous to the level code used in a bill of materials.
- 3 SLN03 is the configuration code indicating the relationship of the subline item to the baseline item.
- 4 SLN08 is a code indicating the relationship of the price or amount to the associated segment.

Comments:

- 1 See the Data Element Dictionary for a complete list of IDs.
- 2 SLN01 is related to (but not necessarily equivalent to) the baseline item number. Example: 1.1 or 1A might be used as a subline number to relate to baseline number 1.
- 3 SLN09 through SLN28 provide for ten different product/service IDs for each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Notes: SLN*TCSEC*n*A*1*EA [SLN Loop may repeat]

Data Element Summary

Ref.	Data	Name	Attributes
Des.	Element		
M	SLN01	350 Assigned Identification	M AN 1/20
		Alphanumeric characters assigned for differentiation within a transaction set	
		"TCSEC"	
	SLN02	350 Assigned Identification	O AN 1/20
		Alphanumeric characters assigned for differentiation within a transaction set	
		"n" = nth assigned ID within SLN loop	
M	SLN03	662 Relationship Code	M ID 1/1
		Code indicating the relationship between entities	
		A Add	
	SLN04	380 Quantity	X R 1/15
		Numeric value of quantity	
		1 Always One	

	SLN05	C001	Composite Unit of Measure	X
			To identify a composite unit of measure (See Figures Appendix for examples of use)	
M	C00101	355	Unit or Basis for Measurement Code	M ID 2/2
			Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken	
			EA Each	

Segment: **SI** Service Characteristic Identification

Position: 4800

Loop: SLN Optional

Level: Detail

Usage: Optional

Max Use: >1

Purpose: To specify service characteristic data

Syntax Notes:

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

Semantic Notes:

Comments: 1 SI01 defines the source for each of the service characteristics qualifiers.

Notes: SI*TI*TC*TC TO SEC (EU-59)

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	SI01	559	Agency Qualifier Code Code identifying the agency assigning the code values TI Telecommunications Industry	M ID 2/2
M	SI02	1000	Service Characteristics Qualifier Code from an industry code list qualifying the type of service characteristics TC Transfer Announcement Number	M AN 2/2
M	SI03	234	Product/Service ID Identifying number for a product or service TC TO SEC (EU-59) = Transfer of Calls To Secondary Number	M AN 1/48

Segment: **N1** Name

Position: 5350

Loop: N1 Optional

Level: Detail

Usage: Optional

Max Use: 1

Purpose: To identify a party by type of organization, name, and code

Syntax Notes: 1 At least one of N102 or N103 is required.

2 If either N103 or N104 is present, then the other is required.

Semantic Notes:

Comments:

1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.

2 N105 and N106 further define the type of entity in N101.

Notes: N1*TT*TC NAME (EU-61)

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	N101	98	Entity Identifier Code Code identifying an organizational entity, a physical location, property or an individual TT Transfer To	M ID 2/3
	N102	93	Name Free-form name TC NAME (EU-61) = Transfer of Calls to Name	X AN 1/60

Segment: **REF** Reference Identification

Position: 5800

Loop: N1 Optional

Level: Detail

Usage: Optional

Max Use: 12

Purpose: To specify identifying information

Syntax Notes: 1 At least one of REF02 or REF03 is required.

2 If either C04003 or C04004 is present, then the other is required.

3 If either C04005 or C04006 is present, then the other is required.

Semantic Notes: 1 REF04 contains data relating to the value cited in REF02.

Comments:

Notes: REF*55*TCID (EU-60)*SEC

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>		
M	REF01	128	Reference Identification Qualifier Code qualifying the Reference Identification 55 Sequence Number	M ID 2/3
	REF02	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier TCID (EU-60) = Transfer of Calls To Identifier	X AN 1/30
	REF03	352	Description A free-form description to clarify the related data elements and their content "SEC"	X AN 1/80

Segment: **PO1** **Baseline Item Data - NP Form (Service Details Section)**

Position: 0100

Loop: PO1 Mandatory

Level: Detail

Usage: Mandatory

Max Use: 1

Purpose: To specify basic and most frequently used line item data

Syntax Notes:

- 1 If PO103 is present, then PO102 is required.
- 2 If PO105 is present, then PO104 is required.
- 3 If either PO106 or PO107 is present, then the other is required.
- 4 If either PO108 or PO109 is present, then the other is required.
- 5 If either PO110 or PO111 is present, then the other is required.
- 6 If either PO112 or PO113 is present, then the other is required.
- 7 If either PO114 or PO115 is present, then the other is required.
- 8 If either PO116 or PO117 is present, then the other is required.
- 9 If either PO118 or PO119 is present, then the other is required.
- 10 If either PO120 or PO121 is present, then the other is required.
- 11 If either PO122 or PO123 is present, then the other is required.
- 12 If either PO124 or PO125 is present, then the other is required.

Semantic Notes:

Comments:

- 1 See the Data Element Dictionary for a complete list of IDs.
- 2 PO101 is the line item identification.
- 3 PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Notes: PO1*n*1*EA***ZZ*INP [PO1 Loop repeats NPQTY (NP-5) times]

Data Element Summary

<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
PO101	350	Assigned Identification Alphanumeric characters assigned for differentiation within a transaction set "n" = nth assigned ID within PO1 loop	O AN 1/20
PO102	330	Quantity Ordered Quantity ordered 1 Always One	X R 1/15
PO103	355	Unit or Basis for Measurement Code Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken EA Each	O ID 2/2
PO106	235	Product/Service ID Qualifier Code identifying the type/source of the descriptive number used in Product/Service ID (234) ZZ Mutually Defined	X ID 2/2
PO107	234	Product/Service ID Identifying number for a product or service "INP"	X AN 1/48

Segment: **SI** Service Characteristic Identification

Position: 0180

Loop: PO1 Mandatory

Level: Detail

Usage: Optional

Max Use: >1

Purpose: To specify service characteristic data

Syntax Notes:

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

Semantic Notes:

Comments: 1 SI01 defines the source for each of the service characteristics qualifiers.

Notes:

- SI*TI*SA*LNA (NP-10)
- SI*TI*IT*PORTED NBR (NP-15)
- SI*TI*C2*CFTN (NP-17)
- SI*TI*IP*NPT (NP-18)
- SI*TI*RI*RTI (NP-19)
- SI*TI*TH*NPTG (NP-20)
- SI*TI*FZ*FPI (NP-24)
- SI*TI*T6*TC OPT (NP-26)

Data Element Summary

Ref.	Des.	Data Element	Name	Attributes
M	SI01	559	Agency Qualifier Code Code identifying the agency assigning the code values TI Telecommunications Industry	M ID 2/2
M	SI02	1000	Service Characteristics Qualifier Code from an industry code list qualifying the type of service characteristics C2 Call Forwarding Telephone Number FZ Freeze PIC Indicator IP Number Portability Type IT Ported Telephone Number(s) RI Route Index SA Service Activity T6 Transfer of Calls Options TH Trunk Group Number	M AN 2/2
M	SI03	234	Product/Service ID Identifying number for a product or service LNA (NP-10) = Line Activity C= (DWS: C-Change) D= (DWS: D-Disconnect) V= (DWS: V-Conversion as specified) TC OPT (NP-26) = Transfer of Call Options	M AN 1/48

NPT (NP-18) = Number Portability Type
FPI (NP-24) = Freeze PIC Indicator
CFTN (NP-17) = Call Forward To Number
RTI (NP-19) = Route Index
PORTED NBR (NP-15) = Ported Telephone Number
NPTG (NP-20) = Number Portability Trunk Group

Segment: **REF** Reference Identification

Position: 1000

Loop: PO1 Mandatory

Level: Detail

Usage: Optional

Max Use: >1

Purpose: To specify identifying information

Syntax Notes: 1 At least one of REF02 or REF03 is required.

2 If either C04003 or C04004 is present, then the other is required.

3 If either C04005 or C04006 is present, then the other is required.

Semantic Notes: 1 REF04 contains data relating to the value cited in REF02.

Comments:

Notes: REF*IX*LNUM (NP-8)*LNUM

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>		
M	REF01	128	Reference Identification Qualifier Code qualifying the Reference Identification IX Item Number	M ID 2/3
	REF02	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier LNUM (NP-8) = Line Number	X AN 1/30
	REF03	352	Description A free-form description to clarify the related data elements and their content "LNUM"	X AN 1/80

Segment: **DTM** Date/Time Reference

Position: 2100

Loop: PO1 Mandatory

Level: Detail

Usage: Optional

Max Use: 10

Purpose: To specify pertinent dates and times

Syntax Notes: 1 At least one of DTM02 DTM03 or DTM05 is required.

2 If DTM04 is present, then DTM03 is required.

3 If either DTM05 or DTM06 is present, then the other is required.

Semantic Notes:

Comments:

Notes: DTM*376*TC PER {CCYYMMDD} (NP-31)

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>		
M	DTM01	374	Date/Time Qualifier Code specifying type of date or time, or both date and time 376 Delivery End The date that deliveries will end	M ID 3/3
	DTM02	373	Date Date expressed as CCYYMMDD TC PER (NP-31) = Transfer of Calls Period	X DT 8/8

Segment: **QTY** Quantity
Position: 2930
Loop: QTY Optional
Level: Detail
Usage: Optional
Max Use: 1
Purpose: To specify quantity information
Syntax Notes:
 1 At least one of QTY02 or QTY04 is required.
 2 Only one of QTY02 or QTY04 may be present.
Semantic Notes:
 1 QTY04 is used when the quantity is non-numeric.
Comments:
Notes: QTY*43*TNP (NP-16)*EA

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>		
M	QTY01	673	Quantity Qualifier Code specifying the type of quantity 43 Talk Paths The total number of talk paths associated with the ordered port(s)	M ID 2/2
	QTY02	380	Quantity Numeric value of quantity TNP (NP-16) = Total Number of Paths	X R 1/15
	QTY03	C001	Composite Unit of Measure To identify a composite unit of measure (See Figures Appendix for examples of use)	O
M	C00101	355	Unit or Basis for Measurement Code Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken EA Each	M ID 2/2

Segment: **N1** Name
Position: 3500
Loop: N1 Optional
Level: Detail
Usage: Optional
Max Use: 1
Purpose: To identify a party by type of organization, name, and code
Syntax Notes: 1 At least one of N102 or N103 is required.
 2 If either N103 or N104 is present, then the other is required.
Semantic Notes:
Comments: 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
 2 N105 and N106 further define the type of entity in N101.
Notes: N1*8V**41*LPIC (NP-25)

Data Element Summary

Ref.	Data	Name	Attributes
<u>Des.</u>	<u>Element</u>		
M	N101	98 Entity Identifier Code Code identifying an organizational entity, a physical location, property or an individual 8V Primary Intra-LATA (Local Access Transport Area) Carrier	M ID 2/3
	N103	66 Identification Code Qualifier Code designating the system/method of code structure used for Identification Code (67) 41 Telecommunications Carrier Identification Code Identifies the Interexchange carrier for the charges being billed	X ID 1/2
	N104	67 Identification Code Code identifying a party or other code LPIC (NP-25) = IntraLATA Pre-subscription Indicator Code	X AN 2/80

Segment: **SLN** Subline Item Detail

Position: 4700

Loop: SLN Optional

Level: Detail

Usage: Optional

Max Use: 1

Purpose: To specify product subline detail item data

Syntax Notes:

- 1 If either SLN04 or SLN05 is present, then the other is required.
- 2 If SLN07 is present, then SLN06 is required.
- 3 If SLN08 is present, then SLN06 is required.
- 4 If either SLN09 or SLN10 is present, then the other is required.
- 5 If either SLN11 or SLN12 is present, then the other is required.
- 6 If either SLN13 or SLN14 is present, then the other is required.
- 7 If either SLN15 or SLN16 is present, then the other is required.
- 8 If either SLN17 or SLN18 is present, then the other is required.
- 9 If either SLN19 or SLN20 is present, then the other is required.
- 10 If either SLN21 or SLN22 is present, then the other is required.
- 11 If either SLN23 or SLN24 is present, then the other is required.
- 12 If either SLN25 or SLN26 is present, then the other is required.
- 13 If either SLN27 or SLN28 is present, then the other is required.

Semantic Notes:

- 1 SLN01 is the identifying number for the subline item.
- 2 SLN02 is the identifying number for the subline level. The subline level is analogous to the level code used in a bill of materials.
- 3 SLN03 is the configuration code indicating the relationship of the subline item to the baseline item.
- 4 SLN08 is a code indicating the relationship of the price or amount to the associated segment.

Comments:

- 1 See the Data Element Dictionary for a complete list of IDs.
- 2 SLN01 is related to (but not necessarily equivalent to) the baseline item number. Example: 1.1 or 1A might be used as a subline number to relate to baseline number 1.
- 3 SLN09 through SLN28 provide for ten different product/service IDs for each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Notes: SLN*TCPRI*n*A*1*EA

Data Element Summary

Ref.	Data	Name	Attributes
Des.	Element		
M	SLN01	350 Assigned Identification	M AN 1/20
		Alphanumeric characters assigned for differentiation within a transaction set	
		"TCPRI"	
	SLN02	350 Assigned Identification	O AN 1/20
		Alphanumeric characters assigned for differentiation within a transaction set	
		"n" = nth assigned ID within SLN loop	
M	SLN03	662 Relationship Code	M ID 1/1
		Code indicating the relationship between entities	
		A Add	
	SLN04	380 Quantity	X R 1/15
		Numeric value of quantity	
		1 Always One	

	SLN05	C001	Composite Unit of Measure	X
			To identify a composite unit of measure (See Figures Appendix for examples of use)	
M	C00101	355	Unit or Basis for Measurement Code	M ID 2/2
			Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken	
			EA Each	

Segment: **SI** Service Characteristic Identification

Position: 4800

Loop: SLN Optional

Level: Detail

Usage: Optional

Max Use: >1

Purpose: To specify service characteristic data

Syntax Notes:

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

Semantic Notes:

Comments: 1 SI01 defines the source for each of the service characteristics qualifiers.

Notes: SI*TI*TC*TC TO PRI (NP-27)

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	SI01	559	Agency Qualifier Code Code identifying the agency assigning the code values TI Telecommunications Industry	M ID 2/2
M	SI02	1000	Service Characteristics Qualifier Code from an industry code list qualifying the type of service characteristics TC Transfer Announcement Number	M AN 2/2
M	SI03	234	Product/Service ID Identifying number for a product or service TC TO PRI (NP-27) = Transfer of Calls To Primary Number	M AN 1/48

Segment: **N1** Name
Position: 5350
Loop: N1 Optional
Level: Detail
Usage: Optional
Max Use: 1
Purpose: To identify a party by type of organization, name, and code
Syntax Notes:

- 1 At least one of N102 or N103 is required.
- 2 If either N103 or N104 is present, then the other is required.

Semantic Notes:
Comments:

- 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
- 2 N105 and N106 further define the type of entity in N101.

Notes: N1*TT*TC NAME (NP-27b)

Data Element Summary

Ref.	Data	Name	Attributes
<u>Des.</u>	<u>Element</u>		
M	N101	98 Entity Identifier Code Code identifying an organizational entity, a physical location, property or an individual TT Transfer To	M ID 2/3
	N102	93 Name Free-form name TC NAME (NP-27b) = Transfer of Calls to Name	X AN 1/60

Segment: **REF** Reference Identification

Position: 5800

Loop: N1 Optional

Level: Detail

Usage: Optional

Max Use: 12

Purpose: To specify identifying information

Syntax Notes: 1 At least one of REF02 or REF03 is required.

2 If either C04003 or C04004 is present, then the other is required.

3 If either C04005 or C04006 is present, then the other is required.

Semantic Notes: 1 REF04 contains data relating to the value cited in REF02.

Comments:

Notes: REF*55*TCID (N27a)*PRI

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>		
M	REF01	128	Reference Identification Qualifier Code qualifying the Reference Identification 55 Sequence Number	M ID 2/3
	REF02	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier TCID (NP-27a) = Transfer of Calls to Identifier	X AN 1/30
	REF03	352	Description A free-form description to clarify the related data elements and their content "PRI"	X AN 1/80

Segment: **SLN** Subline Item Detail

Position: 4700

Loop: SLN Optional

Level: Detail

Usage: Optional

Max Use: 1

Purpose: To specify product subline detail item data

Syntax Notes:

- 1 If either SLN04 or SLN05 is present, then the other is required.
- 2 If SLN07 is present, then SLN06 is required.
- 3 If SLN08 is present, then SLN06 is required.
- 4 If either SLN09 or SLN10 is present, then the other is required.
- 5 If either SLN11 or SLN12 is present, then the other is required.
- 6 If either SLN13 or SLN14 is present, then the other is required.
- 7 If either SLN15 or SLN16 is present, then the other is required.
- 8 If either SLN17 or SLN18 is present, then the other is required.
- 9 If either SLN19 or SLN20 is present, then the other is required.
- 10 If either SLN21 or SLN22 is present, then the other is required.
- 11 If either SLN23 or SLN24 is present, then the other is required.
- 12 If either SLN25 or SLN26 is present, then the other is required.
- 13 If either SLN27 or SLN28 is present, then the other is required.

Semantic Notes:

- 1 SLN01 is the identifying number for the subline item.
- 2 SLN02 is the identifying number for the subline level. The subline level is analogous to the level code used in a bill of materials.
- 3 SLN03 is the configuration code indicating the relationship of the subline item to the baseline item.
- 4 SLN08 is a code indicating the relationship of the price or amount to the associated segment.

Comments:

- 1 See the Data Element Dictionary for a complete list of IDs.
- 2 SLN01 is related to (but not necessarily equivalent to) the baseline item number. Example: 1.1 or 1A might be used as a subline number to relate to baseline number 1.
- 3 SLN09 through SLN28 provide for ten different product/service IDs for each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Notes: SLN*TCSEC*n*A*1*EA [SLN Loop may repeat]

Data Element Summary

Ref.	Data	Name	Attributes
Des.	Element		
M	SLN01	350 Assigned Identification	M AN 1/20
		Alphanumeric characters assigned for differentiation within a transaction set	
		"TCSEC"	
	SLN02	350 Assigned Identification	O AN 1/20
		Alphanumeric characters assigned for differentiation within a transaction set	
		"n" = nth assigned ID within SLN loop	
M	SLN03	662 Relationship Code	M ID 1/1
		Code indicating the relationship between entities	
		A Add	
	SLN04	380 Quantity	X R 1/15
		Numeric value of quantity	
		1 Always One	

	SLN05	C001	Composite Unit of Measure	X
			To identify a composite unit of measure (See Figures Appendix for examples of use)	
M	C00101	355	Unit or Basis for Measurement Code	M ID 2/2
			Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken	
			EA Each	

Segment: **SI** Service Characteristic Identification

Position: 4800

Loop: SLN Optional

Level: Detail

Usage: Optional

Max Use: >1

Purpose: To specify service characteristic data

- Syntax Notes:**
- 1 If either SI04 or SI05 is present, then the other is required.
 - 2 If either SI06 or SI07 is present, then the other is required.
 - 3 If either SI08 or SI09 is present, then the other is required.
 - 4 If either SI10 or SI11 is present, then the other is required.
 - 5 If either SI12 or SI13 is present, then the other is required.
 - 6 If either SI14 or SI15 is present, then the other is required.
 - 7 If either SI16 or SI17 is present, then the other is required.
 - 8 If either SI18 or SI19 is present, then the other is required.
 - 9 If either SI20 or SI21 is present, then the other is required.

Semantic Notes:

Comments: 1 SI01 defines the source for each of the service characteristics qualifiers.

Notes: SI*TI*TC*TC TO SEC (NP-28)

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	SI01	559	Agency Qualifier Code Code identifying the agency assigning the code values TI Telecommunications Industry	M ID 2/2
M	SI02	1000	Service Characteristics Qualifier Code from an industry code list qualifying the type of service characteristics TC Transfer Announcement Number	M AN 2/2
M	SI03	234	Product/Service ID Identifying number for a product or service TC TO SEC (NP-28) = Transfer of Calls To Secondary Number	M AN 1/48

Segment: **N1** Name
Position: 5350
Loop: N1 Optional
Level: Detail
Usage: Optional
Max Use: 1
Purpose: To identify a party by type of organization, name, and code
Syntax Notes:

- 1 At least one of N102 or N103 is required.
- 2 If either N103 or N104 is present, then the other is required.

Semantic Notes:
Comments:

- 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
- 2 N105 and N106 further define the type of entity in N101.

Notes: N1*TT*TC NAME (NP-30)

Data Element Summary

Ref.	Data	Name	Attributes
<u>Des.</u>	<u>Element</u>	<u>Name</u>	<u>Attributes</u>
M	N101	98 Entity Identifier Code Code identifying an organizational entity, a physical location, property or an individual TT Transfer To	M ID 2/3
	N102	93 Name Free-form name TC NAME (NP-30) = Transfer of Calls To Name	X AN 1/60

Segment: **REF** Reference Identification

Position: 5800

Loop: N1 Optional

Level: Detail

Usage: Optional

Max Use: 12

Purpose: To specify identifying information

Syntax Notes: 1 At least one of REF02 or REF03 is required.

2 If either C04003 or C04004 is present, then the other is required.

3 If either C04005 or C04006 is present, then the other is required.

Semantic Notes: 1 REF04 contains data relating to the value cited in REF02.

Comments:

Notes: REF*55*TCID (NP-29)*SEC

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>		
M	REF01	128	Reference Identification Qualifier Code qualifying the Reference Identification 55 Sequence Number	M ID 2/3
	REF02	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier TCID (NP-29) = Transfer of Calls To Identifier	X AN 1/30
	REF03	352	Description A free-form description to clarify the related data elements and their content "SEC"	X AN 1/80

Segment: **SLN** Subline Item Detail

Position: 4700

Loop: SLN Optional

Level: Detail

Usage: Optional

Max Use: 1

Purpose: To specify product subline detail item data

Syntax Notes:

- 1 If either SLN04 or SLN05 is present, then the other is required.
- 2 If SLN07 is present, then SLN06 is required.
- 3 If SLN08 is present, then SLN06 is required.
- 4 If either SLN09 or SLN10 is present, then the other is required.
- 5 If either SLN11 or SLN12 is present, then the other is required.
- 6 If either SLN13 or SLN14 is present, then the other is required.
- 7 If either SLN15 or SLN16 is present, then the other is required.
- 8 If either SLN17 or SLN18 is present, then the other is required.
- 9 If either SLN19 or SLN20 is present, then the other is required.
- 10 If either SLN21 or SLN22 is present, then the other is required.
- 11 If either SLN23 or SLN24 is present, then the other is required.
- 12 If either SLN25 or SLN26 is present, then the other is required.
- 13 If either SLN27 or SLN28 is present, then the other is required.

Semantic Notes:

- 1 SLN01 is the identifying number for the subline item.
- 2 SLN02 is the identifying number for the subline level. The subline level is analogous to the level code used in a bill of materials.
- 3 SLN03 is the configuration code indicating the relationship of the subline item to the baseline item.
- 4 SLN08 is a code indicating the relationship of the price or amount to the associated segment.

Comments:

- 1 See the Data Element Dictionary for a complete list of IDs.
- 2 SLN01 is related to (but not necessarily equivalent to) the baseline item number. Example: 1.1 or 1A might be used as a subline number to relate to baseline number 1.
- 3 SLN09 through SLN28 provide for ten different product/service IDs for each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Notes: SLN*BL*n*A*1*EA

Data Element Summary

Ref.	Des.	Data Element	Name	Attributes	
				M	AN
M	SLN01	350	Assigned Identification	M	AN 1/20
			Alphanumeric characters assigned for differentiation within a transaction set		
			"BL"		
	SLN02	350	Assigned Identification	O	AN 1/20
			Alphanumeric characters assigned for differentiation within a transaction set		
			"n" = nth assigned ID within SLN loop		
M	SLN03	662	Relationship Code	M	ID 1/1
			Code indicating the relationship between entities		
			A Add		
	SLN04	380	Quantity	X	R 1/15
			Numeric value of quantity		
			1 Always One		

	SLN05	C001	Composite Unit of Measure	X
			To identify a composite unit of measure (See Figures Appendix for examples of use)	
M	C00101	355	Unit or Basis for Measurement Code	M ID 2/2
			Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken	
			EA Each	

Segment: **SI** Service Characteristic Identification

Position: 4800

Loop: SLN Optional

Level: Detail

Usage: Optional

Max Use: >1

Purpose: To specify service characteristic data

- Syntax Notes:**
- 1 If either SI04 or SI05 is present, then the other is required.
 - 2 If either SI06 or SI07 is present, then the other is required.
 - 3 If either SI08 or SI09 is present, then the other is required.
 - 4 If either SI10 or SI11 is present, then the other is required.
 - 5 If either SI12 or SI13 is present, then the other is required.
 - 6 If either SI14 or SI15 is present, then the other is required.
 - 7 If either SI16 or SI17 is present, then the other is required.
 - 8 If either SI18 or SI19 is present, then the other is required.
 - 9 If either SI20 or SI21 is present, then the other is required.

Semantic Notes:

Comments: 1 SI01 defines the source for each of the service characteristics qualifiers.

Notes: SI*TI*BB*BA (NP-22)*TB*BLOCK (NP-23)

Data Element Summary

Ref.	Data	Name		Attributes
Des.	Element			
M	SI01	559	Agency Qualifier Code	M ID 2/2
			Code identifying the agency assigning the code values	
			TI Telecommunications Industry	
M	SI02	1000	Service Characteristics Qualifier	M AN 2/2
			Code from an industry code list qualifying the type of service characteristics	
			BB Blocking Activity	
M	SI03	234	Product/Service ID	M AN 1/48
			Identifying number for a product or service	
			BA (NP-22) = Blocking Activity	
	SI04	1000	Service Characteristics Qualifier	X AN 2/2
			Code from an industry code list qualifying the type of service characteristics	
			TB Blocking/Billing Exception	
	SI05	234	Product/Service ID	X AN 1/48
			Identifying number for a product or service	
			BLOCK (NP-23) = Block	

Segment: **PO1** **Baseline Item Data - Dummy**

Position: 0100

Loop: PO1 Mandatory

Level: Detail

Usage: Mandatory

Max Use: 1

Purpose: To specify basic and most frequently used line item data

Syntax Notes:

- 1 If PO103 is present, then PO102 is required.
- 2 If PO105 is present, then PO104 is required.
- 3 If either PO106 or PO107 is present, then the other is required.
- 4 If either PO108 or PO109 is present, then the other is required.
- 5 If either PO110 or PO111 is present, then the other is required.
- 6 If either PO112 or PO113 is present, then the other is required.
- 7 If either PO114 or PO115 is present, then the other is required.
- 8 If either PO116 or PO117 is present, then the other is required.
- 9 If either PO118 or PO119 is present, then the other is required.
- 10 If either PO120 or PO121 is present, then the other is required.
- 11 If either PO122 or PO123 is present, then the other is required.
- 12 If either PO124 or PO125 is present, then the other is required.

Semantic Notes:

Comments:

- 1 See the Data Element Dictionary for a complete list of IDs.
- 2 PO101 is the line item identification.
- 3 PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Notes: PO1*DUMMY*1*EA***ZZ*DD

Data Element Summary

Ref. Des.	Data Element	Name	Attributes
PO101	350	Assigned Identification Alphanumeric characters assigned for differentiation within a transaction set "DUMMY"	O AN 1/20
PO102	330	Quantity Ordered Quantity ordered 1 Always One	X R 1/15
PO103	355	Unit or Basis for Measurement Code Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken EA Each	O ID 2/2
PO106	235	Product/Service ID Qualifier Code identifying the type/source of the descriptive number used in Product/Service ID (234) ZZ Mutually Defined	X ID 2/2
PO107	234	Product/Service ID Identifying number for a product or service "DD"	X AN 1/48

Segment: **CTT** Transaction Totals

Position: 0100

Loop: CTT Optional

Level: Summary

Usage: Optional

Max Use: 1

Purpose: To transmit a hash total for a specific element in the transaction set

Syntax Notes: 1 If either CTT03 or CTT04 is present, then the other is required.

2 If either CTT05 or CTT06 is present, then the other is required.

Semantic Notes:

Comments: 1 This segment is intended to provide hash totals to validate transaction completeness and correctness.

Notes: CTT*Number of PO1 Segments

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>		
M	CTT01	354	Number of Line Items Total number of line items in the transaction set	M NO 1/6

Segment: **SE** Transaction Set Trailer
Position: 0300
Loop:
Level: Summary
Usage: Mandatory
Max Use: 1
Purpose: To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Syntax Notes:

Semantic Notes:

Comments: 1 SE is the last segment of each transaction set.

Notes: SE*Number of Segments*TRAN SET CONTROL #

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
M	SE01	96	Number of Included Segments	M NO 1/10
			Total number of segments included in a transaction set including ST and SE segments	
M	SE02	329	Transaction Set Control Number	M AN 4/9
			Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set	

18.6.2 860 Interim Number Portability Supplemental Service Request (860INP)

Functional Group ID=**PC**

Introduction:

The 860INP will be used by the Co-Provider to initiate Interim Number Portability Supplemental Service Requests to Qwest.

This implementation guideline references the following:

1. ANSI ASC X12 Version 4020
2. LSOG5 and Qwest assigned fields
3. TCIF/SOSC Guidelines ELMS 5

Notes:

This 860 Transaction includes the mappings for Local Service Request, End User and Number Portability.

Heading:

	<u>Pos. No.</u>	<u>Seg. ID</u>	<u>Name</u>	<u>Req. Des.</u>	<u>Max.Use</u>	<u>Loop Repeat</u>	<u>Notes and Comments</u>
M	0100	ST	Transaction Set Header	M	1		
M	0200	BCH	Beginning Segment for Purchase Order	M	1		
	0500	REF	Reference Identification	O	>1		
	0950	PAM	Period Amount	O	10		
	1500	DTM	Date/Time Reference	O	10		
	1850	SI	Service Characteristic Identification	O	>1		
	1900	PID	Product/Item Description	O	200		
						LOOP ID - N9	1000
	2850	N9	Reference Identification	O	1		
	2900	MTX	Text	O	>1		
						LOOP ID - N9	1000
	2850	N9	Reference Identification	O	1		
	2900	MTX	Text	O	>1		
						LOOP ID - N9	1000
	2850	N9	Reference Identification	O	1		
	2900	MTX	Text	O	>1		
						LOOP ID - N1	200
	3000	N1	Name	O	1		
	3500	PER	Administrative Communications Contact	O	>1		
						LOOP ID - N1	200
	3000	N1	Name	O	1		
						LOOP ID - N1	200
	3000	N1	Name	O	1		
	3100	N2	Additional Name Information	O	2		

3300	N4	Geographic Location	O	>1
3350	NX2	Location ID Component	O	>1
3500	PER	Administrative Communications Contact	O	>1
3550	SI	Service Characteristic Identification	O	>1

Detail:

<u>Pos. No.</u>	<u>Seg. ID</u>	<u>Name</u>	<u>Req. Des.</u>	<u>Max.Use</u>	<u>Loop Repeat</u>	<u>Notes and Comments</u>
LOOP ID - POC						>1
0100	POC	Line Item Change - End User Form (Location and Access Section)	O	1		
LOOP ID - N1						200
3400	N1	Name	O	1		
3700	N4	Geographic Location	O	1		
3750	NX2	Location ID Component	O	>1		
3950	SI	Service Characteristic Identification	O	>1		
LOOP ID - POC						>1
0100	POC	Line Item Change - End User Form (Disconnect Information Section)	O	1		
0180	SI	Service Characteristic Identification	O	>1		
1000	REF	Reference Identification	O	>1		
2000	DTM	Date/Time Reference	O	10		
LOOP ID - SLN						>1
4600	SLN	Subline Item Detail	O	1		
4700	SI	Service Characteristic Identification	O	>1		
LOOP ID - N1						10
5360	N1	Name	O	1		
5700	REF	Reference Identification	O	12		
LOOP ID - SLN						>1
4600	SLN	Subline Item Detail	O	1		
4700	SI	Service Characteristic Identification	O	>1		
LOOP ID - N1						10
5360	N1	Name	O	1		
5700	REF	Reference Identification	O	12		
LOOP ID - POC						>1
0100	POC	Line Item Change - INP Form (Service Details Section)	O	1		
0180	SI	Service Characteristic Identification	O	>1		
1000	REF	Reference Identification	O	>1		
2000	DTM	Date/Time Reference	O	10		
LOOP ID - QTY						>1
2930	QTY	Quantity	O	1		
LOOP ID - N1						200
3400	N1	Name	O	1		
LOOP ID - SLN						>1
4600	SLN	Subline Item Detail	O	1		
4700	SI	Service Characteristic Identification	O	>1		

		LOOP ID - N1		10
5360	N1	Name	O	1
5700	REF	Reference Identification	O	12
		LOOP ID - SLN		>1
4600	SLN	Subline Item Detail	O	1
4700	SI	Service Characteristic Identification	O	>1
		LOOP ID - N1		10
5360	N1	Name	O	1
5700	REF	Reference Identification	O	12
		LOOP ID - SLN		>1
4600	SLN	Subline Item Detail	O	1
4700	SI	Service Characteristic Identification	O	>1

Summary:

<u>Pos. No.</u>	<u>Seg. ID</u>	<u>Name</u>	<u>Req. Des.</u>	<u>Max.Use</u>	<u>Loop Repeat</u>	<u>Notes and Comments</u>
		LOOP ID - CTT			1	
0100	CTT	Transaction Totals	O	1		n1
M	0300	SE	Transaction Set Trailer	M	1	

Transaction Set Notes

1. Number of line items (CTT01) is the accumulation of the number of POC segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (POC03) for each POC segment.

Segment: **ST** Transaction Set Header
Position: 0100
Loop:
Level: Heading
Usage: Mandatory
Max Use: 1
Purpose: To indicate the start of a transaction set and to assign a control number
Syntax Notes:
Semantic Notes:

- 1 The transaction set identifier (ST01) is used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).
- 2 The implementation convention reference (ST03) is used by the translation routines of the interchange partners to select the appropriate implementation convention to match the transaction set definition.

Comments:
Notes: ST*860*TRAN SET CONTROL #

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	ST01	143	Transaction Set Identifier Code Code uniquely identifying a Transaction Set 860 Purchase Order Change Request - Buyer Initiated	M ID 3/3
M	ST02	329	Transaction Set Control Number Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set	M AN 4/9

Segment: **BCH** Beginning Segment for Purchase Order Change
Position: 0200
Loop:
Level: Heading
Usage: Mandatory
Max Use: 1
Purpose: To indicate the beginning of the Purchase Order Change Transaction Set and transmit identifying numbers and dates

Syntax Notes:
Semantic Notes:

- 1 BCH06 is the date assigned by the purchaser to purchase order.
- 2 BCH09 is the seller's order number.
- 3 BCH10 is the date assigned by the sender to the acknowledgment.
- 4 BCH11 is the date of the purchase order change request.

Comments:
Notes: BCH*SUP (LSR-25)*SS*PON (LSR-2)**VER (LSR-3)*PO Date (See Trading Partner Access Information)

Data Element Summary

	Ref. Des.	Data Element	Name	Attributes
M	BCH01	353	Transaction Set Purpose Code Code identifying purpose of transaction set SUP (LSR-25) = Supplement Type 01 = (DWS: "1" = Cancel) 04 = (DWS: "2" = DDD - Change) 05 = (DWS: "3" = Other)	M ID 2/2
M	BCH02	92	Purchase Order Type Code Code specifying the type of Purchase Order SS Supply or Service Order	M ID 2/2
M	BCH03	324	Purchase Order Number Identifying number for Purchase Order assigned by the orderer/purchaser PON (LSR-2) = Purchase Order Number	M AN 1/22
	BCH05	327	Change Order Sequence Number Number assigned by the orderer identifying a specific change or revision to a previously transmitted transaction set VER (LSR-3) = Version Identification	O AN 1/8
M	BCH06	373	Date Date expressed as CCYYMMDD PO Date (See Trading Partner Access Information)	M DT 8/8

Segment: **REF** Reference Identification

Position: 0500

Loop:

Level: Heading

Usage: Optional

Max Use: >1

Purpose: To specify identifying information

- Syntax Notes:**
- 1 At least one of REF02 or REF03 is required.
 - 2 If either C04003 or C04004 is present, then the other is required.
 - 3 If either C04005 or C04006 is present, then the other is required.
- Semantic Notes:**
- 1 REF04 contains data relating to the value cited in REF02.

Comments:

Notes:

```
REF*11*AN (LSR-7)*AN
REF*12*BAN1 (LSR-61)*BAN1
REF*JB*PROJECT (LSR-20)
REF*SU*RTR (LSR-28)*RTR
REF*CO*RPON (LSR-51)*RPON
REF*1V*RORD (LSR-52)*RORD
```

Data Element Summary

M	Ref. Des.	Data Element	Name	Attributes	
				M	ID 2/3
	REF01	128	Reference Identification Qualifier Code qualifying the Reference Identification		
			11 Account Number Number identifies a telecommunications industry account		
			12 Billing Account Account number under which billing is rendered		
			1V Related Vendor Order Number A vendor's order number that is in addition to a primary order number		
			CO Customer Order Number		
			JB Job (Project) Number		
			SU Special Processing Code Unique code identifying the special handling requirements for the claim		
	REF02	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier	X	AN 1/30
			AN (LSR-7) = Account Number BAN1 (LSR-61) = Billing Account Number 1 PROJECT (LSR-20) = Project Identification RTR (LSR-28) = Response Type Requested RPON (LSR-51) = Related Purchase Order Number RORD (LSR-52) = Related Order Number		
	REF03	352	Description A free-form description to clarify the related data elements and their content	X	AN 1/80
			"AN" "BAN1" "RTR" "RPON"		

"RORD"

Segment: **PAM** Period Amount

Position: 0950

Loop:

Level: Heading

Usage: Optional

Max Use: 10

Purpose: To indicate a quantity, and/or amount for an identified period

Syntax Notes:

- 1 If any of PAM01 PAM02 or PAM03 is present, then all are required.
- 2 At least one of PAM02 PAM05 or PAM14 is required.
- 3 If either PAM04 or PAM05 is present, then the other is required.
- 4 If either PAM06 or PAM07 is present, then the other is required.
- 5 If PAM07 is present, then at least one of PAM08 or PAM09 is required.
- 6 If PAM07 is present, then PAM06 is required.
- 7 If PAM08 is present, then PAM07 is required.
- 8 If PAM09 is present, then PAM07 is required.
- 9 If PAM10 is present, then at least one of PAM11 or PAM12 is required.
- 10 If PAM11 is present, then PAM10 is required.
- 11 If either PAM13 or PAM14 is present, then the other is required.

Semantic Notes:

- 1 PAM10, PAM11, or PAM12 are used when two dates are required.
- 2 PAM15 indicates whether the monetary amount identified in PAM05 is a net or gross value. A "Y" indicates amount is a gross value; an "N" indicates amount is a net value.

Comments:

Notes:

```
PAM*48*PG_of_ (LSR-10) (1st 2 Bytes)*EA
PAM*47*PG_of_ (LSR-10) (2nd 2 Bytes)*EA
PAM*OC*NPQTY (NP-5)*EA
```

Data Element Summary

Ref. Des.	Data Element	Name	Attributes
PAM01	673	Quantity Qualifier Code specifying the type of quantity 47 Primary Net Quantity 48 Secondary Net Quantity OC Order Count	X ID 2/2
PAM02	380	Quantity Numeric value of quantity First 2 bytes of PG_of_ (LSR-10) Second 2 bytes of PG_of_ (LSR-10) NPQTY (NP-5) = Number Portability Quantity	X R 1/15
PAM03	C001	Composite Unit of Measure To identify a composite unit of measure (See Figures Appendix for examples of use)	X
M C00101	355	Unit or Basis for Measurement Code Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken EA Each	M ID 2/2

Segment: **DTM** Date/Time Reference

Position: 1500

Loop:

Level: Heading

Usage: Optional

Max Use: 10

Purpose: To specify pertinent dates and times

Syntax Notes: 1 At least one of DTM02 DTM03 or DTM05 is required.

2 If DTM04 is present, then DTM03 is required.

3 If either DTM05 or DTM06 is present, then the other is required.

Semantic Notes:

Comments:

Notes:

DTM*097*D/TSENT{CCYYMMDD} (LSR-12)*D/TSENT{HHMM} (LSR-12)

DTM*150*DDD{CCYYMMDD} (LSR-14)

DTM*992****TM*DFDT(HHMM) (LSR-19)

DTM*270*DATED{CCYYMMDD} (LSR-36)

Data Element Summary

Ref.	Data	Name	Attributes
Des.	Element		
M	DTM01	374 Date/Time Qualifier	M ID 3/3
		Code specifying type of date or time, or both date and time	
		097 Transaction Creation	
		150 Service Period Start	
		270 Date Filed	
		992 Date Requested	
	DTM02	373 Date	X DT 8/8
		Date expressed as CCYYMMDD	
		D/TSENT (LSR-12) = Date Sent	
		DDD (LSR-14) = Desired Due Date	
		DATED (LSR-36) = Date of Agency Authorization	
	DTM03	337 Time	X TM 4/8
		Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)	
		D/TSENT{HHMM} (LSR-12) = Time Sent	
	DTM05	1250 Date Time Period Format Qualifier	X ID 2/3
		Code indicating the date format, time format, or date and time format	
		TM Time Expressed in Format HHMM	
		Time expressed in the format HHMM where HH is the numerical expression of hours in the day based on a twenty-four hour clock and MM is the numerical expression of minutes within an hour	
	DTM06	1251 Date Time Period	X AN 1/35
		Expression of a date, a time, or range of dates, times or dates and times	
		DFDT {HHMM} (LSR-19) = Desired Frame Due Time	

Segment: **SI** Service Characteristic Identification
Position: 1850
Loop:
Level: Heading
Usage: Optional
Max Use: >1
Purpose: To specify service characteristic data
Syntax Notes:

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

Semantic Notes:
Comments: 1 SI01 defines the source for each of the service characteristics qualifiers.
Notes:

- SI*TI*RE*REQTYP (LSR-23)
- SI*TI*AA*ACT (LSR-24)
- SI*TI*TY*TOS (LSR-44)

Data Element Summary

Ref.	Data			
<u>Des.</u>	<u>Element</u>	<u>Name</u>	<u>Attributes</u>	
M	SI01	559	Agency Qualifier Code	M ID 2/2
			Code identifying the agency assigning the code values	
			TI Telecommunications Industry	
M	SI02	1000	Service Characteristics Qualifier	M AN 2/2
			Code from an industry code list qualifying the type of service characteristics	
			AA Account Activity	
			RE Requisition Type	
			TY Type of Service	
M	SI03	234	Product/Service ID	M AN 1/48
			Identifying number for a product or service	
			ACT (LSR-24) = Activity	
			D= (DWS: D = Disconnect)	
			C= (DWS: C = Change)	
			V= (DWS: V = Conversion as specified)	
			Z= (DWS: Z = Total Conversion as Spec/no listing)	
			TOS (LSR-44) = Type of Service	
			REQTYP (LSR-23) = Requisition Type and Status	

Segment: **PID** Product/Item Description

Position: 1900

Loop:

Level: Heading

Usage: Optional

Max Use: 200

Purpose: To describe a product or process in coded or free-form format

Syntax Notes:

- 1 If PID04 is present, then PID03 is required.
- 2 At least one of PID04 or PID05 is required.
- 3 If PID07 is present, then PID03 is required.
- 4 If PID08 is present, then PID04 is required.
- 5 If PID09 is present, then PID05 is required.

Semantic Notes:

- 1 Use PID03 to indicate the organization that publishes the code list being referred to.
- 2 PID04 should be used for industry-specific product description codes.
- 3 PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
- 4 PID09 is used to identify the language being used in PID05.

Comments:

- 1 If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
- 2 Use PID06 when necessary to refer to the product surface or layer being described in the segment.
- 3 PID07 specifies the individual code list of the agency specified in PID03.

Notes:

PID*S**TI*CONVIND***SO-RSQ*CONVIND (LSR-24a)
 PID*S**TI*AO***SO-RSQ*AGAUTH (LSR-35)
 PID*S**TI*BI***SO-RSQ*FBI (EU-42)
 PID*S**TI*PENDING***SO-RSQ*PENDING ORDER (LSR-108b)

Data Element Summary

Ref.	Data Element	Name	Attributes
M	PID01	Item Description Type	M ID 1/1
		Code indicating the format of a description	
		S Structured (From Industry Code List)	
	PID03	Agency Qualifier Code	X ID 2/2
		Code identifying the agency assigning the code values	
		TI Telecommunications Industry	
	PID04	Product Description Code	X AN 1/12
		A code from an industry code list which provides specific data about a product characteristic	
		AO Agency Authorization Status	
		BI Final Bill Information Indicator	
		CONVIND Conversion Indicator	
		PENDING Pending Order	
	PID07	Source Subqualifier	O AN 1/15
		A reference that indicates the table or text maintained by the Source Qualifier	
		SO-RSQ Service Order - Reseller Questions list	
	PID08	Yes/No Condition or Response Code	O ID 1/1
		Code indicating a Yes or No condition or response	
		FBI (EU-42) = Final Bill Information Indicator	

Y= (DWS: D (Different))
N= (DWS: E (Existing (Default)))

CONVIND (LSR-24a) = Conversion Indicator

Y= (DWS: F - Full)
N= (DWS: P - Partial)

AGAUTH (LSR-35) = Agency Authorization Status

PENDING ORDER (LSR-108b) = Pending Order Indicator

Segment: **N9 Reference Identification**
Position: 2850
Loop: N9 Optional
Level: Heading
Usage: Optional
Max Use: 1
Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Syntax Notes:
 1 At least one of N902 or N903 is required.
 2 If N906 is present, then N905 is required.
 3 If either C04003 or C04004 is present, then the other is required.
 4 If either C04005 or C04006 is present, then the other is required.

Semantic Notes:
 1 N906 reflects the time zone which the time reflects.
 2 N907 contains data relating to the value cited in N902.

Comments:

Notes: N9*H7*ORI*INP****2W>MANUAL IND (NP-34a)

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	N901	128	Reference Identification Qualifier Code qualifying the Reference Identification H7 Standard Clause	M ID 2/3
	N902	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier ORI Order Instructions	X AN 1/30
	N903	369	Free-form Description Free-form descriptive text	X AN 1/45
	N907	C040	Reference Identifier To identify one or more reference numbers or identification numbers as specified by the Reference Qualifier	O
M	C04001	128	Reference Identification Qualifier Code qualifying the Reference Identification 2W Change Order Authority	M ID 2/3
M	C04002	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier MANUAL IND (NP-34a) = Manual Indicator	M AN 1/30

Segment: **MTX** Text
Position: 2900
Loop: N9 Optional
Level: Heading
Usage: Optional
Max Use: >1
Purpose: To specify textual data
Syntax Notes:

- 1 If MTX01 is present, then MTX02 is required.
- 2 If MTX03 is present, then MTX02 is required.
- 3 If MTX05 is present, then MTX04 is required.

Semantic Notes:

- 1 MTX05 is the number of lines to advance before printing.

Comments:

- 1 If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

Notes: MTX**REMARKS (NP-34)

Data Element Summary

<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
<u>Des.</u>	<u>Element</u>		
MTX02	1551	Message Text	X AN 1/4096
		To transmit large volumes of message text	
		REMARKS (NP-34) = Remarks	

Segment: **N9 Reference Identification**
Position: 2850
Loop: N9 Optional
Level: Heading
Usage: Optional
Max Use: 1
Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

- Syntax Notes:**
- 1 At least one of N902 or N903 is required.
 - 2 If N906 is present, then N905 is required.
 - 3 If either C04003 or C04004 is present, then the other is required.
 - 4 If either C04005 or C04006 is present, then the other is required.

- Semantic Notes:**
- 1 N906 reflects the time zone which the time reflects.
 - 2 N907 contains data relating to the value cited in N902.

Comments:

Notes: N9*H7*ORI*LSR****2W>MANUAL IND (LSR-108a)

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	N901	128	Reference Identification Qualifier Code qualifying the Reference Identification H7 Standard Clause	M ID 2/3
	N902	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier ORI Order Instructions	X AN 1/30
	N903	369	Free-form Description Free-form descriptive text	X AN 1/45
	N907	C040	Reference Identifier To identify one or more reference numbers or identification numbers as specified by the Reference Qualifier	O
M	C04001	128	Reference Identification Qualifier Code qualifying the Reference Identification 2W Change Order Authority	M ID 2/3
M	C04002	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier MANUAL IND (LSR-108a) = Manual Indicator	M AN 1/30

Segment: **MTX** Text
Position: 2900
Loop: N9 Optional
Level: Heading
Usage: Optional
Max Use: >1
Purpose: To specify textual data
Syntax Notes:

- 1 If MTX01 is present, then MTX02 is required.
- 2 If MTX03 is present, then MTX02 is required.
- 3 If MTX05 is present, then MTX04 is required.

Semantic Notes:

- 1 MTX05 is the number of lines to advance before printing.

Comments:

- 1 If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

Notes: MTX**REMARKS (LSR-108)

Data Element Summary

<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
<u>Des.</u>	<u>Element</u>		
MTX02	1551	Message Text	X AN 1/4096
		To transmit large volumes of message text	
		REMARKS (LSR-108) = Remarks	

Segment: **N9** Reference Identification
Position: 2850
Loop: N9 Optional
Level: Heading
Usage: Optional
Max Use: 1
Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Syntax Notes:
 1 At least one of N902 or N903 is required.
 2 If N906 is present, then N905 is required.
 3 If either C04003 or C04004 is present, then the other is required.
 4 If either C04005 or C04006 is present, then the other is required.

Semantic Notes:
 1 N906 reflects the time zone which the time reflects.
 2 N907 contains data relating to the value cited in N902.

Comments:

Notes: N9*H7*ORI*EU****2W>MANUAL IND (EU-63a)

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	N901	128	Reference Identification Qualifier Code qualifying the Reference Identification H7 Standard Clause	M ID 2/3
	N902	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier ORI Order Instructions	X AN 1/30
	N903	369	Free-form Description Free-form descriptive text	X AN 1/45
	N907	C040	Reference Identifier To identify one or more reference numbers or identification numbers as specified by the Reference Qualifier	O
M	C04001	128	Reference Identification Qualifier Code qualifying the Reference Identification 2W Change Order Authority	M ID 2/3
M	C04002	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier MANUAL IND (EU-63a) = Manual Indicator	M AN 1/30

Segment: **MTX** Text
Position: 2900
Loop: N9 Optional
Level: Heading
Usage: Optional
Max Use: >1
Purpose: To specify textual data
Syntax Notes:

- 1 If MTX01 is present, then MTX02 is required.
- 2 If MTX03 is present, then MTX02 is required.
- 3 If MTX05 is present, then MTX04 is required.

Semantic Notes:

- 1 MTX05 is the number of lines to advance before printing.

Comments:

- 1 If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

Notes: MTX**REMARKS (EU-63)

Data Element Summary

<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
<u>Des.</u>	<u>Element</u>	<u>Name</u>	<u>Attributes</u>
MTX02	1551	Message Text To transmit large volumes of message text REMARKS (EU-63) = Remarks	X AN 1/4096

Segment: **N1** Name
Position: 3000
Loop: N1 Optional
Level: Heading
Usage: Optional
Max Use: 1
Purpose: To identify a party by type of organization, name, and code
Syntax Notes:

- 1 At least one of N102 or N103 is required.
- 2 If either N103 or N104 is present, then the other is required.

Semantic Notes:
Comments:

- 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
- 2 N105 and N106 further define the type of entity in N101.

Notes: N1*78*CCNA (LSR-1)

Data Element Summary

Ref.	Data	Name	Attributes
<u>Des.</u>	<u>Element</u>	<u>Name</u>	<u>Attributes</u>
M	N101	98 Entity Identifier Code Code identifying an organizational entity, a physical location, property or an individual 78 Service Requester	M ID 2/3
	N102	93 Name Free-form name CCNA (LSR-1) = Customer Carrier Name Abbreviation	X AN 1/60

Segment: **PER Administrative Communications Contact**
Position: 3500
Loop: N1 Optional
Level: Heading
Usage: Optional
Max Use: >1
Purpose: To identify a person or office to whom administrative communications should be directed

- Syntax Notes:**
- 1 If either PER03 or PER04 is present, then the other is required.
 - 2 If either PER05 or PER06 is present, then the other is required.
 - 3 If either PER07 or PER08 is present, then the other is required.

Semantic Notes:

Comments:

Notes: PER*AG*INIT (LSR-81)*TE*TEL NO (LSR-82)*FX*FAX NO (LSR-84)*EM*EMAIL (LSR-83)

PER*CN*IMPCON (LSR-91)*TE*TEL NO (LSR-92)

Data Element Summary

Ref.	Data	Name	Attributes
Des.	Element		
M	PER01	366 Contact Function Code Code identifying the major duty or responsibility of the person or group named AG Agent CN General Contact	M ID 2/2
	PER02	93 Name Free-form name INIT (LSR-81) = Initiator Identification IMPCON (LSR-91) = Implementation Contact	O AN 1/60
	PER03	365 Communication Number Qualifier Code identifying the type of communication number TE Telephone	X ID 2/2
	PER04	364 Communication Number Complete communications number including country or area code when applicable TEL NO (LSR-82) = Telephone Number TEL NO (LSR-92) = Telephone Number	X AN 1/256
	PER05	365 Communication Number Qualifier Code identifying the type of communication number FX Facsimile	X ID 2/2
	PER06	364 Communication Number Complete communications number including country or area code when applicable FAX NO (LSR-84) = Facsimile Number	X AN 1/256
	PER07	365 Communication Number Qualifier Code identifying the type of communication number EM Electronic Mail	X ID 2/2
	PER08	364 Communication Number Complete communications number including country or area code when applicable	X AN 1/256

EMAIL (LSR-83) = Electronic Mail Address

Segment: **N1** Name

Position: 3000

Loop: N1 Optional

Level: Heading

Usage: Optional

Max Use: 1

Purpose: To identify a party by type of organization, name, and code

Syntax Notes: 1 At least one of N102 or N103 is required.

2 If either N103 or N104 is present, then the other is required.

Semantic Notes:

Comments:

1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.

2 N105 and N106 further define the type of entity in N101.

Notes: N1*AN*AUTHNM (LSR-37)

Data Element Summary

Ref.	Data	Name	Attributes
<u>Des.</u>	<u>Element</u>		
M	N101	98 Entity Identifier Code	M ID 2/3
		Code identifying an organizational entity, a physical location, property or an individual	
		AN Authorized From	
			A geographic location designated as an authorized pick-up or origin point for a shipment
	N102	93 Name	X AN 1/60
		Free-form name	
		AUTHNM (LSR-37) = Authorization Name	

Segment: **N1** Name
Position: 3000
Loop: N1 Optional
Level: Heading
Usage: Optional
Max Use: 1
Purpose: To identify a party by type of organization, name, and code
Syntax Notes:

- 1 At least one of N102 or N103 is required.
- 2 If either N103 or N104 is present, then the other is required.

Semantic Notes:
Comments:

- 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
- 2 N105 and N106 further define the type of entity in N101.

Notes: N1*X1*BILLNM (EU-43)

Data Element Summary

Ref.	Data	Name	Attributes
<u>Des.</u>	<u>Element</u>		
M	N101	98 Entity Identifier Code	M ID 2/3
		Code identifying an organizational entity, a physical location, property or an individual	
		X1 Mail to	
		An address to which a specified item is to be mailed	
	N102	93 Name	X AN 1/60
		Free-form name	
		BILLNM (EU-43) = Bill Name	

Segment: **N2** Additional Name Information
Position: 3100
Loop: N1 Optional
Level: Heading
Usage: Optional
Max Use: 2
Purpose: To specify additional names
Syntax Notes:
Semantic Notes:
Comments:
Notes: N2*SBILLNM (EU-44)

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>	<u>Name</u>	
M	N201	93	Name Free-form name	M AN 1/60
			SBILLNM (EU-44) = Secondary Bill Name	

Segment: **N4** Geographic Location

Position: 3300

Loop: N1 Optional

Level: Heading

Usage: Optional

Max Use: >1

Purpose: To specify the geographic place of the named party

- Syntax Notes:**
- 1 Only one of N402 or N407 may be present.
 - 2 If N406 is present, then N405 is required.
 - 3 If N407 is present, then N404 is required.

Semantic Notes:

- Comments:**
- 1 A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
 - 2 N402 is required only if city name (N401) is in the U.S. or Canada.

Notes: N4**STATE (EU-49)*ZIP (EU-50)

Data Element Summary

<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
N402	156	State or Province Code Code (Standard State/Province) as defined by appropriate government agency STATE (EU-49) = State/Province	X ID 2/2
N403	116	Postal Code Code defining international postal zone code excluding punctuation and blanks (zip code for United States) ZIP (EU-50) = ZIP/Postal Code	O ID 3/15

Segment: **NX2** Location ID Component
Position: 3350
Loop: N1 Optional
Level: Heading
Usage: Optional
Max Use: >1
Purpose: To define types and values of a geographic location
Syntax Notes:
Semantic Notes:
Comments:
Notes:

NX2*01*SANO (EU-45b)
 NX2*02*SASN (EU-45e)
 NX2*03*SASD (EU-45d)
 NX2*07*CITY (EU-48)
 NX2*32*FLOOR (EU-46)
 NX2*35*ROOM/MAIL STOP (EU-47)
 NX2*40*SASS (EU-45g)
 NX2*59*SAPR (EU-45a)
 NX2*61*SASF (EU-45c)
 NX2*62*SATH (EU-45f)

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	NX201	1106	Address Component Qualifier Code qualifying the type of address component 01 Street Number 02 Street Name 03 Prefix Direction 07 City Name 32 Floor A particular floor or level of a building 35 Room A walled room or partitioned area of a building 40 Street Suffix 59 Street Number Low 61 Street Number Fraction 62 Street Name Suffix	M ID 2/2
M	NX202	166	Address Information Address information SANO (EU-45b) = Service Address Number SASN (EU-45e) = Service Address Street Name SASD (EU-45d) = Service Address Street Directional Prefix CITY (EU-48) = City FLOOR (EU-46) = Floor ROOM/MAIL STOP (EU-47) = Room/Mail Stop SASS (EU-45g) = Service Address Street Directional Suffix SAPR (EU-45a) = Service Address Number Prefix SASF (EU-45c) = Service Address Number Suffix SATH (EU-45f) = Service Address Street Type	M AN 1/55

Segment: **PER** Administrative Communications Contact
Position: 3500
Loop: N1 Optional
Level: Heading
Usage: Optional
Max Use: >1
Purpose: To identify a person or office to whom administrative communications should be directed

- Syntax Notes:**
- 1 If either PER03 or PER04 is present, then the other is required.
 - 2 If either PER05 or PER06 is present, then the other is required.
 - 3 If either PER07 or PER08 is present, then the other is required.

Semantic Notes:

Comments:

Notes: PER*BI*BILLCON (EU-51)*TE*TEL NO (EU-52)

Data Element Summary

Ref.	Data Element	Name	Attributes
M	PER01	366 Contact Function Code Code identifying the major duty or responsibility of the person or group named BI Bill Inquiry Contact Service Provider contact for making inquires about information on the invoice	M ID 2/2
	PER02	93 Name Free-form name BILLCON (EU-51) = Billing Contact	O AN 1/60
	PER03	365 Communication Number Qualifier Code identifying the type of communication number TE Telephone	X ID 2/2
	PER04	364 Communication Number Complete communications number including country or area code when applicable TEL NO (EU-52) = Telephone Number	X AN 1/256

Segment: **SI** Service Characteristic Identification

Position: 3550

Loop: N1 Optional

Level: Heading

Usage: Optional

Max Use: >1

Purpose: To specify service characteristic data

Syntax Notes:

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

Semantic Notes:

Comments: 1 SI01 defines the source for each of the service characteristics qualifiers.

Notes: SI*TI*AF*AFT (EU-44a)

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	SI01	559	Agency Qualifier Code Code identifying the agency assigning the code values TI Telecommunications Industry	M ID 2/2
M	SI02	1000	Service Characteristics Qualifier Code from an industry code list qualifying the type of service characteristics AF Address Format Type	M AN 2/2
M	SI03	234	Product/Service ID Identifying number for a product or service AFT (EU-44a) = Address Format Type	M AN 1/48

Segment: **POC** Line Item Change - End User Form (Location and Access Section)

Position: 0100
Loop: POC Optional
Level: Detail
Usage: Optional
Max Use: 1
Purpose: To specify changes to a line item
Syntax Notes: 1 If POC03 is present, then both POC04 and POC05 are required.
 2 If POC07 is present, then POC06 is required.
 3 If either POC08 or POC09 is present, then the other is required.
 4 If either POC10 or POC11 is present, then the other is required.
 5 If either POC12 or POC13 is present, then the other is required.
 6 If either POC14 or POC15 is present, then the other is required.
 7 If either POC16 or POC17 is present, then the other is required.
 8 If either POC18 or POC19 is present, then the other is required.
 9 If either POC20 or POC21 is present, then the other is required.
 10 If either POC22 or POC23 is present, then the other is required.
 11 If either POC24 or POC25 is present, then the other is required.
 12 If either POC26 or POC27 is present, then the other is required.
Semantic Notes: 1 POC01 is the purchase order line item identification.

Comments:

Notes: POC*n*RZ*****ZZ*EU_SA [POC Loop may repeat]

Data Element Summary

Ref.	Data	Name	Attributes
<u>Des.</u>	<u>Element</u>		
POC01	350	Assigned Identification Alphanumeric characters assigned for differentiation within a transaction set "n" = nth assigned ID within POC loop	O AN 1/20
M	POC02	670 Change or Response Type Code Code specifying the type of change to the line item RZ Replace All Values Receiver should replace the corresponding values in the original purchase order with the values contained in the Purchase Order Change Transaction Set	M ID 2/2
	POC08	235 Product/Service ID Qualifier Code identifying the type/source of the descriptive number used in Product/Service ID (234) ZZ Mutually Defined	X ID 2/2
	POC09	234 Product/Service ID Identifying number for a product or service "EU_SA"	X AN 1/48

Segment: **N1** Name

Position: 3400

Loop: N1 Optional

Level: Detail

Usage: Optional

Max Use: 1

Purpose: To identify a party by type of organization, name, and code

Syntax Notes: 1 At least one of N102 or N103 is required.

2 If either N103 or N104 is present, then the other is required.

Semantic Notes:

Comments:

1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.

2 N105 and N106 further define the type of entity in N101.

Notes: N1*IT*NAME (EU-8)

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>		
M	N101	98	Entity Identifier Code Code identifying an organizational entity, a physical location, property or an individual IT Installation on Site	M ID 2/3
	N102	93	Name Free-form name NAME (EU-8) = End User Name	X AN 1/60

Segment: **N4** Geographic Location

Position: 3700

Loop: N1 Optional

Level: Detail

Usage: Optional

Max Use: 1

Purpose: To specify the geographic place of the named party

Syntax Notes: 1 Only one of N402 or N407 may be present.

2 If N406 is present, then N405 is required.

3 If N407 is present, then N404 is required.

Semantic Notes:

Comments: 1 A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.

2 N402 is required only if city name (N401) is in the U.S. or Canada.

Notes: N4**STATE (EU-25)*ZIP (EU-26)**RJ*CALA (EU-26a)

Data Element Summary

<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
N402	156	State or Province Code Code (Standard State/Province) as defined by appropriate government agency STATE (EU-25) = State/Province	X ID 2/2
N403	116	Postal Code Code defining international postal zone code excluding punctuation and blanks (zip code for United States) ZIP (EU-26) = ZIP/Postal Code	O ID 3/15
N405	309	Location Qualifier Code identifying type of location RJ Region	X ID 1/2
N406	310	Location Identifier Code which identifies a specific location CALA (EU-26a) = Customer Address Location Area	O AN 1/30

Segment: **NX2** Location ID Component
Position: 3750
Loop: N1 Optional
Level: Detail
Usage: Optional
Max Use: >1
Purpose: To define types and values of a geographic location
Syntax Notes:
Semantic Notes:
Comments:
Notes:

NX2*01*SANO (EU-11)
 NX2*02*SASN (EU-14)
 NX2*03*SASD (EU-13)
 NX2*05*BOX (EU-23c)
 NX2*06*ROUTE (EU-23b)
 NX2*07*CITY (EU-24)
 NX2*39*AHN (EU-23a)
 NX2*40*SASS (EU-16)
 NX2*59*SAPR (EU-10)
 NX2*61*SASF (EU-12)
 NX2*62*SATH (EU-15)
 NX2*LD1 (EU-17)*LV1 (EU-18)
 NX2*LD2 (EU-19)*LV2 (EU-20)
 NX2*LD3 (EU-21)*LV3 (EU-22)

Data Element Summary

Ref.	Data			Attributes
<u>Des.</u>	<u>Element</u>	<u>Name</u>		
M	NX201	1106	Address Component Qualifier	M ID 2/2
			Code qualifying the type of address component	
			LD1 (EU-17) = Location Designator 1	
			13 = (DWS: APT)	
			34 = (DWS: LOT)	
			35 = (DWS: RM)	
			36 = (DWS: SLIP)	
			37 = (DWS: UNIT)	
			14 = (DWS: SUIT)	
			LD2 (EU-19) = Location Designator 2	
			32 = (DWS: FLR)	
			LD3 (EU-21) = Location Designator 3	
			12 = (DWS: BLDG)	
			63 = (DWS: WNG)	
			30 = (DWS: PIER)	
		01	Street Number	
		02	Street Name	
		03	Prefix Direction	
		05	P.O. Box Number	
		06	Rural Route Number	
		07	City Name	
		12	Building Name	
		13	Apartment Number	

14	Suite Number
30	Pier The pier at which a ship or boat is docked
32	Floor A particular floor or level of a building
34	Lot A particular lot or piece of land
35	Room A walled room or partitioned area of a building
36	Slip The slip or location on a pier at which a ship or boat is docked
37	Unit A unit or separate structure
39	Unstructured Property
40	Street Suffix
59	Street Number Low
61	Street Number Fraction
62	Street Name Suffix
63	Secondary Unit Identifier

M **NX202** **166** **Address Information** **M** **AN 1/55**

Address information

SANO (EU-11) = Service Address Number
SASN (EU-14) = Service Address Street Name
SASD (EU-13) = Service Address Street Directional Prefix
BOX (EU-23c) = Box
ROUTE (EU-23b) = Route
CITY (EU-24) = City
AHN (EU-23a) = Assigned House Number
SASS (EU-16) = Service Address Street Directional Suffix
SAPR (EU-10) = Service Address Number Prefix
SASF (EU-12) = Service Address Number Suffix
SATH (EU-15) = Service Address Street Type
LV1 (EU-18) = Location Value 1
LV2 (EU-20) = Location Value 2
LV3 (EU-22) = Location Value 3

Segment: **SI** Service Characteristic Identification

Position: 3950

Loop: N1 Optional

Level: Detail

Usage: Optional

Max Use: >1

Purpose: To specify service characteristic data

Syntax Notes:

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

Semantic Notes:

Comments: 1 SI01 defines the source for each of the service characteristics qualifiers.

Notes: SI*TI*AF*AFT (EU-9)

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	SI01	559	Agency Qualifier Code Code identifying the agency assigning the code values TI Telecommunications Industry	M ID 2/2
M	SI02	1000	Service Characteristics Qualifier Code from an industry code list qualifying the type of service characteristics AF Address Format Type	M AN 2/2
M	SI03	234	Product/Service ID Identifying number for a product or service AFT (EU-9) = Address Format Type	M AN 1/48

Segment: **POC** Line Item Change - End User Form (Disconnect Information Section)

Position: 0100
Loop: POC Optional

Level: Detail
Usage: Optional

Max Use: 1

Purpose: To specify changes to a line item

- Syntax Notes:**
- 1 If POC03 is present, then both POC04 and POC05 are required.
 - 2 If POC07 is present, then POC06 is required.
 - 3 If either POC08 or POC09 is present, then the other is required.
 - 4 If either POC10 or POC11 is present, then the other is required.
 - 5 If either POC12 or POC13 is present, then the other is required.
 - 6 If either POC14 or POC15 is present, then the other is required.
 - 7 If either POC16 or POC17 is present, then the other is required.
 - 8 If either POC18 or POC19 is present, then the other is required.
 - 9 If either POC20 or POC21 is present, then the other is required.
 - 10 If either POC22 or POC23 is present, then the other is required.
 - 11 If either POC24 or POC25 is present, then the other is required.
 - 12 If either POC26 or POC27 is present, then the other is required.

Semantic Notes: 1 POC01 is the purchase order line item identification.

Comments:

Notes: POC*n*RZ*****ZZ*EU_DISC [POC Loop may repeat]

Data Element Summary

Ref.	Data	Name	Attributes
<u>Des.</u>	<u>Element</u>		
POC01	350	Assigned Identification Alphanumeric characters assigned for differentiation within a transaction set "n" = nth assigned ID within POC loop	O AN 1/20
M	POC02	670 Change or Response Type Code Code specifying the type of change to the line item RZ Replace All Values Receiver should replace the corresponding values in the original purchase order with the values contained in the Purchase Order Change Transaction Set	M ID 2/2
	POC08	235 Product/Service ID Qualifier Code identifying the type/source of the descriptive number used in Product/Service ID (234) ZZ Mutually Defined	X ID 2/2
	POC09	234 Product/Service ID Identifying number for a product or service "EU_DISC"	X AN 1/48

Segment: **SI** Service Characteristic Identification

Position: 0180

Loop: POC Optional

Level: Detail

Usage: Optional

Max Use: >1

Purpose: To specify service characteristic data

Syntax Notes:

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

Semantic Notes:

Comments: 1 SI01 defines the source for each of the service characteristics qualifiers.

Notes: SI*TI*ND*DISC NBR (EU-55)

SI*TI*T6*TC OPT(EU-57)

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	SI01	559	Agency Qualifier Code Code identifying the agency assigning the code values TI Telecommunications Industry	M ID 2/2
M	SI02	1000	Service Characteristics Qualifier Code from an industry code list qualifying the type of service characteristics ND Disconnect Number T6 Transfer of Calls Options	M AN 2/2
M	SI03	234	Product/Service ID Identifying number for a product or service DISC NBR (EU-55) = Disconnect Telephone Number TC OPT (EU-57) = Transfer of Call Options	M AN 1/48

Segment: **REF** Reference Identification

Position: 1000

Loop: POC Optional

Level: Detail

Usage: Optional

Max Use: >1

Purpose: To specify identifying information

Syntax Notes: 1 At least one of REF02 or REF03 is required.

2 If either C04003 or C04004 is present, then the other is required.

3 If either C04005 or C04006 is present, then the other is required.

Semantic Notes: 1 REF04 contains data relating to the value cited in REF02.

Comments:

Notes: REF*IX*DNUM (EU-54)*DNUM

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	REF01	128	Reference Identification Qualifier Code qualifying the Reference Identification IX Item Number	M ID 2/3
	REF02	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier DNUM (EU-54) = Disconnect Line Number	X AN 1/30
	REF03	352	Description A free-form description to clarify the related data elements and their content "DNUM"	X AN 1/80

Segment: **DTM** Date/Time Reference

Position: 2000

Loop: POC Optional

Level: Detail

Usage: Optional

Max Use: 10

Purpose: To specify pertinent dates and times

Syntax Notes: 1 At least one of DTM02 DTM03 or DTM05 is required.

2 If DTM04 is present, then DTM03 is required.

3 If either DTM05 or DTM06 is present, then the other is required.

Semantic Notes:

Comments:

Notes: DTM*376*TC PER {CCYYMMDD} (EU-62)

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>		
M	DTM01	374	Date/Time Qualifier Code specifying type of date or time, or both date and time 376 Delivery End The date that deliveries will end	M ID 3/3
	DTM02	373	Date Date expressed as CCYYMMDD TC PER (EU-62) = Transfer of Calls Period	X DT 8/8

Segment: **SLN** Subline Item Detail

Position: 4600

Loop: SLN Optional

Level: Detail

Usage: Optional

Max Use: 1

Purpose: To specify product subline detail item data

Syntax Notes:

- 1 If either SLN04 or SLN05 is present, then the other is required.
- 2 If SLN07 is present, then SLN06 is required.
- 3 If SLN08 is present, then SLN06 is required.
- 4 If either SLN09 or SLN10 is present, then the other is required.
- 5 If either SLN11 or SLN12 is present, then the other is required.
- 6 If either SLN13 or SLN14 is present, then the other is required.
- 7 If either SLN15 or SLN16 is present, then the other is required.
- 8 If either SLN17 or SLN18 is present, then the other is required.
- 9 If either SLN19 or SLN20 is present, then the other is required.
- 10 If either SLN21 or SLN22 is present, then the other is required.
- 11 If either SLN23 or SLN24 is present, then the other is required.
- 12 If either SLN25 or SLN26 is present, then the other is required.
- 13 If either SLN27 or SLN28 is present, then the other is required.

Semantic Notes:

- 1 SLN01 is the identifying number for the subline item.
- 2 SLN02 is the identifying number for the subline level. The subline level is analogous to the level code used in a bill of materials.
- 3 SLN03 is the configuration code indicating the relationship of the subline item to the baseline item.
- 4 SLN08 is a code indicating the relationship of the price or amount to the associated segment.

Comments:

- 1 See the Data Element Dictionary for a complete list of IDs.
- 2 SLN01 is related to (but not necessarily equivalent to) the baseline item number. Example: 1.1 or 1A might be used as a subline number to relate to baseline number 1.
- 3 SLN09 through SLN28 provide for ten different product/service IDs for each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Notes: SLN*TCPRI*n*A*1*EA

Data Element Summary

Ref.	Data	Name	Attributes
Des.	Element		
M	SLN01	350 Assigned Identification	M AN 1/20
		Alphanumeric characters assigned for differentiation within a transaction set	
		"TCPRI"	
	SLN02	350 Assigned Identification	O AN 1/20
		Alphanumeric characters assigned for differentiation within a transaction set	
		"n" = nth assigned ID within SLN loop	
M	SLN03	662 Relationship Code	M ID 1/1
		Code indicating the relationship between entities	
		A Add	
	SLN04	380 Quantity	X R 1/15
		Numeric value of quantity	
		1 Always One	

	SLN05	C001	Composite Unit of Measure	X
			To identify a composite unit of measure (See Figures Appendix for examples of use)	
M	C00101	355	Unit or Basis for Measurement Code	M ID 2/2
			Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken	
			EA Each	

Segment: **SI** Service Characteristic Identification

Position: 4700

Loop: SLN Optional

Level: Detail

Usage: Optional

Max Use: >1

Purpose: To specify service characteristic data

Syntax Notes:

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

Semantic Notes:

Comments: 1 SI01 defines the source for each of the service characteristics qualifiers.

Notes: SI*TI*TC*TC TO PRI (EU-58)

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	SI01	559	Agency Qualifier Code Code identifying the agency assigning the code values TI Telecommunications Industry	M ID 2/2
M	SI02	1000	Service Characteristics Qualifier Code from an industry code list qualifying the type of service characteristics TC Transfer Announcement Number	M AN 2/2
M	SI03	234	Product/Service ID Identifying number for a product or service TC TO PRI (EU-58) = Transfer of Calls To Primary Number	M AN 1/48

Segment: **N1** Name
Position: 5360
Loop: N1 Optional
Level: Detail
Usage: Optional
Max Use: 1
Purpose: To identify a party by type of organization, name, and code
Syntax Notes:

- 1 At least one of N102 or N103 is required.
- 2 If either N103 or N104 is present, then the other is required.

Semantic Notes:
Comments:

- 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
- 2 N105 and N106 further define the type of entity in N101.

Notes: N1*TT*TC NAME (EU-58b)

Data Element Summary

Ref.	Data	Name	Attributes
<u>Des.</u>	<u>Element</u>	<u>Name</u>	<u>Attributes</u>
M	N101	98 Entity Identifier Code Code identifying an organizational entity, a physical location, property or an individual TT Transfer To	M ID 2/3
	N102	93 Name Free-form name TC NAME (EU-58b) = Transfer of Calls to Name	X AN 1/60

Segment: **REF** Reference Identification

Position: 5700

Loop: N1 Optional

Level: Detail

Usage: Optional

Max Use: 12

Purpose: To specify identifying information

Syntax Notes: 1 At least one of REF02 or REF03 is required.

2 If either C04003 or C04004 is present, then the other is required.

3 If either C04005 or C04006 is present, then the other is required.

Semantic Notes: 1 REF04 contains data relating to the value cited in REF02.

Comments:

Notes: REF*55*TCID (EU-58a)*PRI

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>		
M	REF01	128	Reference Identification Qualifier Code qualifying the Reference Identification 55 Sequence Number	M ID 2/3
	REF02	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier TCID (EU-58a) = Transfer of Calls to Identifier	X AN 1/30
	REF03	352	Description A free-form description to clarify the related data elements and their content "PRI"	X AN 1/80

Segment: **SLN** Subline Item Detail

Position: 4600

Loop: SLN Optional

Level: Detail

Usage: Optional

Max Use: 1

Purpose: To specify product subline detail item data

Syntax Notes:

- 1 If either SLN04 or SLN05 is present, then the other is required.
- 2 If SLN07 is present, then SLN06 is required.
- 3 If SLN08 is present, then SLN06 is required.
- 4 If either SLN09 or SLN10 is present, then the other is required.
- 5 If either SLN11 or SLN12 is present, then the other is required.
- 6 If either SLN13 or SLN14 is present, then the other is required.
- 7 If either SLN15 or SLN16 is present, then the other is required.
- 8 If either SLN17 or SLN18 is present, then the other is required.
- 9 If either SLN19 or SLN20 is present, then the other is required.
- 10 If either SLN21 or SLN22 is present, then the other is required.
- 11 If either SLN23 or SLN24 is present, then the other is required.
- 12 If either SLN25 or SLN26 is present, then the other is required.
- 13 If either SLN27 or SLN28 is present, then the other is required.

Semantic Notes:

- 1 SLN01 is the identifying number for the subline item.
- 2 SLN02 is the identifying number for the subline level. The subline level is analogous to the level code used in a bill of materials.
- 3 SLN03 is the configuration code indicating the relationship of the subline item to the baseline item.
- 4 SLN08 is a code indicating the relationship of the price or amount to the associated segment.

Comments:

- 1 See the Data Element Dictionary for a complete list of IDs.
- 2 SLN01 is related to (but not necessarily equivalent to) the baseline item number. Example: 1.1 or 1A might be used as a subline number to relate to baseline number 1.
- 3 SLN09 through SLN28 provide for ten different product/service IDs for each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Notes: SLN*TCSEC*n*A*1*EA [SLN Loop may repeat]

Data Element Summary

Ref.	Data	Name	Attributes
Des.	Element		
M	SLN01	350 Assigned Identification	M AN 1/20
		Alphanumeric characters assigned for differentiation within a transaction set	
		"TCSEC"	
	SLN02	350 Assigned Identification	O AN 1/20
		Alphanumeric characters assigned for differentiation within a transaction set	
		"n" = nth assigned ID within SLN loop	
M	SLN03	662 Relationship Code	M ID 1/1
		Code indicating the relationship between entities	
		A Add	
	SLN04	380 Quantity	X R 1/15
		Numeric value of quantity	
		1 Always One	

	SLN05	C001	Composite Unit of Measure	X
			To identify a composite unit of measure (See Figures Appendix for examples of use)	
M	C00101	355	Unit or Basis for Measurement Code	M ID 2/2
			Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken	
			EA Each	

Segment: **SI** Service Characteristic Identification

Position: 4700

Loop: SLN Optional

Level: Detail

Usage: Optional

Max Use: >1

Purpose: To specify service characteristic data

Syntax Notes:

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

Semantic Notes:

Comments: 1 SI01 defines the source for each of the service characteristics qualifiers.

Notes: SI*TI*TC*TC TO SEC (EU-59)

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	SI01	559	Agency Qualifier Code Code identifying the agency assigning the code values TI Telecommunications Industry	M ID 2/2
M	SI02	1000	Service Characteristics Qualifier Code from an industry code list qualifying the type of service characteristics TC Transfer Announcement Number	M AN 2/2
M	SI03	234	Product/Service ID Identifying number for a product or service TC TO SEC (EU-59) = Transfer of Calls To Secondary Number	M AN 1/48

Segment: **N1** Name

Position: 5360

Loop: N1 Optional

Level: Detail

Usage: Optional

Max Use: 1

Purpose: To identify a party by type of organization, name, and code

Syntax Notes: 1 At least one of N102 or N103 is required.

2 If either N103 or N104 is present, then the other is required.

Semantic Notes:

Comments: 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.

2 N105 and N106 further define the type of entity in N101.

Notes: N1*TT*TC NAME (EU-61)

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>		
M	N101	98	Entity Identifier Code Code identifying an organizational entity, a physical location, property or an individual TT Transfer To	M ID 2/3
	N102	93	Name Free-form name TC NAME (EU-61) = Transfer of Calls to Name	X AN 1/60

Segment: **REF** Reference Identification

Position: 5700

Loop: N1 Optional

Level: Detail

Usage: Optional

Max Use: 12

Purpose: To specify identifying information

Syntax Notes: 1 At least one of REF02 or REF03 is required.

2 If either C04003 or C04004 is present, then the other is required.

3 If either C04005 or C04006 is present, then the other is required.

Semantic Notes: 1 REF04 contains data relating to the value cited in REF02.

Comments:

Notes: REF*55*TCID (EU-60)*SEC

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>		
M	REF01	128	Reference Identification Qualifier Code qualifying the Reference Identification 55 Sequence Number	M ID 2/3
	REF02	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier TCID (EU-60) = Transfer of Calls To Identifier	X AN 1/30
	REF03	352	Description A free-form description to clarify the related data elements and their content "SEC"	X AN 1/80

Segment: **POC** Line Item Change - INP Form (Service Details Section)

Position: 0100
Loop: POC Optional
Level: Detail
Usage: Optional
Max Use: 1

Purpose: To specify changes to a line item
Syntax Notes:
 1 If POC03 is present, then both POC04 and POC05 are required.
 2 If POC07 is present, then POC06 is required.
 3 If either POC08 or POC09 is present, then the other is required.
 4 If either POC10 or POC11 is present, then the other is required.
 5 If either POC12 or POC13 is present, then the other is required.
 6 If either POC14 or POC15 is present, then the other is required.
 7 If either POC16 or POC17 is present, then the other is required.
 8 If either POC18 or POC19 is present, then the other is required.
 9 If either POC20 or POC21 is present, then the other is required.
 10 If either POC22 or POC23 is present, then the other is required.
 11 If either POC24 or POC25 is present, then the other is required.
 12 If either POC26 or POC27 is present, then the other is required.
Semantic Notes:
 1 POC01 is the purchase order line item identification.

Comments:

Notes: POC*n*RZ*****ZZ*INP [PO1 Loop repeats NPQTY (NP-5) times]

Data Element Summary

Ref.	Data	Name	Attributes
Des.	Element		
POC01	350	Assigned Identification	O AN 1/20
		Alphanumeric characters assigned for differentiation within a transaction set	
		"n" = nth assigned ID within POC loop	
M	POC02	Change or Response Type Code	M ID 2/2
		Code specifying the type of change to the line item	
		RZ Replace All Values	
		Receiver should replace the corresponding values in the original purchase order with the values contained in the Purchase Order Change Transaction Set	
	POC08	Product/Service ID Qualifier	X ID 2/2
		Code identifying the type/source of the descriptive number used in Product/Service ID (234)	
		ZZ Mutually Defined	
	POC09	Product/Service ID	X AN 1/48
		Identifying number for a product or service	
		"INP"	

Segment: **SI** Service Characteristic Identification
Position: 0180
Loop: POC Optional
Level: Detail
Usage: Optional
Max Use: >1
Purpose: To specify service characteristic data
Syntax Notes:

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

Semantic Notes:

Comments: 1 SI01 defines the source for each of the service characteristics qualifiers.

Notes:

SI*TI*SA*LNA (NP-10)
SI*TI*IT*PORTED NBR (NP-15)
SI*TI*C2*CFTN (NP-17)
SI*TI*IP*NPT (NP-18)
SI*TI*RI*RTI (NP-19)
SI*TI*TH*NPTG (NP-20)
SI*TI*FZ*FPI (NP-24)
SI*TI*T6*TC OPT (NP-26)

Data Element Summary

Ref.	Des.	Data Element	Name	Attributes
M	SI01	559	Agency Qualifier Code Code identifying the agency assigning the code values TI Telecommunications Industry	M ID 2/2
M	SI02	1000	Service Characteristics Qualifier Code from an industry code list qualifying the type of service characteristics C2 Call Forwarding Telephone Number FZ Freeze PIC Indicator IP Number Portability Type IT Ported Telephone Number(s) RI Route Index SA Service Activity T6 Transfer of Calls Options TH Trunk Group Number	M AN 2/2
M	SI03	234	Product/Service ID Identifying number for a product or service LNA (NP-10) = Line Activity C= (DWS: C-Change) D= (DWS: D-Disconnect) V= (DWS: V-Conversion as specified) TC OPT (NP-26) = Transfer of Call Options	M AN 1/48

NPT (NP-18) = Number Portability Type
FPI (NP-24) = Freeze PIC Indicator
CFTN (NP-17) = Call Forward To Number
RTI (NP-19) = Route Index
PORTED NBR (NP-15) = Ported Telephone Number
NPTG (NP-20) = Number Portability Trunk Group

Segment: **REF** Reference Identification

Position: 1000

Loop: POC Optional

Level: Detail

Usage: Optional

Max Use: >1

Purpose: To specify identifying information

Syntax Notes: 1 At least one of REF02 or REF03 is required.

2 If either C04003 or C04004 is present, then the other is required.

3 If either C04005 or C04006 is present, then the other is required.

Semantic Notes: 1 REF04 contains data relating to the value cited in REF02.

Comments:

Notes: REF*IX*LNUM (NP-8)*LNUM

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>		
M	REF01	128	Reference Identification Qualifier Code qualifying the Reference Identification IX Item Number	M ID 2/3
	REF02	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier LNUM (NP-8) = Line Number	X AN 1/30
	REF03	352	Description A free-form description to clarify the related data elements and their content "LNUM"	X AN 1/80

Segment: **DTM** Date/Time Reference

Position: 2000

Loop: POC Optional

Level: Detail

Usage: Optional

Max Use: 10

Purpose: To specify pertinent dates and times

Syntax Notes: 1 At least one of DTM02 DTM03 or DTM05 is required.

2 If DTM04 is present, then DTM03 is required.

3 If either DTM05 or DTM06 is present, then the other is required.

Semantic Notes:

Comments:

Notes: DTM*376*TC PER {CCYYMMDD} (NP-31)

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>		
M	DTM01	374	Date/Time Qualifier Code specifying type of date or time, or both date and time 376 Delivery End The date that deliveries will end	M ID 3/3
	DTM02	373	Date Date expressed as CCYYMMDD TC PER (NP-31) = Transfer of Calls Period	X DT 8/8

Segment: **QTY** Quantity
Position: 2930
Loop: QTY Optional
Level: Detail
Usage: Optional
Max Use: 1
Purpose: To specify quantity information
Syntax Notes:
 1 At least one of QTY02 or QTY04 is required.
 2 Only one of QTY02 or QTY04 may be present.
Semantic Notes:
 1 QTY04 is used when the quantity is non-numeric.
Comments:
Notes: QTY*43*TNP (NP-16)*EA

Data Element Summary

Ref.	Data	Name	Attributes
<u>Des.</u>	<u>Element</u>	<u>Name</u>	<u>Attributes</u>
M	QTY01	673 Quantity Qualifier Code specifying the type of quantity 43 Talk Paths The total number of talk paths associated with the ordered port(s)	M ID 2/2
	QTY02	380 Quantity Numeric value of quantity TNP (NP-16) = Total Number of Paths	X R 1/15
	QTY03	C001 Composite Unit of Measure To identify a composite unit of measure (See Figures Appendix for examples of use)	O
M	C00101	355 Unit or Basis for Measurement Code Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken EA Each	M ID 2/2

Segment: **N1** Name
Position: 3400
Loop: N1 Optional
Level: Detail
Usage: Optional
Max Use: 1
Purpose: To identify a party by type of organization, name, and code
Syntax Notes: 1 At least one of N102 or N103 is required.
 2 If either N103 or N104 is present, then the other is required.
Semantic Notes:
Comments: 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
 2 N105 and N106 further define the type of entity in N101.
Notes: N1*8V**41*LPIC (NP-25)

Data Element Summary

Ref.	Data	Name	Attributes
<u>Des.</u>	<u>Element</u>		
M	N101	98 Entity Identifier Code Code identifying an organizational entity, a physical location, property or an individual 8V Primary Intra-LATA (Local Access Transport Area) Carrier	M ID 2/3
	N103	66 Identification Code Qualifier Code designating the system/method of code structure used for Identification Code (67) 41 Telecommunications Carrier Identification Code Identifies the Interexchange carrier for the charges being billed	X ID 1/2
	N104	67 Identification Code Code identifying a party or other code LPIC (NP-25) = IntraLATA Pre-subscription Indicator Code	X AN 2/80

Segment: **SLN** Subline Item Detail

Position: 4600

Loop: SLN Optional

Level: Detail

Usage: Optional

Max Use: 1

Purpose: To specify product subline detail item data

Syntax Notes:

- 1 If either SLN04 or SLN05 is present, then the other is required.
- 2 If SLN07 is present, then SLN06 is required.
- 3 If SLN08 is present, then SLN06 is required.
- 4 If either SLN09 or SLN10 is present, then the other is required.
- 5 If either SLN11 or SLN12 is present, then the other is required.
- 6 If either SLN13 or SLN14 is present, then the other is required.
- 7 If either SLN15 or SLN16 is present, then the other is required.
- 8 If either SLN17 or SLN18 is present, then the other is required.
- 9 If either SLN19 or SLN20 is present, then the other is required.
- 10 If either SLN21 or SLN22 is present, then the other is required.
- 11 If either SLN23 or SLN24 is present, then the other is required.
- 12 If either SLN25 or SLN26 is present, then the other is required.
- 13 If either SLN27 or SLN28 is present, then the other is required.

Semantic Notes:

- 1 SLN01 is the identifying number for the subline item.
- 2 SLN02 is the identifying number for the subline level. The subline level is analogous to the level code used in a bill of materials.
- 3 SLN03 is the configuration code indicating the relationship of the subline item to the baseline item.
- 4 SLN08 is a code indicating the relationship of the price or amount to the associated segment.

Comments:

- 1 See the Data Element Dictionary for a complete list of IDs.
- 2 SLN01 is related to (but not necessarily equivalent to) the baseline item number. Example: 1.1 or 1A might be used as a subline number to relate to baseline number 1.
- 3 SLN09 through SLN28 provide for ten different product/service IDs for each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Notes: SLN*TCPRI*n*A*1*EA

Data Element Summary

Ref.	Des.	Data Element	Name	Attributes	
				M	AN
M	SLN01	350	Assigned Identification	M	AN 1/20
			Alphanumeric characters assigned for differentiation within a transaction set		
			"TCPRI"		
	SLN02	350	Assigned Identification	O	AN 1/20
			Alphanumeric characters assigned for differentiation within a transaction set		
			"n" = nth assigned ID within SLN loop		
M	SLN03	662	Relationship Code	M	ID 1/1
			Code indicating the relationship between entities		
			A Add		
	SLN04	380	Quantity	X	R 1/15
			Numeric value of quantity		
			1 Always One		

	SLN05	C001	Composite Unit of Measure	X
			To identify a composite unit of measure (See Figures Appendix for examples of use)	
M	C00101	355	Unit or Basis for Measurement Code	M ID 2/2
			Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken	
			EA Each	

Segment: **SI** Service Characteristic Identification

Position: 4700

Loop: SLN Optional

Level: Detail

Usage: Optional

Max Use: >1

Purpose: To specify service characteristic data

Syntax Notes:

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

Semantic Notes:

Comments: 1 SI01 defines the source for each of the service characteristics qualifiers.

Notes: SI*TI*TC*TC TO PRI (NP-27)

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	SI01	559	Agency Qualifier Code Code identifying the agency assigning the code values TI Telecommunications Industry	M ID 2/2
M	SI02	1000	Service Characteristics Qualifier Code from an industry code list qualifying the type of service characteristics TC Transfer Announcement Number	M AN 2/2
M	SI03	234	Product/Service ID Identifying number for a product or service TC TO PRI (NP-27) = Transfer of Calls To Primary Number	M AN 1/48

Segment: **N1** Name
Position: 5360
Loop: N1 Optional
Level: Detail
Usage: Optional
Max Use: 1
Purpose: To identify a party by type of organization, name, and code
Syntax Notes:

- 1 At least one of N102 or N103 is required.
- 2 If either N103 or N104 is present, then the other is required.

Semantic Notes:
Comments:

- 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
- 2 N105 and N106 further define the type of entity in N101.

Notes: N1*TT*TC NAME (NP-27b)

Data Element Summary

Ref. Des.	Data Element	Name	Attributes
M	N101	98 Entity Identifier Code Code identifying an organizational entity, a physical location, property or an individual TT Transfer To	M ID 2/3
	N102	93 Name Free-form name TC NAME (NP-27b) = Transfer of Calls to Name	X AN 1/60

Segment: **REF** Reference Identification

Position: 5700

Loop: N1 Optional

Level: Detail

Usage: Optional

Max Use: 12

Purpose: To specify identifying information

Syntax Notes: 1 At least one of REF02 or REF03 is required.

2 If either C04003 or C04004 is present, then the other is required.

3 If either C04005 or C04006 is present, then the other is required.

Semantic Notes: 1 REF04 contains data relating to the value cited in REF02.

Comments:

Notes: REF*55*TCID (N27a)*PRI

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>		
M	REF01	128	Reference Identification Qualifier Code qualifying the Reference Identification 55 Sequence Number	M ID 2/3
	REF02	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier TCID (NP-27a) = Transfer of Calls to Identifier	X AN 1/30
	REF03	352	Description A free-form description to clarify the related data elements and their content "PRI"	X AN 1/80

Segment: **SLN** Subline Item Detail

Position: 4600

Loop: SLN Optional

Level: Detail

Usage: Optional

Max Use: 1

Purpose: To specify product subline detail item data

Syntax Notes:

- 1 If either SLN04 or SLN05 is present, then the other is required.
- 2 If SLN07 is present, then SLN06 is required.
- 3 If SLN08 is present, then SLN06 is required.
- 4 If either SLN09 or SLN10 is present, then the other is required.
- 5 If either SLN11 or SLN12 is present, then the other is required.
- 6 If either SLN13 or SLN14 is present, then the other is required.
- 7 If either SLN15 or SLN16 is present, then the other is required.
- 8 If either SLN17 or SLN18 is present, then the other is required.
- 9 If either SLN19 or SLN20 is present, then the other is required.
- 10 If either SLN21 or SLN22 is present, then the other is required.
- 11 If either SLN23 or SLN24 is present, then the other is required.
- 12 If either SLN25 or SLN26 is present, then the other is required.
- 13 If either SLN27 or SLN28 is present, then the other is required.

Semantic Notes:

- 1 SLN01 is the identifying number for the subline item.
- 2 SLN02 is the identifying number for the subline level. The subline level is analogous to the level code used in a bill of materials.
- 3 SLN03 is the configuration code indicating the relationship of the subline item to the baseline item.
- 4 SLN08 is a code indicating the relationship of the price or amount to the associated segment.

Comments:

- 1 See the Data Element Dictionary for a complete list of IDs.
- 2 SLN01 is related to (but not necessarily equivalent to) the baseline item number. Example: 1.1 or 1A might be used as a subline number to relate to baseline number 1.
- 3 SLN09 through SLN28 provide for ten different product/service IDs for each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Notes: SLN*TCSEC*n*A*1*EA [SLN Loop may repeat]

Data Element Summary

Ref.	Data	Name	Attributes
Des.	Element		
M	SLN01	350 Assigned Identification	M AN 1/20
		Alphanumeric characters assigned for differentiation within a transaction set	
		"TCSEC"	
	SLN02	350 Assigned Identification	O AN 1/20
		Alphanumeric characters assigned for differentiation within a transaction set	
		"n" = nth assigned ID within SLN loop	
M	SLN03	662 Relationship Code	M ID 1/1
		Code indicating the relationship between entities	
		A Add	
	SLN04	380 Quantity	X R 1/15
		Numeric value of quantity	
		1 Always One	

	SLN05	C001	Composite Unit of Measure	X
			To identify a composite unit of measure (See Figures Appendix for examples of use)	
M	C00101	355	Unit or Basis for Measurement Code	M ID 2/2
			Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken	
			EA Each	

Segment: **SI** Service Characteristic Identification

Position: 4700

Loop: SLN Optional

Level: Detail

Usage: Optional

Max Use: >1

Purpose: To specify service characteristic data

- Syntax Notes:**
- 1 If either SI04 or SI05 is present, then the other is required.
 - 2 If either SI06 or SI07 is present, then the other is required.
 - 3 If either SI08 or SI09 is present, then the other is required.
 - 4 If either SI10 or SI11 is present, then the other is required.
 - 5 If either SI12 or SI13 is present, then the other is required.
 - 6 If either SI14 or SI15 is present, then the other is required.
 - 7 If either SI16 or SI17 is present, then the other is required.
 - 8 If either SI18 or SI19 is present, then the other is required.
 - 9 If either SI20 or SI21 is present, then the other is required.

Semantic Notes:

Comments: 1 SI01 defines the source for each of the service characteristics qualifiers.

Notes: SI*TI*TC*TC TO SEC (NP-28)

Data Element Summary

	<u>Ref. Des.</u>	<u>Data Element</u>	<u>Name</u>	<u>Attributes</u>
M	SI01	559	Agency Qualifier Code Code identifying the agency assigning the code values TI Telecommunications Industry	M ID 2/2
M	SI02	1000	Service Characteristics Qualifier Code from an industry code list qualifying the type of service characteristics TC Transfer Announcement Number	M AN 2/2
M	SI03	234	Product/Service ID Identifying number for a product or service TC TO SEC (NP-28) = Transfer of Calls To Secondary Number	M AN 1/48

Segment: **N1** Name

Position: 5360

Loop: N1 Optional

Level: Detail

Usage: Optional

Max Use: 1

Purpose: To identify a party by type of organization, name, and code

Syntax Notes: 1 At least one of N102 or N103 is required.

2 If either N103 or N104 is present, then the other is required.

Semantic Notes:

Comments:

1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.

2 N105 and N106 further define the type of entity in N101.

Notes: N1*TT*TC NAME (NP-30)

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>		
M	N101	98	Entity Identifier Code Code identifying an organizational entity, a physical location, property or an individual TT Transfer To	M ID 2/3
	N102	93	Name Free-form name TC NAME (NP-30) = Transfer of Calls To Name	X AN 1/60

Segment: **REF** Reference Identification

Position: 5700

Loop: N1 Optional

Level: Detail

Usage: Optional

Max Use: 12

Purpose: To specify identifying information

Syntax Notes: 1 At least one of REF02 or REF03 is required.

2 If either C04003 or C04004 is present, then the other is required.

3 If either C04005 or C04006 is present, then the other is required.

Semantic Notes: 1 REF04 contains data relating to the value cited in REF02.

Comments:

Notes: REF*55*TCID (NP-29)*SEC

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>		
M	REF01	128	Reference Identification Qualifier Code qualifying the Reference Identification 55 Sequence Number	M ID 2/3
	REF02	127	Reference Identification Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier TCID (NP-29) = Transfer of Calls To Identifier	X AN 1/30
	REF03	352	Description A free-form description to clarify the related data elements and their content "SEC"	X AN 1/80

Segment: **SLN** Subline Item Detail

Position: 4600

Loop: SLN Optional

Level: Detail

Usage: Optional

Max Use: 1

Purpose: To specify product subline detail item data

Syntax Notes:

- 1 If either SLN04 or SLN05 is present, then the other is required.
- 2 If SLN07 is present, then SLN06 is required.
- 3 If SLN08 is present, then SLN06 is required.
- 4 If either SLN09 or SLN10 is present, then the other is required.
- 5 If either SLN11 or SLN12 is present, then the other is required.
- 6 If either SLN13 or SLN14 is present, then the other is required.
- 7 If either SLN15 or SLN16 is present, then the other is required.
- 8 If either SLN17 or SLN18 is present, then the other is required.
- 9 If either SLN19 or SLN20 is present, then the other is required.
- 10 If either SLN21 or SLN22 is present, then the other is required.
- 11 If either SLN23 or SLN24 is present, then the other is required.
- 12 If either SLN25 or SLN26 is present, then the other is required.
- 13 If either SLN27 or SLN28 is present, then the other is required.

Semantic Notes:

- 1 SLN01 is the identifying number for the subline item.
- 2 SLN02 is the identifying number for the subline level. The subline level is analogous to the level code used in a bill of materials.
- 3 SLN03 is the configuration code indicating the relationship of the subline item to the baseline item.
- 4 SLN08 is a code indicating the relationship of the price or amount to the associated segment.

Comments:

- 1 See the Data Element Dictionary for a complete list of IDs.
- 2 SLN01 is related to (but not necessarily equivalent to) the baseline item number. Example: 1.1 or 1A might be used as a subline number to relate to baseline number 1.
- 3 SLN09 through SLN28 provide for ten different product/service IDs for each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Notes: SLN*BL*n*A*1*EA

Data Element Summary

Ref.	Data	Name	Attributes
Des.	Element		
M	SLN01	350 Assigned Identification	M AN 1/20
		Alphanumeric characters assigned for differentiation within a transaction set	
		"BL"	
	SLN02	350 Assigned Identification	O AN 1/20
		Alphanumeric characters assigned for differentiation within a transaction set	
		"n" = nth assigned ID within SLN loop	
M	SLN03	662 Relationship Code	M ID 1/1
		Code indicating the relationship between entities	
		A Add	
	SLN04	380 Quantity	X R 1/15
		Numeric value of quantity	
		1 Always One	

	SLN05	C001	Composite Unit of Measure	X
			To identify a composite unit of measure (See Figures Appendix for examples of use)	
M	C00101	355	Unit or Basis for Measurement Code	M ID 2/2
			Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken	
			EA Each	

Segment: **SI** Service Characteristic Identification

Position: 4700

Loop: SLN Optional

Level: Detail

Usage: Optional

Max Use: >1

Purpose: To specify service characteristic data

Syntax Notes:

- 1 If either SI04 or SI05 is present, then the other is required.
- 2 If either SI06 or SI07 is present, then the other is required.
- 3 If either SI08 or SI09 is present, then the other is required.
- 4 If either SI10 or SI11 is present, then the other is required.
- 5 If either SI12 or SI13 is present, then the other is required.
- 6 If either SI14 or SI15 is present, then the other is required.
- 7 If either SI16 or SI17 is present, then the other is required.
- 8 If either SI18 or SI19 is present, then the other is required.
- 9 If either SI20 or SI21 is present, then the other is required.

Semantic Notes:

Comments: 1 SI01 defines the source for each of the service characteristics qualifiers.

Notes: SI*TI*BB*BA (NP-22)*TB*BLOCK (NP-23)

Data Element Summary

Ref.	Data			Attributes
Des.	Element	Name		
M	SI01	559	Agency Qualifier Code	M ID 2/2
			Code identifying the agency assigning the code values TI Telecommunications Industry	
M	SI02	1000	Service Characteristics Qualifier	M AN 2/2
			Code from an industry code list qualifying the type of service characteristics BB Blocking Activity	
M	SI03	234	Product/Service ID	M AN 1/48
			Identifying number for a product or service BA (NP-22) = Blocking Activity	
	SI04	1000	Service Characteristics Qualifier	X AN 2/2
			Code from an industry code list qualifying the type of service characteristics TB Blocking/Billing Exception	
	SI05	234	Product/Service ID	X AN 1/48
			Identifying number for a product or service BLOCK (NP-23) = Block	

Segment: **CTT** Transaction Totals

Position: 0100

Loop: CTT Optional

Level: Summary

Usage: Optional

Max Use: 1

Purpose: To transmit a hash total for a specific element in the transaction set

Syntax Notes: 1 If either CTT03 or CTT04 is present, then the other is required.

2 If either CTT05 or CTT06 is present, then the other is required.

Semantic Notes:

Comments: 1 This segment is intended to provide hash totals to validate transaction completeness and correctness.

Notes: CTT*Number of POC Segments

Data Element Summary

	<u>Ref.</u>	<u>Data</u>	<u>Name</u>	<u>Attributes</u>
	<u>Des.</u>	<u>Element</u>		
M	CTT01	354	Number of Line Items Total number of line items in the transaction set	M NO 1/6

Segment: **SE** Transaction Set Trailer
Position: 0300
Loop:
Level: Summary
Usage: Mandatory
Max Use: 1
Purpose: To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Syntax Notes:

Semantic Notes:

Comments: 1 SE is the last segment of each transaction set.

Notes: SE*Number of Segments*TRAN SET CONTROL #

Data Element Summary

	Ref.	Data		
	<u>Des.</u>	<u>Element</u>	<u>Name</u>	<u>Attributes</u>
M	SE01	96	Number of Included Segments	M NO 1/10
			Total number of segments included in a transaction set including ST and SE segments	
M	SE02	329	Transaction Set Control Number	M AN 4/9
			Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set	